DATA HANDBOOK

Signetics
Programmable
Logic
Devices

Signetics

Philips Components







PHILIPS

PLD Data Handbook 1990

Programmable Logic Devices

Programmable Logic Devices

Philips Components



Signetics reserves the right to make changes, without notice, in the products, including circuits, standard cells, and/or software, described or contained herein in order to improve design and/or performance. Signetics assumes no responsibility or liability for the use of any of these products, conveys no license or title under any patent, copyright, or mask work right to these products, and makes no representations or warranties that these products are free from patent, copyright, or mask work right infringement, unless otherwise specified. Applications that are described herein for any of these products are for illustrative purposes only. Signetics makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

LIFE SUPPORT APPLICATIONS

Signetics Products are not designed for use in life support appliances, devices, or systems where malfunction of a Signetics Product can reasonably be expected to result in a personal injury. Signetics customers using or selling Signetics Products for use in such applications do so at their own risk and agree to fully indemnify Signetics for any damages resulting from such improper use or sale.

Signetics registers eligible circuits under the Semiconductor Chip Protection Act.

© Copyright 1990 NAPC.

Preface

Programmable Logic Devices

The 1990 Philips Components—Signetics PLD Data Handbook is loaded with information on new parts. Using the fastest technologies in the most innovative architectures, today's system designer can pick from the largest selection of PLDs in the industry. Some highlights of this handbook include the fastest silicon PLDs available (PHD16N8 and PHD48N22)—at 5 nanoseconds! These devices make ideal decoders to squeeze maximum performance from powerful microprocessors.

Designers using DRAM, VRAM and graphics will appreciate the speed and power of the new line of sequencers which include the PLC415, PLC42VA12, PLUS405 and PLUS105. These sequencers also make innovative bus and LAN controllers for emerging standard protocols. At last, the logical power of dual programmable arrays comes forth in the PLUS153 and PLUS173 devices—at 10 nanosecond propagation delays. The PLC18V8Z is the only zero power 20—pin device which can replace 16V8's! And finally, our –7 and D speed PAL-type devices are the industry's fastest. For maximum density in a truly compact system, the Programmable Macro Logic family now boasts four members—the PML2552 and PLHS601 are added to the original PLHS501 and PLHS502. The PML2552 is the PLD industry's first dense device to implement SCAN test.

To complement the devices, AMAZE design software is offered through our Sales Offices (see Section 11) and SNAP software is available for high level support. Read about them under Product Support.

Expanding customer service has been an ongoing effort. Our Applications staff is available to answer your technical questions on PLD designs and our free computer Bulletin Board, with 24-hour service, is at (800)451-6644.

New PLD users are encouraged to read the Introduction and AN8 for an overview of PLD ideas. More seasoned PLD users are encouraged to go through the PLD applications and PML applications at the end of the handbook to gain understanding and ideas for new designs.

January 1990

Product Status

Programmable Logic Devices

DEFINITIONS					
Data Sheet Identification	Product Status	Definition			
Objective Specification	Formative or In Design	This data sheet contains the design target or goal specifications for product development. Specifications may change in any manner without notice.			
Preliminary Specification	Preproduction Product	This data sheet contains preliminary data and supplementary data will be published at a later date. Signetics reserves the right to make changes at any time without notice in order to improve design and supply the best possible product.			
Product Specification	Full Production	This data sheet contains Final Specifications. Signetics reserves the right to make changes at any time without notice in order to improve design and supply the best possible product.			

Contents

Programmable Logic Devices

Preface		iii
Product Status		V
Selection Guide	nation	4
	grammable Logic	
Section 3 – PAL [®] -Type De Series 20	evices Data Sheets	
PLHS16L8A/B	PAL [®] -Type Devices (16 × 64 × 8)	9
PLUS16R8D/-7	PAL® -Type Devices (Includes: PLUS16L8D/-7, PLUS16R4D/-7, PLUS16R6D/-7, PLUS16R8D/-7)	
PHD16N8-5	Programmable High Speed Decoder (16 × 16 × 8); 5ns	
PLHS18P8A/B	PAL [®] -Type Devices	
PLC18V8Z/I Series 24	PAL [®] –Type Devices	
10H20EV8/10020EV8	ECL PAL®-Type Devices	7
PLUS20R8D/-7	PAL [®] -Type Devices (Includes: PLUS20L8D/-7, PLUS20R4D/-7, PLUS20R6D/-7, PLUS20R8D/-7)	11
Series 68		
PHD48N22-7	Programmable High Speed Decoder (48 × 73 × 22); 7.5ns	5
Section 4 – Programmable Series 20	e Logic Array Devices Data Sheets	
PLS153/A	Programmable Logic Arrays (18 × 42 × 10); 40/30ns	7
PLUS153B/D	Programmable Logic Arrays (18 × 42 × 10); 15/12ns	4
PLUS153-10 Series 24	Programmable Logic Array (18 × 42 × 10); 10ns	-1
PLS173	Programmable Logic Array (22 \times 42 \times 10); 30ns	8
PLUS173B/D	Programmable Logic Arrays (22 × 42 × 10); 15/12ns	4
PLUS173-10	Programmable Logic Array (22 × 42 × 10); 10ns	1
PLHS473	Programmable Logic Array (20 \times 24 \times 11); 22ns	8
PLHS473S Series 28	Programmable Logic Array (20 × 24 × 11); 25ns	4
PLS100/101	Programmable Logic Arrays (16 × 48 × 8); 50ns	1

Contents

tion 5 – Programmable id	ogic Sequencer Devices Data Sneets	
Series 20		
PLS155	Programmable Logic Sequencer (16 × 45 × 12); 14MHz	191
PLS157	Programmable Logic Sequencer (16 × 45 × 12); 14MHz	202
PLS159A Series 24	Programmable Logic Sequencer (16 \times 45 \times 12); 18MHz	213
PLS167/A	Programmable Logic Sequencers (14 × 48 × 6); 14, 20MHz	223
PLS168/A	Programmable Logic Sequencers (12 × 48 × 8); 14, 20MHz	234
PLS179		245
PLC42VA12 Series 28	CMOS Programmable Logic Sequencer (42 × 105 × 12); 25MHz	256
PLC415-16	Programmable Logic Sequencer (17 × 68 × 8); 16MHz	275
PLS105/A	Programmable Logic Sequencers (16 × 48 × 8); 14, 20MHz	294
PLUS105-40	Programmable Logic Sequencer (16 × 48 × 8); 40MHz	305
PLUS105-55	Programmable Logic Sequencer (16 × 48 × 8); 55MHz	317
PLUS405-37/-45		329
		344
_	*	004
		361 372
	· ·	384
PML2552		395
tion 7 Military Products		
tion 7 - Military Products	Military Selection Guide	417
tion 8 – Development So	ftware	
	AMAZE – Automatic Map and Zap Equations Design Software	421
	· · · · · · · · · · · · · · · · · · ·	425
		427
	Device Programmer Reference Guide	429
	S	
		435
		447
		459 463
		476
AN18		487
AN21	9–Bit Parity Generator/Checker with PLS153/153A	495
AN23	PLS168/168A Primer	501
AN24	PLS173 as a 10–Bit Comparator, 74LS460	514
AN26		520
		529
	High-Speed 12-Bit Tracking A/D Converter Using PLS179	537
	PLUSEO1 Programmable Magra Logic Primer	547
		547
		562
		562
	NAND Gate Flip-Flops	569
Chapter 2	Functional Fit	572
Chapter 3	Design Examples	575
Chapter 4	Successor Architectures	580
	Series 20 PLS155 PLS157 PLS159A Series 24 PLS167/A PLS168/A PLS179 PLC42VA12 Series 28 PLC415–16 PLS105/A PLUS105–40 PLUS105–55 PLUS405–55 PLUS	PLS155

January 1990

Contents

Chapter 5	Support issues	581
Chapter 6	PLHS501 Examples Using AMAZE Revision 1.6	582
	Simple Gate Implementations	582
	8-Bit Barrel Shifter	585
	12-Bit Comparator with Dual 1-of-8 Decoders	591
	8-Bit Carry Look-Ahead Adder	594
	32-to-5-Bit Priority Encoder	597
	8–Bit Shift Register with Sequence Detector	602
	4-Bit Synchronous Counter	608
DI USENI Application No		000
	otes, Vol. 2: Designing with Programmable Macro Logic	640
Chapter 1	Introduction	612
Chapter 2	PLHS501 Review	613
Chapter 3	Flip-Flop Basics	615
	Notation	615
	Flip—Flop Merging	615
Chapter 4	VME Bus Examples	621
	Omnibyte VSBC20 Mailbox Interrupt Structure	621
	VME Bus EPROM Interface	626
Chapter 5	Micro Channel Interface	633
Chapter 6	NuBus Interface	638
Chapter 7	Nuggets	644
	Data Bus Parity	644
	Data Bus Operations	651
PLHS502 Application No	otes, Vol. 1: Designing with Programmable Macro Logic	
Chapter 1	Introduction	652
Chapter 2	Development Support	654
Chapter 3	Capacity and Partitioning Considerations	656
Chapter 4	State Machine Design	657
Chapter 5	· ·	668
	Additional Design Guidelines	
Chapter 6	Additional PLHS501 Applications	670
Chapter 7	Advanced Flip-Flop Merging	689
Programmable Logic De	sign and Application Notes	
	Introduction	691
	Acknowledgements	691
	AMAZE Software	691
	on	691
Chapter 1	PLA Devices	692
	Signetics PLUS153D	692
	Signetics PLUS173D	692
	The PLHS473	692
Chapter 2	PAL-Type Devices	696
·	Signetics PLHS18P8B	696
	The PLUS16L8D and –7	698
	The PLUS16R8D and –7	699
	The PLUS20L8D and –7	700
	The PLUS20R8D and –7	701
	The PLC18V8Z	701
Chapter 3	Sequencer Devices	703
Onapter 5	Introduction	703
	State Equation Tutorial	704
		704
	The PLUS105	
	The PLS155	707
	The PLS157	708
	The PLS159A	709
	TI DI 04074	
	The PLS167A The PLS168A	710 711

January 1990 vii

Contents

		The PLS179 The PLUS405	712 713
	Application Section Introdu	uction	715
			715
	Chapter 4	Microprocessor Interfacing with Signetics PLDs	
		Introduction	715
		System Partitioning	715
		Bus Size Decoding for the 68020 — PLUS18P8B	716
		Interfacing to SPARC — PLUS20L8–7	717
		The 80386 Pipeline Decoder — PLUS153D	721
		68030 Address Decoding — PLUS173D	725
		The 29000, SRAM and the PLUS20L8D	727
		Interrupt Handler — PLS179	730
		SCSI Target Interface — PLS105A and PLUS153B	735
		Introduction	735
		Functional Description	735
		Programmer's Interface	735
		Port Operation	736
		Arbitration Software Sequence	737
		RESELECT Software Sequence	737
		TRANSFER Software Sequence	737
		DISCONNECT Software Sequence	737
		Hardware Description	738
	Chapter 5	Communications using PLDs	750
		The CCITT V2.7 Scrambler — PLC18V8Z	750
		A Novel Speech Synthesizer — PLS159A	752
		CCITT Forward CRC Polynomial — PLUS405	755
	Chapter 6	Instrumentation	757
		Heart Beat Monitor — PLS159A, PLS168A and PLS153	757
		The Pulse Width Monitor — PLS168	764
		Scope Trace Sweep Circuit — PLS153 and PLS155	769
	Charter 7		772
	Chapter 7	General Applications	
	01	Motor Stepper Controller with the PLS155	772
	Chapter 8	Security Systems	776
		A Programmable Alarm System — PLS168	776
Se	ction 10 – Package Outlin	es	
	A	Plastic Leaded Chip Carrier	785
	F	Ceramic Dual-In-Line	788
	FA	Ceramic Dual-In-Line with Quartz Window	790
	LA	Ceramic Leaded Chip Carrier with Quartz Window	792
	N	·	
	IN	Plastic Dual-In-Line	793
Sec	ction 11 – Sales Offices		700
	Office Listing		799

January 1990 viii

Section 1 General Information

Programmable Logic Devices

INDEX

Alphanumeric Index	3
Selection Guide	4
Ordering Information	6

Alphanumeric Index

Programmable Logic Devices

AN7		Single Chip Multiprocessor Arbiter	
AN8		Introduction to Signetics Programmable Logic	
AN11		PLD Programmable Retriggerable One–Shot	
AN14		Latches and Flip—Flops with PLS153	
AN15 AN18		PLS159 Primer Schmitt Trigger Using PLS153 and PLS159	4/0
AN21		9–Bit Parity Generator/Checker with PLS153/153A	407
AN23		PLS168/168A Primer	
AN24		PLS173 as a 10–Bit Comparator, 74LS460	
AN26		PLHS18P8A Primer	
AN27		PLHS473 Primer	
AN28		High-Speed 12-Bit Tracking A/D Converter Using PLS179	
AN29		PLHS501 Programmable Macro Logic Primer	
PHD16N8-5	Series 20	Programmable High-Speed Decoder (16 \times 16 \times 8); 5ns	
PHD48N22-7	Series 68	Programmable High-Speed Decoder (48 \times 73 \times 22); 7.5ns	
PLC18V8Z/I	Series 20	PAL [®] -Type Devices	
PLC42VA12	Series 24	CMOS Programmable Logic Sequencer (42 \times 105 \times 12); 25MHz $\ \ldots \ \ldots$	
PLC415-16	Series 28	Programmable Logic Sequencer (17 \times 68 \times 8); 16MHz	
PLHS16L8A/B	Series 20	$PAL^{\textcircled{\tiny{\textbf{B}}}}-Type \ Devices \ (16\times 64\times 8) \$. 39
PLHS18P8A/B	Series 20	PAL [®] -Type Devices	
PLHS473	Series 24	Programmable Logic Array (20 \times 24 \times 11); 22ns	
PLHS473S	Series 24	Programmable Logic Array (20 \times 24 \times 11); 25ns	
PLHS501		Programmable Macro Logic	
PLHS502		Programmable Macro Logic	
PLHS601	Ci 00	Programmable Macro Logic	
PLS100/101	Series 28	Programmable Logic Arrays (16 × 48 × 8); 50ns	
PLS105/A	Series 28	Programmable Logic Sequencers (16 × 48 × 8); 14, 20MHz	
PLS153/A	Series 20	Programmable Logic Arrays (18 × 42 × 10); 40/30ns	
PLS155	Series 20	Programmable Logic Sequencer (16 × 45 × 12); 14MHz	
PLS157	Series 20	Programmable Logic Sequencer (16 × 45 × 12); 14MHz	
PLS159A	Series 20	Programmable Logic Sequencer (16 × 45 × 12); 18MHz	
PLS167/A	Series 24	Programmable Logic Sequencers (14 × 48 × 6); 14, 20MHz	
PLS168/A	Series 24	Programmable Logic Sequencers (12 × 48 × 8); 14, 20MHz	
PLS173	Series 24	Programmable Logic Array $(22 \times 42 \times 10)$; 30ns	
PLS179	Series 24	PAL® –Type Devices	
PLUS16R8D/-7	Series 20	PAL®—Type Devices PAL®—Type Devices	
PLUS20R8D/-7	Series 24 Series 28	Programmable Logic Sequencer (16 × 48 × 8); 40MHz	305
PLUS105-40	Series 28	Programmable Logic Sequencer (16 × 48 × 8), 40MHz	
PLUS105-55	Series 28 Series 20	Programmable Logic Sequencer (16 × 48 × 8); 55MHZ Programmable Logic Arrays (18 × 42 × 10); 15/12ns	
PLUS153B/D	Series 20 Series 20	Programmable Logic Arrays (18 × 42 × 10); 15/12/15	
PLUS153-10	Series 24	Programmable Logic Arrays (18 × 42 × 10); 10/18 Programmable Logic Arrays (22 × 42 × 10); 15/12ns	
PLUS173B/D			
PLUS173-10 PLUS405-37/-45	Series 24 Series 28	Programmable Logic Array ($22 \times 42 \times 10$); 10ns	
PLUS405-37/-45 PLUS405-55	Series 28	Programmable Logic Sequencers (16 × 64 × 8); 37, 45MHz	
PML2552	Selles 28	Programmable Macro Logic	
10H20EV8/10020EV8	Sprips 24	ECL PAL®—Type Devices	
INITAL AN INNTAL AN	001103 L4	LULIAL - 1700 D07 1000	. 01

Selection Guide

Programmable Logic Devices

SIGNETICS PART NUMBER	ARCHITECTURE (INPUTS × TERMS × OUTPUTS)	PACKAGE	TOTAL INPUTS (# Dedicated)	LOGIC TERMS	INTERNAL STATE REGISTERS (# Dedicated)	OUTPUTS C, I/O, R, R I/O	t _{PD} (Max)	f _{MAX}	I _{CC} (Max)
PAL [®] -TYPE DEVICES									
PLUS16L8-7	16×64×8	20-Pin	16 (10)	64	0	2 C, 6 I/O	7.5ns		180mA
PLUS16R4-7	16×64×8	20-Pin	16 (8)	64	4 (0)	4 VO, 4 R	7.5ns	74MHz	180mA
PLUS16R6-7	16×64×8	20-Pin	16 (8)	64	6 (0)	2 I/O, 6 R	7.5ns	74MHz	180mA
PLUS16R8-7	16 × 64 × 8	20-Pin	16 (8)	64	8 (0)	8 R		74MHz	180mA
PLUS16L8D	16 × 64 × 8	20-Pin	16 (10)	64	0	2 C, 6 I/O	10ns		180mA
PLUS16R4D	16×64×8	20-Pin	16 (8)	64	4 (0)	4 I/O, 4 R	10ns	60MHz	180mA
PLUS16R6D	16×64×8	20-Pin	16 (8)	64	6 (0)	2 VO, 6R	10ns	60MHz	180mA
PLUS16R8D	16×64×8	20-Pin	16 (8)	64	8 (0)	8 R		60MHz	180mA
PLUS20L8-7	20 × 64 × 8	24-Pin	20 (14)	64	0	2 C, 6 I/O	7.5ns		210mA
PLUS20R4-7	20 × 64 × 8	24-Pin	20 (12)	64	4 (0)	4 VO, 4 R	7.5ns	74MHz	210mA
PLUS20R6-7	20 × 64 × 8	24-Pin	20 (12)	64	6 (0)	2 VO, 6 R	7.5ns	74MHz	210mA
PLUS20R8-7	20 × 64 × 8	24–Pin	20 (12)	64	8 (0)	8 R		74MHz	210mA
PLUS20L8D	20×64×8	24-Pin	20 (14)	64	0	2 C, 6 I/O	10ns		210mA
PLUS20R4D	20 × 64 × 8	24-Pin	20 (12)	64	4 (0)	4 I/O, 4R	10ns	60MHz	210mA
PLUS20R6D	20×64×8	24–Pin	20 (12)	64	6 (0)	2 I/O, 6 R	10ns	60MHz	210mA
PLUS20R8D	20×64×8	24-Pin	20 (12)	64	8 (0)	8 R		60MHz	210mA
PLHS16L8A	16×64×8	20-Pin	16 (10)	64	0	2 C, 6 I/O	20ns		155mA
PLHS16L8B	16×64×8	20-Pin	16 (10)	64	0	2 C, 6 I/O	15ns		155mA
PLHS18P8A	18×72×8	20-Pin	18 (10)	72	0	8 I/O	20ns		155mA
PLHS18P8B	18×72×8	20-Pin	18 (10)	72	0	8 I/O	15ns		155mA
PHD16N8-5	16×16×8	20-Pin	16 (10)	16	0	2 C, 6 I/O	5ns		180mA
PHD48N22-7**	48 × 73 × 22	68–Pin	48 (36)	73	0	10 C, 12 I/O	7.5ns		420mA
PLC18V8Z/18V8ZI	18×74×8	20-Pin	18 (8)	74	8 (0)	8 varied	35, 40ns	21MHz	100μA, 1mA/MHz
10H20EV8/10020EV8**	20 × 90 × 8	24-Pin	20 (12)	90	0	8 varied	4.5ns	222MHz	230mA
PLA									
PLS100/101	16×48×8	28–Pin	16 (16)	48	0	8 C	50ns		170mA
PLS153	18 × 42 × 10	20-Pin	18 (8)	42	0	10 I/O	40ns		155mA
PLS153A	18×42×10	20-Pin	18 (8)	42	0	10 VO	30ns		155mA
PLUS153B	18×42×10	20-Pin	18 (8)	42	0	10 VO	15ns		200mA
PLUS153D	18×42×10	20-Pin	18 (8)	42	0	10 VO	12ns		200mA
PLUS153-10**	18×42×10	20-Pin	18 (8)	42	0	10 VO	10ns		200mA
PLS173	22×42×10	24-Pin	22 (12)	42	0	10 I/O	30ns		170mA
PLUS173B	22×42×10	24–Pin	22 (12)	42	0	10 VO	15ns		200mA
PLUS173D	22×42×10	24-Pin	22 (12)	42	0	10 I/O	12ns		200mA
PLUS173-10**	22×42×10	24-Pin	22 (12)	42	0	10 I/O	10ns		200mA
PLHS473	20 × 42 × 11	24–Pin	20 (11)	24	0	2 C, 9 I/O	22ns		155mA
PLHS473S**	20 × 42 × 11	24–Pin	20 (11)	24	0	2 C, 9 I/O	25ns		155mA

Selection Guide

SIGNETICS PART NUMBER	ARCHITECTURE (INPUTS×TERMS ×OUTPUTS)	PACKAGE	TOTAL INPUTS (# Dedicated)	LOGIC TERMS	INTERNAL STATE REGISTERS (# Dedicated)	OUTPUTS C, I/O, R, R I/O	t _{PD} (Max)	f _{MAX}	I _{CC} (Max)
PLS			•		9.7	•	*		
PLS105	22×48×8	28-Pin	22 (16)	48	6 (6)	8 R		14MHz	180mA
PLS105A	22×48×8	28-Pin	22 (16)	48	6 (6)	8 R		20MHz	180mA
PLS105-40	22 × 48 × 8	28-Pin	22 (16)	48	6 (6)	8 R		40MHz	200mA
PLS105-55**	22 × 48 × 8	28-Pin	22 (16)	48	6 (6)	8 R		55MHz	200mA
PLUS405-37	24 × 64 × 8	28-Pin	24 (16)	64	8 (8)	8 R		37MHz	225mA
PLUS405-45	24 × 64 × 8	28-Pin	24 (16)	64	8 (8)	8 R		45MHz	225mA
PLUS405-55**	24 × 64 × 8	28-Pin	24 (16)	64	8 (8)	8 R		55MHz	225mA
PLS155	16×45×12	20-Pin	16 (4)	45	4 (0)	8 I/O, 4 R I/O	50ns	14MHz	190mA
PLS157	16×45×12	20-Pin	16 (4)	45	6 (0)	6 I/O, 6 R I/O	50ns	14MHz	190mA
PLS159A	16×45×12	20-Pin	16 (4)	45	8 (0)	4 I/O, 8 R I/O	35ns	18MHz	190mA
PLS167	22 × 48 × 6	24-Pin	22 (14)	48	8 (6)	6 R		14MHz	180mA
PLS167A	22 × 48 × 6	24-Pin	22 (14)	48	8 (6)	6 R		20MHz	180mA
PLS168	22×48×6	24-Pin	22 (12)	48	10 (6)	8 R		14MHz	180mA
PLS168A	22×48×6	24-Pin	22 (12)	48	10 (6)	8 R		20MHz	180mA
PLS179	20×45×12	24-Pin	20 (8)	45	8 (0)	4 I/O, 8 R I/O	35ns	18MHz	210mA
PLC42VA12**	42×105×12	24-Pin	42 (10)	105	10 (0)	10 C or R I/O, 2 I/O	35ns	25MHz	90mA*
PLC415-16	25 × 68 × 8	28-Pin	25 (17)	68	8 (8)	8 R			100µA/ 80mA
PML TM			•			•			
PLHS501	104×116×24	52–Pin	24	116	0	16 C, 8 I/O	22ns		295mA
PLHS502	128 × 144 × 24	68–Pin	24	144	16 (16)	16 C or R, 8 I/O or R I/O	20ns	50MHz	370mA
PLHS601**	68 × 134 × 24	68-Pin	28	134	0	12 C, 12 I/O	20ns		340mA
PML2552**	185 × 226 × 24	68–Pin	29	226	36 (20)	24 C, 16 R, 16 I/O	40, 50ns	50, 33MHz	100mA

PAL-Type = Programmable Array Logic (Fixed OR Array)-Type
PHD = Programmable High-Speed Decoder
PLA = Programmable Logic Array
PLS = Programmable Logic Sequencer
PML = Programmable Macro Logic

OUTPUTS:

C = Combinatorial output
R = Registered output
I/O = Combinatorial I/O
R I/O = Registered I/O

** Under development

**Hoder development

**AMD Trademark of AMD/MMI.

**AMD Trademark of AMD/MMI.

**AMD Trademark of AMD/MMI.

PML is a trademark of Philips Components-Signetics.

Ordering Information

Programmable Logic Devices

Signetics Programmable Logic Devices may be ordered by contacting either the local Signetics sales office, Signetics representatives or authorized distributors. A complete listing is located in the back of this handbook.

Table 1 provides part number definition for Signetics PLDs. The Signetics part number system allows complete ordering information to specified in the part number. The part number and product description is located on each data sheet.

Military versions of these commercial products may be ordered. Please refer to the military products data handbook for complete ordering information.

New Signetics PLD Part Numbering System

(L)	XX	YYYY	Z	Р	
					 Package Designator F - 20-, 24-, 28-Pin CERDIP DIP N - 20-, 24-, 28-Pin Plastic DIP A - 20-, 28-lead Plastic Leaded Chip Carrier FA - 20-, 24-Pin CERDIP DIP with Quartz Window Performance Indicator (May be blank, A, B, D, etc. to designate speed variatic basic part.) Basic Part Number
					(3 to 8 characters) (e.g., 100, 105, 153, 168, 173, 18P8, 42VA12) Process/Architecture Indicator S - Bipolar Junction Isolated Schottky - Nichrome fu C - CMOS - EPROM cells HS - High Speed Bipolar Oxide Isolated - Vertical Fus US - High Speed Bipolar Oxide Isolated - Lateral Fus HD - High Speed Decoder ML - Macro Logic (Blank for ECL devices) Indicator for Signetics Programmable Logic (Can be either P, PL, or blank) (P for PHD and PML and blank for ECL devices)

Section 2 Introduction

Programmable Logic Devices

INI	n	v
11.4	$\boldsymbol{\nu}$	$\mathbf{\Lambda}$

What is	Signetics Prog	rammable	Logic	 	 9
Quality	and Reliability			 	 27




Introduction Signetics Programmable Logic

Programmable Logic Devices

WHAT IS PROGRAMMABLE LOGIC

In 1975, Signetics Corporation developed a new product family by combining its expertise in semi-custom gate array products and fuse-link Programmable Read Only Memories (PROMs). Out of this marriage came Signetics Programmable Logic Family. The PLS100 Field— Programmable Logic Array (FPLA) was the first member of this family. The FPLA was an important industry first in two ways. First, the AND/OR/INVERT archi-

tecture allowed the custom implementations of Sum of Product logic equations. Second, the three-level fusing allows complete flexibility in the use of this device family. All logic interconnections from input to output are programmable.




Introduction

Table 1. PLD Product Family

PART NUMBER	TYPE	CONFIGURATION		
	20-PIN			
PHD16N8	PHD	12-Input/8-Output		
PLS153/153A	PLA	18-Input/10-Output - 42-Term		
PLUS153B/153D/153-10	PLA	18-Input/10-Output - 42-Term		
PLS155-159A	PLS	16-Input/12-Output - 45-Term		
PLS155	PLS	4 Registered Outputs		
PLS157	PLS	6 Registered Outputs		
PLS159A	PLS	8 Registered Outputs		
PLHS18P8A/B	PAL-Type	18-Input/10-Output - 72-Term		
PLHS16L8A/B	PAL-Type	16-Input/8-Output - 64-Term		
PLC18V8Z/I	PAL-Type	18-Input/8-Output - 72-Term		
PLUS16L8D/-7	PAL-Type	16-Input/8-Output - 72-Term		
PLUS16R4D/-7	PAL-Type	16-Input/4-Output, 4 Registers		
PLUS16R6D/7	PAL-Type	16-Input/6-Output, 6 Registers		
PLUS16R8D/-7	PAL-Type	16-Input/8-Output, 8 Registers		
	24-PIN			
PLS167/A	PLS	14-Input/6-Output - 48-Term 8-Bit State Registers 6-Output Registers		
PLS168/A	PLS	12-Input/8-Output - 48-Term 10-Bit State Registers 8-Output Registers		
PLS173/PLUS173B/D/-10	PLA	22-Input/10-Output - 42-Term		
PLS179	PLS	22-Input/10-Output - 42-Term		
PLHS473	PLA	20-Input/11-Output - 24-Term		
PLC42VA12	PLS	42-Input/12-Output, 10 Registers		
PLUS20L8D/-7	PAL-Type	20-Input/8-Output		
PLUS20R4D/-7	PAL-Type	20-Input/4-Output		
PLUS20R6D/-7	PAL-Type	20-Input/6-Output		
PLUS20R8D/-7	PAL-Type	20-Input/8-Output		
	28-PIN			
PLS100/101	PLA	16-Input/8-Output - 48-Term		
PLS105/105A/PLUS105	PLS	16-Input/8-Output - 48-Term 6-Bit State Register 8-Output Registers		
PLUS405	PLS	16-Input/8-Output - 64-Term 8-Bit State and Output Registers		
	52-, 68-PIN	l		
PLHS501	PML	32-Input/24-Output - 116-Term		
PLHS502	PML	32-Input/24-Output - 144-Term		
PLHS601	PML	40-Input/24-Output - 150-Term		
PML2552	PML	55-Input/24-Output - 226-Term		
PHD48N22	PHD	48-Input/22-Output		

Introduction




Introduction


PLD LOGIC SYNTHESIS

No intermediate step is required to implement Boolean Logic Equations with PLDs. Each term

in each equation simply becomes a direct entry into the Logic Program Table. The following example illustrates this straightforward concept: $X_0 = AB + \overline{C}D + B\overline{D}$

$$\overline{X}_1 = \overline{A}B + \overline{C}D + EFG$$






Introduction

In the previous example, the two Boolean Logic equations were broken into Product terms. Each P-term was then programmed into the P-term section of the PLA Program Table. This was accomplished in the following manner:

Step 1

Select which input pins I₀ - I₁₅ will correspond to the input variables. In this case A - G are the input variable names. I₆ through Io were selected to accept inputs A - G respectively.




Step 2

Transfer the Boolean Terms to the PLA Program Table. This is done simply by defining each term and entering it on the Program Table.

e.g., $P_0 = AB$

This P-term translates to the Program Table by selecting $A = I_6 = H$ and $B = I_5 = H$ and entering the information in the appropriate column.


This term is defined by selecting $C = I_4 = L$ and $D = I_3 = H$, and entering the data into the Program Table. Continue this operation until all P-terms are entered into the Program Table.



January 1990 13

Introduction


Step 3 Select which output pins correspond to each output function. In this case $F_0 = Pin 18 = X_0$, and $F_1 = Pin 17 = X_1$.



Step 4
Select the Output Active Level desired for each Output Function. For X₀ the active level

is high for a positive logic expression of this equation. Therefore, it is only necessary to place an (H) in the Active Level box above Out-

put Function 0, (F_0) . Conversely, X_1 can be expressed as X_1 by placing an (L) in the Active Level box above Output Function 1, (F_1) .



Introduction

Step 5


Select the P–Terms you wish to make active for each Output Function. In this case $X_0 = P_0 + P_1 + P_2$, so an A has been placed in the intersection box for P_0 and X_0 , P_1 and X_0 and P_2 and X_0 .

Terms which are not active for a given output are made inactive by placing a (•) in the box under that P-term. Leave all unused P-terms unprogrammed.

Continue this operation until all outputs have been defined in the Program Table.

Step 6

Enter the data into a Signetics approved programmer. The input format is identical to the Signetics Program Table. You specify the P-terms, Output Active Level, and which P-terms are active for each output exactly the way it appears on the Program Table.



Introduction


PLD LOGIC SYNTHESIS


(Continued)

When fewer inputs and outputs are required in a logic design and low cost is most important, the Signetics 20—pin PLD should be considered

first choice. The PLUS153 is a PLA with 8 inputs, 10 I/O pins, and 42 product terms. The user can configure the device by defining the direction of the I/O pins. This is easily accomplished by using the direction control terms

 D_0-D_θ to establish the direction of pins B_0-B_θ . The D-terms control the 3–State buffers found on the outputs of the Ex–OR gates. Figures 10 and 11 show how the D-term configures each B_χ pin.







Introduction

To control each D-term, it is necessary to understand that each control gate is a 36-input AND gate. To make the 3-State buffer active (B_x pin an output), the output of the control gate must be at logic HIGH (1). This can be accomplished in one of two ways. A HIGH can

be forced on all control gate input nodes, or fuses can be programmed. When a fuse is programmed, that control gate input node is internally pulled up to HIGH (1). See Figure 12 and Figure 13.

Programming the fuse permanently places a HIGH (1) on the input to the control gate. The input pin no longer has any effect on that state.





Introduction


DEDICATING B_X PIN DIRECTION

Since each input to the D-terms is true and complement buffered (see Figure 11), when the device is shipped with all fuses intact, all control gates have half of the 36 input lines at logic low (0). The result of this is all Control Gate outputs are low (0) and the 3-State buffers are inactive. This results in all B_X pins being in the input condition, the resultant device is, therefore, an 18-input, 0-output FPLA. While useful as a bit

bucket or Write–Only–Memory (WOM), most applications require at least one output. Clearly, the first task is to determine which of the B_X pins are to be outputs. The next step is to condition the control gate to make the 3–State buffer for those gates active. To dedicate B_0 and B_1 as outputs, it is necessary to program all fuses to the inputs to Control Gates D_0 and D_1 . This internally pulls all inputs to those gates to HIGH (1) permanently. since all inputs to the Control

Gates are HIGH (1), the output is HIGH (1) and the 3–State buffers for B_0 and B_1 are active. This permanently enables B_0 and B_1 as outputs. Note that even though B_0 and B_1 are outputs, the output data is available to the AND array via the internal feedback (see Figure 11a).

To program this data, the PLUS153 Program Table is used as shown in Figure 14.



Introduction


By placing a (—) Don't Care in each input box you are specifying that the True and Complement fuses are programmed on each Control Gate, thus permanently dedicating the B_0 and B_1 pins as outputs. By placing a (0) in all input boxes for B_2-B_9 , you are specifying that both True and Complement fuses are intact. This causes a low (0) to be forced on half of the Control Gate inputs, guaranteeing the output of the Control Gate outputs are low (0). When the Control Gate outputs are low (0), the 3–State buffer is inactive and the B_2-B_9 pins are

enabled as inputs. All B_X pin directions can be controlled in this manner

ACTIVE DIRECTION CONTROL

Sometimes it is necessary to be able to actively change the direction of the B_X pins without permanently dedicating them. Some applications which require this include 3—State bus enable, multi–function decoding, etc. This can easily be

done by programming the Control Gate to respond to one or more input pins. It is only necessary to select which I_X and B_X pins will control the pin directions and the active level HIGH (H) or LOW (L) that will be used. The PLUS153 Program Table in Figure 15 shows the method of controlling B_0-B_9 with I_7 . When I_7 is LOW (L), pins B_0-B_9 are outputs; when I_7 is HIGH (H), pins B_0-B_9 are inputs. Note that by programming all other I_X and B_X pins as DON'T CARE (—), they are permanently disconnected from control of B_X pin direction.



Introduction

The previous 28-pin logic synthesis example could be done on the PLUS153 as follows:

$$X_0 = AB + \overline{C}D + B\overline{D}$$


$$\overline{X}_1 = \overline{A}B + \overline{C}D + EFG$$

Note that B_0 was used as a CHANGE input. When B_0 is HIGH (H) the outputs appear on B_8 and B_9 . When B_0 is LOW (L), the outputs ap-

pear on B₆ and B₇. B₁ through B₅ are not used and therefore left unprogrammed.

Signetics offers two packages for user friendly design assistance. The first package, AMAZE, has evolved over 10 years to support Signetics programmable products with logic equation, state equation, and schematic entry. AMAZE can compile designs quite well for Signetics

lower density parts. However, to satisfy the needs of Programmable Macro Logic users, Signetics developed an additional software package called SNAP. SNAP expands upon the capabilities of AMAZE in its approach to design implementation, more closely resembling a gate array methodology. Both of these products are described in more depth at a later point in this handbook.



Introduction

SEQUENTIAL LOGIC CONSIDERATIONS

The PLUS405, PLUS105 and PLC42VA12 represent significant increases in complexity when compared to the combinatorial logic devices previously discussed. By combining the AND/OR combinatorial logic with clock output flip—flops and appropriate feedback, Signetics has created the first family of totally flexible sequential logic machines.

The PLUS405 (Programmable Logic Sequencer) is an example of a high-order machine whose applications are many. Application areas for this device include VRAM, DRAM, Bus and LAN control. The PLUS405 is fully capable of performing fast sequential operations in relatively high-speed processor systems. By placing repetitive sequential operations on the PLUS405, processor overhead is reduced.

The following pages summarize the PLUS405 architecture and features.

Sequencer Architecture

The PLUS405 Logic Sequencer is a programmable state machine, in which the output is a function of the present state and the present input.

With the PLUS405, a user can program any logic sequence expressed as a series of jumps between stable states, triggered by a valid input condition (I) at clock time (t). All stable states are stored in the State Register. The logic output of the machine is also programmable, and is stored in the Output Register. The PLUS105 is a subset of the PLUS405.

Clocked Sequence

A synchronous logic sequence can be represented as a group of circles interconnected with arrows. The circles represent stable states, labeled with an arbitrary numerical code (binary, hex, etc.) corresponding to discrete states of a suitable register. The arrows represent state transitions, labeled with symbols denoting the jump condition and the required change in output. The number of states in the sequence depends on the length and complexity of the desired algorithm.




Figure 17. Basic Architecture of PLS105 FPLS. I, P, N, and F are Multi-line Paths Denoting Groups of Binary Variables Programmed by The User.




Figure 18. Typical State Diagram. I_{1-3} Are Jump Conditions Which Must be Satisfied Before Any Transitions Take Place. F_r Are Changes in Output Triggered by I_{m_r} , and Stored in The Output Register. State Transitions a \rightarrow b and c \rightarrow d Involve No Output Change.




Figure 19. Typical State Transition Between Any Two States of Figure 18. The Arrow Connecting the Two States Gives Rise to a Transition Term T_n. I is the Jump Condition.

Introduction


State Jumps

The state from which a jump originates is referred to as the Present state (P), and the state to which a jump terminates is defined as the Next state (N). A state jump always causes a change in state, but may or may not cause a change in machine output (F).


State jumps can occur only via "transition terms" Tn. These are logical AND functions of the clock (t), the Present state (P), and a valid input (I). Since the clock is actually applied to the State Register, T_n = I P. When T_n is "true", a control signal is generated and used at clock time (t) to force the contents of the State Register from (P) to (N), and to change the contents of the Output Register (if necessary). The simple state jump in Figure 20, involving 2 inputs, 1 state bit, and 1 output bit, illustrates the equivalence of discrete and programmable logic implementations.

Sequencer Logic Structure

The Sequencer consists of programmable AND and OR gate arrays which control the Set and Reset inputs of a State Register, as well as monitor its output via an internal feedback path. The arrays also control an independent Output Register, added to store output commands generated during state transitions, and to hold the output constant during state sequences involving no output changes. If desired, any number of bits of the Output Register can be used to extend the width of the State Register, via external feedback.



if Inputs A = B = "1". The Jump Also Forces F = "1", as Required.



January 1990 22

Introduction





Figure 22. Typical AND Gate Coupled to (I) and (P) Inputs. If at Least One Link Pair Remains Intact, T_n is Unconditionally Forced Low.






Figure 24. Typical Transition Terms Involving Arbitrary Inputs and State Variables. All Remaining Gate Inputs Are Programmed Don't Care. Note That T₂ Output is State Independent.

Input Buffers

16 external inputs (I_m) and 6 internal inputs (P_s), fed back from the State Register, are combined in the AND array through two sets of True/Complement (T/C) buffers. There are a total of 22 T/C buffers, all connected to multi–input AND gates via fusible links which are initially intert

Selective fusing of these links allows coupling either True, Complement, or Don't Care values of (I_m) and (P_s) .

"AND" Array

State jumps and output changes are triggered at clock time by valid transition terms T_n . These are logical AND functions of the present state (P) and the present input (I).

The PLUS105 AND Array contains a total of 48 AND gates. Each gate has 45 inputs – 44 connected to 22 T/C input buffers, and 1 dedicated to the Complement Array. The outputs of all AND gates are propagated through the OR Array, and used at clock time (t) to force the contents of the State Register from (P) to (N). they are also used to control the Output Register, so that the FPLS 8-bit output F_r is a function of the inputs and the present state. The PLUS405 contains 64 AND gates in its' AND array.

Introduction

"OR" Array

In general, a clocked sequence will consist of several stable states and transitions, as determined by the complexity of the desired algorithm. All state and output changes in the state diagram imply changes in the contents of State and Output Registers.

Thus, each flip—flop in both registers may need to be conditionally set or reset several times with T_n commands. This is accomplished by selectively ORing through a programmable OR Array all AND gate outputs T_n necessary to activate the proper flip—flop control inputs.

The PLUS105 OR Array consists of 14 pairs of OR gates, controlling the S/R inputs of 14 State and Output Register stages, and a single NOR gate for the Complement Array. All gates have 48 inputs for connecting to all 48 AND gates. The PLUS405 uses 64 input gates.

The PLUS405 contains 16 pairs of OR gates controlling state transitions and output stages and two additional NOR gates for dual complement arrays.

Complement Array

The COMPLEMENT Array provides an asynchronous feedback path from the OR Array back to the AND Array.

This structure enables the sequencer to perform both direct and complement sequential state jumps with a minimum of transition (AND)

Typically direct jumps, such as T_1 and T_2 in Figure 27 require only a single AND gate each.

But a complement jump such as T_3 generally requires many AND gates if implemented as a direct jump. However, by using the Complement Array, the logic requirements for this type of jump can be handled with just one more gate from the AND Array. Because it can be split into separate machines (2 clocks), the PLUS405 incorporates two COMPLEMENT Arrays.




Figure 25. Typical OR Array Gating of Transition Terms T_{1,2,3} Controlling Arbitrary State and Output Register Stages.





Figure 26. The COMPLEMENT Array is Logically Constructed from a multiple input Programmable NOR Gate. All AND Terms Coupled to the OR Gate are Complemented at the Inverter Output, and Can be Fed Back as Inputs to the AND Array.


Introduction



As indicated in Figure 28, the single Complement Array gate may be used for many states of the state diagram. This happens because all transition terms linked to the OR gate include the present state as a part of their conditional logic. In any particular state, only those transition terms which are a function of that state are enabled; all other terms coupled to different states are disabled and do not influence the output of the Complement Array. As a general rule of thumb, the Complement Array can be used as many times as there are states.

Figure 27. a. X And Y Specify the Conditional Logic for Direct Jump Transition Terms T_1 and T_2 . The Complement Jump Term T_3 is True Only When Both T_1 and T_2 are False. b. Note that the Complementary Logic Expression for T_3 , $\overline{T_1+T_2}$, Corresponds Exactly to the Logic Structure of the Complement Array.

Introduction



Additional features are available depending on a specific part. In particular, the PLC42VA12 has everything mentioned here, and more. More details on PLAs, PAL-Type devices and Sequencers can be found in the application section later in the manual.

Programmable Macro Logic, Signetics very high density logic is fully described in detail in its own section.

Signetics

Quality and Reliability

Programmable Logic Devices

SIGNETICS PROGRAMMABLE LOGIC QUALITY

Signetics has put together winning processes for manufacturing Programmable Logic. Our standard is zero defects, and current customer quality statistics demonstrate our commitment to this goal.

The PLDs produced in the Standard Products Group must meet rigid criteria as defined by our design rules and as evaluated with a thorough product characterization and quality process. The capabilities of our manufacturing process are measured and the results evaluated and reported through our corporate—wide QA05 data base system. The SURE (Systematic Uniform Peliability Evaluation) program monitors the performance of our productin a variety of accelerated environmental stress conditions. All of these programs and systems are intended to prevent product—related problems and to inform our customers and employees of our progress in achieving zero defects.

RELIABILITY BEGINS WITH THE DESIGN

Quality and reliability must begin with design. No amount of extra testing or inspection will produce reliable ICs from a design that is inherently unreliable. Signetics follows very strict design and layout practices with its circuits. To eliminate the possibility of metal migration, current density in any path cannot exceed 2 × 10⁵ amps/cm². Layout rules are followed to minimize the possibility of shorts, circuit anomalies, and SCR type latch—up effects. Numerous ground—to—substrate connections are required to ensure that the entire chip is at the same ground potential, thereby precluding internal noise problems.

PRODUCT CHARACTERIZATION

Before a new design is released, the characterization phase is completed to insure that the distribution of parameters resulting from lot-to-lot variations is well within specified limits. Such extensive characterization data also provides a

basis for identifying unique application—related problems which are not part of normal data sheet guarantees. Characterization takes place from -55°C to +125°C and at \pm 10% supply voltage.

QUALIFICATION

Formal qualification procedures are required for all new or changed products, processes and facilities. These procedures ensure the high level of product reliability our customers expect. New facilities are qualified by corporate groups as well as by the qualify organizations of specific units that will operate in the facility. After qualification, products manufactured by the new facility are subjected to highly accelerated environmental stresses to ensure that they can meet rigorous failure rate requirements. New or changed processes are similarly qualified.

QA05 — QUALITY DATA BASE REPORTING SYSTEM

The QA05 data reporting system collects the results of product assurance testing on all finished lots and feeds this data back to concerned organizations where appropriate action can be taken. The QA05 reports EPQ (Estimated Process Quality) and AOQ (Average Outgoing Quality) results for electrical, visual/mechanical, hermeticity, and documentation audits. Data from this system is available upon request.

THE SURE PROGRAM

The SURE (Systematic Uniform Reliability Evaluation) program audits/monitors products from all Signetics' divisions under a variety of accelerated environmental stress conditions. This program, first introduced in 1964, has evolved to suit changing product complexities and performance requirements.

The SURE program has two major functions: Long-term accelerated stress performance audit and a short-term accelerated stress monitor. In the case of Bipolar Memory and Programmable Logic products, samples are selected that represent all generic product groups in all wafer fabrication and assembly locations.

THE LONG-TERM AUDIT

One-hundred devices from each generic family are subjected to each of the following stresses every eight weeks:

- High Temperature Operating Life:
 T_J = 150°C, 1000 hours, static biased or dynamic operation, as appropriate (worst case bias configuration is chosen)
- High Temperature Storage: T_J = 150°C, 1000 hours
- Temperature Humidity Biased Life: 85°C, 85% relative humidity, 1000 hours, static biased
- Temperature Cycling (Air-to-Air): -65°C to +150°C, 1000 cycles

THE SHORT-TERM MONITOR

Every other week a 50-piece sample from each generic family is run to 168 hours of pressure pot (15psig, 121°C, 100% saturated steam) and 300 cycles of thermal shock (-65°C to +150°C).

In addition, each Signetics assembly plant performs SURE product monitor stresses weekly on each generic family and molded package by pin count and frame type. Fifty-piece samples are run on each stress, pressure pot to 96 hours, thermal shock to 300 cycles.

SURE REPORTS

The data from these test matrices provides a basic understanding of product capability, an indication of major failure mechanisms and an estimated failure rate resulting from each stress. This data is compiled periodically and is available to customers upon request.

Many customers use this information in lieu of running their own qualification tests, thereby eliminating time-consuming and costly additional testing.

January 1990 27

RELIABILITY ENGINEERING

In addition to the product performance monitors encompassed in the Programmable Logic SURE program, Signetics' Corporate and Division Reliability Engineering departments sustain a broad range of evaluation and qualification activities.

Included in the engineering process are:

- Evaluation and qualification of new or changed materials, assembly/wafer-fab processes and equipment, product designs, facilities and subcontractors
- Device or generic group failure rate studies
- Advanced environmental stress development
- Failure mechanism characterization and corrective action/prevention reporting

The environmental stresses utilized in the engineering programs are similar to those utilized for the SURE monitor; however, more highly-accelerated conditions and extended durations typify the engineering projects. Additional stress systems such as biased pressure pot, power-temperature cycling, and cycle-biased temperature-humidity, are also included in the evaluation programs.

FAILURE ANALYSIS

The SURE Program and the Reliability Engineering Program both include failure analysis activities and are complemented by corporate, divisional and plant failure analysis departments. These engineering units provide a service to our customers who desire detailed failure analysis support, who in turn provide Signetics with the technical understanding of the failure modes and mechanisms actually experienced in service. This information is essential in our ongoing effort to accelerate and improve our understanding of product failure mechanisms and their prevention.

ZERO DEFECTS PROGRAM

In recent years, United States industry has increasingly demanded improved product quality. We at Signetics believe that the customer has every right to expect quality products from a supplier. The benefits which are derived from quality products can be summed up in the words, lower cost of ownership.

Those of you who invest in costly test equipment and engineering to assure that incoming products meet your specifications have a special understanding of the cost of ownership. And your cost does not end there; you are also burdened with inflated inventories, lengthened lead times and more rework.

SIGNETICS UNDERSTANDS CUSTOMERS' NEEDS

Signetics has long had an organization of quality professionals, inside all operating units, coordinated by a corporate quality department. This broad decentralized organization provides leadership, feedback, and direction fo achieving a high level of quality.


In 1980 we recognized that in order to achieve outgoing levels on the order of 100ppm (parts per million), down from an industry practice of 10,000ppm, we needed to supplement our traditional quality programs with one that encompassed all activities and all levels of the company, such unprecedented low defect levels could only be achieved by contributions from all employees, from the R and D laboratory to the shipping dock. In short, from a program that would effect a total cultural change within Signetics in our attitude toward quality.

QUALITY PAYS OFF FOR OUR CUSTOMERS

Signetics' dedicated programs in product quality improvement, supplemented by close working relationships with many of our customers, have improved outgoing product quality more than twenty-fold since 1980. Today, many major customers no longer test Signetics circuits. Incoming product moves directly from the receiving dock to the production line, greatly accelerating throughput and reducing inventories. Other customers have pared significantly the amount of sampling done on our products. Others are beginning to adopt these costsaving practices.

We closely monitor the electrical, visual, and mechanical quality of all our products and review each return to find and correct the cause. Since 1981, over 90% of our customers report a significant improvement in overall quality (see Figure 1).

At Signetics, quality means more than working circuits. It means on-time delivery of the right product at the agreed-upon price. Signetics considers Performance to Customer Request and Performance to Original Schedule Date to be key Quality issues. Employees treat delinquencies as quality defects. They analyze the cause for the delinquency and seek corrective action to prevent future occurrence. Continuous effort is given to try to achieve the ultimate goal of zero delinquencies.



ONGOING QUALITY PROGRAM

The quality improvement program at Signetics is based on "Do It Right the First Time". The intent of this innovative program is to change the perception of Signetics' employees that somehow quality is solely a manufacturing issue where some level of defects is inevitable. this attitude has been replaced by one of acceptance of the fact that all errors and defects are preventable, a point of view shared by all technical and administrative functions equally.

This program extends into every area of the company, and more than 40 quality improvement teams throughout the organization drive its ongoing refinement and progress.

Key components of the program are the Quality College, the "Make Certain" Program, Corrective Action Teams, and the Error Cause Removal System.

The core concepts of doing it right the first time are embodied in the four absolutes of quality:

- The definition of quality is conformance to requirements.
- The system to achieve quality improvement is prevention.
- The performance standard is zero defects.
- The measurement system is continuous improvement.

"MAKING CERTAIN" — ADMINISTRATIVE QUALITY IMPROVEMENT

Signetics' experience has shown that the largest source of errors affecting product and service quality is found in paperwork and in other administrative functions. The "Make Certain" program focuses the attention of management and administrative personnel on error prevention, beginning with each employee's own actions.

This program promotes defect prevention in three ways: by educating employees as to the impact and cost of administrative errors, by changing attitudes from accepting occasional errors to one of accepting a personal work standard of zero defects, and by providing a formal mechanism for the prevention of errors.

CORRECTIVE ACTION TEAMS

Employees with the perspective, knowledge, and necessary skills to solve a problem are formed into ad hoc groups called Corrective Action Teams. These teams, a major force within the company for quality improvement, resolve administrative, technical and manufacturing issues.

ECR SYSTEM (ERROR CAUSE REMOVAL)

The ECR System permits employees to report to management any impediments to doing the job right the first time. Once such an impediment is reported, management is obliged to respond promptly with a corrective program. Doing it right the first time in all company activities produces lower cost of ownership through defect prevention.

PRODUCT QUALITY PROGRAM

To reduce defects in outgoing products, we created the Product Quality Program. This is managed by the Product Engineering Council, composed of the top product engineering and test professionals in the company, this group:


- Sets aggressive product quality improvement goals:
- provides corporate-level visibility and focus on problem areas:
- serves as a corporate resource for any group requiring assistance in quality improvement; and
- 4. drives quality improvement projects.

As a result of this aggressive program, every major customer who reports back to us on product performance is reporting significant progress.

VENDOR CERTIFICATION PROGRAM

Our vendors are taking ownership of their own product quality by establishing improved process control and inspection systems. They subscribe to the zero defects philosophy. Progress has been excellent.

Through intensive work with vendors, we have improved our lot acceptance rate on incoming materials as shown in Figure 2. Simultaneously, waivers of incoming material have been eliminated.



MATERIAL WAIVERS

1988 - 0

1987 -

1986 - 0

1985 - 0 1984 - 0

1983 - 0

1983 - 0

1981 –134

Higher incoming quality material ensures higher outgoing quality products.

QUALITY AND RELIABILITY ORGANIZATION

Quality and reliability professionals at the divisional level are involved with all aspects of the product, from design through every step in the manufacturing process, and provide product assurance testing of outgoing product. A separate corporate-level group provides direction and common facilities.

Quality and Reliability Functions

- Manufacturing quality control
- Product assurance testing
- Laboratory facilities failure analysis, chemical, metallurgy, thin film, oxides
- Environmental stress testing
- Quality and reliability engineering
- Customer liaison

January 1990

COMMUNICATING WITH EACH

For information on Signetics' quality programs or for any question concerning product quality, the field salesperson in your area will provide you with the quickest access to answers. Or, write on your letterhead directly to the corporate VP of quality at the corporate address shown at the back of this manual.

We are dedicated to preventing defects. When product problems do occur, we want to know about them so we can eliminate their causes. Here are some ways we can help each other:

- Provide us with one informed contact within your organization. This will establish continuity and build confidence levels.
- Periodic face-to-face exchanges of data and quality improvement ideas between your engineers and ours can help prevent problems before they occur.
- Test correlation data is very useful. Linepull information and field failure reports also help us improve product performance.
- Provide us with as much specific data on the problem as soon as possible to speed analysis and enable us to take corrective action.
- An advance sample of the devices in question can start us on the problem resolution before physical return of shipment.

This teamwork with you will allow us to achieve our mutual goal of improved product quality.

MANUFACTURING: DOING IT RIGHT THE FIRST TIME

In dealing with the standard manufacturing flows, it was recognized that significant improvement would be achieved by "doing every job right the first time", a key concept of the quality improvement program. During development of the program many profound changes were made. Figure 3, Programmable Logic Process Flow, shows the result. Key changes included such things as implementing 100% temperature testing on all products as well as upgrading test handlers to insure 100% positive binning. Some of the other changes and additions were to tighten the outgoing QA lot acceptance criteria to the tightest in the industry, with zero defect lot acceptance sampling across all three temperatures.


The achievements resulting from the improved process flow have helped Signetics to be recognized as the leading Quality supplier of Programmable Logic. These achievements have also led to our participation in several Ship-to-Stock programs, which our customers use to eliminate incoming inspection, such programs reduce the user cost of ownership by saving both time and money.

OUR GOAL: 100% PROGRAMMING YIELD

Our original goal back in the early 1970s was to develop a broad line of programmable products which would be recognized as having the best programming yield in the industry. Within the framework of a formal quality program, our efforts to improve circuit designs and refine manufacturing controls have resulted in major advances toward that goal.

Also within the framework of our formal quality program we have now established a stated goal of 100% programming yield. through the increasing effectiveness of a quality attitude of "Do It Right the First Time" we're moving ever closer to that target.

Signetics PLD programming yields have been shown in collected data from internal audits and customer reporting to be consistently higher than comparable devices produced by our competition. We use systematic methods involving publication of exacting specifications of our programming algorithms, and through evaluation of those algorithms as implemented in industry standard programming equipment. Because of this we can assure our customers who program Signetics PLDs on such qualified equipment they will see consistently high yields. Our data base shows that average lot programming yield exceeds 97%.




31

January 1990

As time goes on the drive for a product line that has Zero Defects will grow in intensity. These efforts will provide both Signetics and our customers with the ability to achieve the mutual goal of improved product quality.

The Customer Specific Quality Assurance department has monitored PPM progress, which can be seen in Figure 4. We are pleased with the progress that has been made, and expect to achieve even more impressive results as the procedures for accomplishing these tasks are fine tuned.



January 1990 32

The Customer Specific Reliability Department has established an ongoing Infant Mortality Monitor. This monitor is used to determine and drive ongoing Corrective Action for the purposes of continuously improving product reliability.

The real measure of any quality improvement program is the result that our customers see. The meaning of *Quality* is more than just working circuits. It means commitment to *On Time Delivery* at the *Right Place* of the *Right Quantity* of the *Right Product* at the *Agreed Upon Price*.

33

CMOS RELIABILITY INFORMATION

All Signetics' EPROM die are designed as low power UV light erasable and electrically programmable read only memories. They have been designed to perform over military and commercial temperature ranges. These die are assembled in EPROM packages that comply with industry standard packages: CERDIP (Quartz window), Plastic DIP (One Time Programmable) and Plastic Leaded Chip Carrier (One Time Programmable).

The following descriptions are of the tests and calculations performed on each device organization and package type to validate the quality and reliability of the CMOS design and technology. All described tests are performed on each package type, with the exception of the 'Program-erase cycling' test for the One Time Programmable devices.

ELECTROSTATIC DISCHARGE PROTECTION (ESD)

This test is performed to validate the product's tolerance to electrostatic discharge damage.

Both MIL—STD—883 criteria (human body model) and mechanical model charged device test are performed.

HIGH TEMPERATURE STORAGE LIFE TEST (HTSL)

Another popular name for this test is data retention bake. This process is used to thermally accelerate charge loss from the floating gate. The test is performed by subjecting devices that contain a 100% programmed data pattern to a 250°C bake with no applied electrical bias or clocks.

In addition to charge loss, this test is used to detect mechanical reliability (i.e., bond integrity) and process instability.

DYNAMIC LOW TEMPERATURE LIFE TEST (DLTL)

This test is performed at -10°C to detect the effects of hot electron injection into the gate oxide as well as package-related failures (i.e., metal corrosion). The biasing and clocking conditions for this test are identical to the DHTL #1 test.

TEMPERATURE CYCLE (TMCL)

This test consists of performing 200 cycles of ambient air temperature of the chamber and housing the unbiased subject devices from -65°C to +150°C and back. The 200 cycles are performed at 20 minutes per cycle.

DYNAMIC HIGH TEMPERATURE LIFE TEST (DHTL #1)

This test is used to accelerate failure mechanisms by operating the devices at 125°C ambient temperature with worst-case specified power supply voltages of V_{CC} and V_{PP} at 5.5V. The memory is sequentially addressed to exercise the fully-loaded outputs. A checkerboard complement data pattern is used to simulate random patterns expected during actual use.

DYNAMIC HIGH TEMPERATURE LIFE TEST (DHTL #2)

This test is used to accelerate oxide breakdown failures and to further accelerate the failure mechanisms of DHTL #1. The test setup is identical to the one used for the DHTL #1 test except the temperature is 150°C and the V_{CC} and V_{PP} power supply voltages are 6.5V, resulting in a 20% increase over the specified operational electrical field across the gate oxides of the device (1.25mV/cm for 325Å oxide thickness). This represents a 55 X electrical field in-

ness). This represents a 55 × electrical field induced acceleration in addition to the thermal acceleration at 150°C.

PROGRAM-ERASE CYCLING AND PROGRAMMABILITY

All four power supply voltage combinations for V_{CC} and V_{PP} are tested for programmability (V_{CC} = 6.0V ± 0.25V and V_{PP} = 12.5V ± 0.5V in program mode). The number of possible program/erase cycles is then tested to establish program-erase cycling expectations.

FAILURE RATE PREDICTIONS

In preparation for the various life tests, a 168 hour, 125°C, 5.5V production burn-in is performed on the devices. The infant mortality rejects are removed from the population in order to develop long-term failure rate information during the random failure rate portion of the device life cycle

The failure rate calculation combines all failure mechanisms by activation energies and associated device hours for the 125°C, 5.5V Dynamic Life Test (DHTL #1), the 150°C, 6.5V Dynamic Life Test (DHTL #2), the 150°C, 7.5V Static Life Test and the 250°C Bake.

The activation energies for the various EPROM failure mechanisms are:

IOTE.

Intrinsic charge loss

The combined failure rate for the stresses is the sum of failure rates by activation energies.

1.4eV

January 1990 34

METHODS OF FAILURE RATE CALCULATIONS

Actual Device Hours = Number of Devices \times Number of Hours. In order to determine the Equivalent Hours derated to a given operation temperature, the junction temperatures of the devices should be calculated using the known thermal resistance of the package (θ_{JA}) and the power dissipation of the devices:

$$T_{1,2} = \theta_{JA} (IV)_{1,2} + T_{A1,2}$$
 (1)

Using the Arrhenius relation, the test temperature and the derated operation temperature will yield the thermal acceleration factor from T_1 to T_2 :

$$\frac{R_1}{R_2} = \frac{A \cdot exp\left[\frac{E_A}{kT_1}\right]}{A \cdot exp\left[\frac{E_A}{kT_2}\right]} = exp\left[\frac{E_A}{k}\right] \left[\frac{1}{T_1} - \frac{1}{T_2}\right] \qquad ($$

k = 8.617 × 10⁻⁵ eV/Kelvin (Boltzmann's constant)

A = Proportionality constant for a given failure mechanism

R₁ = mean time to failure @ T₁

R₂ = mean time to failure @ T₂

E_A = activation energy for the failure mechanism

T₁ = operating temperature

T₂ = life test temperature

An additional $55 \times$ acceleration factor should be added for the 150°C/6.5V dynamic life test due to the time-dependent oxide failure acceleration (20% higher than specified power supply voltage).

Multiplying the actual device hours by the acceleration factor for each failure mechanism will result in the equivalent hours.

Poisson statistics are applied to estimate the performance of the population from the life test results of a sample test. This is useful when the probability of failures is small and the failures occur randomly in time. A commonly used formula for estimating the failure rate is the "chisquared" equation:

$$F_C = \frac{\chi^2}{2nt} \times 100\% \tag{3}$$

F_C = calculated failure rate estimate (in %/1000 hrs) at upper confidence limit

χ² = "chi-squared" value for 2F_A + 2 degrees of freedom for ∞ where F_A is the number of actual failures (χ² comes from available tables for a known ∞)

≈ = 1–B, where B is the confidence limit
 (B is stated in %).

n = number of units in test

 t = test time in thousands of hours (equivalent) Equation 3 will calculate the estimated failure rates/1000 hrs for 60% confidence level (industry standard) for each failure mechanism.

THE SURE PROGRAM

The SURE (Systematic Uniform Reliability Evaluation) program audits/monitors products from all Signetics' divisions under a variety of accelerated environmental stress conditions. this program, first introduced in 1964, has evolved to suit changing product complexities and performance requirements.

The SURE program has two major functions: long-term accelerated stress performance audit and a short-term accelerated stress monitor. In the case of Memory products, samples are selected that represent product groups from all wafer fabrication and assembly locations.

SURE REPORTS

The data from these test matrices provides a basic understanding of product capability, an indication of major failure mechanisms and an estimated failure rate resulting from each stress. This data is compiled periodically and is available to customers upon request.

January 1990 35

Signetics

Section 3 PAL®-Type Device Data Sheets

Programmable Logic Devices

INDEX

Series 20	
PLHS16L8A/B	$PAL^{\textcircled{B}}$ -Type Devices (16 × 64 × 8)
PLUS16R8D/-7	PAL®—Type Devices
	(Includes PLUS16L8D/–7, PLUS16R4D/–7, PLUS16R6D/–7, PLUS16R8D/–7)
PHD16N8-5	Programmable High Speed Decoder (16 × 16 × 8)
PLHS18P8A/B	PAL®-Type Devices
PLC18V8Z/I	PAL [®] -Type Devices
Series 24 10H20EV8/	
10020EV8	ECL PAL®-Type Devices
PLUS20R8D/-7	PAL [®] -Type Devices
	(Includes PLUS20L8D/-7, PLUS20R4D/-7,
	PLUS20R6D/-7, PLUS20R8D/-7)
Series 68	



Signetics

Document No.	853-0960			
ECN No.	97887			
Date of Issue	October 16, 1989			
Status Product Specification				
Programmable Logic Devices				

PLHS16L8A/B

Programmable AND Array Logic

 $(16 \times 64 \times 8)$

DESCRIPTION

The PLHS16L8A is a high-speed "A" version, and the PLHS16L8B is a very highspeed "B" version PAL®-type device. The sum of products (AND-OR) architecture is comprised of 64 AND gates and 8 OR gates. The Signetics PLHS16L8A/B devices offer 100% functional compatibility with other PAL 16L8 devices. Specified at a t_{PD} of 20ns (maximum), the PLHS16L8A is 20% faster than other "A" version PAL 16L8 devices, and consumes 20% less power than most other "A" speed 16L8 devices. The PLHS16L8B, specified at 155mA I_{CC} (maximum), consumes 20% less power than other "B" version PAL 16L8 devices.

All AND gates are linked to 10 dedicated inputs, 6 bidirectional I/O and 2 dedicated outputs. On-chip buffers couple either true (I, B) or complement (I, B) input polarities to all AND gates. The 64 AND gates are separated into eight groups of eight product terms each. Within each group, seven of the AND terms are OR'ed together, while the eighth is used to control the 3-State function of the bidirectional I/O. All outputs (bidirectional and dedicated) are inverting.


In the virgin state, the AND array fuses are back-to-back CB-EB diode pairs which act as open connections. Current is avalanched across individual diode pairs during fusing, which essentially short circuits the EB diode and provides the connection for the associated product term.

The PLHS16L8A/B is field-programmable, allowing the user to quickly generate custom patterns using standard programming equipment. Order codes are listed in the Ordering Information Table.

FEATURES

- "A" version 100% functionally and pin-for-pin compatible with AmPAL16L8A, MMI PAL16L8A, TIBPAL16L8-25, and NSC PAL16L8A devices
 - 20% faster than other "A" version
 PAL devices
 - $-t_{PD} = 20ns (max)$
- "B" version 100% functionally and pin-for-pin compatible with AmPAL16L8B, MMI PAL16L8B, TIBPAL16L8-15 and NSC PAL16L8B devices
 - Consumes 20% less power than other "B" version PAL devices
- 155mA I_{CC} (worst case)
- I/O propagation delay: 15ns (max) ("B" version)
- Field-programmable
- 10 dedicated inputs
- 8 outputs
 - 6 bidirectional I/O
 - 2 dedicated outputs
- Individual 3-State control of all outputs
- 64 AND gates/product terms
- Security fuse

PIN CONFIGURATIONS



APPLICATIONS

- 100% functional replacement for 20-pin 16L8 combinatorial PAL devices
- Random logic
- Code converters
- Fault detectors
- Function generators
- Address mapping/decoding
- Multiplexing

Philips Components






BPAL is a registered trademark of Monolithic Memories, Inc., a wholly owned subsidiary of Advanced Micro Devices, Inc.


PLHS16L8A/B

FPLA LOGIC DIAGRAM



PLHS16L8A/B

FUNCTIONAL DIAGRAM



ORDERING INFORMATION

DESCRIPTION	ORDER CODE
20-Pin Plastic Dual In-Line (300mil-wide)	PLHS16L8AN, PLHS16L8BN
20-Pin Plastic Leaded Chip Carrier	PLHS16L8AA, PLHS16L8BA

ABSOLUTE MAXIMUM RATINGS¹

SYMBOL	PARAMETER	RATINGS	UNIT
V _{CC}	Supply voltage	-0.5 to +7	V _{DC}
V _{IN}	Input voltage	-0.5 to +5.5	V _{DC}
V _{OUT}	Output voltage	-0.5 to V _{CC} Max	V _{DC}
V _{OUTPRG}	Output voltage (programming)	+21	V _{DC}
I _{IN}	Input current	−30 to +5	mA
I _{OUT}	Output current	+100	mA
I _{OUTPRG}	Output current (programming)	+170	mA
T _A	Operating temperature range	0 to +75	°C
T _{STG}	Storage temperature range -65 to +150		°C

NOTES:

THERMAL RATINGS

TEMPERATURE						
Maximum junction	150°C					
Maximum ambient	75°C					
Allowable thermal rise ambient to junction	75°C					

October 16, 1989

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

PLHS16L8A/B

DC ELECTRICAL CHARACTERISTICS 0°C ≤ TA ≤ +75°C, 4.75 ≤ V_{CC} ≤ 5.25V

SYMBOL PARAMETER			LIMITS			
		TEST CONDITIONS	Min	Typ1	Max	UNIT
Input volta	age ²				•	-
V _{IL}	Low	V _{CC} = MIN			+0.8	V
$V_{\mathbb{H}}$	High	V _{CC} = MAX	+2.0			V
V _{IC}	Clamp	V _{CC} = MIN, I _{IN} = -18mA		-0.9	-1.2	V
Output vo	Itage					
		V _{CC} = MIN, V _{IN} = V _{IH} or V _{IL}				
V_{OL}	Low	I _{OL} = +24mA			+0.50	V
V_{OH}	High	$I_{OH} = -3.2 \text{mA}$	+2.4	+3.5		V
Input curr	ent				-	
		V _{CC} = MAX				
I _{IL}	Low	$V_{IN} = +0.40V$		-20	-100	μΑ
I _H	High	V _{IN} = +2.7V			+25	μΑ
I_{\parallel}	High	V _{IN} = +5.5V			+1.0	mA
Output cu	rrent					-
		$V_{CC} = MAX, V_{ L} = 0.8V, V_{ H} = 2.0V$				
I _{OZH}	Output leakage	V _{OUT} = +2.7V			+100	μА
l _{OZL}	Output leakage	V _{OUT} = +0.40V			-50	μА
Ios	Short circuit ³	V _{OUT} = +0.5V	-30	-60	-90	mA
Icc	V _{CC} current	V _{CC} = MAX, All inputs = GND		100	155	mA
Capacitan	ice4			•		*
		V _{CC} = +5V				
CIN	Input	V _{IN} = 2.0V @ f = 1MHz		6		pF
C _{OUT}	1/0	V _{OUT} = 2.0V @ f = 1MHz		9		pF

NOTES:

2. These are absolute values with respect to device ground and all overshoots due to system or tester noise are included.

^{1.} Typical limits are at $V_{CC} = 5.0 \text{V}$ and $T_A = +25 ^{\circ}\text{C}$.

^{3.} Not more than one output should be tested at a time. Duration of the short circuit should not be more than one second. V_{OUT} = 0.5V has been chosen to avoid test problems caused by tester ground degradation.

^{4.} These parameters are not 100% tested, but are periodically sampled.

PLHS16L8A/B

AC ELECTRICAL CHARACTERISTICS 0°C \leq T_A \leq +75°C, 4.75 \leq V_{CC} \leq 5.25V, R₁ = 200 Ω , R₂ = 390 Ω

							LIM	ITS			
SYMBOL	PARAMETER	FROM	то	TEST	PL	HS16L	ВА	PL	HS16L	8B	UNIT
				CONDITIONS	Min	Тур	Max	Min	Тур	Max	
t _{PD}	Propagation delay	Output ±	Input ±	C _L = 50pF		14	20		12	15	ns
t _{EA}	Output enable	Output –	Input ±	C _L = 50pF		14	20		12	15	ns
t _{ER}	Output disable	Output +	Input ±	C _L = 5pF		14	20		12	15	ns

NOTES:

- 1. Typical limits are at $V_{CC} = 5.0V$ and $T_A = +25^{\circ}C$. 2. t_{PD} is tested with switch S_1 closed and $C_L = 50pF$.
- For 3-State output; output enable times are tested with C_L = 50pF to the 1.5V level, and S₁ is open for high-impedance to High tests and closed for high-impedance to Low tests. Output disable times are tested with C_L = 5pF. High-to-High impedance tests are made to an output voltage of $V_{OH} = -0.5V$ with S_1 open, and Low-to-High impedance tests are made to the $V_{OL} = +0.5V$ level with S_1 closed.

VIRGIN STATE


A factory shipped virgin device contains all fusible links open, such that:

- 1. All outputs are enabled.
- 2. All p-terms are enabled in the AND array.

TIMING DEFINITIONS

SYMBOL	PARAMETER			
t _{PD}	Input to output propagation delay.			
t _{ER}	Input to output disable (3–State) delay (Output Disable).			
t _{EA}	Input to Output Enable delay (Output Enable).			


TIMING DIAGRAM




43

PLHS16L8A/B

AC TEST LOAD CIRCUIT



VOLTAGE WAVEFORMS




LOGIC PROGRAMMING

PLHS16L8A/B logic designs can be generated using any commercially available, JEDEC standard design software that supports the 16L8 architecture. No JEDEC fuse map conversion or translation is necessary when using the PLHS16L8A/B.

PLHS16L8A/B designs can also be generated using the program table format, detailed on the following page. This program table entry (PTE) format is supported on the Signetics AMAZE PLD design software. AMAZE is available free of charge to qualified users.

To implement the desired logic functions, each logic variable (I, B, P and D) from the logic equations is assigned a symbol. TRUE (High), COMPLEMENT (Low), DON'T CARE and INACTIVE symbols are defined below.

"AND" ARRAY - (I, B)



NOTE

- 1. This is the initial state of all diodes pairs.
- All unused product terms must be programmed with all pairs of diodes in the INACTIVE state (all fuses on an unused p-term must be programmed).

PROGRAM TABLE

CUSTOMER NAME		AND	OR (FIXED)	
				NOTES:
PURCHASE ORDER	R #	INACTIVE O	DIRECTION D	The FPLA is shipped with all links open. Unused I and B bits in the AND array exist as Don't.
CICHETION DEVICE	# OF (MAAA)	I, B H I, B(I)	ACTIVE OUTPUT A	Care (-) in the virgin state.
SIGNETICS DEVICE	# CF (XXXX)	I, B L	NOT USED	All p-terms are active until programmed otherwise.
CUSTOMER SYMBO	OLIZED PART #	DON'T CARE -		4. All unused product terms must be programmed with
COSTOMEN STWDO	DEIZED FAITI #			all pairs of fuses in the INACTIVE state (all fuses on an unused p-term must be programmed).
TOTAL NUMBER OF	PARTS			Data cannot be entered into the OR array field due
	,			to the fixed nature of the device architecture.
PROGRAM TABLE #	# REV DATE			
VARIABLE 🗵 🔉 🔉 🔉	37 38 38 39 39 39 39 40 40 40 40 40 40 40 40 40 40 40 40 40	22222222222	22222222	11111111111111111111111111111111111111
TORME	0 0 0 7 0 0 2 0 0 7 0 0 7 0 0 7 0 0 7	6 6 4 3 2 4 0 6 8 7 6	5 4 3 2 1 0 0 8 7 6	
= =				0
60				7
7				
o				S 4
υ U				()
4				
ω				N ≥
N				2 1 AND
_				0
1 1 1 1				01
17				on =
16	 			INPUTS
	╶┝┥╃┿╂┣┝┥╃┾┾┝┥╉┼┾┝┤┥┼╂┝┤╴		t++	
= = = = = = = = = = = = = = = = = = = =				(B)
13				
5 M		MANAMANA		
= \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \	XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX	/////////////////////////////////////	/////////////////////////////////////	>>>>>
= 1	XXXXXXXXXXXXXXXXXXXXXXXXXXXXXX	/////////////////////////////////////		2 2 1/1/1/1/1/1/1/1/1/1/1/1/1/1/1/1/1/1/
5	*************************			OR (FIXED) OUTPUTS (B, O) 5 4 3 2
		>>>	****	
= 1			 	
		XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX	<i>{XXXXXXXXXXX</i> }	[\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\

Signetics

_				
Document No.	853–1358			
ECN No.	98103			
Date of Issue	November 14, 1989			
Status Product Specification				
Programmable Logic Devices				

PLUS16R8D/-7 SERIES PAL®-Type Devices 16L8, 16R8, 16R6, 16R4

FEATURES

- Ultra high-speed
 - t_{PD} = 7.5ns and f_{MAX} = 74MHz for the PLUS16R8-7 Series
 - t_{PD} = 10ns and f_{MAX} = 60 MHz for the PLUS16R8D Series
- 100% functionally and pin-for-pin compatible with industry standard 20-pin PAL ICs
- Power-up reset function to enhance state machine design and testability
- Design support provided via AMAZE and other CAD tools for Series 20 PAL devices
- Field-programmable on industry standard programmers
- Security fuse
- Individual 3-State control of all outputs

DESCRIPTION

The Signetics PLUS16XX family consists of ultra high-speed 7.5ns and 10ns versions of Series 20 PAL devices.

The PLUS16XX family is 100% functional and pin-compatible with the 16L8, 16R8, 16R6, and 16R4 Series devices.

The sum of products (AND-OR) architecture is comprised of 64 programmable AND gates and 8 fixed OR gates. Multiple bidirectional pins provide variable input/output pin ratios. Individual 3-State control of all outputs and registers with feedback (R8, R6, R4) is also provided. Proprietary designs can be protected by programming the security fuse.

The PLUS16R8, R6, and R4 have D-type flip-flops which are loaded on the Low-to-High transition of the clock input.

In order to facilitate state machine design and testing, a power-up reset function has been incorporated into these devices to reset all internal registers to active-Low after a specific period of time.

The Signetics State-of-the-Art oxide isolation Bipolar fabrication process is employed to achieve high-performance operation.

The PLUS16XX family of devices are field programmable, enabling the user to quickly generate custom patterns using standard programming equipment. See the programmer chart for qualified programmers.

The AMAZE software package from Signetics supports easy design entry for the PLUS16XX series as well as other PLD devices from Signetics. The PLUS16XX series are also supported by other standard CAD tools for PAL-type devices.

Order codes are listed in the Ordering Information table.

DEVICE NUMBER	DEDICATED INPUTS	COMBINATORIAL OUTPUTS	REGISTERED OUTPUTS
PLUS16L8	10	8(6 I/O)	0
PLUS16R8	8	0	8
PLUS16R6	8	2 I/O	6
PLUS16R4	8	4 I/O	4

Philips Components







RPAL is a registered trademark of Monolithic Memories, Inc., a wholly owned subsidiary of Advanced Micro Devices, Inc.

PLUS16R8D/-7 SERIES


PIN CONFIGURATIONS








PLUS16R8D/-7 SERIES


PIN CONFIGURATIONS














PLUS16R8D/-7 SERIES

FUNCTIONAL DESCRIPTIONS

The PLUS16XX series utilizes the familiar sum-of-products implementation consisting of a programmable AND array and a fixed OR array. These devices are capable of replacing an equivalent of four or more SSI/MSI integrated circuits to reduce package count and board area occupancy, consequently improving reliability and design cycle over Standard Cell or gate array options. By programming the security fuse, proprietary designs can be protected from duplication.

The PLUS16XX series consists of four PALtype devices. Depending on the particular device type, there are a variable number of combinatorial and registered outputs available to the designer. The PLUS16L8 is a combinatorial part with 8 user configurable outputs (6 bidirectional), while the other three devices, PLUS16R8, PLUS16R6, PLUS16R4, have respectively 8, 8, and 4 output registers.

3-State Outputs

The PLUS16XX series devices also feature 3—State output buffers on each output pin which can be programmed for individual control of all outputs. The registered outputs (Qn) are controlled by an external input (/OE), and the combinatorial outputs (On, Bn) use a product term to control the enable function.

Programmable Bidirectional Pins

The PLUS16XX products feature variable Input/Output ratios. In addition to 8 dedicated inputs, each combinatorial output pin of the registered devices can be individually programmed as an input or output. The PLUS16L8 provides 10 dedicated inputs and 6 Bidirectional I/O lines that can be individually configured as inputs or outputs.

Output Registers

The PLUS16A8 has 8 output registers, the 16R6 has 6, and the 16R4 has 4. Each output register is a D-type flip-flop which is loaded on the Low-to-High transition of the clock input. These output registers are capable of feeding the outputs of the registers back into the array to facilitate design of synchronous state machines.

Power-up Reset

By resetting all flip—flops to a logic Low, as the power is turned on, the PLUS16R8, R6, R4 enhance state machine design and initialization capability.

Software Support

Like other Programmable Logic Devices from Signetics, the PLUS16XX series are supported

by AMAZE, the PC-based software development tool from Signetics. The PLUS16XX family of devices are also supported by standard CAD tools for PAL devices, including ABEL and CUPL.


AMAZE is available free of charge to qualified users.

Logic Programming

Logic designs for PLUS16XX series can be generated using any commercially available JEDEC standard design software that supports the 20-pin PAL devices. No JEDEC fuse map conversion or translation is necessary when transferring designs from slower 20-pin PAL devices.

To implement the desired logic functions, each logic variable from the logic equations is assigned a symbol. True (High), Complement (Low), Don't Care and Inactive symbols are defined below.

AND ARRAY - (I, B)



VIRGIN STATE

A factory shipped virgin device contains all fusible links intact, such that:

- 1. All outputs are at "H" polarity.
- 2. All P_n terms are disabled
- 3. All Pn terms are active on all outputs

PLUS16R8D/-7 SERIES

ORDERING INFORMATION

DESCRIPTION	ORDER CODE
20-Pin Plastic Dual-In-Line 300mil-wide	PLUS16R8DN PLUS16R6DN PLUS16R4DN PLUS16L8DN PLUS16R8-7N PLUS16R6-7N PLUS16R4-7N PLUS16R4-7N PLUS16R8-7N
20-Pin Plastic Leaded Chip Carrier (PLCC)	PLUS16R8DA PLUS16R6DA PLUS16R4DA PLUS16L8DA PLUS16R8-7A PLUS16R6-7A PLUS16R4-7A PLUS16R4-7A

THERMAL RATINGS

TEMPERATURE			
Maximum junction	150°C		
Maximum ambient	75°C		
Allowable thermal rise ambient to junction	75°C		

NOTE:

The PLUS16XX series of devices are also processed to military requirements for operation over the military temperature range. For specifications and ordering information, consult the Signetics Military Data Book.

ABSOLUTE MAXIMUM RATINGS¹

		RATINGS		
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage	-0.5	+7	V_{DC}
V _{IN}	Input voltage	-0.5	+5.5	V_{DC}
V _{OUT}	Output voltage		+5.5	V_{DC}
I _{IN}	Input currents	-30	+30	mA
I _{OUT}	Output currents		+100	mA
T _{STG}	Storage temperature range	-65	+150	°C

NOTE:

OPERATING RANGES

		RATINGS		
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage	+4.75	+5.25	V _{DC}
TA	Operating free—air temperature	0	+75	°C

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

PLUS16R8D/-7 SERIES

DC ELECTRICAL CHARACTERISTICS $0^{\circ}C \le T_{A} \le +75^{\circ}C$, $4.75 \le V_{CC} \le 5.25V$

	-		LIMITS			
SYMBOL	PARAMETER	TEST CONDITIONS	Min	Typ ¹	Typ ¹ Max	
Input voltag	je ²					
V _{IL}	Low	V _{CC} = Min			0.8	V
V_{IH}	High	V _{CC} = Max	2.0			V
V_{IC}	Clamp	$V_{CC} = Min, I_{IN} = -18mA$		-0.8	-1.5	V
Output volt	age					
		V _{CC} = Min, V _{IN} = V _{IH} or V _{IL}				2 -
V_{OL}	Low	$I_{OL} = 24mA$		-	0.5	V
V_{OH}	High	$I_{OH} = -3.2 \text{ mA}$	2.4			V
Input curre	nt					
		V _{CC} = Max		7		
I _{IL}	Low ³	$V_{IN} = 0.40V$	-250			μА
I _{IH}	High ³	$V_{IN} = 2.7V$			25	μА
l _l	Maximum input current	$V_{\text{IN}} = V_{\text{CC}} = V_{\text{CCMAX}}$			100	μА
Output curr	ent					
		V _{CC} = Max				
l _{OZH}	Output leakage	$V_{OUT} = 2.7V$			100	μА
lozL	Output leakage	$V_{OUT} = 0.4V$	-100			μА
los	Short circuit ^{4, 5}	$V_{OUT} = 0V$	-30		-90	mA
Icc	V _{CC} supply current	V _{CC} = Max			180	mA
Capacitano	e ⁶			1		
C _{IN}	Input	V _{CC} = 5V				
		$V_{OUT} = 2.0V$		8		pF
C _B	I/O (B)	$V_{OUT} = 2V$, $f = 1MHz$		8		pF

NOTES:

- 1. All typical values are at $V_{CC} = 5V$, $T_A = +25^{\circ}C$.
- 2. All voltage values are with respect to network ground terminal.
- 3. Leakage current for bidirectional pins is the worst case of I_{IL} and I_{OZL} or I_{IH} and I_{OZH}.
- 4. Test one at a time.
- 5. Duration of short circuit should not exceed 1 second.
- 6. These parameters are not 100% tested but periodically sampled.

PLUS16R8D/-7 SERIES

AC ELECTRICAL CHARACTERISTICS $R_1 = 200\Omega$, $R_2 = 390\Omega$, $0^{\circ}C \le T_A \le +75^{\circ}C$, $4.75 \le V_{CC} \le 5.25V$

	i a				LIM	IITS		
SYMBOL	PARAMETER	FROM	то	_	-7 D)	רואט	
				Min ¹	Max	Min ¹	Max	
Pulse Widt	h							
t _{CKH}	Clock High	CK+	CK-	5		7		ns
t _{CKL}	Clock Low	CK-	CK+	5		7		ns
t _{CKP}	Period	CK+	CK+	10		14		ns
Setup & Ho	old time							
t_{IS}	Input	Input or feedback	CK+	7		9		ns
t _{IH}	Input	CK+	Input or feedback	0		0		ns
Propagatio	n delay							
t _{CKO}	Clock	CK±	Q±	3	6.5	3	7.5	ns
t _{CKF}	Clock ³	CK±	۵		3		7	ns
t _{PD}	Output (20L8, R6, R4) ²	I, B	Output		7.5		10	ns
t _{OE1}	Output enable ⁴	ŌE	Output enable	3	8	3	10	ns
t _{OE2}	Output enable ^{4,5}	1	Output enable	3	10	3	10	ns
t _{OD1}	Output disable ⁴	ŌE	Output disable	3	8	3	10	ns
t _{OD2}	Output disable ^{4,5}	ı	Output disable	3	10	3	10	ns
t _{SKW}	Output	Q	Q		1		1	ns
t _{PPR}	Power-Up Reset	V _{CC} +	Q+		10		10	ns
Frequency	(20R8, R6, R4)						•	*
	No feedback 1/ (t _{CKL} + t _{CK}	H) ⁶		100		71.4		MH:
f _{MAX}	Internal feedback 1/ (t _{IS} +	tckf)6		100		62.5		MH:
	External feedback 1/ (t _{IS} +	t _{CKO}) ⁶		74		60.6		MH:


^{*} For definitions of the terms, please refer to the Timing/Frequency Definitions tables.

NOTES:


- 1. CL = 0pF while measuring minimum output delays.
- 2. t_{PD} test conditions: CL = 50pF (with jig and scope capacitance), $V_{IH} = 3V$, $V_{IL} = 0V$, $V_{OH} = V_{OL} = 1.5V$.
- 3. t_{CKF} was calculated from measured Internal f_{MAX}.
- 4. In reference to 3—State outputs, output enable times are tested with CL = 50pF to the 2.0V or 0.8V level. Output disable times are tested with CL = 5pF. High to High-impedence tests are made to an output voltage of V_T = V_{OH}-0.5V; Low to High-impedence tests are made to the V_T = V_{OL}+0.5V level.
- 5. Same function as t_{OE1} and t_{OD1}, with the difference of using product term control.
- 6. Not 100% tested, but calculated at initial characterization and at any time a modification in design takes place which may affect the frequency.

PLUS16R8D/-7 SERIES


TEST LOAD CIRCUIT



OUTPUT REGISTER SKEW




CLOCK TO FEEDBACK PATH



PLUS16R8D/-7 SERIES

TIMING DIAGRAMS^{1, 2}



TIMING DEFINITIONS

SYMBOL	PARAMETER
t _{CKH}	Width of input clock pulse.
t _{CKL}	Interval between clock pulses.
t _{CKP}	Clock period.
t _{IS}	Required delay between beginning of valid input and positive transition of clock.
t _{IH}	Required delay between positive transition of clock and end of valid input data.
t _{CKF}	Delay between positive transition of clock and when internal Q output of flip-flop becomes valid.
^t cкo	Delay between positive transition of clock and when outputs become valid (with OE Low).
t _{OE1}	Delay between beginning of Output Enable Low and when outputs become valid.
t _{OD1}	Delay between beginning of Output Enable High and when outputs are in the Off–State.
t _{OE2}	Delay between predefined Output Enable High, and when combinational outputs become valid.
toD2 Delay between predefi Output Enable Low and w combinational outputs are the Off–State.	
t _{PPR}	Delay between V _{CC} (after pow- er-on) and when flip-flop out- puts become preset at "1" (in- ternal Q outputs at "0").
t _{PD}	Propagation delay between combinational inputs and outputs.

FREQUENCY DEFINITIONS

fmax	No feedback: Determined by the minimum clock period, 1/(tckl + tckh). Internal feedback: Deter-
	mined by the internal delay from flip—flop outputs through the internal feedback and array to the flip—flop inputs, 1/(t _{IS} +
	t_{CKF}). External feedback: Determined by clock-to-output delay and input setup time, $1/(t_{1S} + t_{CKO})$.


NOTES:

- 1. Input pulse amplitude is 0V to 3V.
- 2. Input rise and fall times are 2.5ns.

Programmable High-Speed Decoder Logic (16 \times 16 \times 8)

PHD16N8-5

LOGIC DIAGRAM




October 1989

Programmable High-Speed Decoder Logic ($16 \times 16 \times 8$)

PHD16N8-5

FUNCTIONAL DIAGRAM



ORDERING INFORMATION

DESCRIPTION	ORDER CODE
20-Pin Plastic Dual In Line Package; (300mil-wide)	PHD16N8-5N
20-Pin Plastic Leaded Chip Carrier; (350mil square)	PHD16N8-5A

ABSOLUTE MAXIMUM RATINGS1

	2 2	RATINGS		
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage	-0.5	+7	V _{DC}
V _{IN}	Input voltage	-0.5	+5.5	V _{DC}
V _{OUT}	Output voltage		+5.5	V _{DC}
I _{IN}	Input currents	-30	+30	mA
lout	Output currents		+100	mA
T _A	Operating temperature range	0	+75	°C
T _{STG}	Storage temperature range	-65	+150	°C

NOTES:

OPERATING RANGES

		RATI	NGS	2 -2
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage	+4.75	+5.25	V _{DC}
TA	Operating free-air temperature	0	+75	°C

THERMAL RATINGS

TEMPERAT	JRE
Maximum junction	150°C
Maximum ambient	75°C
Allowable thermal rise ambient to junction	75°C

October 1989 62

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

Programmable High-Speed Decoder Logic ($16 \times 16 \times 8$)

PHD16N8-5

DC ELECTRICAL CHARACTERISTICS 0°C ≤ T_A ≤ +75°C, 4.75 ≤ V_{CC} ≤ 5.25V

				LIMITS		
SYMBOL	PARAMETER	TEST CONDITIONS	Min	Typ1	Max	UNIT
Input volta	age ²					
V _{IL}	Low	V _{CC} = MIN			0.8	V
VIH	High	V _{CC} = MAX	2.0			V
V _{IC}	Clamp	V _{CC} = MIN, I _{IN} = -18mA		-0.8	-1.5	V
Output vo	Itage	-				
		V _{CC} = MIN, V _{IN} = V _{IH} or V _{IL}				
V_{OL}	Low	$I_{OL} = +24mA$			0.5	V
V_{OH}	High	I _{OH} = −3.2mA	2.4			V
Input curr	ent					10
		V _{CC} = MAX				
IL	Low	$V_{IN} = +0.40V$		-20	-250	μА
I _{IH}	High	$V_{1N} = +2.7V$			25	μА
II	High	V _{IN} = V _{CC} = V _{CC MAX}			100	μА
Output cu	rrent	•				
		V _{CC} = MAX				
I _{OZH}	Output leakage 3	V _{OUT} = +2.7V			100	μΑ
lozL	Output leakage ³	V _{OUT} = +0.40V			-100	μА
los	Short circuit ⁴	V _{OUT} = 0V	-30		-90	mA
Icc	V _{CC} supply current	V _{CC} = MAX		115	180	mA
Capacitan	Ce ⁵	•		*	•	•
		V _{CC} = +5V				
CIN	Input	V _{IN} = 2.0V @ f = 1MHz		8		pF
C _{OUT}	I/O (B)	V _{OUT} = 2.0V @ f = 1MHz		8		pF

NOTES:

- Typical limits are at V_{CC} = 5.0V and T_A = +25°C.
 These are absolute values with respect to device ground and all overshoots due to system or tester noise are included.
- Leakage current for bidirectional pins is the worst case of I_{IL} and I_{OZI} or I_{IH} and I_{OZH}.
 Not more than one output should be tested at a time. Duration of the short circuit should not be more than one second.
- 5. These parameters are not 100% tested, but are periodically sampled.

October 1989 63

Programmable High-Speed Decoder Logic ($16 \times 16 \times 8$)

PHD16N8-5

AC ELECTRICAL CHARACTERISTICS $0^{\circ}C \le T_{A} \le +75^{\circ}C$, $4.75 \le V_{CC} \le 5.25V$, $R_1 = 200\Omega$, $R_2 = 390\Omega$

				TEST	LIMITS		
SYMBOL	PARAMETER	FROM	то	CONDITIONS	Min	Max	UNIT
t _{PD} 1	Propagation delay	(I, B) ±	Output ±	C _L = 50pF		5	ns
t _{OE} ²	Output Enable	(I, B) ±	Output enable	C _L = 50pF		10	ns
t _{OD} ²	Output Disable	(I, B) ±	Input disable	C _L = 5pF		10	ns

NOTES:

1. t_{PD} is tested with switch S₁ closed and C_L = 50pF.

For 3-State output; output enable times are tested with C_L = 50pF to the 1.5V level, and S₁ is open for high-impedance to High tests and closed for high-impedance to Low tests. Output disable times are tested with C_L = 5pF. High-to-High impedance tests are made to an output voltage of V_T = V_{OL} + 0.5V with S₁ open, and Low-to-High impedance tests are made to the V_T = V_{OL} + 0.5V level with S₁ closed.


VIRGIN STATE

A factory shipped virgin device contains all fusible links open, such that:


- 1. All outputs are disabled.
- 2. All p-terms are disabled in the AND array.

TIMING DEFINITIONS

SYMBOL	PARAMETER		
t _{PD}	Input to output propagation delay.		
top	Input to Output Disable (3-State) delay (Output Disable).		
t _{OE}	Input to Output Enable delay (Output Enable).		



TIMING DIAGRAM




October 1989


Programmable High-Speed Decoder Logic ($16 \times 16 \times 8$)

PHD16N8-5

AC TEST LOAD CIRCUIT



VOLTAGE WAVEFORMS




LOGIC PROGRAMMING

PHD16N8-5 logic designs can be generated using any commercially available, JEDEC standard design software.

PHD16N8–5 designs can also be generated using the program table format, detailed on the following page. This program table entry (PTE) format is supported on the Signetics AMAZE PLD design software. AMAZE is available free of charge to qualified users.


To implement the desired logic functions, each logic variable (I, B, P and D) from the logic equations is assigned a symbol. TRUE (High), COMPLEMENT (Low), DON'T CARE and INACTIVE symbols are defined below.


"AND" ARRAY - (I, B)











NOTE:

1. This is the initial state.

Programmable High-Speed Decoder Logic ($16 \times 16 \times 8$)

PHD16N8-5


PROGRAM TABLE

PRO	un	AIVI	IA	DL				_					2000			-						-	_	_	_						
- 1	۵	<					т	L					Allerton			AND	-		-			-			L			OR (FI	-		
1			\rightarrow				E R					INPU	T (1)	_					-	NPUT	S (B				OUTPUTS (B, O)						
ED)		5					М	9	8	7	6	5	4	3	2	1	0	6	5	4	3	2	1		7	6	5	4	3	2	1 0
OR (FIXED)	N	ACTIVE OUTPUT	۵				0			ļ				_											D	K,	Z,	\angle	4	4	4
8 ;	DIRECTION	IVE (NOT USED				1														_				A,	K	Z,	$\angle \downarrow$	4	4	4
	DIR	ACI	ž				2			ļ				<u> </u>											K,	D	Z,	\angle	4	4	4
- +							3														_				K,	A	\angle	\angle	4	4	4
1			l. Bd)	È			4			 				_											K	K,	D	\angle	Δ	4	4
1	_		_=	-			5														_			L	K,	K,	A	$\angle \downarrow$	4	4	4
		0	Ξ	-	1		6			<u> </u>				_							_				K,	K,	Z,	D	4	4	4
AND]		7																	L	K,	Z,	K,	Αį	4	4	4
		m l			CARE		8			 				_											K	Z,	K,	4	D	Δ	4
1		INACTIVE	_		DON'T CARE		9			<u> </u>											Ĺ				K,	Z,	K,	<u>/i</u>	A	4	4
1		ž	1,8	l, B	8		10			<u> </u>				_			Ш								K	K,	K,	4	4	D	4
							11	_		<u> </u>												_		_	K	K,	K	\angle	4	A	4
- 1		1	1	1	1	1	12			<u> </u>				 							 				K	K,	K,	4	4	4	D /
							13	_			_	_		_							<u> </u>	_		_	K	K,	K,	\angle	4	4	A/
							14	_		-		_		 	_					_	-		_		K	K,	K,	\angle	4	4	
		X					15	_	_		_				_	_				-	_	_		_	\vee	\angle	\angle	\angle	4	4	_ A
		CF(XXXX)				DATE	PIN	11	9	8	7	6	5	4	3	2	1	18	17	16	15	14	13	_	19	18	17	16	15	14	13 12
				ZED PART #	ARTS	REV	VARIABLE NAME																								
CUSTOMER NAME	PURCHASE ORDER #	SICNETICE DEVICE #		CUSTOMER SYMBOLIZED PART	TOTAL NUMBER OF PARTS	PROGRAM TABLE #	NOT 1. T 2. U 3. A 4. D	he F Inus	ed I	and	B bi	ts in	the	AN ntil p	D ar	ray e	exist	as I	NA(e.			_			e de	vice	archi	itect	ture.	

Programmable High-Speed Decoder Logic (16 \times 16 \times 8)

PHD16N8-5

DECODING 1/2 MEG STATIC MEMORY



Signetics

Document No.	853-0863					
ECN No.	97886					
Date of Issue	October 16, 1989					
Status	Product Specification					
Programmable Logic Devices						

PLHS18P8A/B PAL®-Type Devices

DESCRIPTION

The PLHS18P8A and the PLHS18P8B are two-level logic elements consisting of 72 AND gates and 8 OR gates with fusible connections for programming I/O polarity and direction.

All AND gates are linked to 10 inputs (I) and 8 bidirectional I/O lines (B). These yield variable I/O gate configurations via 8 direction control gates, ranging from 18 inputs to 8 outputs.

On-chip T/C buffers couple either True (I, B) or Complement (I, B) input polarities to all AND gates. The 72 AND gates are separated into 8 groups of 9 each. Each group of 9 is associated with one bidirectional pin. In each group, eight of the AND terms are ORed together, while the ninth is used to establish I/O direction. All outputs are individually programmable via an Ex-OR gate to allow implementation of AND/OR or NAND/NOR logic functions.

In the virgin state, the AND array fuses are back-to-back CB-EB diode pairs which will act as open connections. Current is avalanched across individual diode pairs during fusing, which essentially short circuits the EB diode and provides the connection for the associated product term.


The PLHS18P8A/B is field-programmable, allowing the user to quickly generate custom patterns using standard programming equipment.

Order codes are listed in the Ordering Information Table.

FEATURES

- "A" version 100% functionally compatible with AmPAL18P8A and all 16L8, 16P8, 16H8, 16L2, 16H2, 14L4, 14H4, 12L6, 12H6, 10L8, 10H8, 16LD8 and 16HD8 "A" speed PAL-type products
- "B" version 100% functionally compatible with AmPAL18P8B and all 16L8, 16P8, 16H8, 16L2, 16H2, 14L4, 14H4, 12L6, 12H6, 10L8, 10H8, 16LD8 and 16HD8 "B" speed PAL-type products
- Field-programmable
- 10 inputs
- 8 bidirectional I/O lines
- 72 AND gates/product terms
 - configured into eight groups of nine
- Programmable output polarity (3-State output)
- I/O propagation delay:
- PLHS18P8A: 20ns (max)
- PLHS18P8B: 15ns (max)
- Power dissipation: 500mW (typ)
- TTL compatible
- Security fuse

PIN CONFIGURATIONS



APPLICATIONS

- 100% functional replacement for all 20-pin combinatorial PAL devices
- Random logic
- Code converters
- Fault detectors
- Function generators
- Address mapping
- Multiplexing

®PAL is a registered trademark of Monolithic Memories, Inc., a wholly owned subsidiary of Advanced Micro Devices, Inc.


Philips Components






PLHS18P8A/B

FPLA LOGIC DIAGRAM



PLHS18P8A/B

FUNCTIONAL DIAGRAM



ORDERING INFORMATION

DESCRIPTION	ORDER CODE
20-Pin Plastic Dual In-Line (300mil-wide)	PLHS18P8AN, PLHS18P8BN
20-Pin Plastic Leaded Chip Carrier	PLHS18P8AA, PLHS18P8BA

ABSOLUTE MAXIMUM RATINGS¹

SYMBOL	PARAMETER	RATINGS	UNIT
V _{CC}	Supply voltage	-0.5 to +7	V _{DC}
V _{IN}	Input voltage	-0.5 to +5.5	V _{DC}
V _{OUT}	Output voltage	-0.5 to V _{CC} Max	V _{DC}
V _{OUTPRG}	Output voltage (programming)	+21	V _{DC}
I _{IN}	Input current	-30 to +5	mA
I _{OUT}	Output current	+100	mA
I _{OUTPRG}	Output current (programming)	+170	mA
T _A	Operating temperature range	0 to +75	°C
T _{STG}	Storage temperature range	-65 to +150	°C

NOTES

THERMAL RATINGS

TEMPERATURE							
Maximum junction	150°C						
Maximum ambient	75°C						
Allowable thermal rise ambient to junction	75°C						

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

PLHS18P8A/B

DC ELECTRICAL CHARACTERISTICS 0°C ≤ TA ≤ +75°C, 4.75 ≤ V_{CC} ≤ 5.25V

					LIM	ITS			
SYMBOL	PARAMETER	TEST CONDITIONS	Р	LHS18P8	BA	P	LHS18P8	B	UNIT
			Min	Typ1	Max	Min	Typ ¹	Max	
Input volta	age ²				-				
V _{IL}	Low	V _{CC} = MIN			+0.8			+0.8	V
V _{IH}	High	V _{CC} = MAX	+2.0		-	+2.0			V
V _{IC}	Clamp	V _{CC} = MIN, I _{IN} = -18mA		-0.9	-1.2		-0.9	-1.2	V
Output vo	Itage							***************************************	
		V _{CC} = MIN, V _{IN} = V _{IH} or V _{IL}							
V_{OL}	Low	$I_{OL} = +24mA$			+0.50			+0.50	V
V_{OH}	High	I _{OH} = -3.2mA	+2.4	+3.5		+2.4	+3.5		V
Input curr	ent				<u> </u>			A	
		V _{CC} = MAX							
I _{IL}	Low	$V_{IN} = +0.40V$		-20	-100		-20	-100	μА
I _H	High	$V_{IN} = +2.7V$			+25			+25	μА
I_1	High	$V_{1N} = +5.5V$			+1.0			+1.0	mA
Output cu	rrent			december on manufacture communications				***************************************	
		V _{CC} = MAX, V _{IL} = 0.8V, V _{IH} = 2.0V	,						
lozh	Output leakage	V _{OUT} = +2.7V			+100			+100	μА
lozL	Output leakage	V _{OUT} = +0.40V			-250			-250	μΑ
Ios	Short circuit 3	V _{OUT} = +0.5V	-25	-60	-90	-30	-60	-90	mA
Icc	V _{CC} current	V _{CC} = MAX, All inputs = GND		100	155		100	155	mA
Capacitan	ce ⁴						A		
		V _{CC} = +5V							
CIN	Input	V _{IN} = 2.0V @ f = 1MHz		6			6		pF
C _{OUT}	1/0	V _{OUT} = 2.0V @ f = 1MHz		9			9		pF

NOTES:

- 1. Typical limits are at $V_{CC} = 5.0V$ and $T_A = +25$ °C.
- These are absolute values with respect to device ground and all overshoots due to system or tester noise are included.
 Not more than one output should be tested at a time. Duration of the short circuit should not be more than one second. V_{OUT} = 0.5V has been chosen to awoid test problems caused by tester ground degradation.

71

4. These parameters are not 100% tested, but are periodically sampled.

PLHS18P8A/B

AC ELECTRICAL CHARACTERISTICS 0°C \leq T_A \leq +75°C, 4.75 \leq V_{CC} \leq 5.25V, R₁ = 200 Ω , R₂ = 390 Ω

		LIMITS									
SYMBOL	PARAMETER	ETER FROM TO TEST PLHS18P8A		8A	PL	UNIT					
				CONDITIONS	Min	Тур	Max	Min	Тур	Max	
t _{PD}	Propagation delay	Output ±	Input ±	C _L = 50pF		14	20		12	15	ns
t _{EA}	Output enable	Output –	Input ±	C _L = 50pF		14	20		12	15	ns
t _{ER}	Output disable	Output +	Input ±	C _L = 5pF		14	20		12	15	ns

NOTES:

- Typical limits are at V_{CC} = 5.0V and T_A = +25°C.
 t_{PD} is tested with switch S₁ closed and C_L = 50pF.
- For 3—State output; output enable times are tested with C_L = 50pF to the 1.5V level, and S₁ is open for high-impedance to High tests and closed for high-impedance to Low tests. Output disable times are tested with C_L = 5pF. High-to-High impedance tests are made to an output voltage of $V_{OH} = -0.5V$ with S_1 open, and Low-to-High impedance tests are made to the $V_{OL} = +0.5V$ level with S_1 closed.

VIRGIN STATE


A factory shipped virgin device contains all fusible links open, such that:

- 1. All outputs are at "H" polarity.
- 2. All outputs are enabled
- 3. All p-terms are enabled.

TIMING DEFINITIONS


SYMBOL	PARAMETER
t _{PD}	Input to output propagation delay.
t _{ER}	Input to output disable (3–State) delay (Output Disable).
t _{EA}	Input to Output Enable delay (Output Enable).

TIMING DIAGRAM




PLHS18P8A/B

AC TEST LOAD CIRCUIT



VOLTAGE WAVEFORMS




LOGIC PROGRAMMING


PLHS18P8A/Blogic designs can be generated using Signetics' AMAZE PLD design software or one of several other commercially available, JEDEC standard PLD design software packages. Boolean and/or state equation entry is accepted.

PLHS18P8A/B logic designs can also be generated using the program table format detailed on the following pages. This program table entry (PTE) format is supported by the Signetics' AMAZE PLD design software (PTP module). AMAZE is available free of charge to qualified users.


To implement the desired logic functions, the state of each logic variable from logic equations (I, B, O, P, etc.) is assigned a symbol. The symbols for TRUE, COMPLEMENT, INACTIVE, PRESET, etc., are defined below.

OUTPUT POLARITY - (B)





"AND" ARRAY - (I, B)



NOTE:

- 1. This is the initial state of all link pairs.
- All unused product terms must be programmed with all pairs of fuses in the INACTIVE state (all fuses on an unused p-term must be programmed).

Signetics Programmable Logic Devices

PROGRAM TABLE

CUSTOMER NAME	AND	CONTROL	
PURCHASE ORDER #	INACTIVE O	HIGH H	NOTES: 1. The FPLA is shipped with all links open.
TOTOTAGE OTIBETT	I, B H	LOW L (POL)	Unused I and B bits in the AND array exist as Don't
SIGNETICS DEVICE # CF (XXXX)	ī, B L I, B(I)	L	Care (-) in the virgin state. 3. All p-terms are active until programmed otherwise.
OUCTOMED CYMDOLITED DADT #	DON'T CARE -	OR (FIXED)	All unused product terms must be programmed with
CUSTOMER SYMBOLIZED PART #			all pairs of fuses in the INACTIVE state (all fuses
TOTAL NUMBER OF PARTS		DIRECTION D ACTIVE OUTPUT A	on an unused p-term must be programmed). 5. Data cannot be entered into the OR array field due
PROGRAM TABLE # REV DATE		NOT USED	to the fixed nature of the device architecture.
		i	
VARIABLE P 7 7 7 8 8 8 6 5 6 6 6 6 7 5 5 5 5 5 5 5 5 5 5 5 5 5	40 38 37 8 33 33 32 30 29	28 27 26 22 23 22 24 28 28 28 28 28 28 28 28 28 28 28 28 28	1 15 15 15 15 15 15 15 15 15 15 15 15 15
	 		0
0	 	++++++++	0
┠──────────────────────────────────────	H++H++H++	+ + + + + + + + + + + + + + + + + + +	┝┝┥┽┾┝┥┽┾┣┥┽┾┝┥┽┾┝╉╦╣╴┃╴┃
	 		n
o	+++++++++++++++++++++++++++++++++++++++		
01	 	+++++++++	
┠┈┈┈┈┈╏╸┨┿╀┾┼┩┿┾┝┥╋┾┝┥┿┾├┥┿╂├┥┿╄┝┥┿┼┠┪┿┼	┝┥┿┾┝┫┿┾┝┥┿┾	┝┥╉┾┝┥┿┾┝┥┿╺	┝┝┥┿┾┝┥┿┾┡┥┿┾┝┥┼┾┝╂╦╣╏╏
	+++++++++++++++++++++++++++++++++++++++		
N N N N N N N N N N N N N N N N N N N			
	+++++		AND AND
			
<u> </u>			7
80			0
3			σ
6	$\square \bot \bot \square \bot \bot \bot \bot$		
5			
14			N
3			
12			
	MMMMM	MMMMM	
	MMMMM	MMMMM	>>>>>
	MMMMM	DOCCEC	
		>0/////////////////////////////////////	OR (FIXED
<u> </u>		*********	

Signetics

Document No.	853–1396						
ECN No.	97550						
Date of Issue	September 1, 1989						
Status	Product Specification						
Programmable Logic Devices							

DESCRIPTION

The PLC18V8Z35 and PLC18V8ZI are universal PAL-type devices featuring high performance and virtually zero-standby power for power sensitive applications. They are reliable, user-configurable substitutes for discrete TTL/CMOS logic. While compatible with TTL and HCT logic, the PLC18V8ZI can also replace HC logic over the $\rm V_{CC}$ range of 4.5 to 5.5V.

The PLC18V8Z is a two-level logic element comprised of 10 inputs, 74 AND gates (product terms) and 8 output Macro cells.

Each output features an "Output Macro Cell" which can be individually configured as a dedicated input, a combinatorial output, or a registered output with internal feedback. As a result, the PLC18V8Z is capable of emulating all common 20-pin PAL devices to reduce documentation, inventory, and manufacturing costs.

A power-up reset function and a Register Preload function have been incorporated in the PLC18V8Z architecture to facilitate state machine design and testing.

With a standby current of less than 100µA and active power consumption of 1.5mA/MHz, the PLC18V8Z is ideally suited for power sensitive applications in battery operated/backed portable instruments and computers.

The PLC18V8Z is also processed to industrial requirements for operation over an extended temperature range of -40°C to +85°C and supply voltage of 4.5V to 5.5V.

Ordering information can be found in the Ordering Information table.

PLC18V8Z35/PLC18V8ZI

Zero Standby Power Universal PAL®-type Devices


FEATURES

- 20-pin Universal Programmable Array Logic
- Virtually Zero-Standby-power
- Functional replacement for Series 20 PAL devices
 - $-I_{OL} = 24mA$
- High-performance CMOS EPROM cell technology
 - Erasable
 - Reconfigurable
- 100% testable
- 35ns Max propagation delay (comm)
- 40ns Max propagation delay (Industrial)
- Up to 18 inputs and 8 input/output macro cells
- Programmable output polarity
- Power-up reset on all registers
- · Register Preload capability
- Synchronous Preset/Asynchronous Reset
- Security fuse to prevent duplication of proprietary designs
- Design support provided using AMAZE software development package and other CAD tools for PLDs
- Available in 300mil-wide DIP with quartz window, plastic DIP (OTP) or PLCC (OTP)

APPLICATIONS

- Battery powered instruments
- Laptop and pocket computers
- Industrial control
- Medical Instruments
- Portable communications equipment

PIN CONFIGURATIONS



Ground

®PAL is a registered trademark of Monolithic Memories, Inc., a wholly owned subsidiary of Advanced Micro Devices, Inc.


Philips Components





PLC18V8Z Series

LOGIC DIAGRAM



Output polarity is inverting.

All cells are in a conductive state.

All AND gate locations are pulled to a logic "0" (Low).

Denotes a programmable cell location.

All output macro cells (OMC) are configured as bidirectional I/O, with the outputs disabled via the direction term.

PLC18V8Z Series


PAL DEVICE TO PLC18V8Z OUTPUT PIN CONFIGURATION CROSS REFERENCE

PIN NO.	PLC 18V8Z	16L8 16H8 16P8 16P8	16R4 16RP4	16R6 16RP6	16R8 16RP8	16L2 16H2 16P2	14L4 14H4 14P4	12L6 12H6 12P6	10L8 10H8 10P8
1	I ₀ /CLK	ı	CLK	CLK	CLK	- 1	I	- 1	1
19	F7	В	В	В	D	L	I	1	0
18	F6	В	В	D	D	1	- 1	0	0
17	F5	В	D	D	D	ı	0	0	0
16	F4	В	D	D	D	0	0	0	0
15	F3	В	D	D	D	0	0	0	0
14	F2	В	D	D	D	I	0	0	0
13	F1	В	В	D	D	1	ı	0	0
12	F0	В	В	В	D	I	1	1	0
11	I ₉ ∕ŌE	- 1	ŌE	ŌĒ	OE	I	- 1	ı	1


The Signetics state-of-the-art Floating-Gate CMOS EPROM process yields bipolar equivalent performance at less than one-quarter the power consumption. The erasable nature of the EPROM process enables Signetics to functionally test the devices prior to shipment

to the customer. Additionally, this allows Signetics to extensively stress test, as well as ensure the threshold voltage of each individual EPROM cell. 100% programming yield is subsequently guaranteed.

FUNCTIONAL DIAGRAM



OUTPUT MACRO CELL (OMC)



THE OUTPUT MACRO CELL (OMC)

The PLC18V8Z series devices have 8 individually programmable Output Macro Cells. The 72 AND inputs (or product terms) from the programmable AND array are connected to the 8 OMCs in groups of 9. Eight of the AND terms are dedicated to logic functions; the ninth is for asynchronous direction control, which enables/disables the respective bidirectional I/O pin. Two product terms are dedicated for the Synchronous Preset and Asynchronous Reset functions.

Each OMC can be independently programmed via 16 architecture control bits, AC1_n and AC2_n (one pair per macro cell). Similarly, each OMC has a programmable output polarity control bit (Xn). By configuring the pair of architecture control bits according to the configuration cell table, 4 different configurations may be implemented. Note that the configuration cell is automatically programmed based on the OMC configuration.

DESIGN SECURITY

The PLC18V8Z series devices have a programmable security fuse that controls the access to the data programmed in the device. By using this programmable feature, proprietary designs implemented in the device cannot be copied or retrieved.

PLC18V8Z Series

CONFIGURATION CELL

A single configuration cell controls the functions of Pins 1 and 11. Refer to Functional Diagram. When the configuration cell is programmed, Pin 1 is a dedicated clock and Pin 11 is dedicated for output enable. When the configuration cell is unprogrammed, Pins 1 and 11 are both dedicated inputs. Note that the output

enable for all registered OMCs is common from Pin 11 only. Output enable control of the bidirectional I/O OMCs is provided from the AND array via the direction product term.

If any one OMC is configured as registered, the configuration cell will be automatically configured (via the design software) to ensure that the dock and output enable functions are en-

abled on Pins 1 and 11, respectively. If none of the OMCs are registered, the configuration cell will be programmed such that Pins 1 and 11 are dedicated inputs. The programming codes are as follows:


Pin 1 = CLK, Pin 11 = OE	L
Pin 1 and Pin 11 = Input	Н


	CONTR	OL CELL CONFIGURA		
FUNCTION	AC1 ₁	AC2 _N	CONFIG. CELL	COMMENTS
Registered mode	Programmed	Programmed	Programmed	Dedicated clock from Pin 1. OE Control for all registerd OMCs from Pin 11 only.
Bidirectional I/O mode ¹	Unprogrammed	Unprogrammed	Unprogrammed	Pins 1 and 11 are dedicated inputs. 3-State control from AND array only.
Fixed input mode	Unprogrammed	Programmed	Unprogrammed	Pins 1 and 11 are dedicated inputs.
Fixed output mode	Programmed	Unprogrammed	Unprogrammed	Pins 1 and 11 are dedicated inputs. The feedback path (via F _{MUX}) is disabled.

NOTE:

3. This is the virgin state as shipped from the factory.

ARCHITECTURE CONTROL—AC1 and AC2





NOTE:

A factory shipped unprogrammed device is configured such that:

- 1. This is the initial unprogrammed state. All cells are in a conductive state.
- 2. All AND gates are pulled to a logic "0" (Low).
- 3. Output polarity is inverting.
- 4. Pins 1 and 11 are configured as inputs 0 and 9. The clock and OE functions are disabled.
- 5. All Output Macro Cells (OMCs) are configured as bidirectional I/O, with the outputs disabled via the direction term.
- 6. This configuration cannot be used if any OMCs are configured as registered (Code = D). The configuration cell will be automatically configured to ensure that the clock and output enable functions are enabled on Pins 1 and 11, respectively, if any one OMC is programmed as registered.

PLC18V8Z Series

ORDERING INFORMATION

DESCRIPTION	OPERATING CONDITIONS	ORDER CODE
20-Pin Plastic Dual In-Line Package 300mil-wide (t _{PD} = 35ns)	Commercial Temperature Range	PLC18V8Z35N
20-Pin Ceramic Dual In-Line Package 300mil-wide with quartz window (t _{PD} = 35ns)	± 5% Power Supplies	PLC18V8Z35FA
20-Pin Plastic Leaded Chip Carrier 350mil square (tp _D = 35ns)		PLC18V8Z35A
20-Pin Plastic Dual In-Line Package 300mil-wide (tp _D = 40ns)	Industrial Temperature Range	PLC18V8ZIN
20-Pin Ceramic Dual In-Line Package 300mil-wide with quartz window (tpD = 40ns)	± 10% Power Supplies	PLC18V8ZIFA
20-Pin Plastic Leaded Chip Carrier 350mil square (t _{PD} = 40ns)		PLC18V8ZIA

ABSOLUTE MAXIMUM RATINGS1


SYMBOL	PARAMETER	RATINGS	UNIT
Vcc	Supply voltage	-0.5 to +7	V _{DC}
V _{CC}	Operating supply voltage	4.5 to 5.5 (Industrial) 4.75 to 5.25 (Commercial)	V _{DC}
VIN	Input voltage	-0.5 to V _{CC} + 0.5	V _{DC}
V _{OUT}	Output voltage	-0.5 to V _{CC} + 0.5	V _{DC}
I _{IN}	Input currents	-10 to +10	mA
l _{out}	Output currents	+24	mA
T _A	Operating temperature range	-40 to +85 (Industrial) 0 to +75 (Commercial)	°C
T _{STG}	Storage temperature range	-65 to +150	°C

THERMAL RATINGS


TEMPERATURE	
Maximum junction	150°C
Maximum ambient	75°C
Allowable thermal rise ambient to junction	75°C

NOTE:

AC TEST CONDITIONS



VOLTAGE WAVEFORMS



Stresses above those listed may cause malfuncion or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

PLC18V8Z Series


DC ELECTRICAL CHARACTERISTICS Commercial = $0^{\circ}C \le T_{A} \le +75^{\circ}C$, $4.75V \le V_{CC} \le 5.25V$;

Industrial = -40° C $\leq T_A \leq +85^{\circ}$ C, 4.5V $\leq V_{CC} \leq 5.5$ V

				LIMITS		
SYMBOL	PARAMETER	TEST CONDITION	Min	Typ ¹	Max	UNIT
Input volt	age					
V _{IL}	Low	V _{CC} = Min	-0.3		0.8	٧
VIH	High	V _{CC} = Max	2.0		V _{CC} + 0.3	V
Output vo	oltage ²					
V _{OL}	Low	$V_{CC} = Min, I_{OL} = 20\mu A$ $V_{CC} = Min, I_{OL} = 24mA$			0.100 0.500	V V
V _{OH}	High	V_{CC} = Min, I_{OH} = -3.2mA V_{CC} = Min, I_{OH} = -20 μ A	2.4 V _{CC} - 0.1V			V
Input curi	rent					
I _{IL}	Low ⁷	V _{IN} = GND			-10	μА
I _{IH}	High	$V_{IN} = V_{CC}$			10	μА
Output cu	irrent					
I _{O(OFF)}	Hi–Z state	$V_{OUT} = V_{CC}$ $V_{OUT} = GND$			10 -10	μА μΑ
los	Short-circuit ³	V _{OUT} = GND			-130	mA
Icc	V _{CC} supply current (Standby)	V _{CC} = Max, V _{IN} = 0 or V _{CC} ⁸			100	μА
I _{CC} /f	V _{CC} supply current (Active) ⁴	V _{CC} = Max (CMOS inputs) ^{5, 6}			1.5	mA/MH
Capacitar	nce		-			
Cı	Input	V _{CC} = 5V V _{IN} = 2.0V		12		pF
C _B	1/0	V _B = 2.0V		15		pF

NOTES:

- 1. All typical values are at $V_{CC} = 5V$, $T_A = +25^{\circ}C$.
- 2. All voltage values are with respect to network ground terminal.
- 3. Duration of short-circuit should not exceed one second. Test one at a time.
- 4. Tested with TTL input levels: $V_{IL} = 0.45V$, $V_{IH} = 2.4V$. Measured with all outputs switching.
- 5. $\Delta I_{CC}/TTL$ input = 2mA.
- 6. ΔI_{CC} vs frequency (registered configuration) = 2mA/MHz.
- 7. I_{IL} for Pin 1 (I_0 /CLK) is \pm 10 μ A with V_{IN} = 0.4V.
- 8. V_{IN} includes CLK and OE if applicable.






Figure 2. ∆t_{PD} vs Output Capacitance Loading (Typical)

PLC18V8Z Series

AC ELECTRICAL CHARACTERISTICS Commercial = 0° C \leq T_A \leq +75°C, 4.75V \leq V_{CC} \leq 5.25V;

Industrial = -40° C \leq T_A \leq +85°C, 4.5V \leq V_{CC} \leq 5.5V; R₂ = 390 Ω

	,			TEST CONDITIO	N¹		V8Z35 nercial)	PLC18V8ZI (Industrial)		
SYMBOL	PARAMETER	FROM	то	R ₁ (Ω)	C _L (pF)	Min	Max	Min	Max	וואט
Pulse wi	dth		•				4		•	-
t _{CKP}	Clock period (Minimum t _{IS} + t _{CKO})	CLK+	CLK+	200	50	47		57		ns
t _{CKH}	Clock width High	CLK+	CLK-	200	50	20		25		ns
t _{CKL}	Clock width Low	CLK-	CLK+	200	50	20		25		ns
t _{ARW}	Async reset pulse width	I±, F±	1∓, F∓			35		40	ns	
Hold time	е		-				A		•	
tiH	Input or feedback data hold time	CLK+	Input ±	200	50	0		0		ns
Setup tin	ne			***************************************				A	-	***************************************
t _{IS}	Input or feedback data setup time	I±, F±	CLK+	200	50	25		30		ns
Propaga	tion delay		•				A	A	A	
t _{PD}	Delay from input to active output	I±, F±	F±	200	50	2. 7	35	-, 6	40	ns
tско	Clock High to output valid access Time	CLK+	F±	200	50		22		27	ns
t _{OE1} 3	Product term enable to outputs off	I ±, F±	F±	Active-High R = 1.5k Active-Low R = 550	50		35		40	ns
t _{OD1} ²	Product term disable to outputs off	I ±, F±	F±	From V _{OH} R = ∞ From V _{OL} R = 200	5		35		40	ns
t _{OD2} 2	Pin 11 output disable High to outputs off	OE –	F±	From V _{OH} R = ∞ From V _{OL} R = 200	5		25		30	ns
t _{OE2} 3	Pin 11 output enable to active output	OE +	F±	Active-High R = 1.5k Active-Low R = 550	50		25		30	ns
t _{ARD}	Async reset delay	I±, F±	F+		,		35		40	ns
t _{ARR}	Async reset recovery time	I±, F±	CLK+			25		30		ns
t _{SPR}	Sync preset recovery time	I±, F±	CLK+			25		30		ns
t _{PPR}	Power-up reset	V _{CC} +	F+				35		40	ns
Frequence	cy of operation			_						
MAX OTES:	Maximum frequency	I/(t _{IS} -	t _{CKO})	200	50		21		18	МН

NOTES

- 1. Refer also to AC Test Conditions. (Test Load Circuit)
- 2. 3–State levels are measured $\pm 0.5 V$ from the active steady–state level.
- 3. Resistor values of 1.5k and 550Ω provide 3–State levels of 1.0V and 2.0V, respectively. Output timing measurements are to 1.5V level.

PLC18V8Z Series


POWER-UP RESET

In order to facilitate state machine design and testing, a power-up reset function has been incorporated in the PLC18V8Z. All internal registers will reset to active-Low (logical "0") after a specified period of time (tppR). Therefore, any

OMC that has been configured as a registered output will always produce an active-High on the associated output pin because of the inverted output buffer. The internal feedback (Q)


of a registered OMC will also be set Low. The programmed polarity of OMC will not affect the active-High output condition during a system power-up condition.

TIMING DIAGRAMS



PLC18V8Z Series

TIMING DIAGRAMS (Continued)



PLC18V8Z Series

REGISTER PRELOAD FUNCTION (DIAGNOSTIC MODE ONLY)

In order to facilitate the testing of state machine/controller designs, a diagnostic mode register preload feature has been incorporated into the PLC18V8Z series device. This feature enables the user to load the registers with pre-


determined states while a super voltage is applied to Pins 11 and 6 (Ig/OE and I₅). (See diagram for timing and sequence.)

To read the data out, Pins 11 and 6 must be returned to normal TTL levels. The outputs, F_{0-7} , must be enabled in order to read data out. The

Q outputs of the registers will reflect data in as input via F_{0-7} during preload. Subsequently, the register Q output via the feedback path will reflect the data in as input via F_{0-7} .

Refer to the voltage waveform for timing and voltage references. $t_{PL} = 10 \mu sec.$

REGISTER PRELOAD (DIAGNOSTIC MODE)




LOGIC PROGRAMMING

The PLC18V8Z can be programmed by means of Logic Programming equipment.


With Logic programming, the AND/OR/Ex-OR gate input connections necessary to implement the desired logic function are coded directly from logic equations using the Program Table. Similarly, various OMC configurations are implemented by programming the Architecture Control bits AC1 and AC2. Note that the configuration cell is automatically programmed based on the OMC configuration.

In this table, the logic state of variables I, P and B associated with each Sum Term S is assigned a symbol which results in the proper fusing pattern of corresponding link pairs, defined as follows:

OUTPUT POLARITY - (O, B)



"AND" ARRAY - (I, B)



NOTE:

1. A factory shipped unprogrammed device is configured such that all cells are in a conductive state.

PLC18V8Z Series

ERASURE CHARACTERISTICS (For Quartz Window Packages Only)

The erasure characteristics of the PLC18V8Z Series devices are such that erasure begins to occur upon exposure to light with wavelengths shorter than approximately 4000 Angstroms (Å). It should be noted that sunlight and certain types of fluorescent lighting could erase a typical PLC18V8Z in approximately three years, while it would take approximately one week to cause erasure when exposed to direct sunlight.

If the PLC18V8Z is to be exposed to these types of lighting conditions for extended periods of time, opaque labels should be placed over the window to prevent unintentional erasure

The recommended erasure procedure for the PLC18V8Z is exposure to shortwave ultraviolet light which has a wavelength of 2537 Angstroms (Å). The integrated dose (i.e., UV intensity × exposure time) for erasure should be a minimum of 15Wsec/cm². The erasure time with this dosage is approximately 30 to 35

minutes using an ultraviolet lamp with a 12,000μW/cm² power rating. The device should be placed within one inch of the lamp tubes during erasure. The maximum integrated dose a CMOS EPLD can be exposed to without damage is 7258Wsec/cm²). Exposure of these CMOS EPLDs to high intensity UV light for longer periods may cause permanent damage.

The maximum number of guaranteed erase/ write cycles is 50. Data retention exceeds 20 years.

PROGRAMMING


The PLC18V8Z35/I is programmable on conventional programmers for 20—pin PAL devices. Refer to the following charts for qualified manufacturers of programmers and software tools:

PROGRAMMER MANUFACTURER	PROGRAMMER MODEL	FAMILY/PINOUT CODES
DATA I/O CORPORATION 10525 WILLOWS ROAD, N.E. P.O. BOX 97046 REDMOND, WASHINGTON 98073–9746 (800)247–5700	System 29B, LogicPak TM 303A-011A; V09 (DIL) 303A-011B; V04 (PLCC) UNISITE 40/48 V2.5 (DIL) Chipsite (PLCC) - TBA MODEL 60 TBA	86/4F
STAG MICROSYSTEMS, INC. 1600 WYATT DRIVE SUITE 3 SANTA CLARA, CALIFORNIA 95054 (408)988–1118	ZL30/30A PROGRAMMER REV. 30A34 (DIL) 30A001 Adaptor (PLCC) PPZ PROGRAMMER TBA	12/205

SOFTWARE MANUFACTURER	DEVELOPMENT SYSTEM
SIGNETICS COMPANY 811 EAST ARQUES AVENUE P.O. BOX 3409 SUNNYVALE, CALIFORNIA 94088–3409 (408)991–2000	AMAZE SOFTWARE REV. 1.8 AND LATER
DATA I/O 10525 WILLOWS ROAD, N.E. P.O. BOX 97046 REDMOND, WASHINGTON 98073–9746 (800)247–5700	ABEL™ SOFTWARE
LOGICAL DEVICES, INC. 1201 NORTHWEST 65TH PLACE FORT LAUDERDALE, FLORIDA 33309 (800)331–7766	CUPL™ SOFTWARE

PLC18V8Z Series

PROGRAM TABLE



^{*} THE CONFIGURATION CELL IS AUTOMATICALLY PROGRAMMED BASED ON THE OMC ARCHITECTURE. ** FOR SP, AR: "-" IS NOT ALLOWED.

Signetics

Document No.	
ECN No.	
Date of Issue	October 1989
Status	Preliminary Specification
Programmable	Logic Devices

10H20EV8/10020EV8 ECL Programmable Array Logic

DESCRIPTION

The 10H20EV8/10020EV8 is an ultra high-speed universal ECL PAL®-type device. Combining versatile output macrocells with a standard AND/OR single programmable array, this device is ideal in implementing a user's custom logic. The use of Signetics state-of-the-art bipolar oxide isolation process enables the 10H20EV8/10020EV8 to achieve optimum speed in any design. The AMAZE design software package from Signetics simplifies design entry based upon Boolean or state equations.

The 10H20EV8/10020EV8 is a two-level logic element comprised of 11 fixed inputs, an input pin that can either be used as a clock or 12th input, 90 AND gates, and 8 Output Logic Macrocells. Each Output Macrocell can be individually configured as a dedicated input, dedicated output with polarity control, a bidirectional I/O, or as a registered output that has both output polarity control and feedback to the AND array. This gives the part the capability of having up to 20 inputs and eight outputs.


The 10H20EV8/10020EV8 has a variable number of product terms that can be OR'd per output. Four of the outputs have 12 AND terms available and the other four have 8 terms per output. This allows the designer the extra flexibility to implement those functions that he couldn't in a standard PAL device. Asynchronous Preset and Reset product terms are also included for system design ease. Each output has a separate output enable product term. Another feature added for the system designer is a power-up Reset on all registered outputs.

The 10H20EV8/10020EV8 also features the ability to Preload the registers to any desired state during testing. The Preload is not affected by the pattern within the device, so can be performed at any step in the testing sequence. This permits full logical verification even after the device has been patterned.

FEATURES

- Ultra high speed ECL device
- $-t_{PD} = 4.5ns (max)$
- $t_{IS} = 2.5 ns (max)$
- t_{CKO} = 2ns (max)
- $-f_{MAX} = 222MHz$
- Universal ECL Programmable Array Logic
 - 8 user programmable output macrocells
 - Up to 20 inputs and 8 outputs
- Individual user programmable output polarity
- Variable product term distribution allows increased design capability
- Asynchronous Preset and Reset capability
- 10KH and 100K options
- Power-up Reset and Preload function to enhance state machine design and testing
- Design support provided via AMAZE and other CAD tools
- Security fuse for preventing design duplication
- Available in 24-Pin 300mil-wide DIP and 28-Pin PLCC.

PIN CONFIGURATION



Philips Components






[®]PAL is a registered trademark of Monolithic Memories, Inc., a wholly owned subsidiary of Advanced Micro Devices, Inc.

10H20EV8/10020EV8


LOGIC DIAGRAM



October 1989

10H20EV8/10020EV8

FUNCTIONAL DIAGRAM



FUNCTIONAL DESCRIPTION

The 10H20EV8/10020EV8 is an ultra high-speed universal ECL PAL-type device. Combining versatile Output Macrocells with a standard AND/OR single programmable array, this device is ideal in implementing a user's custom logic.


As can be seen in the Logic Diagram, the device is a two-level logic element with a programmable AND array. The 20EV8 can have up to 20 inputs and 8 outputs. Each output has a versatile Macrocell whereby the output can either be configured as a dedicated input, a dedicated combinatorial output with polarity control, a bidirectional I/O, or as a registered output that has both output polarity control and feedback into the AND array.

The device also features 90 product terms. Two of the product terms can be used for a global asynchronous preset and/or reset. Eight of the product terms can be used for individual output enable control of each Macrocell. The other 80 product terms are distributed among the outputs. Four of the outputs have eight product terms, while the other four have 12. This arrangement allows the utmost in flexibility when implementing user patterns.

Output Logic Macrocell

The 10H20EV8/10020EV8 incorporates an extremely versatile Output Logic Macrocell that allows the user complete flexibility when configuring outputs.

As seen in Figure 1, the 10H20EV8/10020EV8 Output Logic Macrocell consists of an edgetriggered D-type flip-flop, an output select MUX, and a feedback select MUX. Fuses So and S₁ allow the user to select between the various cells. S₁ controls whether the output will be either registered with internal feedback or combinatorial I/O. So controls the polarity of the output (Active-HIGH or Active-LOW). This allows the user to achieve the following configurations: Registered Active-HIGH output, Registered Active-LOW output, Combinatorial Active-HIGH output, and Combinatorial Active-LOW output. With the output enable product term, this list can be extended by adding the configurations of a Combinatorial I/O with Polarity or another input.



10H20EV8/10020EV8

ORDERING INFORMATION

DESCRIPTION	ORDER CODE
24-Pin Ceramic Dual In-Line (300mil-wide)	10H20EV8-6F 10H20EV8-4F 10020EV8-6F 10020EV8-4F
28-Pin Plastic Leaded Chip Carrier	10H20EV8-6A 10H20EV8-4A 10020EV8-6A 10020EV8-4A

ABSOLUTE MAXIMUM RATINGS¹

SYMBOL	PARAMETER	RATING	UNIT
V _{EE}	Supply voltage (V _{CC} = 0)	-8	V _{DC}
V _{IN}	Input voltage (V _{CC} = 0)	0 to V _{EE}	V _{DC}
Io	Output source current	40	mA _{DC}
TA	Operating Temperature range	0 to +75 (10KH) 0 to +85 (100K)	°C
T _{STG}	Storage Temperature range	-55 to +150	°C


OPERATING RANGES

			RATINGS		
DEVICE	SYMBOL	PARAMETER	Min	Max	UNIT
10H20EV8	V _{EE}	Supply voltage	-5.46	-4.94	V _{DC}
	TA	Operating free-air temperature	0	+75	°C
10020EV8	V _{EE}	Supply voltage	-4.8	-4.2	V _{DC}
	TA	Operating free-air temperature	0	+85	°C

NOTE:

1. Stresses above those listed may cause malfunction or permanent damage to the device. This is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

10H20EV8/10020EV8



OUTPUT MACRO CELL CONFIGURATION

Shown in Figure 2 are the four possible configurations of the output macrocell using fuses S_0 and S_1 . As seen, the output can either be registered Active—HIGH/LOW with feedback or combinatorial Active—HIGH/LOW with feedback. If the registered mode is chosen, the feedback is from the $\overline{\Omega}$ output to the AND array enables one to make state machines or shift registers without having to tie the output to one of the inputs. If a combinatorial output is chosen, the feedback gate is enabled from the pin and allows one to create permanent outputs, permanent inputs, or I/O pins through the use of the output enable (D) product term.

OUTPUT ENABLE

Each output on the 10H20EV8/10020EV8 has its own individual product term for output enable. The use of the D product term (direction control) allows the user three possible configurations of the outputs. They are always enabled, always disabled, and controlled by a programmed pattern. A HIGH on the D term enables the output, while a LOW performs the disable function. Output enable control can be achieved by programming a pattern on the D term.

The output enable control can also be used to expand a designer's possibilities once a combinatorial output has been chosen. If the D term is always HIGH, the pin becomes a permanent

Active-HIGH/LOW output. If the D term is always LOW (all fuses left intact), the pin now becomes an extra input.

PRESET AND RESET

The 10H20EV8/10020EV8 also includes a separate product term for asynchronous Preset and asynchronous Reset. These lines are common for all registers and are asserted when the specific product term goes HIGH. Being asynchronous, they are independent of the clock. It should be noted that the actual state of the output is dependent on how the polarity of the particular output has been chosen. If the outputs are a mix of Active—HIGH and Active—LOW, a Preset signal will force the Active—HIGH outputs HIGH while the Active—LOW outputs would go LOW, even though the Q output of all flip—flops would go HIGH. A Reset signal would force the opposite conditions.

PRELOAD

To simplify testing, the 10H20EV8/10020EV8 has also included PRELOAD circuitry. This allows a user to load any particular data desired into the registers regardless of the programmed pattern. This means that the PRELOAD can be done on a blank part and after that same part has been programmed to facilitate any post-fuse testing desired.

It can also be used by a designer to help debug his/her circuit. This could be important if a state machine was implemented in the 10H20EV8/

10020EV8. The PRELOAD would allow a designer to enter any state in the sequence desired and start clocking from that particular point. Any or all transitions could be verified.

AMAZE

The AMAZE PLD Design Software development system also supports the 10H20EV8/ 10020EV8. AMAZE provides the following capabilities for the 10H20EV8/10020EV8:

- State equation entry
- Boolean equation entry
- Logic and timing simulation
- Automatic test vector generation

AMAZE operates on an IBM PC/XT, PC/AT, PS/2, or any compatible system with DOS 2.0 or higher. The minimum system configuration for AMAZE is 640K bytes of RAM and a hard disk.

AMAZE compiles the design after completion for syntax and completeness. Programming data is generated in JEDEC format.

DESIGN SECURITY

The 10H20EV8/10020EV8 has a programmable security fuse that controls the access to the data programmed in the device. By using this programmable feature, proprietary designs implemented in the device cannot be copied or retrieved.

October 1989

10H20EV8/10020EV8

DC ELECTRICAL CHARACTERISTICS 10H20EV8: $0^{\circ}C \le T_A \le +75^{\circ}C$, $V_{EE} = -5.2V \pm 5\%$, $V_{CC} = V_{CO1} = V_{CO2} = GND$ 10020EV8: $0^{\circ}C \le T_A \le +85^{\circ}C$, $-4.8V \le V_{EE} \le -4.2V$, $V_{CC} = V_{CO1} = V_{CO2} = GND$

					LIMITS		
SYMBOL	PARAMETER ¹	TEST CONDITIONS ²		TA	Min	Max	UNITS
V _{OH}	High level output voltage	$V_{IN} = V_{IH}$ Max. or V_{IL} Min.	10KH	0°C +25°C +75°C	-1020 -980 -920	-840 -810 -735	mV
			100K	0°C to 85°C	-1025	-880	mV
V _{OHT}	High level output threshold voltage	V _{IN} = V _{IH} Max. or V _{IL} Min.	100K	0°C to 85°C	-1035		mV
V _{OL}	Low level output voltage	$V_{IN} = V_{IH}$ Max. or V_{IL} Min.	10KH	0°C +25°C +75°C	-1950 -1950 -1950	-1630 -1630 -1600	mV
			100K	0°C to 85°C	-1810	-1620	mV
V _{OLT}	High level output threshold voltage	V _{IN} = V _{IH} Max. or V _{IL} Min.	100K	0°C to 85°C		-1610	mV
V _{IH}	High level input voltage	Guaranteed input voltage high for all inputs	10KH	0°C +25°C +75°C	-1170 -1130 -1070	-840 -810 -735	mV
			100K	0°C to 85°C	-1165	-880	mV
V _{IL}	Low level input voltage	Guaranteed input voltage low for all inputs	10KH	0°C +25°C +75°C	-1950 -1950 -1980	-1480 -1480 -1450	mV
			100K	0°C to 85°C	-1810	-1475	mV
I _{IH}	High level input current	V _{IN} = V _{IH} Max.	10KH	0°C +75°C		220	μА
			100K	0°C to 85°C			
I _{IL}	Low level input current	V _{IN} = V _{IL} Min. Except I/O Pins	10KH	0°C +75°C	0.3		μА
			100K	0°C to 85°C	0.5		
I _{EE}	Supply current	V _{EE} = Max. All inputs and outputs open	10KH	0°C to 75°C	-230		mA
			100K	0°C to 85°C			

NOTES:


^{1.} All voltage measurements are referenced to the ground terminal.

Each ECL 10KH/100K series device has been designed to meet the DC specification after thermal equilibrium has been established. The
circuit is in a test socket or mounted on a printed circuit board and transverse air flow greater than 500 (150 meters) linear fpm is maintained.
 Voltage levels will shift approximately 4mV with an air flow of 200 linear fpm. Outputs are terminated through a 50Ω resistor to -2V.

Terminals not specifically referenced can be left electrically open. Open inputs assume a logic LOW state. Any unused pins can be terminated to –2V. If tied to V_{EE}, it must be through a resistor > 10K.

10H20EV8/10020EV8

AC TEST CIRCUIT




NOTES

- Use decoupling capacitors of 0.1μF and 25μF from GND to V_{CC}, and 0.01μF and 25μF from GND to V_{EE} (0.01 and 0.1μF capacitors should be NPO Ceramic or MLC type). Decoupling capacitors should be placed as close as physically possible to the DUT and lead length should be kept to less than ¹/₄ inch (6mm).
- 2. All unused inputs should be connected to either HIGH or LOW state consistent with the LOGIC function required.
- 3. All unused outputs are loaded with 50Ω to GND.
- 4. L_1 and L_2 are equal length 50Ω impedance lines, L_3 , the distance from the DUT pin to the junction of the cable from the Pulse Generator and the cable to the Scope, should not exceed $^{1}/_{4}$ inch (6mm).
- 5. $R_T = 50\Omega$ terminator internal to Scope.
- 6. The unmatched wire stub between coaxial cable and pins under test must be less than 1/4 inch (6mm) long for proper test.
- 7. C_L = Fixture and stray capacitance ≤ 3pF.
- 8. Any unterminated stubs connected anywhere along the transmission line between the Pulse Generator and the DUT or between the DUT and the Scope should not exceed 1/4 inch (6mm) in length (refer to section on AC setup procedure).
- 9. All 50Ω resistors should have tolerance of \pm 1% or better.
- 10. Test procedures are shown for only one input or set of input conditions. Other inputs are tested in the same manner.
- 11. Two 10μF capacitors between V_{CC} and V_{CO1} and V_{CO2} respectively located as close to the device as possible is recommended to reduce ringing.
- 12. Normal practice in test fixtures layout should be followed. Lead lengths, particular to the power supply, should be as short as possible.

10H20EV8/10020EV8

VOLTAGE WAVEFORMS



10H20EV8/10020EV8

AC ELECTRICAL CHARACTERISTICS 10H20EV8: 0°C \leq T_A \leq +75°C, V_{EE} = -5.2V \pm 5%, V_{CC} = V_{CO1} = V_{CO2} = GND 10020EV8: $0^{\circ}C \le T_A \le +85^{\circ}C$, $-4.8V \le V_{EE} \le -4.2V$, $V_{CC} = V_{CO1} = V_{CO2} = GND$


	PARAMETER	FROM	то	TEST CONDITIONS ¹	LIMITS				
SYMBOL					-4		-6		UNIT
					Min	Max	Min	Max	
Pulse Width									
tckH	Clock High	CLK+	CLK-		2		3		ns
t _{CKL}	Clock Low	CLK-	CLK+		2		3		ns
t _{CKP}	Clock Period	CLK+	CLK+		. 4		6		ns
t _{PRH}	Preset/Reset Pulse	(I, I/O) ±	(I, I/O) ±		4.5		6		ns
Setup and Hold Time									
t _{IS}	Input	(I, I/O) ±	CLK+		2.5		4		ns
t _{IH}	Input	CLK+	(I, I/O) ±		0		0		ns
t _{PRS}	Clock Resume after Preset/Reset	(I, I/O) ±	CLK+		4.5		6		ns
Propagation Delay									
t _{PD}	Input	(I, I/O) ±	I/O ±			4.5		6	ns
t _{CKO}	Clock	CLK+	I/O ±			2		3	ns
toE	Output Enable	(I, I/O) ±	1/0			4.5		6	ns
t _{OD}	Output Disable	(I, I/O) ±	1/0			4.5		6	ns
t _{PRO}	Preset/Reset	(I, I/O) ±	I/O ±			4.5		6	ns
tppR	Power-on Reset	V _{EE}	1/0		1	10			ns

NOTES:

1. Refer to AC Test Circuit and Voltage Wafeforms diagrams.


10H20EV8/10020EV8

TIMING DIAGRAMS



10H20EV8/10020EV8

TIMING DIAGRAMS (Continued)




10H20EV8/10020EV8

REGISTER PRELOAD

The 10H20EV8/10020EV8 has included circuitry that allows a user to load data into the output registers. Register PRELOAD can be done at any time and is not dependent on any particular pattern programmed into the device. This simplifies the ability to fully verify logic states and sequences even after the device has been patterned.

The pin levels and sequence necessary to perform the register PRELOAD are shown below.



		LIMITS			
SYMBOL	PARAMETER	Min.	Тур.	Max	UNIT
V _{IH}	Input HIGH level during PRELOAD and Verify	-1.1	-0.9	-0.7	٧
V _{IL}	Input LOW level during PRELOAD and Verify	-1.85	-1.65	-1.45	٧
V _{PP}	PRELOAD enable voltage applied to I ₁₁	1.45	1.6	1.75	٧

NOTE:

- Unused inputs should be handled as follows:

 - Set at V_{IH} or V_{IL}
 Terminated to -2V
 - Tied to V_{EE} through a resistor > 10K
 - Open

October 1989 98

10H20EV8/10020EV8


LOGIC PROGRAMMING

10H20EV8/10020EV8 logic designs can be generated using Signetics' AMAZE PLD design software or one of several other commercially available, JEDEC standard PLD design software packages. Boolean and/or state equation entry is accepted.

10H20EV8/10020EV8 logic designs can also be generated using the program table entry format detailed on the following pages. This program table entry format is supported by the Signetics' AMAZE PLD design software (PTP module), AMAZE is available free of charge to qualified users.

To implement the desired logic functions, the state of each logic variable from logic equations (I, F, Q, etc.) is assigned a symbol. The symbols for TRUE, COMPLEMENT, INACTIVE, PRESET, etc., are defined below.

"AND" ARRAY – (I), (F), (\overline{Q}_p)



NOTES

- 1. This is the initial unprogrammed state of all link pairs. It is normally associated with all unused (inactive) AND gates.
- 2. Any gate (P, D, AP, AR) will be unconditionally inhibited if any one of the I, F or Q link pairs is left intact.

OUTPUT MACROCELL CONFIGURATIONS


OUTPUT MACROCELL CONFIGURATION	CONTROL WORD FUSE	POLARITY FUSE	
Registered Output, Active-HIGH	D	Н	
Registered Output, Active-LOW	D ¹	L1	
Combinatorial I/O, Active-HIGH	В	Н	
Combinatorial I/O, Acitve-LOW	В	L	

NOTES:

^{1.} This is the initial (unprogrammed) state of the device.

10H20EV8/10020EV8

PROGRAM TABLE



October 1989

Signetics

Document No.	853–1359	
ECN No.	98104	
Date of Issue	November 14, 1989	
Status Product Specification		
Programmable Logic Devices		

FEATURES

- Ultra high-speed
 - t_{PD} = 7.5ns and f_{MAX} = 74MHz for the PLUS20R8-7 Series
 - t_{PD} = 10ns and f_{MAX} = 60 MHz for the PLUS20R8D Series
- 100% functionally and pin-for-pin compatible with industry standard 24-pin PAL ICs
- Power-up reset function to enhance state machine design and testability
- Design support provided via AMAZE and other CAD tools for Series 24 PAL devices
- Field-programmable on industry standard programmers
- Security fuse
- Individual 3-State control of all outputs

PLUS20R8D/-7 SERIES

PAL®-Type Devices 20L8, 20R8, 20R6, 20R4

DESCRIPTION

The Signetics PLUS20XX family consists of ultra high-speed 7.5ns and 10ns versions of Series 24 PAL devices.

The PLUS20XX family is 100% functional and pin-compatible with the 20L8, 20R8, 20R6, and 20R4 Series devices.

The sum of products (AND-OR) architecture is comprised of 64 AND gates and 8 fixed OR gates. Multiple bidirectional pins provide variable input/output pin ratios. Individual 3-State control of all outputs and registers with feedback (R8, R6, R4) is also provided. Proprietary designs can be protected by programming the security fuse.

The PLUS20R8, R6, and R4 have D-type flip-flops which are loaded on the Low-to-High transition of the clock input.

In order to facilitate state machine design and testing, a power-up reset function has been incorporated into these devices to reset all internal registers to active-Low after a specific period of time. The Signetics State-of-the-Art oxide isolation Bipolar fabrication process is employed to achieve high-performance operation.

The PLUS20XX family of devices are field programmable, enabling the user to quickly generate custom patterns using standard programming equipment. See the programmer chart for qualified programmers.

The AMAZE software package from Signetics supports easy design entry for the PLUS20XX series as well as other PLD devices from Signetics. The PLUS20XX series are also supported by other standard CAD tools for PAL-type devices.

Order codes are listed in the Ordering Information table.

DEVICE NUMBER	DEDICATED INPUTS	COMBINATORIAL OUTPUTS	REGISTERED OUTPUTS
PLUS20L8	14	8(6 I/O)	0
PLUS20R8	12	0	8
PLUS20R6	12	2 I/O	6
PLUS20R4	12	4 I/O	4

Philips Components







RPAL is a registered trademark of Monolithic Memories, Inc., a wholly owned subsidiary of Advanced Micro Devices, Inc.

PLUS20R8D/-7 SERIES


PIN CONFIGURATIONS







PLUS20R8D/-7 SERIES

PIN CONFIGURATIONS






PLUS20R8D/-7 SERIES



PLUS20R8D/-7 SERIES



PLUS20R8D/-7 SERIES

PLUS20R8D/-7 SERIES

LOGIC DIAGRAM PLUS20R4 CLK 1 -D 23 I₁₁ 22 B₇ 11 3 21 B₆ 20 Q₅ PRODUCT TERMS (0-63) 18 Q₃ Q 15 7 - 17 Q₂ a 16 8 16 B₁ 17 9 15 B₀ I₈ 10 14 I₁₀ lg 11 13 OE INPUTS (0-39) 1. All unprogrammed or virgin "AND" gate locations are pulled to logic "0" 2. Programmable connections

PLUS20R8D/-7 SERIES

FUNCTIONAL DESCRIPTIONS

The PLUS20XX series utilizes the familiar sum-of-products implementation consisting of a programmable AND array and a fixed OR array. These devices are capable of replacing an equivalent of four or more SSI/MSI integrated circuits to reduce package count and board area occupancy, consequently improving reliability and design cycle over Standard Cell or gate array options. By programming the security fuse, proprietary designs can be protected from duplication.

The PLUS20XX series consists of four PALtype devices. Depending on the particular device type, there are a variable number of combinatorial and registered outputs available to the designer. The PLUS20L8 is a combinatorial part with 8 user configurable outputs (6 bidirectional), while the other three devices, PLUS20R8, PLUS20R6, PLUS20R4, have respectively 8, 6, and 4 output registers.

3-State Outputs

The PLUS20XX series devices also feature 3—State output buffers on each output pin which can be programmed for individual control of all outputs. The registered outputs (Qn) are controlled by an external input (/OE), and the combinatorial outputs (On, Bn) use a product term to control the enable function.

Programmable Bidirectional Pins

The PLUS20XX products feature variable Input/Output ratios. In addition to 12 dedicated inputs, each combinatorial output pin of the registered devices can be individually programmed as an input or output. The PLUS20L8 provides 14 dedicated inputs and 6 Bidirectional I/O lines that can be individually configured as inputs or outputs.

Output Registers

The PLUS20R8 has 8 output registers, the 20R6 has 6, and the 20R4 has 4. Each output register is a D-type flip-flop which is loaded on the Low-to-High transition of the dock input. These output registers are capable of feeding the outputs of the registers back into the array to facilitate design of synchronous state machines.

Power-up Reset

By resetting all flip-flops to a logic Low, as the power is turned on, the PLUS20R8, R6, R4 enhance state machine design and initialization capability.

Software Support

Like other Programmable Logic Devices from Signetics, the PLUS20XX series are supported

by AMAZE, the PC-based software development tool from Signetics. The PLUS20XX family of devices are also supported by standard CAD tools for PAL devices, including ABEL and CIJPI


AMAZE is available free of charge to qualified users.

Logic Programming

Logic designs for PLUS20XX series can be generated using any commercially available JEDEC standard design software that supports the 24-pin PAL devices. No JEDEC fuse map conversion or translation is necessary when transferring designs from slower 24-pin PAL devices.

To implement the desired logic functions, each logic variable from the logic equations is assigned a symbol. True (High), Complement (Low), Don't Care and Inactive symbols are defined below.

AND ARRAY - (I, B)



VIRGIN STATE

A factory shipped virgin device contains all fusible links intact, such that:

- 1. All outputs are at "H" polarity.
- 2. All Pn terms are disabled.
- 3. All P_n terms are active on all outputs.

PLUS20R8D/-7 SERIES

ORDERING INFORMATION

DESCRIPTION	ORDER CODE
24–Pin Plastic Dual–In–Line 300mil–wide	PLUS20R8DN PLUS20R6DN PLUS20R4DN PLUS20L8DN PLUS20R8-7N PLUS20R6-7N PLUS20R6-7N PLUS20R4-7N PLUS20R8-7N
28-Pin Plastic Leaded Chip Carrier (PLCC)	PLUS20R8DA PLUS20R6DA PLUS20R4DA PLUS20L8DA PLUS20R8-7A PLUS20R6-7A PLUS20R4-7A PLUS20R4-7A

NOTE:

The PLUS20XX series of devices are also processed to military requirements for operation over the military temperature range. For specifications and ordering information, consult the Signetics Military Data Book.

ABSOLUTE MAXIMUM RATINGS1

	RATINGS		-	
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage	-0.5	+7	V _{DC}
VIN	Input voltage	-0.5	+5.5	V _{DC}
V _{OUT}	Output voltage		+5.5	V _{DC}
I _{IN}	Input currents	-30	+30	mA
l _{out}	Output currents		+100	mA
T _{STG}	Storage temperature range	-65	+150	°C

NOTE:

OPERATING RANGES

		RATINGS		
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage	+4.75	+5.25	V _{DC}
TA	Operating free—air temperature	0	+75	°C

THERMAL RATINGS

TEMPERATURE		
Maximum junction	150°C	
Maximum ambient	75°C	
Allowable thermal rise ambient to junction	75°C	

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

PLUS20R8D/-7 SERIES

DC ELECTRICAL CHARACTERISTICS 0°C ≤ TA ≤ +75°C, 4.75 ≤ V_{CC} ≤ 5.25V

				LIMITS		
SYMBOL	PARAMETER TEST CONDITIONS		Min	Typ ¹	Max	UNIT
Input voltag	je ²	2				
V _{IL}	Low	V _{CC} = Min			0.8	V
V _{IH}	High	V _{CC} = Max	2.0			V
V _{IC}	Clamp	$V_{CC} = Min, I_{IN} = -18mA$		-0.8	-1.5	٧
Output volt	age	2				
		V_{CC} = Min, V_{IN} = V_{IH} or V_{IL}				
V _{OL}	Low	I _{OL} = 24mA			0.5	V
V_{OH}	High	$I_{OH} = -3.2 \text{ mA}$	2.4			V
Input curre	nt					
		V _{CC} = Max				
I _{IL}	Low ³	V _{IN} = 0.40V -250				μА
I _{IH}	High ³	V _{IN} = 2.7V			25	μΑ
I	Maximum input current	$V_{IN} = V_{CC} = V_{CCMAX}$			100	μΑ
Output curr	rent					
		V _{CC} = Max				
l _{OZH}	Output leakage	$V_{OUT} = 2.7V$			100	μΑ
lozL	Output leakage	$V_{OUT} = 0.4V$	-100			μΑ
los	Short circuit ^{4, 5}	$V_{OUT} = 0V$	-30		-90	mA
Icc	V _{CC} supply current	V _{CC} = Max		150	210	mA
Capacitano	e 6			1		
C _{IN}	Input	V _{CC} = 5V				
		V _{OUT} = 2.0V		8		pF
C _B	I/O (B)	$V_{OUT} = 2V$, $f = 1MHz$		8		pF

NOTES:

- All typical values are at V_{CC} = 5V, T_A = +25°C.
 All voltage values are with respect to network ground terminal.
 Leakage current for bidirectional pins is the worst case of I_{IL} and I_{OZL} or I_{IH} and I_{OZH}.
- 4. Test one at a time.
- 5. Duration of short circuit should not exceed 1 second.
 6. These parameters are not 100% tested but periodically sampled.

PLUS20R8D/-7 SERIES

AC ELECTRICAL CHARACTERISTICS $R_1 = 200\Omega$, $R_2 = 390\Omega$, $0^{\circ}C \le T_A \le +75^{\circ}C$, $4.75 \le V_{CC} \le 5.25V$

				LIMITS				
SYMBOL	PARAMETER	FROM	то	-	-7	1	D	TINU
			Min ¹	Max	Min ¹	Max	1	
Pulse Width	h							
t _{CKH}	Clock High	CK+	CK-	5		7		ns
t _{CKL}	Clock Low	CK-	CK+	5		7		ns
t _{CKP}	Period	CK+	CK+	10		14		ns
Setup & Ho	ld time							
t _{IS}	Input	Input or feedback	CK+	7		9		ns
t _{IH}	Input	CK+	Input or feedback	0		0		ns
Propagation	n delay				•	•		-
t _{CKO}	Clock	ск±	Q±	3	6.5	3	7.5	ns
t _{CKF}	Clock ³	ск±	۵		3		7	ns
t _{PD}	Output (20L8, R6, R4) ²	I, B	Output		7.5		10	ns
t _{OE1}	Output enable ⁴	ŌĒ	Output enable	3	8	3	10	ns
t _{OE2}	Output enable ^{4,5}	ı	Output enable	3	10	3	10	ns
t _{OD1}	Output disable ⁴	ŌE	Output disable	3	8	3	10	ns
t _{OD2}	Output disable ^{4,5}	ı	Output disable	3	10	3	10	ns
tskw	Output	Q	Q		1		1	ns
t _{PPR}	Power-Up Reset	V _{CC} +	Q+		10		10	ns
Frequency	(20R8, R6, R4)				-	•	•	•
	No feedback 1/ (t _{CKL} + t _{CK}	H) ⁶		100		71.4		MHz
f _{MAX}	Internal feedback 1/ (t _{IS} +	t _{CKF})6		100		62.5		MHz
	External feedback 1/ (t _{IS} +	t _{CKO}) ⁶		74		60.6		MHz


^{*} For definitions of the terms, please refer to the Timing/Frequency Definitions tables. NOTES:

NOTES


- 1. CL = 0pF while measuring minimum output delays.
- 2. tpD test conditions: CL = 50pF (with jig and scope capacitance), V_{IH} = 3V, V_{IL} = 0V, V_{OH} = V_{OL} = 1.5V.
- 3. t_{CKF} was calculated from measured Internal f_{MAX}.
- 4. In reference to 3—State outputs, output enable times are tested with CL = 50pF to the 2.0V or 0.8V level. Output disable times are tested with CL = 5pF. High to High-impedence tests are made to an output voltage of V_T = V_{OH}-0.5V; Low to High-impedence tests are made to the V_T = V_{OL}+0.5V level.
- 5. Same function as t_{OE1} and t_{OD1}, with the difference of using product term control.
- 6. Not 100% tested, but calculated at initial characterization and at any time a modification in design takes place which may affect the frequency.

PLUS20R8D/-7 SERIES


TEST LOAD CIRCUIT



OUTPUT REGISTER SKEW




CLOCK TO FEEDBACK PATH



PLUS20R8D/-7 SERIES

TIMING DIAGRAMS^{1, 2}



TIMING DEFINITIONS

SYMBOL	PARAMETER
tckH	Width of input clock pulse.
t _{CKL}	Interval between clock pulses.
t _{CKP}	Clock period.
t _{IS}	Required delay between be- ginning of valid input and posi- tive transition of clock.
t _{IH}	Required delay between positive transition of clock and end of valid input data.
t _{CKF}	Delay between positive transition of clock and when internal Q output of flip-flop becomes valid.
tско	Delay between positive transition of clock and when outputs become valid (with OE Low).
t _{OE1}	Delay between beginning of Output Enable Low and when outputs become valid.
t _{OD1}	Delay between beginning of Output Enable High and when outputs are in the Off–State.
t _{OE2}	Delay between predefined Output Enable High, and when combinational outputs become valid.
t _{OD2}	Delay between predefined Output Enable Low and when combinational outputs are in the Off–State.
t _{PPR}	Delay between V _{CC} (after pow- er—on) and when flip—flop out- puts become preset at "1" (in- ternal Q outputs at "0").
t _{PD}	Propagation delay between combinational inputs and outputs.

FREQUENCY DEFINITIONS

fmax	No feedback: Determined by the minimum clock period, 1/(t _{CKL} + t _{CKH}). Internal feedback: Determined by the internal delay from flip-flop outputs through the internal feedback and array to the flip-flop inputs, 1/(t _{IS} + t _{CKF}). External feedback: Determined by clock-to-output delay and input setup time, 1/(t _{IS} + t _{CKO}).

NOTES

- 1. Input pulse amplitude is 0V to 3V.
- Input rise and fall times are 2.5ns.

PLUS20R8D/-7 SERIES

PROGRAMMING

The PLUS20XX Series are programmable on conventional programmers for 24-pin PAL® devices. Refer to the following charts for qualified manufacturers of programmers and software tools:

PROGRAMMER MANUFACTURER	PROGRAMMER MODEL	FAMILY/PINOUT CODES
DATA I/O CORPORATION 10525 WILLOWS ROAD, N.E. P.O. BOX 97046 REDMOND, WASHINGTON 98073–9746 (800)247–5700	SYSTEM 29B, LogicPak TM 303A-V04 ADAPTER 303A-011A-V08 (DIP) 303A-011B-V04 (PLCC) UNISITE 40/48, V2.3 (DIP) V2.5 (PLCC) MODEL 60, 60A/H, V.13	20L8-7/20L8D : 1B/26 20R8-7/20R8D : 1B/27 20R6-7/20R6D : 1B/27 20R4-7/20R4D : 1B/27
STAG MICROSYSTEMS, INC. 1600 WYATT DRIVE SUITE 3 SANTA CLARA, CALIFORNIA 95054 (408)988–1118	ZL30/30A PROGRAMMER REV. 30A31 PPZ PROGRAMMER TBA	20L8-7/20L8D : 11/56 20R8-7/20R8D : 11/57 20R6-7/20R6D : 11/57 20R4-7/20R4D : 11/57

SOFTWARE MANUFACTURER	DEVELOPMENT SYSTEM
SIGNETICS COMPANY 811 EAST ARQUES AVENUE P.O. BOX 3409 SUNNYVALE, CALIFORNIA 94088–3409 (408)991–2000	AMAZE SOFTWARE REV. 1.7
DATA I/O 10525 WILLOWS ROAD, N.E. P.O. BOX 97046 REDMOND, WASHINGTON 98073–9746 (800)247–5700	ABEL [™] SOFTWARE REV. 1.0 AND LATER
LOGICAL DEVICES, INC. 1201 NORTHWEST 65TH PLACE FORT LAUDERDALE, FLORIDA 33309 (800)331–7766	CUPL™ SOFTWARE REV. 1.01 AND LATER

Signetics

Document No.	
ECN No.	
Date of Issue	November 1989
Status	Preliminary Specification
Programmable	Logic Devices

DESCRIPTION

The PHD48N22-7 is an ultra fast Programmable High-speed Decoder featuring a 7.5ns maximum propagation delay. The architecture has been optimized using Philips Components—Signetics state—of—the—art bipolar oxide isolation process coupled with titanium—tungsten fuses to achieve superior speed in any design.

The PHD48N22-7 is a two level logic element comprised of 36 fixed inputs, 73 AND gates, 10 outputs, and 12 bidirectional I/Os. This gives the device the ability to have as many as 48 inputs. Individual 3-State control of all outputs is also provided.

The device is field—programmable, enabling the user to quickly generate custom patterns using standard programming equipment. Proprietary designs can be protected by programming the security fuse.

The AMAZE software package from Philips Components—Signetics supports easy design entry for the PHD48N22—7 as well as other PLD devices.

Order codes are listed in the pages following.

PHD48N22-7

Programmable High-Speed Decoder Logic ($48 \times 73 \times 22$)


FEATURES

- Ideal for high speed system decoding
- Super high speed at 7.5ns tpp
- 36 dedicated inputs
- 22 outputs
- 12 bidirectional I/O
- 10 dedicated outputs
- Security fuse to prevent duplication of proprietary designs.
- Individual 3–State control of all outputs
- Field-programmable on industry standard programmers
- Available in 68—Pin Plastic Leaded Chip Carrier (PLCC)

APPLICATIONS

- High speed memory decoders
- High speed code detectors
- Random logic
- Peripheral selectors
- Machine state decoders

PIN CONFIGURATION



Pin	Function	Pin	Function
1	Ю	35	129
2	11	36	130
3	12	37	131
4	V _{CC3}	38	V _{CC4}
5	13	39	132
6	14	40	133
7	15	41	134
8	16	42	135
9	17	43	BO
10	18	44	B1
11	19	45	B2
12	110	46	B3
13	111	47	B4
14	GND5	48	GND6
15	GND1	49	GND2
16	112	50	B5
17	113	51	B6
18	114	52	B7
19	115	53	00
20	116	54	01
21	V _{CC2}	55	V _{CC1}
22		56	02
23	118	57	O3
24	119	58	04
25	120	59	O5
26	121	60	O6
27	122	61	07
28	123	62	O8
29	124	63	O9
30	125	64	OR0
31	126	65	OR1
32	GND3	66	GND4
33	127	67	OR2
34	128	68	OR3


Philips Components






PHD48N22-7

LOGIC DIAGRAM



PHD48N22-7

FUNCTIONAL DIAGRAM



ORDERING INFORMATION

DESCRIPTION	ORDER CODE
68-Pin Plastic Leaded Chip Carrier	PHD48N22-7A

ABSOLUTE MAXIMUM RATINGS¹

		RATI		
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage	-0.5	+7	V _{DC}
V _{IN}	Input voltage	-0.5	+5.5	V _{DC}
V _{OUT}	Output voltage		+5.5	V _{DC}
I _{IN}	Input currents	-30	+30	mA
lout	Output currents		+100	mA
T _A	Operating temperature range	0	+75	°C
T _{STG}	Storage temperature range	-65	+150	°C

NOTES:

OPERATING RANGES

		RATI		
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage	+4.75	+5.25	V _{DC}
T _A	Operating free-air temperature	0	+75	°C

THERMAL RATINGS

TEMPERATUR	RE
Maximum junction	150°C
Maximum ambient	75°C
Allowable thermal rise ambient to junction	75°C

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

PHD48N22-7

DC ELECTRICAL CHARACTERISTICS 0° C \leq T_A \leq +75 $^{\circ}$ C, 4.75 \leq V_{CC} \leq 5.25V

SYMBOL	PARAMETER	TEST CONDITIONS	Min	Typ1	Max	UNIT	
Input volta	age ²				1		
V _{IL}	Low	V _{CC} = MIN			0.8	V	
V_{IH}	High	V _{CC} = MAX	2.0			V	
V _{IC}	Clamp	V _{CC} = MIN, I _{IN} = -18mA		-0.8	-1.5	V	
Output vo	ltage						
		V _{CC} = MIN, V _{IN} = V _{IH} or V _{IL}					
V_{OL}	Low	I _{OL} = +24mA			0.5	V	
V_{OH}	High	$I_{OH} = -3.2 \text{mA}$	2.4			V	
Input curr	ent						
		V _{CC} = MAX					
I _{IL}	Low	$V_{IN} = +0.40V$		-20	-250	μА	
I _{IH}	High	$V_{1N} = +2.7V$			25	μА	
I_{\parallel}	High	V _{IN} = V _{CC} = V _{CC MAX}			100	μА	
Output cu	rrent		•	•	•	•	
		V _{CC} = MAX					
lozh	Output leakage 3	V _{OUT} = +2.7V			100	μА	
lozL	Output leakage 3	V _{OUT} = +0.40V			-100	μА	
los	Short circuit ⁴	V _{OUT} = +0V	-30	-60	-90	mA	
Icc	V _{CC} current	V _{CC} = MAX			420	mA	
Capacitan	ice ⁵			-		4	
		V _{CC} = +5V				g1112	
CIN	Input	V _{IN} = 2.0V @ f = 1MHz	,	8		pF	
C _{OUT}	1/0	V _{OUT} = 2.0V @ f = 1MHz		8		pF	

- Typical limits are at V_{CC} = 5.0V and T_A = +25°C.
 These are absolute values with respect to device ground and all overshoots due to system or tester noise are included.
 Leakage current for bidirectional pins is the worst case of I_{IL} and I_{OZL} or I_{IH} and I_{OZL}.
 Not more than one output should be tested at a time. Duration of the short circuit should not be more than one second.
 These parameters are not 100% tested, but are periodically sampled.

PHD48N22-7

AC ELECTRICAL CHARACTERISTICS 0°C \leq T_A \leq +75°C, 4.75 \leq V_{CC} \leq 5.25V, R₁ = 200 Ω , R₂ = 390 Ω

				TEST	LIM		
SYMBOL	PARAMETER	FROM	то	CONDITIONS	Min	Max	UNIT
t _{PD1} 1	Propagation delay through B/O outputs	(I, B, OR) ±	Output ±	C _L = 50pF		7.5	ns
t _{PD2} 1	Propagation delay through OR outputs	(I, B, OR) ±	Output ±	C _L = 50pF		10	ns
t _{OE} ²	Output Enable	(I, B, OR) ±	Output enable	C _L = 50pF		10	ns
t _{OD} ²	Output Disable	(I, B, OR) ±	Output disable	C _L = 5pF		10	ns

NOTES:

- tp_{11,2} are tested with switch S₁ closed and C_L = 50pF.
 For 3-State output; output enable times are tested with C_L = 50pF to the 1.5V level, and S₁ is open for high-impedance to High tests and closed for high-impedance to Low tests. Output disable times are tested with C_L = 5pF. High-to-High impedance tests are made to an output voltage of $V_T = V_{OH} - 0.5V$ with S_1 open, and Low-to-High impedance tests are made to the $V_T = V_{OL} + 0.5V$ level with S_1 closed.

VIRGIN STATE


A factory shipped virgin device contains all fusible links open, such that:

- 1. All outputs are disabled.
- 2. All p-terms are disabled in the AND array.

TIMING DEFINITIONS

SYMBOL	PARAMETER
t _{PD1}	Input to output propagation delay (through B/O outputs).
t _{PD2}	Input to output propagation delay (through OR outputs).
ton	Input to Output Disable (3–State) delay (Output Disable).
t _{OE}	Input to Output Enable delay (Output Enable).


TIMING DIAGRAM




November 1989 119

PHD48N22-7

AC TEST LOAD CIRCUIT



VOLTAGE WAVEFORMS




LOGIC PROGRAMMING

PHD48N22-7 logic designs can be generated using any commercially available, JEDEC standard design software.

PHD48N22—7 designs can also be generated using the program table format, detailed on the following page. This program table entry (PTE) format is supported on the Signetics AMAZE PLD design software. AMAZE is available free of charge to qualified users.

To implement the desired logic functions, each logic variable (I, B, P and D) from the logic equations is assigned a symbol. TRUE (High), COMPLEMENT (Low), DON'T CARE and INACTIVE symbols are defined below.

"AND" ARRAY - (I, B)



NOTE:

1. This is the initial state.

PHD48N22-7

PROGRAM TABLE

Ţ	INPUTS													_																																		
T E R M																			ı																	I			_	В					OR			_
0	35	34	33	32	31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	9	7	6	5	4	3	2	1	0	3	2	1	0
1																																			1	1		1	7	\exists	4		口		\Box	コ		F
2	\vdash	_	-	\vdash	⊢	-	-	\vdash	-	\vdash	\vdash	-	-	_		\vdash	-	\vdash	-	-		\vdash	Н	-	Н	Н	H	Н	_	Н	Н	H	\vdash	\vdash	+	+	+	+	+	+	+	\dashv	\vdash	\dashv	\vdash	+	_	H
4																																				1			士									
3 4 5 6	-		-	-	\vdash	-	-	\vdash	-	-		-	-	L		_	-	-		-			Н	-	Н	H		Н		\vdash	Н	\vdash	-	\vdash	\rightarrow	+	+	-	+	+	\dashv	\vdash	\vdash	\vdash	\vdash	-	_	H
7	Н		\vdash	\vdash	\vdash	+		+	\vdash			\vdash		Н		-	\vdash		\vdash			Н	Н	\vdash	Н			Н		Н	Н	Н	\vdash	\vdash	\dashv	+	+	\dashv	+	+	1	\vdash		\vdash	\Box	+		
7																																				1	\Box	\perp	1	\Box			\Box		\Box	\exists		
9	Н	_	-	\vdash	\vdash	+	-	\vdash	\vdash	-	\vdash	\vdash	\vdash	-		\vdash	\vdash			-			Н	Н				Н		Н	Н	Н	\vdash	Н	+	+	\dashv	+	+	\dashv	\dashv	\vdash	\vdash	Н	\vdash	+	_	-
11																																			\dashv	7	\exists	\dashv	\exists	\exists	\Box				\Box	\exists		
12	Н	_	-	\vdash		H	-	\vdash	-	-	-	-	\vdash	H	Н	-	Н	H	H	Н	_	Н	Н	Н	Н	Н	+	+	\dashv	+	+	+	+	\vdash	\vdash	Н	\vdash	+	_	H								
14																																							\exists									
15 16				L	F	-		F	F																	-									-	-	-	-	\dashv	-	-		\vdash	\perp	\vdash	\vdash	_	-
17	Н		\vdash	-	+	+	-	+	+																					Н				Н	\forall	+	\forall	+	+				\vdash					-
18																																			\Box	1			\exists						П	\Box		
19 20	H	-	-	-	+	+	-	+	+	\vdash	\vdash	\vdash	\vdash	-	\vdash	-	-	\vdash	\vdash	-	-	\vdash	\vdash	Н	H		\vdash	\vdash	_	Н		\vdash	Н	Н	+	+	+	+	+	+	-	\vdash	Н	H	\vdash	+	Н	+
21																																				1			\exists						口			L
22			F		F	F		F	F		П		F	F					F			F		П			F			H				H	7	4	1	1	1	-	-				H	1		F
23 24	H		\vdash		+	1		+	+				\vdash		\vdash				_					Н						H			\vdash		1	1	+	+	+	_		H	Н	H		\dashv		t
25																																				7		7	\exists						口	二		F
26 27	\vdash	_	\vdash	\vdash	\vdash	+	-	+	+	+	\vdash	\vdash	-	\vdash	-	-	-	-	\vdash	-	-	-	\vdash	Н	\vdash	\vdash			\vdash	Н	\vdash	\vdash	\vdash	\vdash	+	+	\dashv	+	+	-	-	Н	Н	Н	\vdash	+	_	+
28																																				コ			コ						口			
29 30	\vdash	_	-	\vdash	\vdash	\vdash	-	\vdash	\vdash	-		-	-	-	\vdash	-	\vdash	-	-	H	\vdash			Н					_	H	-	H	\vdash	-	\dashv	\dashv	\dashv	-	+	\dashv	\dashv	Н	Н	Н	\vdash	\rightarrow	_	H
31																																				1			\pm									İ
32				F	F	1	L	F	F	F							L																		\dashv	4	\exists	-	\dashv	-	4			\Box	\Box	\neg		F
33	\vdash			\vdash	+	+	\vdash	+	\vdash				1		-			\vdash			\vdash			H					_				Н		1	+	+	+	+	\dashv		Н	Н	\vdash	\Box			t
35																																			\Box	\exists		\Box	\exists	\Box					\Box	\Box		F
36 37 38	Н	_	⊢	\vdash	+	+	\vdash	⊬	╁	\vdash		\vdash	\vdash	H	\vdash	H	Н	Н					H	H	Н	Н	Н	Н	+	+	\dashv	\dashv	+	\dashv	\dashv	Н	\vdash	Н	\vdash	\dashv	_	H						
36																																							\exists									İ
39 40		_	-	-	\vdash	-	-	-	-	-		-	-	-	-	-	-	-	-	-	-	-	\vdash	_			_		L	-			\vdash		-	+	+	-	+	-	-	\vdash	\vdash	\vdash	\vdash	\rightarrow	_	H
41					+	+		+				\vdash												Н					\vdash							\forall	+	1	\pm				Н					t
42					F																															4	4	\neg	\exists						П	\exists		F
43 44	Н	_		-	+	+	-	\vdash	\vdash	\vdash		\vdash	\vdash	-	\vdash	\vdash	-	\vdash	-	\vdash	\vdash	-	Н	Н			\vdash		H	Н	Н		Н		+	+	-	+	+	\dashv	\dashv	Н	H	Н	\vdash	\vdash		H
45 46																										-										1												
46 47	H	_	⊢	\vdash	+	╀	-	+-	\vdash	\vdash		-	\vdash	-	-	-	\vdash	-	\vdash	\vdash	\vdash	-	H	_	H		H	-	-		-		Н	Н	\dashv	+	-	\dashv	+	\dashv	\dashv	Н	\vdash	Н	Н	\vdash	_	H
48 49					İ			İ																												\exists			\exists									İ
49			-	-	\vdash	-	-	\vdash	\vdash	-		-	-	_	\vdash	L	⊢	_	-		-												Н	Щ	-	4	-	-	+	-	-		\vdash	Н	\vdash	\vdash	_	H
50 51																																				\exists												t
52					F			F	F											L																\exists	\Box	\neg	\exists	_					П	\Box		F
53 54	-		-		+	\vdash		\vdash	-	+		-	+	-	-	-	-		-						\vdash					\vdash			\vdash		\dashv	-	\dashv	-	+			Н	\vdash	Н	\vdash	\vdash		t
56																																				\exists			\exists						口	口		F
56 57	\vdash	_	-	-	+	+	-	+	+	+	\vdash	\vdash	-	-	-	+	-	\vdash	-	-	-	-	H	-	-	-	-	-	-	H			Н		+	+	\dashv	+	+	-	\dashv	Н	Н	Н	Н	\vdash		H
58																																				_			\exists									İ
59 60			-	-	-	-		1	1	-	-	-	-	-	-	-	-	-	-	-	-	-			-				-	H		-			-	+	\dashv	+	+	-	-	H	\vdash	Н	Н	\dashv		+
31					1			\perp							\vdash																					_		_	7									t
52					F			F																						\Box					\Box	7		7	7			П	П	П	П	П		F
53 54		_	-	+	+	+		+	+	\vdash	-	-	+			\vdash	\vdash	+	-	+	+	-	-	H	\vdash		-	\vdash	-	\vdash					\dashv	\dashv	-	+	+	-	\dashv	Н	Н	Н	H	\vdash		t
35								İ	İ																											\exists		\Box	\exists						口			T
6	\vdash	_	-	-	+	+	-	\vdash	+	+	-	-	-	-	-	-	-	-	-	-	-	-		-	-	-	-	-		H		-		H	-	\dashv	-	\dashv	+	-	-	Н	H	Н	\vdash	\vdash		+
8																																																İ
99 70			-	-	1	-	-	-	-	-		-	-		-	-	-	-	-	-	-	-			-	-	-	-	-			-	H		-	\dashv	-	\dashv	+	-	-	H	\vdash	Н	\vdash	\vdash		+
71																																							\exists									t
72	40	4.	40	20	02	20	~	24	20	21	20	000	28	27	26	25	24	22	20	200	10	10	17	16	12	10	14	10	0	6	7	6	F	2	2	\Box	52	51	55	47	A.F	AE.	AA	42	60	67	65	Ĺ
MN	42	41	40	39	37	36	35	34	33	31	30	28	28	27	26	۵	24	23	22	20	19	18	17	16	13	12	11	10	Я	ő	-	0	5	3	2	┧	32	31	30	4/	40	40	44	43	00	01	00	t
NAME																																																


PHD48N22-7

PROGRAM TABLE (Continued)

Т	OUTPUTS																					
T E R	H	-	-		******	0	on or other teams	electric de		_			_		3	-			Г	0	R	
	9	8	7	6	5	4	3	2	1	0	7	6	5			2	1	0	3			0
0	\vdash	\vdash	-		-	-	-	-	-		\vdash	-	-	-	-	-	-		\vdash	-		Н
2																						
3									-		H					\vdash	\vdash		\vdash	\vdash		Н
5	-	-	-								F								F			\Box
7																						
8	\vdash	\vdash	-	-	-	-	-	-	-	\vdash	\vdash	-	-	H	-	-	\vdash	-	\vdash	-	-	Н
10																						
11											\vdash	-	-	\vdash	-	H			\vdash	-		Н
13											F											
15																						
16	F	\vdash									F		-						F			Н
18																						
19	\vdash	\vdash	-		-	-	-		-	-	-	-	\vdash	-	-	-	-	H	\vdash	-	-	Н
21																						
22		-	-	-	-	-	-		-		-	-	-	-	-	-	-	-	\vdash	-	-	Н
24																						
25 26																						H
27 28	F	F			F	F					F							F	F			H
29																						
30	\vdash	\vdash	-	-	-		-	-	-		H	-	-	H	-	-	\vdash		\vdash	H	-	Н
32																						
33	\vdash	-	-	-	-		-		-		Н	-	\vdash	\vdash	-	-	-	-	\vdash	-	-	Н
35																						
36											-	-	-	-	\vdash	\vdash	\vdash	\vdash	\vdash	-	\vdash	Н
38		-									F						F		F			H
40																						
41	\vdash	\vdash	-	-	-	-	-		H		\vdash	\vdash	\vdash	-	-	-	-	-	\vdash	\vdash	-	Н
43																						
44	\vdash	\vdash	\vdash	\vdash	-		-				\vdash	-	-	\vdash	-	-	\vdash	\vdash	\vdash	-	\vdash	Н
46																						П
48																						Н
49 50	-										F								F			
51																						
52 53	-	-	-	-	H	-	-		H	H	H	-	-	-	-	-	-	H	H	-	-	H
54																						
55 56																			\vdash			Н
57 58	F															F						П
50																						
60	-	-	-			H				H	F	H				F	F	F	F	F		H
62																						
63 64						-			-	Н	\vdash	-		-	-	-	-	H	\vdash	-	-	Н
65																			F			口
66 67																						
68 69	F	F					F			F	F								F			
70																						
71	-	-	-	H	H		H			H	H	H	F	H	-	_	F	H	F	F		H
PIN	63	62	61	60	50	58	57	56	54	53	52	51	50	47	46	45	44	43	68	67	65	64
VARIABLE																						

PHD48N22-7

TYPICAL SYSTEM APPLICATION



Signetics

Programmable Logic Devices

Section 4 Programmable Logic Array Device Data Sheets

INDEX

Series 20		
PLS153/A	Programmable Logic Arrays (18 × 42 × 10); 40/30ns	127
PLUS153B/D	Programmable Logic Arrays (18 × 42 × 10); 15/12ns	134
PLUS153-10	Programmable Logic Array (18 \times 42 \times 10); 10ns	141
Series 24		
PLS173	Programmable Logic Array (22 × 42 × 10); 30ns	148
PLUS173B/D	Programmable Logic Arrays (22 × 42 × 10); 15/12ns	154
PLUS173-10	Programmable Logic Array (22 × 42 × 10); 10ns	161
PLHS473	Programmable Logic Array (20 × 24 × 11); 22ns	168
PLHS473S	Programmable Logic Array ($20 \times 24 \times 11$); 25ns	174
Series 28		
PLS100/101	Programmable Logic Arrays (16 × 48 × 8): 50ns	181



Signetics

Document No.	853-0311			
ECN No.	97883			
Date of Issue	October 16, 1989			
Status Product Specification				
Programmable Logic Devices				

DESCRIPTION

The PLS153 and PLS153A are two–level logic elements, consisting of 42 AND gates and 10 OR gates with fusible link connections for programming I/O polarity and direction.

All AND gates are linked to 8 inputs (I) and 10 bidirectional I/O lines (B). These yield variable I/O gate configurations via 10 direction control gates (D), ranging from 18 inputs to 10 outputs.

On-chip T/C buffers couple either True (I, B) or Complement (I, B) input polarities to all AND gates, whose outputs can be optionally linked to all OR gates. Their output polarity, in turn, is individually programmable through a set of Ex-OR gates for implementing AND/OR or AND/NOR logic functions.

The PLS153 and PLS153A are field-programmable, enabling the user to quickly generate custom patterns using standard programming equipment.

Order codes are listed in the Ordering Information Table.

PLS153/A

Field-Programmable Logic Arrays

 $(18 \times 42 \times 10)$


FEATURES

- Field-Programmable (Ni-Cr links)
- 8 inputs
- 42 AND gates
- 10 OR gates
- 10 bidirectional I/O lines
- Active—High or –Low outputs
- 42 product terms:
 - 32 logic terms
 - 10 control terms
- I/O propagation delay:
- PLS153: 40ns (max)
- PLS153A: 30ns (max)
- Input loading: –100µA (max)
- Power dissipation: 650mA (typ)
- 3–State outputs
- TTL compatible

APPLICATIONS

- Random logic
- Code converters
- Fault detectors
- Function generators
- Address mapping
- Multiplexing

PIN CONFIGURATIONS



LOGIC FUNCTION

TYPICAL PRODUCT TERM: $Pn = A \cdot B \cdot C \cdot D \cdot \dots$ $TYPICAL LOGIC FUNCTION: AT OUTPUT POLARITY = H <math display="block">Z = P0 + P1 + P2 \dots$ $AT OUTPUT POLARITY = L <math display="block">Z = P0 + P1 + P2 + \dots$ $Z = P0 \cdot P1 \cdot P2 \cdot \dots$

NOTES:

- For each of the 10 outputs, either function Z (Active-High) or Z (Active-Low) is available, but not both. The desired output polarity is programmed via the Ex-OR gates.
 Z, A, B, C, etc. are user defined connections to fixed.
- inputs (I) and bidirectional pins (B).

Philips Components






Field-Programmable Logic Arrays (18 \times 42 \times 10)

PLS153/A


LOGIC DIAGRAM



Field-Programmable Logic Arrays (18 × 42 × 10)

PLS153/A

FUNCTIONAL DIAGRAM



ORDERING INFORMATION

DESCRIPTION	ORDER CODE
20-Pin Plastic Dual In-Line, 300mil-wide	PLS153N, PLS153AN
20-Pin Plastic Leaded Chip Carrier	PLS153A, PLS153AA

ABSOLUTE MAXIMUM RATINGS¹

		RATINGS		
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage		+7	V _{DC}
V _{IN}	Input voltage		+5.5	V _{DC}
V _{OUT}	Output voltage		+5.5	V _{DC}
I _{IN}	Input currents	-30	+30	mA
I _{OUT}	Output currents		+100	mA
T _A	Operating temperature range	0	+75	°C
T _{STG}	Storage temperature range	-65	+150	°C

NOTES:

THERMAL RATINGS

TEMPERATURE					
Maximum junction	150°C				
Maximum ambient	75°C				
Allowable thermal rise ambient to junction	75°C				

The PLS153/A devices are also processed to military requirements for operation over the military temperature range. For specifications and ordering information consult the Signetics Military Data Handbook.

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

Field-Programmable Logic Arrays (18 × 42 × 10)

PLS153/A

DC ELECTRICAL CHARACTERISTICS 0°C ≤ T_A ≤ +75°C, 4.75V ≤ V_{CC} ≤ 5.25V

				LIMITS		
SYMBOL	PARAMETER	TEST CONDITIONS	Min	Typ1	Max	UNIT
Input voit	age ²					
V _L	Low	V _{CC} = Min			0.8	٧
V _{IH}	High	V _{CC} = Max	2.0			٧
V _{IC}	Clamp ^{2, 3}	V _{CC} = Min, I _{IN} = -12mA		-0.8	-1.2	V
Output vo	oltage					
		V _{CC} = Min				
V_{OL}	Low ^{2, 4}	I _{OL} = 15mA			0.5	V
V _{OH}	High ^{2, 5}	$I_{OH} = -2mA$	2.4			V
Input curi	rent ⁹	-		•		
		V _{CC} = Max				
I _{IL}	Low	V _{IN} = 0.45V			-100	μΑ
I _{IH}	High	V _{IN} = 5.5V			40	μΑ
Output cu	ırrent		-			
		V _{CC} = Max				
I _{O(OFF)}	Hi–Z state ⁸	V _{OUT} = 5.5V			80	μΑ
		V _{OUT} = 0.45V			-140	
Ios	Short circuit ^{3, 5, 6}	V _{OUT} = 0V	-15		-70	mA
Icc	V _{CC} supply current ⁷	V _{CC} = Max		130	155	mA
Capacitar	nce				•	
		V _{CC} = 5V				
CIN	Input	V _{IN} = 2.0V		8		pF
CB	I/O	V _B = 2.0V		15		pF

- All typical values are at V_{CC} = 5V, T_A = +25°C.
 All voltage values are with respect to network ground terminal.

- All voltage values are wall respect to the state of the s
- 7. I_{CC} is measured with I₀, I₁ at 0V, I₂ I₇ and B₀₋₉ at 4.5V.
 8. Leakage values are a combination of input and output leakage.
- I_{IL} and I_{IH} limits are for dedicated inputs only (I₀ I₇).

Field-Programmable Logic Arrays (18 × 42 × 10)

PLS153/A

AC ELECTRICAL CHARACTERISTICS 0°C \leq T_A \leq +75°C, 4.75V \leq V_{CC} \leq 5.25V, R₁ = 470 Ω , R₂ = 1k Ω

						LIMITS					
SYMBOL	PARAMETER	FROM	то	TEST		PLS153			PLS153/	1	UNIT
				CONDITION	Min	Typ ¹	Max	Min	Typ ¹	Max	
t _{PD}	Propagation delay	Input ±	Output ±	C _L = 30pF		30	40		20	30	ns
t _{OE}	Output enable	Input ±	Output –	C _L = 30pF		25	35		20	30	ns
t _{OD}	Output disable ²	Input ±	Output +	C _L = 5pF		25	35		20	30	ns


NOTES:

- All typical values are at V_{CC} = 5V, T_A = +25°C.
 Measured at V_T = V_{OL} + 0.5V.

VOLTAGE WAVEFORMS

10% +3.0V • MEASUREMENTS: All circuit delays are measured at the +1.5V level of inputs and outputs, unless otherwise specified. Input Pulses


TEST LOAD CIRCUIT



TIMING DEFINITIONS

SYMBOL	PARAMETER
t _{PD}	Propagation delay between input and output.
t _{oo}	Delay between input change and when output is off (Hi-Z or High).
t _{OE}	Delay between input change and when output reflects specified output level.

TIMING DIAGRAM



Field-Programmable Logic Arrays ($18 \times 42 \times 10$)

PLS153/A


LOGIC PROGRAMMING

PLS153/A logic designs can be generated using Signetics AMAZE PLD design software or one of several other commercially available, JEDEC standard PLD design software packages. Boolean and/or state equation entry is accepted.


PLS153/A logic designs can also be generated using the program table entry format detailed on the following page. This program table entry format is supported by the Signetics AMAZE PLD design software (PTP module). AMAZE is available free of charge to qualified users.

To implement the desired logic functions, the state of each logic variable from logic equations (I, B, O, P, etc.) is assigned a symbol. The symbols for TRUE, COMPLEMENT, INACTIVE, PRESET, etc., are defined below.


OUTPUT POLARITY - (B)



AND ARRAY - (I, B)



OR ARRAY - (B)



NOTES:

- 1. This is the initial unprogrammed state of all links.
- Any gate P_n will be unconditioanlly inhibited if both the True and Complement of an input (either I or B) are left intact.

VIRGIN STATE

A factory shipped virgin device contains all fusible links intact, such that:

- 1. All outputs are at "H" polarity.
- 2. All Pn terms are disabled.
- 3. All Pn terms are active on all outputs.

CAUTION: PLS153A TEST COLUMNS


The PLS153A incorporates two columns not shown in the logic block diagram. These columns are used for in-house testing of the device in the unprogrammed state. These columns must be disabled prior to using the PLS153A in your application. If you are using a Signetics-approved programmer, the disabling is accomplished during the device programming sequence. If these columns are not disabled, abnormal operation is possible.

Furthermore, because of these test columns, the PLS153A cannot be programmed using the programmer algorithm for the PLS153.

Field-Programmable Logic Arrays ($18 \times 42 \times 10$)

PLS153/A

FPLA PROGRAM TABLE



Signetics

Document No.	853–1285			
ECN No.	97081			
Date of Issue	July 12, 1989			
Status Product Specification				
Programmable Logic Devices				

DESCRIPTION

The PLUS153 PLDs are high speed, combinatorial Programmable Logic Arrays. The Signetics state-of-the-art Oxide Isolated Bipolar fabrication process is employed to produce propagation delays as short as 12ns.

The 20-pin PLUS153 devices have a programmable AND array and a programmable OR array. Unlike PAL® devices, 100% product term sharing is supported. Any of the 32 logic product terms can be connected to any or all of the 10 output OR gates. Most PAL ICs are limited to 7 AND terms per OR function; the PLUS153 devices can support up to 32 input wide OR functions.

The polarity of each output is user-programmable as either active-High or active-Low, thus allowing AND-OR or AND-NOR logic implementation. This feature adds an element of design flexibility, particularly when implementing complex decoding functions.

The PLUS153 devices are user—programmable using one of several commercially available, industry standard PLD programmers.

PLUS153B/D


Programmable Logic Arrays

 $(18 \times 42 \times 10)$

FEATURES

- I/O propagation delays (worst case)
 - PLUS153B 15ns max.
 - PLUS153D 12ns max.
- Functional superset of 16L8 and most other 20-pin combinatorial PAL devices
- Two programmable arrays
- Supports 32 input wide OR functions
- 8 inputs
- 10 bi-directional I/O
- 42 AND gates
 - 32 logic product terms
 - 10 direction control terms
- Programmable output polarity
- Active-High or Active-Low
- Security fuse
- 3-State outputs
- Power dissipation: 750mW (typ.)
- TTL Compatible

PIN CONFIGURATIONS



APPLICATIONS

- Random logic
- Code converters
- Fault detectors
- Function generators
- Address mapping
- Multiplexing

Philips Components






[®]PAL is a registered trademark of Monolithic Memories, Inc., a wholly owned subsidiary of Advanced Micro Devices Corporation.

Programmable Logic Arrays $(18 \times 42 \times 10)$

PLUS153B/D


LOGIC DIAGRAM



Programmable Logic Arrays $(18 \times 42 \times 10)$

PLUS153B/D

FUNCTIONAL DIAGRAM



ORDERING INFORMATION

DESCRIPTION	t _{PD} (MAX)	ORDER CODE
20-Pin Plastic DIP 300mil-wide	15ns	PLUS153BN
20-Pin Plastic DIP 300mil-wide	12ns	PLUS153DN
20-Pin Plastic Leaded Chip Carrier	15ns	PLUS153BA
20-Pin Plastic Leaded Chip Carrier	12ns	PLUS153DA

ABSOLUTE MAXIMUM RATINGS¹

		RATING		
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage		+7	V _{DC}
V _{In}	Input voltage		+5.5	V _{DC}
V _{OUT}	Output voltage		+5.5	V _{DC}
I _{IN}	Input currents	-30	+30	mA
l _{out}	Output currents		+100	mA
TA	Operating free—air temperature range	0	+75	°C
T _{STG}	Storage temperature range	-65	+150	°C

NOTES:

THERMAL RATINGS

TEMPERATURE	
Maximum junction	150°C
Maximum ambient	75°C
Allowable thermal rise ambient to junction	75°C

The PLUS153 devices are also processed to military requirements for operation over the military temperature range. For specifications and ordering information consult the Signetics Military Data Book.

July 12, 1989

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

PLUS153B/D

DC ELECTRICAL CHARACTERISTICS 0°C ≤ T_A ≤ +75°C, 4.75 ≤ V_{CC} ≤ 5.25V

				LIMITS		
SYMBOL	PARAMETER	TEST CONDITIONS	Min	Typ1	Max	UNIT
Input vol	tage ²			A		
V _{IL}	Low	V _{CC} = Min			0.8	V
$V_{\mathbb{H}}$	High	V _{CC} = Max	2.0			V
V _{IC}	Clamp	V _{CC} = Min, I _{IN} = -12mA		-0.8	-1.2	V
Output v	oltage					
		V _{CC} = Min				
V_{OL}	Low ⁴	I _{OL} = 15mA			0.5	V
V_{OH}	High⁵	$I_{OH} = -2mA$	2.4			V
Input cur	rent ⁹					
		V _{CC} = Max				
I _{IL}	Low	V _{IN} = 0.45V			-100	μА
I _{IH}	High	$V_{IN} = V_{CC}$			40	μА
Output c	urrent			•		
		V _{CC} = Max				
I _{O(OFF)}	Hi–Z state ⁸	V _{OUT} = 5.5V			80	μА
		V _{OUT} = 0.45V			-140	
los	Short circuit ^{3, 5, 6}	V _{OUT} = 0V	-15		-70	mA
Icc	V _{CC} supply current ⁷	V _{CC} = Max		150	200	mA
Capacita	nce			•		-
		V _{CC} = 5V				
CIN	Input	V _{IN} = 2.0V		8		pF
CB	1/0	V _B = 2.0V		15		pF

NOTES:

- All typical values are at V_{CC} = 5V, T_A = +25°C.
- 2. All voltage values are with respect to network ground terminal.
- 3. Test one at a time.
- 4. Measured with inputs $I_0 I_2 = 0V$, inputs $I_3 I_5 = 4.5V$, inputs $I_7 = 4.5V$ and $I_6 = 10V$. For outputs $B_0 B_4$ and for outputs $B_5 B_9$ apply the same conditions except $I_7 = 0V$.
- 5. Same conditions as Note 4 except $I_7 = +10V$.
- 6. Duration of short circuit should not exceed 1 second.
- 7. I_{CC} is measured with inputs $I_0 I_7$ and $B_0 B_9 = 0V$.
- 8. Leakage values are a combination of input and output leakage.
- 9. I_{IL} and I_{IH} limits are for dedicated inputs only $(I_0 I_7)$.

AC ELECTRICAL CHARACTERISTICS 0°C \leq T_A \leq +75°C, 4.75V \leq V_{CC} \leq 5.25V, R₁ = 470 Ω , R₂ = 1k Ω

					LIMITS						
SYMBOL	PARAMETER	FROM	то	TEST	Р	LUS153	В	PLUS153D		UNIT	
				CONDITION	Min	Тур	Max	Min	Тур	Max	
t _{PD}	Propagation Delay ²	Input +/-	Output +/-	C _L = 30pF		11	15		10	12	ns
t _{OE}	Output Enable	Input +/-	Output –	C _L = 30pF		11	15		10	12	ns
t _{OD}	Output Disable ¹	Input +/-	Output +	C _L = 5pF		11	15		10	12	ns


NOTES:

- 1. Measured at $V_T = V_{OL} + 0.5V$.
- 2. Measured with all inputs and outputs switching simultaneously.

July 12, 1989


PLUS153B/D

VOLTAGE WAVEFORMS



Input Pulses


TEST LOAD CIRCUIT



TIMING DEFINITIONS

SYMBOL	PARAMETER
t _{PD}	Propagation delay between input and output.
too	Delay between input change and when output is off (Hi–Z or High).
toE	Delay between input change and when output reflects specified output level.

TIMING DIAGRAM



PLUS153B/D


LOGIC PROGRAMMING

PLUS153 logic designs can be generated using Signetics AMAZE PLD design software or one of several other commercially available, JEDEC standard PLD design software packages. Boolean equation entry is accepted.


PLUS153 logic designs can also be generated using the program table entry format detailed on the following pages. This program table entry format is supported by the Signetics AMAZE PLD design software (PTP module). AMAZE is available free of charge to qualified users

To implement the desired logic functions, the state of each logic variable from logic equations (I, B, O, P, etc.) is assigned a symbol. The symbols for TRUE, COMPLEMENT, INACTIVE, PRESET, etc., are defined below.


OUTPUT POLARITY - (B)



AND ARRAY - (I, B)



OR ARRAY - (B)



NOTES:

- 1. This is the initial unprogrammed state of all links.
- Any gate P_n will be unconditionally inhibited if both the true and complement of an input (either I or B) are left intact.


VIRGIN STATE

A factory shipped virgin device contains all fusible links intact, such that:

- 1. All outputs are at "H" polarity.
- 2. All P_n terms are disabled.
- 3. All Pn terms are active on all outputs.

PLUS153B/D

PLA PROGRAM TABLE



Signetics

Document No.					
ECN No.					
Date of Issue	November 1989				
Status	Preliminary Specification				
Programmable Logic Devices					

DESCRIPTION

The PLUS153–10 PLD is a high speed, combinatorial Programmable Logic Array. The Signetics state-of-the-art Oxide Isolated Bipolar fabrication process is employed to produce propagation delays as short as 10ns.

The 20-pin PLUS153 device has a programmable AND array and a programmable OR array. Unlike PAL® devices, 100% product term sharing is supported. Any of the 32 logic product terms can be connected to any or all of the 10 output OR gates. Most PAL ICs are limited to 7 AND terms per OR function; the PLUS153–10 can support up to 32 input wide OR

The polarity of each output is user-programmable as either active-High or active-Low, thus allowing AND-OR or AND-NOR logic implementation. This feature adds an element of design flexibility, particularly when implementing complex decoding functions.

The PLUS153-10 device is user-programmable using one of several commercially available, industry standard PLD programmers.


PLUS153–10 Programmable Logic Array

 $(18 \times 42 \times 10)$

FEATURES

- I/O propagation delays (worst case)
- PLUS153-10 10ns max.
- Functional superset of 16L8 and most other 20-pin combinatorial PAL devices
- Two programmable arrays
 - Supports 32 input wide OR functions
- 8 inputs
- 10 bi-directional I/O
- 42 AND gates
- 32 logic product terms
- 10 direction control terms
- Programmable output polarity
- Active-High or Active-Low
- Security fuse
- 3-State outputs
- Power dissipation: 750mW (tvp.)
- TTL Compatible

PIN CONFIGURATIONS



APPLICATIONS

- Random logic
- Code converters
- Fault detectors
- Function generators
- Address mapping
- Multiplexing

®PAL is a registered trademark of Monolithic Memories, Inc., a wholly owned subsidiary of Advanced Micro Devices Corporation.


Philips Components





PLUS153-10


LOGIC DIAGRAM



October 1989

PLUS153-10

FUNCTIONAL DIAGRAM



ORDERING INFORMATION

DESCRIPTION	t _{PD} (MAX)	ORDER CODE
20-Pin Plastic DIP 300mil-wide	10ns	PLUS153-10N
20-Pin Plastic Leaded Chip Carrier	10ns	PLUS153-10A

ABSOLUTE MAXIMUM RATINGS1

		RATING		
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage		+7	V _{DC}
V _{In}	Input voltage		+5.5	V _{DC}
V _{OUT}	Output voltage		+5.5	V _{DC}
I _{IN}	Input currents	-30	+30	mA
I _{OUT}	Output currents		+100	mA
T _A	Operating free-air temperature range	0	+75	°C
T _{STG}	Storage temperature range	-65	+150	°C

NOTES:

THERMAL RATINGS

TEMPERATURE					
Maximum junction	150°C				
Maximum ambient	75°C				
Allowable thermal rise ambient to junction	75°C				

The PLUS153 devices are also processed to military requirements for operation over the military temperature range. For specifications and ordering information consult the Signetics Military Data Book.

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those
indicated in the operational and programming specification of the device is not implied.

PLUS153-10

DC ELECTRICAL CHARACTERISTICS 0°C ≤ TA ≤ +75°C, 4.75 ≤ V_{CC} ≤ 5.25V

				LIMITS		
SYMBOL	PARAMETER	TEST CONDITIONS	Min	Typ ¹	Max	UNIT
Input volt	age ²		•	•		
V _{IL}	Low	V _{CC} = Min			0.8	V
V_{IH}	High	V _{CC} = Max	2.0			V
Vic	Clamp	$V_{CC} = Min, I_{IN} = -12mA$		-0.8	-1.2	V
Output vo	ltage					
		V _{CC} = Min				
V_{OL}	Low ⁴	I _{OL} = 15mA			0.5	V
V_{OH}	High ⁵	$I_{OH} = -2mA$	2.4			V
Input curi	ent ⁹					
		V _{CC} = Max				
I _{IL}	Low	$V_{IN} = 0.45V$			-100	μА
I_{IH}	High	$V_{IN} = V_{CC}$			40	μΑ
Output cu	irrent		•			
		V _{CC} = Max				
I _{O(OFF)}	Hi–Z state ⁸	V _{OUT} = 5.5V			80	μΑ
		V _{OUT} = 0.45V			-140	
los	Short circuit ^{3, 5, 6}	V _{OUT} = 0V	-15		-70	mA
I _{CC}	V _{CC} supply current ⁷	V _{CC} = Max		150	200	mA
Capacitar	nce					
		V _{CC} = 5V				
C_{IN}	Input	V _{IN} = 2.0V		8		pF
C_B	1/0	V _B = 2.0V		15		pF

NOTES:

- 1. All typical values are at $V_{CC} = 5V$, $T_A = +25$ °C.
- 2. All voltage values are with respect to network ground terminal.
- 3. Test one at a time.
- Measured with inputs I₀ I₂ = 0V, inputs I₃ I₅ = 4.5V, inputs I₇ = 4.5V and I₆ = 10V. For outputs B₀ B₄ and for outputs B₅ B₉ apply the same conditions except I₇ = 0V.
- 5. Same conditions as Note 4 except $I_7 = +10V$.
- 6. Duration of short circuit should not exceed 1 second.
- 7. I_{CC} is measured with inputs $I_0 I_7$ and $B_0 B_9 = 0V$.
- 8. Leakage values are a combination of input and output leakage.
- 9. I_{IL} and I_{IH} limits are for dedicated inputs only $(I_0 I_7)$.

AC ELECTRICAL CHARACTERISTICS 0°C \leq T_A \leq +75°C, 4.75V \leq V_{CC} \leq 5.25V, R₁ = 470 Ω , R₂ = 1k Ω


				TEST		LIMITS		
SYMBOL	PARAMETER	FROM	то	CONDITION	Min	Тур	Max	UNIT
t _{PD}	Propagation Delay ²	Input +/-	Output +/-	C _L = 30pF		8	10	ns
toE	Output Enable	Input +/-	Output –	C _L = 30pF		8	10	ns
t _{OD}	Output Disable ¹	Input +/-	Output +	C _L = 5pF		8	10	ns

NOTES:


- Measured at V_T = V_{OL} + 0.5V.
- 2. Measured with all inputs and outputs switching simultaneously.

PLUS153-10

VOLTAGE WAVEFORMS




TEST LOAD CIRCUIT



TIMING DEFINITIONS

SYMBOL	PARAMETER					
t _{PD}	Propagation delay between input and output.					
t _{OD}	Delay between input change and when output is off (Hi–Z or High).					
t _{OE}	Delay between input change and when output reflects specified output level.					

TIMING DIAGRAM



PLUS153-10


LOGIC PROGRAMMING

PLUS153–10 logic designs can be generated using Signetics AMAZE PLD design software or one of several other commercially available, JEDEC standard PLD design software packages. Boolean equation entry is accepted.


PLUS153–10 logic designs can also be generated using the program table entry format detailed on the following pages. This program table entry format is supported by the Signetics AMAZE PLD design software (PTP module). AMAZE is available free of charge to qualified users.

To implement the desired logic functions, the state of each logic variable from logic equations (I, B, O, P, etc.) is assigned a symbol. The symbols for TRUE, COMPLEMENT, INACTIVE, PRESET, etc., are defined below.


OUTPUT POLARITY - (B)



AND ARRAY - (I, B)



OR ARRAY - (B)



NOTES:

- 1. This is the initial unprogrammed state of all links.
- Any gate P_n will be unconditionally inhibited if both the true and complement of an input (either l or B) are left intact.


VIRGIN STATE

A factory shipped virgin device contains all fusible links intact, such that:

- 1. All outputs are at "H" polarity.
- 2. All P_n terms are disabled.
- 3. All Pn terms are active on all outputs.

PLUS153-10

PLA PROGRAM TABLE



Signetics

PLS173 Field-Programmable Logic Array (22 \times 42 \times 10)

Signetics Programmable Logic Product Specification

Application Specific Products • Series 24

DESCRIPTION

The PLS173 is a two-level logic element consisting of 42 AND gates and 10 OR gates with fusible link connections for programming I/O polarity and direction.

All AND gates are linked to 12 inputs (I) and 10 bidirectional I/O lines (B). These yield variable I/O gate configurations via 10 direction control gates (D), ranging from 22 inputs to 10 outputs.

On chip T/C buffers couple either True (I, B) or Complement (Ī, B) input polarities to all AND gates, whose outputs can be optionally linked to all OR gates. Their output polarity, in turn, is individually programmable through a set of EX-OR gates for implementing AND/OR or AND/NOR logic functions.

The PLS173 is field programmable, enabling the user to quickly generate custom patterns using standard programming equipment.

Order codes for this device are contained in the pages following.


FEATURES

- Field-Programmable (Ni-Cr links)
- 12 inputs
- 42 AND gates
- 10 OR gates
- 10 bidirectional I/O lines
- · Active-High or -Low outputs
- 42 product terms:
 - 32 logic terms
- 10 control terms
- I/O propagation delay: 30ns (max.)
- Input loading: -100μA (max.)
- Power dissipation: 750mW (typ.)
- 3-State outputs
- TTL compatible


APPLICATIONS

- Random logic
- Code converters
- Fault detectors
- Function generators
- Address mapping
- Multiplexing

PIN CONFIGURATIONS



FUNCTIONAL DIAGRAM



LOGIC FUNCTION

TYPICAL PRODUCT TERM: $Pn = A \cdot \overline{B} \cdot C \cdot D \cdot \dots$ TYPICAL LOGIC FUNCTION: $AT \ OUTPUT \ POLARITY = H$ $Z = P0 + P1 + P2 \dots$ AT OUTPUT POLARITY = L $Z = \overline{P0} \cdot P1 \cdot \overline{P2} \cdot \dots$ $Z = \overline{P0} \cdot P1 \cdot \overline{P2} \cdot \dots$ ach of the 10 outputs, either function Z


NOTEs: 1. For each of the 10 outputs, either function Z (Active-High) or Z (Active-Low) is available, but not both. The desired output polarity is programmed via the EX-OR gates.

via the EX-OR gates.

2. Z, A, B, C, etc. are user defined connections to fixed inputs (I), and bidirectional pins (B).

PLS173

FPLA LOGIC DIAGRAM



May 11, 1988

Field-Programmable Logic Array (22 × 42 × 10)

PLS173

ORDERING INFORMATION

DESCRIPTION	ORDER CODE			
24–Pin Plastic DIP 300mil–wide	PLS173N			
28-Pin Plastic Leaded Chip Carrier	PLS173A			

THERMAL RATINGS

TEMPERATURE					
Maximum junction	150°C				
Maximum ambient	75°C				
Allowable thermal rise ambient to junction	75°C				

ABSOLUTE MAXIMUM RATINGS1

	x	RAT		
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage		+7	V _{DC}
V _{In}	Input voltage		+5.5	V _{DC}
V _{OUT}	Output voltage		+5.5	V _{DC}
I _{IN}	Input currents	-30	+30	mA
I _{OUT}	Output currents		+100	mA
T _A	Operating free—air temperature range	0	+75	°C
T _{STG}	Storage temperature range	-65	+150	°C

NOTES:

DC ELECTRICAL CHARACTERISTICS $0^{\circ}C \le T_{A} \le +75^{\circ}C$, $4.75 \le V_{CC} \le 5.25V$

				LIMITS		
SYMBOL	PARAMETER	TEST CONDITIONS	Min	Typ ¹	Max	UNIT
Input volt	age ²	•				
V _{IL}	Low	V _{CC} = Min			0.8	V
V_{IH}	High	V _{CC} = Max	2.0			V
ViC	Clamp ^{2, 3}	$V_{CC} = Min, I_{IN} = -12mA$		-0.8	-1.2	V
Output vo	oltage					
		V _{CC} = Min				
VOL	Low ^{2, 4}	$I_{OL} = 15mA$			0.5	V
V _{OH}	High ^{2, 5}	$I_{OH} = -2mA$	2.4	-		V
Input cur	rent ¹⁰					
		V _{CC} = Max				
IIL	Low	V _{IN} = 0.45V			-100	μА
I_{IH}	High	$V_{IN} = V_{CC}$			40	μА
Output cu	urrent					
		V _{CC} = Max				
I _{O(OFF)}	Hi–Z state ⁹	V _{OUT} = 5.5V			80	μА
		V _{OUT} = 0.45V			-140	
los	Short circuit ^{3, 5, 6}	V _{OUT} = 0V	-15		-70	mA
Icc	V _{CC} supply current ⁷	V _{CC} = Max		150	170	mA
Capacita	nce					
		V _{CC} = 5V				
I _{IN}	Input	V _{IN} = 2.0V		8		pF
CB	1/0	$V_{B} = 2.0V$		15		pF

Notes on following page.

May 11, 1988 150

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those
indicated in the operational and programming specification of the device is not implied.

PLS173


AC ELECTRICAL CHARACTERISTICS $0^{\circ}\text{C} \le \text{T}_{\text{A}} \le +75^{\circ}\text{C}$, $4.75 \le \text{V}_{\text{CC}} \le 5.25\text{V}$, $\text{R}_1 = 470\Omega$, $\text{R}_2 = 1\text{k}\Omega$

				TEST	LIMITS			
SYMBOL	PARAMETER	FROM	то	CONDITION	Min	Тур	Max	UNIT
t _{PD}	Propagation delay	Input ±	Output ±	C _L = 30pF		20	30	ns
t _{OE}	Output enable	Input ±	Output –	C _L = 30pF		20	30	ns
t _{OD}	Output disable ⁸	Input ±	Output +	C _L = 5pF		20	30	ns


NOTES:

- 1. All typical values are at $V_{CC} = 5V$, $T_A = +25^{\circ}C$.
- 2. All voltage values are with respect to network ground terminal.
- 3. Test one at a time.
- 4. Measured with inputs V_{\parallel} applied to I_{11} . Pins 1–5 = 0V, Pins 6–10 = 4.5V, Pin 11 = 0V and Pin 13 = 10V.
- 5. Same conditions as Note 4 except Pin 11 = +10V.
- 6. Duration of short circuit should not exceed 1 second.
- 7. I_{CC} is measured with I_0 and $I_1 = 0V$, and $I_2 I_{11}$ and $I_0 I_{9} = 4.5V$. Part in Virgin State.
- 8. Measured at $V_T = V_{OL} + 0.5V$.
- 9. Leakage values are a combination of input and output leakage.
- 10. I_{IL} and I_{IH} limits are for dedicated inputs only ($I_0 I_{11}$).

VOLTAGE WAVEFORM




TEST LOAD CIRCUIT



TIMING DEFINITIONS

TIMING DELIMITIONS							
SYMBOL	PARAMETER						
t _{PD}	Propagation delay between input and output.						
t _{OD}	Delay between input change and when output is off (Hi–Z or High).						
t _{OE}	Delay between input change and when output reflects specified output level.						

TIMING DIAGRAM



PLS173


LOGIC PROGRAMMING

PLS173 logic designs can be generated using Signetics AMAZE PLD design software or one of several other commercially available, JEDEC standard PLD design software packages. Boolean and/or state equation entry is accepted.


PLS173 logic designs can also be generated using the program table entry format detailed on the following pages. This program table entry format is supported by the Signetics AMAZE PLD design software (PTP module). AMAZE is available free of charge to qualified

To implement the desired logic functions, the state of each logic variable from logic equations (I, B, O, P, etc.) is assigned a symbol. The symbols for TRUE, COMPLEMENT, INACTIVE, PRESET, etc., are defined below.


OUTPUT POLARITY - (B)



AND ARRAY - (I, B)



OR ARRAY - (B)



NOTES

- This is the initial unprogrammed state of all link pairs. It is normally associated with all unused (inactive) AND gates P_n, D_n.
- Any gate P_n, D_n will be unconditionally inhibited if both the True and Complement of any input (I, B) are left intact.


VIRGIN STATE

A factory shipped virgin device contains all fusible links intact, such that:

- 1. All outputs are at "H" polarity.
- 2. All Pn terms are disabled.
- 3. All Pn terms are active on all outputs.

PLS173

FPLA PROGRAM TABLE



TB00956

Signetics

Document No.	853–1298				
ECN No.	97080				
Date of Issue	July 12, 1989				
Status	Product Specification				
Programmable Logic Devices					

DESCRIPTION

The PLUS173 PLDs are high speed, combinatorial Programmable Logic Arrays. The Signetics state-of-the-art Oxide Isolated Bipolar fabrication process is employed to produce propagation delays as short as 12ns.

The 24–pin PLUS173 devices have a programmable AND array and a programmable OR array. Unlike PAL® devices, 100% product term sharing is supported. Any of the 32 logic product terms can be connected to any or all of the 10 output OR gates, Most PAL ICs are limited to 7 AND terms per OR function; the PLUS173 devices can support up to 32 input wide OR functions.

The polarity of each output is userprogrammable as either active-High or active-Low, thus allowing AND-OR or AND-NOR logic implementation. This feature adds an element of design flexibility, particularly when implementing complex decoding functions.

The PLUS173 devices are user—programmable using one of several commercially available, industry standard PLD programmers.

PLUS173B/D

Programmable Logic Arrays

 $(22 \times 42 \times 10)$


FEATURES

- I/O propagation delays (worst case)
 - PLUS173B 15ns max.
 - PLUS173D 12ns max.
- Functional superset of 20L10 and most other 24-pin combinatorial PAL devices
- Two programmable arrays
- Supports 32 input wide OR functions
- 12 inputs
- 10 bi-directional I/O
- 42 AND gates
 - 32 logic product terms
 - 10 direction control terms
- Programmable output polarity
- Active-High or Active-Low
- Security fuse
- 3-State outputs
- Power dissipation: 750mW (typ.)
- TTL Compatible

APPLICATIONS

- Random logic
- Code converters
- Fault detectors
- Function generators
- Address mapping
- Multiplexing

PIN CONFIGURATIONS



Philips Components






[®]PAL is a registered trademark of Monolithic Memories, Inc., a wholly owned subsidiary of Advanced Micro Devices Corporation.


PLUS173B/D

LOGIC DIAGRAM



PLUS173B/D

FUNCTIONAL DIAGRAM



ORDERING INFORMATION

DESCRIPTION	t _{PD} (MAX)	ORDER CODE	
24-Pin Plastic DIP 300mil-wide	15ns	PLUS173BN	
24-Pin Plastic DIP 300mil-wide	12ns	PLUS173DN	
28-Pin Plastic Leaded Chip Carrier	15ns	PLUS173BA	
28-Pin Plastic Leaded Chip Carrier	12ns	PLUS173DA	

THERMAL RATINGS

TEMPERATURE					
Maximum junction	150°C				
Maximum ambient	75°C				
Allowable thermal rise ambient to junction	75°C				

ABSOLUTE MAXIMUM RATINGS¹

		RATING		
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage		+7	V _{DC}
V _{In}	Input voltage		+5.5	V _{DC}
V _{OUT}	Output voltage		+5.5	V _{DC}
I _{IN}	Input currents	-30	+30	mA
I _{OUT}	Output currents		+100	mA
TA	Operating free—air temperature range	0	+75	°C
T _{STG}	Storage temperature range	-65	+150	°C

NOTES:

July 12, 1989

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

PLUS173B/D

DC ELECTRICAL CHARACTERISTICS $0^{\circ}C \le T_{\Delta} \le +75^{\circ}C$, $4.75 \le V_{CC} \le 5.25V$

				LIMITS		
SYMBOL	PARAMETER	TEST CONDITIONS	Min	Typ1	Max	UNIT
Input vol	tage ²			•		
V _{IL}	Low	V _{CC} = Min			0.8	V
V_{IH}	High	V _{CC} = Max	2.0			V
Vic	Clamp	$V_{CC} = Min, I_{IN} = -12mA$		-0.8	-1.2	V
Output v	oltage ²					
		V _{CC} = Min				
V_{OL}	Low ⁴	I _{OL} = 15mA			0.5	V
V_{OH}	High ⁵	$I_{OH} = -2mA$	2.4			V
Input cur	rent ⁹	-				
		V _{CC} = Max				
IL	Low	V _{IN} = 0.45V			-100	μА
I_{IH}	High	$V_{IN} = V_{CC}$			40	μΑ
Output c	urrent					
		V _{CC} = Max				
I _{O(OFF)}	Hi–Z state ⁸	V _{OUT} = 5.5V			80	μΑ
	·	V _{OUT} = 0.45V			-140	
los	Short circuit ^{3, 5, 6}	V _{OUT} = 0V	-15		-70	mA
Icc	V _{CC} supply current ⁷	V _{CC} = Max		150	200	mA
Capacita	nce	•				
		V _{CC} = 5V			- 1	
I _{IN}	Input	V _{IN} = 2.0V		8		рF
CB	1/0	V _B = 2.0V		15		pF

NOTES:

- All typical values are at V_{CC} = 5V, T_A = +25°C.
 All voltage values are with respect to network ground terminal.
- 3. Test one at a time.
- 4. Measured with inputs $I_0 I_4 = 0V$, inputs $I_5 I_9 = 4.5V$, $I_{11} = 4.5V$ and $I_{10} = 10V$. For outputs $B_0 B_4$ and for outputs $B_5 B_9$ apply the same conditions except $I_{11} = 0V$.
- 5. Same conditions as Note 4 except input $I_{11} = +10V$.
- 6. Duration of short circuit should not exceed 1 second.
- I_{CC} is measured with inputs I_0-I_{11} and $B_0-B_9=0$ V. Part in Virgin State.
- 8. Leakage values are a combination of input and output leakage.
- 9. I_{IL} and I_{IH} limits are for dedicated inputs only ($I_0 I_{11}$).

AC ELECTRICAL CHARACTERISTICS $0^{\circ}\text{C} \le \text{T}_{\text{A}} \le +75^{\circ}\text{C}$, $4.75 \le \text{V}_{\text{CC}} \le 5.25\text{V}$, $\text{R}_1 = 470\Omega$, $\text{R}_2 = 1\text{k}\Omega$

					LIMITS						
SYMBOL	PARAMETER	FROM	то	TEST	PLUS173B		Р	LUS173	D	UNIT	
				CONDITION	Min	Тур	Max	Min	Тур	Max	
t _{PD}	Propagation Delay ²	Input +/-	Output +/-	C _L = 30pF		11	15		10	12	ns
t _{OE}	Output Enable	Input +/-	Output –	C _L = 30pF		11	15		10	12	ns
t _{OD}	Output Disable ¹	Input +/-	Output +	$C_L = 5pF$		11	15		10	12	ns


NOTES:

- 1. Measured at $V_T = V_{OL} + 0.5V$.
- 2. Measured with all inputs and outputs switching simultaneously.


July 12, 1989 157

PLUS173B/D

VOLTAGE WAVEFORM




TEST LOAD CIRCUIT



TIMING DEFINITIONS

SYMBOL	PARAMETER
t _{PD}	Propagation delay between input and output.
t _{OD}	Delay between input change and when output is off (Hi–Z or High).
t _{OE}	Delay between input change and when output reflects specified output level.

TIMING DIAGRAM



July 12, 1989 158

PLUS173B/D


LOGIC PROGRAMMING

PLUS173 logic designs can be generated using Signetics AMAZE PLD design software or one of several other commercially available, JEDEC standard PLD design software packages. Boolean equation entry is accepted.


PLUS173 logic designs can also be generated using the program table entry format detailed on the following pages. This program table entry format is supported by the Signetics AMAZE PLD design software (PTP module). AMAZE is available free of charge to qualified

To implement the desired logic functions, the state of each logic variable from logic equations (I, B, O, P, etc.) is assigned a symbol. The symbols for TRUE, COMPLEMENT, INACTIVE, PRESET, etc., are defined below.

OUTPUT POLARITY - (B)



AND ARRAY - (I, B)



OR ARRAY - (B)



NOTES:

- This is the initial unprogrammed state of all link pairs. It is normally associated with all unused (inactive) AND gates P_n, D_n.
- Any gate P_n, D_n will be unconditionally inhibited if both the true and complement of any input (I, B) are left intact.


VIRGIN STATE

A factory shipped virgin device contains all fusible links intact, such that:

- 1. All outputs are at "H" polarity.
- 2. All P_n terms are disabled.
- 3. All Pn terms are active on all outputs.

PLUS173B/D

PLA PROGRAM TABLE



Signetics

Document No.				
ECN No.				
Date of Issue	October 1989			
Status	Preliminary Specification			
Programmable Logic Devices				

DESCRIPTION

The PLUS173–10 PLD is a high speed, combinatorial Programmable Logic Array. The Signetics state-of-the-art Oxide Isolated Bipolar fabrication process is employed to produce propagation delays as short as 10ns.

The 24–pin PLUS173–10 device has a programmable AND array and a programmable OR array. Unlike PAL® devices, 100% product term sharing is supported. Any of the 32 logic product terms can be connected to any or all of the 10 output OR gates. Most PAL ICs are limited to 7 AND terms per OR function; the PLUS173–10 device can support up to 32 input wide OR functions

The polarity of each output is user—programmable as either active—High or active—Low, thus allowing AND—OR or AND—NOR logic implementation. This feature adds an element of design flexibility, particularly when implementing complex decoding functions.

The PLUS173–10 device is userprogrammable using one of several commercially available, industry standard PLD programmers.

PLUS173-10

Programmable Logic Array

 $(22 \times 42 \times 10)$


FEATURES

- I/O propagation delays (worst case)
 PLUS173-10 10ns max.
- Functional superset of 20L10 and most other 24-pin combinatorial PAL devices
- Two programmable arrays
 - Supports 32 input wide OR functions
- 12 inputs
- 10 bi-directional I/O
- 42 AND gates
- 32 logic product terms
- 10 direction control terms
- Programmable output polarity
- Active-High or Active-Low
- Security fuse
- 3-State outputs
- Power dissipation: 750mW (typ.)
- TTL Compatible

APPLICATIONS

- Random logic
- Code converters
- Fault detectors
- Function generators
- Address mapping
- Multiplexing

PIN CONFIGURATIONS



Philips Components






[®]PAL is a registered trademark of Monolithic Memories, Inc., a wholly owned subsidiary of Advanced Micro Devices Corporation


PLUS173-10

LOGIC DIAGRAM



PLUS173-10

FUNCTIONAL DIAGRAM



ORDERING INFORMATION

DESCRIPTION	t _{PD} (MAX)	ORDER CODE
24-Pin Plastic DIP 300mil-wide	10ns	PLUS173-10N
28-Pin Plastic Leaded Chip Carrier	10ns	PLUS173-10A

ABSOLUTE MAXIMUM RATINGS¹

		RATING		
SYMBOL	PARAMETER	Min Max		UNIT
V _{CC}	Supply voltage		+7	V _{DC}
V _{In}	Input voltage		+5.5	V _{DC}
V _{OUT}	Output voltage		+5.5	V _{DC}
I _{IN}	Input currents	-30	+30	mA
l _{out}	Output currents		+100	mA
T _A	Operating free—air temperature range	0	+75	°C
T _{STG}	Storage temperature range	-65	+150	°C

NOTES:

THERMAL RATINGS

TEMPERATURE						
Maximum junction	150°C					
Maximum ambient	75°C					
Allowable thermal rise ambient to junction	75°C					

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

PLUS173-10

DC ELECTRICAL CHARACTERISTICS 0°C ≤ T_A ≤ +75°C, 4.75 ≤ V_{CC} ≤ 5.25V

				LIMITS		
SYMBOL	PARAMETER	TEST CONDITIONS	Min	Typ1	yp¹ Max	
Input vol	tage ²				•	
V _{IL}	Low	V _{CC} = Min			0.8	V
V_{IH}	High	V _{CC} = Max	2.0			V
V _{IC}	Clamp	$V_{CC} = Min, I_{IN} = -12mA$		-0.8	-1.2	V
Output v	oltage ²					
		V _{CC} = Min				
V_{OL}	Low ⁴	I _{OL} = 15mA			0.5	V
V_{OH}	High ⁵	I _{OH} = -2mA	2.4			V
Input cur	rent ⁹	*		•		
		V _{CC} = Max				
IL	Low	V _{IN} = 0.45V			-100	μА
I _{IH}	High	$V_{IN} = V_{CC}$			40	μА
Output c	urrent				-	
		V _{CC} = Max				
I _{O(OFF)}	Hi–Z state ⁸	V _{OUT} = 5.5V			80	μΑ
		V _{OUT} = 0.45V			-140	
Ios	Short circuit ^{3, 5, 6}	V _{OUT} = 0V	-15		-70	mA
Icc	V _{CC} supply current ⁷	V _{CC} = Max		150	200	mA
Capacita	nce	•		*		•
		V _{CC} = 5V		I		
I _{IN}	Input	V _{IN} = 2.0V	8		pF	
CB	1/0	V _B = 2.0V		15	,	pF

NOTES:

- All typical values are at V_{CC} = 5V, T_A = +25°C.
- 2. All voltage values are with respect to network ground terminal.
- 3. Test one at a time.
- Measured with inputs I₀ I₄ = 0V, inputs I₅ I₉ = 4.5V, I₁₁ = 4.5V and I₁₀ = 10V. For outputs B₀ B₄ and for outputs B₅ B₉ apply the same conditions except I₁₁ = 0V.
- Same conditions as Note 4 except input I₁₁ = +10V.
- 6. Duration of short circuit should not exceed 1 second.
- 7. I_{CC} is measured with inputs $I_0 I_{11}$ and $B_0 B_9 = 0V$. Part in Virgin State.
- 8. Leakage values are a combination of input and output leakage.
- 9. I_{IL} and I_{IH} limits are for dedicated inputs only $(I_0 I_{11})$.

AC ELECTRICAL CHARACTERISTICS $0^{\circ}\text{C} \le T_{\text{A}} \le +75^{\circ}\text{C}$, $4.75 \le V_{\text{CC}} \le 5.25\text{V}$, $R_1 = 470\Omega$, $R_2 = 1\text{k}\Omega$


				TEST	LIMITS			
SYMBOL	PARAMETER	FROM	то	CONDITION	Min	Тур	Max	UNIT
t _{PD}	Propagation Delay ²	Input +/-	Output +/-	C _L = 30pF		8	10	ns
t _{OE}	Output Enable	Input +/-	Output –	C _L = 30pF		8	10	ns
top	Output Disable ¹	Input +/-	Output +	C _L = 5pF		8	10	ns

NOTES:


- 1. Measured at $V_T = V_{OL} + 0.5V$.
- 2. Measured with all inputs and outputs switching simultaneously.

PLUS173-10

VOLTAGE WAVEFORM




TEST LOAD CIRCUIT



TIMING DEFINITIONS

SYMBOL	PARAMETER
t _{PD}	Propagation delay between input and output.
t _{OD}	Delay between input change and when output is off (Hi–Z or High).
t _{OE}	Delay between input change and when output reflects specified output level.

TIMING DIAGRAM



PLUS173-10


LOGIC PROGRAMMING

PLUS173–10 logic designs can be generated using Signetics AMAZE PLD design software or one of several other commercially available, JEDEC standard PLD design software packages. Boolean equation entry is accepted.


PLUS173–10 logic designs can also be generated using the program table entry format detailed on the following pages. This program table entry format is supported by the Signetics AMAZE PLD design software (PTP module). AMAZE is available free of charge to qualified

To implement the desired logic functions, the state of each logic variable from logic equations (I, B, O, P, etc.) is assigned a symbol. The symbols for TRUE, COMPLEMENT, INACTIVE, PRESET, etc., are defined below.


OUTPUT POLARITY - (B)



AND ARRAY - (I, B)



OR ARRAY - (B)



NOTES:

- This is the initial unprogrammed state of all link pairs. It is normally associated with all unused (inactive) AND gates P_n, D_n.
- Any gate P_n, D_n will be unconditionally inhibited if both the true and complement of any input (I, B) are left intact.


VIRGIN STATE

A factory shipped virgin device contains all fusible links intact, such that:

- 1. All outputs are at "H" polarity.
- 2. All Pn terms are disabled.
- 3. All Pn terms are active on all outputs.

PLUS173-10

PLA PROGRAM TABLE



Signetics

Application Specific Products • Series 24

DESCRIPTION

The PLHS473 is a two level logic device consisting of 24 AND gates and 22 OR gates with fusible link connections for programming I/O polarity and direction. The Signetics state of the art Oxide-Isolated Bipolar process is used to produce performance not yet achieved in devices of this complexity.

All AND gates are linked to 11 input pins, 9 bidirectional I/O pins, and 2 dedicated output pins. The bidirectional pins are controlled via the OR array. Using these features, the PLHS473 can be configured with up to 20 inputs and as many as 11 outputs.

The AND array input buffers provide both the True and Complement of the inputs (Ix) and the bidirectional signals (B_x) as programmable connections to the AND gates. All 24 AND gates can then be optionally linked to all 22 OR gates (a feature known as Product Term sharing not found in PAL® device architectures or most macrocell architectures). The OR array drives 11 output buffers which can be programmed as active-High for AND-OR functions or active-Low for AND-NOR functions. In addition, the I/O configuration of each bidirectional pin is individually controlled by a sum-of-products (AND-OR) function which may also contain any of the 24 AND gate outputs. This allows dynamic

PLHS473 Field-Programmable Logic Array $(20 \times 24 \times 11)$

Signetics Programmable Logic Product Specification

I/O configuration of all 9 bidirectional pins.

The PLHS473 contains two new features of significance. A code verification lock has been incorporated to improve user security. The addition of three test columns and one test row enables the user to test the device in an unprogrammed state.


The PLHS473 is field programmable using Vertical Avalanche Migration Programmed (VAMPTM) fuses to program the cells. This enables the generation of custom logic patterns using standard programming equipment.

Order codes are listed in the Ordering Information Table.

FEATURES

- Field-Programmable
- 11 dedicated inputs
- 2 dedicated outputs
- 9 bidirectional I/O lines
- 24 product terms
- 22 OR gates
- I/O direction decoded in OR array
- Output Enable decoded in OR array
- Security fuse
- I/O propagation delay: 22ns (max.)

PIN CONFIGURATIONS




- Input loading: -100μA (max.)
- Power dissipation: 700mW (typ.)
- Security fuse
- Testable in unprogrammed state
- Programmable as 3-State or Open-Collector outputs
- TTL compatible
- Programmable output polarity

APPLICATIONS

- Random logic
- Code converters
- Fault detectors
- Function generators
- Address mapping
- Multiplexing


FUNCTIONAL DIAGRAM



PAL is a trademark of Monolithic Memories, Inc., a wholly owned subsidary of Advanced Micro Devices, Inc.

PLHS473

FPLA LOGIC DIAGRAM



PLHS473

ORDERING INFORMATION

DESCRIPTION	ORDER CODE
24-pin Plastic DIP 300mil-wide	PLHS473N
28-pin Plastic Leaded Chip Carrier	PLHS473A

THERMAL RATINGS

TEMPERATURE	
Maximum junction	150°C
Maximum ambient	75°C
Allowable thermal rise ambient to junction	75°C

ABSOLUTE MAXIMUM RATINGS1

SYMBOL	PARAMETER	RATINGS	UNIT
V _{CC}	Supply voltage	+7	V _{DC}
V _{IN}	Input voltage	+ 5.5	V _{DC}
V _{OUT}	Output voltage	+ 5.5	V _{DC}
I _{IN}	Input currents	-30 to +30	mA
lout	Output currents	+ 100	mA
T _A	Operating free-air temperature range	0 to +75	°C
T _{STG}	Storage temperature range	-65 to +150	°C

NOTE:

LOGIC FUNCTION

TYPICAL PRODUCT TERM: $Pn = A \cdot \overline{B} \cdot C \cdot D \cdot \dots$ TYPICAL LOGIC FUNCTION: AT OUTPUT POLARITY = H Z = P0 + P1 + P2 . . .

AT OUTPUT POLARITY = L $Z = \overline{P0 + P1 + P2 + \dots}$ $Z = \overline{P0} \cdot \overline{P1} \cdot \overline{P2} \cdot \dots$

- NOTES:

 1. For each of the 11 outputs, either function Z (Active-High) or Z (Active-Low) is available, but not both. The desired output polarity is programmed via the Ex-OR gates.

 2. Z., A. B. C, etc. are user defined connections to fixed inputs (I), fixed output pins (0) and bidirectional pins (B).

DC ELECTRICAL CHARACTERISTICS $0^{\circ}C \leqslant T_{A} \leqslant +75^{\circ}C$, $4.75 \leqslant V_{CC} \leqslant 5.25V$

	DADAMETED			LIMITS		
SYMBOL	PARAMETER	TEST CONDITION	Min	Typ ¹	Max	UNI
Input vol	tage ²					
V _{IL} V _{IH}	Low High Clamp ³	$V_{CC} = Min$ $V_{CC} = Max$ $V_{CC} = Min, I_{IN} = -12mA$	2.0	-0.8	0.8	V V
Output v		V _{CC} - IVIIII, IIN 12IIIA		-0.8	-1.2	V
V _{OL} V _{OH}	Low ⁴ High ⁵	$V_{CC} = Min$ $I_{OL} = 15mA$ $I_{OH} = -2mA$	2.4		0.5	V
Input cur	rent					
I _{IL}	Low High	$V_{CC} = Max$ $V_{IN} = 0.45V$ $V_{IN} = 5.5V$			-100 40	μA μA
Output c	urrent					
l _{O(OFF)}	Hi-Z state ⁹ Short circuit ^{9, 5, 6}	$\begin{array}{c} V_{CC} = \text{Max} \\ V_{OUT} = 5.5 \text{V} \\ V_{OUT} = 0.45 \text{V} \\ V_{OUT} = 0.5 \text{V} \end{array}$			40 -100 -70	μΑ μΑ mA
Icc	V _{CC} supply current ⁷	V _{CC} = Max	140	155	mA	
Capacitar	nce	•				
I _{IN} C _B	Input I/O	$V_{CC} = 5V$ $V_{IN} = 2.0V$ $V_{B} = 2.0V$		8 15		pF pF

Notes on the following page.

May 11, 1988 170

^{1.} Stresses above those listed may cause malfunction or permanent damage to the device. This is a stress rating only. Functional operation at these or any other conditions above those indicated in the operational and programming specification of the device is not implied.

PLHS473


AC ELECTRICAL CHARACTERISTICS $0^{\circ}C \leqslant T_{A} \leqslant +75^{\circ}C$, $4.75 \leqslant V_{CC} \leqslant 5.25V$, $R_{1} = 470\Omega$, $R_{2} = 1k\Omega$

SYMBOL			FROM	TEST		LIMITS		
	PARAMETER	то	FROM	CONDITION	Min	Тур	Max	UNIT
t _{PD}	Propagation delay	Output ±	Input ±	C _L = 30pF		15	22	ns
t _{OE}	Output enable	Output -	Input ±	C _L = 30pF		15	22	ns
t _{OD}	Output disable ⁸	Output +	Input ±	C _L = 5pF		15	22	ns

NOTES:

- 1. All typical values are at $V_{CC} = 5V$, $T_A = +25$ °C.
- 2. All voltage values are with respect to network ground terminal.
- 3. Test one at a time.
- 4. Measured with inputs 0-4=0V, inputs 5, 7=4.5V, and inputs 6, 8-10=10V.
- 5. Same conditions as Note 5 except input 8 = 4.5V.
- 6. Duration of short circuit should not exceed 1 second.
- 7. I_{CC} is measured with all inputs and bidirectional pins at 4.5V. Part in Virgin State.
- 8. Measured at $V_T = V_{OL} + 0.5V$.
- 9. Leakage values are a combination of input and output leakage.

VOLTAGE WAVEFORMS




of inputs and outputs, unless otherwise specified

TIMING DEFINITIONS


Input Pulses

	Timilita DEL IIII I I I I I					
SYMBOL	PARAMETER					
t _{PD}	Propagation delay between input and output.					
t _{OD}	Delay between input change and when output is off (Hi-Z or High).					
t _{OE}	Delay between input change and when output reflects specified output level.					

TEST LOAD CIRCUITS



TIMING DIAGRAM



PLHS473

LOGIC PROGRAMMING

PLHS473 logic designs can be generated using Signetics' AMAZE PLD design software or one of several other commercially available, JEDEC standard PLD design software packages. Boolean and/or state equation entry is accepted.


PLHS473 logic designs can also be generated using the program table entry format detailed on the following pages. This program table entry format is supported by the Signetics' AMAZE PLD design software (PTP module). AMAZE is available free of charge to qualified users.

To implement the desired logic functions, the state of each logic variable from logic equations (I, B, O, P, etc.) is assigned a symbol. The symbols for TRUE, COMPLEMENT, INACTIVE, PRESET, etc., are defined below.


OUTPUT POLARITY - (O, B)



"AND" ARRAY-(I, B)



OR ARRAY - (O, B)



NOTES:

- 1. This is the initial unprogrammed state of all links. All unused P_n and D_n terms must be programmed as INACTIVE.
- Any gate P_n will be unconditionally inhibited if the True and Complement of either input (I or B) are both programmed for a connection.

VIRGIN STATE

A factory shipped virgin device contains all fusible links intact, such that:

- 1. All outputs are at "L" polarity.
- 2. All P_n terms are enabled in the AND array. (Don't Cares)
- 3. All P_n terms are inactive in the OR array.

FPLA PROGRAM TABLE

Signetics Application Specific Products • Series 24

T	
I	
Ń	
47	
w	

																							Al	ND.					Of	R													
	UST																			_							Г	ACTIV		IA	1												
PI	JRC	HA	SE	OR	DE	R#	ŧ													_	Г				7		-			+	B(0	,											
	GN																				I -	NACT	IVE	- 0	4	į	L	NAC'	TIVE	Ŀ													
	JST																				l L	, В		İ۲		B(I)			CONT														
																				_	[i	, B		Ţ		D(1)			CONT														
	ATC																			-	1	DON'T	CAI	RE I-	-1		L.	HGH		н													
PI	300	RA	M.	TAE	ILE	# _				_ F	REV			[TAC	E_					-				_	j	 -	-		Ľ	(POI	-)		-	_	-	PO	LAR	TY			-	
																										1	L	ow											Г				
т	T	-								A	ND								-		-	Т			and in the		-	-				٦	R R					_	_	_			_
Ē	-					1	-				-	Т				B (I)	-			T ER	F	_					D											B (0	,			-
R M	10	9	8	7	6	5	4	3	2	1	0	8	7	6	5	4	3	2	1	T _o	М	В	A	8	7	6	5	4	3	2	1	0	В	_	8	7	6	5	-	_	2	1	0
0					-	-	<u> </u>	-	1	1	<u> </u>	Ť	1	1	1	1	Ť	1	1	1	0		_	H	Ė	1	Ť		1	-		$\overline{}$	_	-	<u> </u>	<u> </u>	-	1		1			
1																					1																						
2			- 1																		2																						
3	-		-			-	-	-		-	-	-	-	-	-	-	-	-	-	-	3	-		\vdash		-	_	\vdash	-	-	\dashv	\dashv	_	_	-	-	-	-	-	-	-	-	-
5	-	77	-	-		-	-	+-	-	-	+	-	-	-	-	-	+-	-	-	-	5	\vdash		\vdash	-	\vdash	-	\vdash	\vdash	\dashv	\dashv	\dashv		_	\vdash	-	\vdash	\vdash	-	-	-	-	-
6									-		-	1	-	-		-	+		-		6				_		_	\vdash				\neg			\vdash	\vdash		1	1		\vdash		\vdash
7																					7																						
8	_					_	_	-	_	-	-	-	-	-		_	-	-	-	-	8	-	-			-	_		-			_			<u> </u>	_	-	-	-	-	-	-	L
9	-	_	-	_	-	-	-	-	-	-	\vdash	+	-	-	-	├-	+	-	-	-	9	-		Н		-	-	\vdash	-	\dashv	\vdash	-	_		-	-	-	-	-	-	-	-	-
11	\vdash				_		-	-	_	+	+	\vdash	-	-	-	-	-		-		11		_		_				\vdash						-	-			-	1			-
12		Ç.										1									12																						
13	_						_	_	_	_	_	1	_	_	_	_	_	_	_	_	13	\perp				-	_	Н	-	_		_			_	_	_	-	_	_	_	-	_
14	-	_		-		-	-	-	-	-	-	-	-	-	-	-	+	-	-	-	14	\vdash	-	Н	-		-	\vdash	\vdash	\dashv	\dashv	\dashv		-	\vdash	-	-	\vdash	+	-	-	+	⊢
16					-		-	-	-	-	+-	+	-	\vdash	-	-	+-	-	-		16				_	1	-	\vdash		-		\neg	_		\vdash			\vdash	1	\vdash	\vdash	1	\vdash
17																					17																						
18													-	-			-		-	-	18	-				-	_	\vdash		_		_		_	_	_	_	-	-	-	_	-	_
19	-		\vdash	-	-		-	-	-	+-	+	-	-	1	-	+	+	-	-	-	19	-	-	\vdash	_	+	-	\vdash	-	\dashv	\dashv	\dashv		-	-	-	-	+-	+-	-	+	+	-
21			\vdash		-		-	-	_	-	1	+	-	+-	_	1	1	-	-	-	21	1	-	\vdash	_	+				\neg		\neg						\vdash	1			1	
22																					22																						
23																					23																		_			_	L
PIN	11	10	9	8	7	6	5	4	3	2	1	23	22	21	20	17	16	15	14	13						1							19	18	23	22	21	20	17	16	15	14	13
NAME																					3.	TES: The F Unuse as Do All P virgin Unuse must I	n't C term	are (ina	ctive	virgir on a	l state	e. outs (i	в, о) in ti	he							5				

Signetics

п		
	Document No.	
	ECN No.	
	Date of Issue	October 1989
	Status	Preliminary Specification
	Programmable	Logic Devices

Programmable Logic Array $(20 \times 24 \times 11)$

DESCRIPTION

The PLHS473S is a two level logic device consisting of 24 AND gates and 22 OR gates with fusible link connections for programming I/O polarity and direction. The Signetics state-of-the-art Oxide-Isolated Bipolar process is used to produce performance not yet achieved in devices of this complexity.

The PLHS473 has an enhanced drive capability of 24mA. This, coupled with the fact that it can drive both 30pF and 200pF loads, allows it to be directly connected to an external bus.

All AND gates are linked to 11 input pins, 9 bidirectional I/O pins, and 2 dedicated output pins. The bidirectional pins are controlled via the OR array. Using these features, the PLHS473S can be configured with up to 20 inputs and as many as 11 outputs.

The AND array input buffers provide both the True and Complement of the inputs (I_X) and the bidirectional signals (B_X) as programmable connections to the AND gates. All 24 AND gates can then be optionally linked to all 22 OR gates (a feature known as Product Term sharing, not found in PALs® or most macrocell architectures). The OR array drives 11 output buffers which can be programmed as Active-High for AND-OR functions or Active-Low for AND-NOR functions. In addition, the I/O configuration of each bidirectional pin is individually controlled by sum-of-products (AND-OR) function which may also contain any of the 24 AND gate outputs. This allows dynamic I/O configuration of all 9 bidirectional pins.

The PLHS473S is field-programmable using Vertical Avalanche Migration Programmed (VAMPTM) fuses to program the cells. This enables the generation of custom logic patterns using standard programming equipment.

Order codes for this device are contained in the pages following.

PLHS473S


FEATURES

- I/O propagation delay:
 25ns (max) @ 30pF
 35ns (max) @ 200pF
- Field-programmable
- 11 dedicated inputs
- 2 dedicated outputs
- 9 bidirectional I/O lines
- 24 product terms
- 22 OR gates
- I/O direction decoded in OR array
- Output Enable decoded in OR array
- Power dissipation: 700mW (typ)
- Enhanced drive capability of 24mA
- Security fuse
- Programmable as 3–State or Open– Collector outputs
- TTL compatible

APPLICATIONS

- Random logic
- Bus interface
- Code Converters
- Function generators
- Address mapping
- Multiplexing

PIN CONFIGURATIONS



PAL is a registered trademark of Monolithic Memories, Inc., a wholly owned subsidiary of Advanced Micro Devices, Inc.


Philips Components





PLHS473S


PLA LOGIC DIAGRAM



Programmable Logic Array (20 × 24 × 11)

PLHS473S

FUNCTIONAL DIAGRAM



ORDERING INFORMATION

DESCRIPTION	ORDER CODE
24-pin Plastic DIP; (300mil-wide)	PLHS473SN
28-Pin Plastic Leaded Chip Carrier (450mil-wide)	PLHS473SA

ABSOLUTE MAXIMUM RATINGS¹

SYMBOL	PARAMETER	RATINGS	UNIT
V _{CC}	Supply voltage	+7	V _{DC}
V _{IN}	Input voltage	+5.5	V _{DC}
V _{OUT}	Output voltage	+5.5	V_{DC}
I _{IN}	Input currents	-30 to +30	mA
I _{OUT}	Output currents	+100	mA
T _A	Operating temperature range	0 to +75	°C
T _{STG}	Storage temperature range	-65 to +150	°C

NOTES:

1. Stresses above those listed may cause malfunction or permanent damage to the device. This is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

THERMAL RATINGS

TEMPERATUR	RE
Maximum junction	150°C
Maximum ambient	75°C
Allowable thermal rise ambient to junction	75°C

LOGIC FUNCTION

TYPICAL PRODUCT TERM: $P_n = A \cdot \overline{B} \cdot C \cdot D \cdot \dots$

TYPICAL LOGIC FUNCTION: AT OUTPUT POLARITY = H Z = P0 + P1 + P2 . . .

AT OUTPUT POLARITY = L Z = P0 + P1 + P2 + . . . Z = P0 · P1 · P2 · . . .

NOTES:

- For each of the 11 outputs, either function Z (Active—High) or Z (Active—Low) is available, but not both. The desired output polarity is programmed via the Ex—OR gates.
 Z, A, B, C, etc. are user defined connections to fixed inputs (f), fixed output pins (f) and bidirectional pins (B).

October 1989 176

PLHS473S

DC ELECTRICAL CHARACTERISTICS $0^{\circ}C \le T_{A} \le +75^{\circ}C$, $4.75 \le V_{CC} \le 5.25V$

				LIMITS		
SYMBOL	PARAMETER	TEST CONDITIONS	Min	Typ1	Max	UNIT
Input vol	tage ²			•		
V _{IL}	Low	V _{CC} = MIN			0.8	V
V_{IH}	High	$V_{CC} = MAX$	2.0			V
V _{IC}	Clamp ³	$V_{CC} = MIN$, $I_{IN} = -12mA$		-0.8	-1.2	V
Output v	oltage ²				•	
		V _{CC} = MIN				
V_{OL}	Low ⁴	$I_{OL} = 24mA$			0.5	V
V_{OH}	High ⁵	$I_{OH} = -2mA$	2.4			V
Input cur	rent					
		V _{CC} = MAX				
I _{IL}	Low	$V_{IN} = 0.45V$			-100	μА
I _H	High	V _{IN} = 5.5V			40	μА
Output c	urrent					
		V _{CC} = MAX				
1	Hi–Z state ⁹	V _{OUT} = 5.5V			40	μА
I _{O(OFF)}	HI-Z State-	V _{OUT} = 0.45V			-100	μА
Ios	Short circuit 3, 5, 6	V _{OUT} = 0.5V	-15		-70	mA
I _{CC}	V _{CC} supply current ⁷	V _{CC} = MAX		140	155	mA
Capacita	nce	•		•	•	
		V _{CC} = 5V				
I _{IN}	Input	$V_{1N} = 2.0V$		8	15	pF
CB	1/0	V _B = 2.0V		10	15	pF

NOTES:

- 1. All typical values are at V_{CC} = 5V. T_A = +25°C.
- All voltage values are with respect to network ground terminal.
 Test one at a time.
- 4. Measured with inputs 0-4=0V, inputs 5, 7=4.5V, and inputs 6, 8-10+10V.
- 5. Same conditions a Note 4 except input 8 = 4.5V.
 6. Duration of short circuit should not exceed 1 second.
- 7. I_{CC} is measured with all inputs and bidirectional pins at 4.5V. Part in Virgin State
- Measured at V_T = V_{OL} + 0.5V.
 Leakage values are a combination of input and output leakage.

October 1989 177

PLHS473S

AC ELECTRICAL CHARACTERISTICS 0°C \leq T_A \leq +75°C, 4.75 \leq V_{CC} \leq 5.25V, R₁ = 200 Ω , R₂ = 390 Ω

				TEST		LIMITS		
SYMBOL	PARAMETER	FROM	то	CONDITIONS	Min	Typ ¹	Max	UNIT
t _{PD}	Propagation delay	Input ±	Output ±	C _L = 200pF 2 outputs switching		20	35	ns
t _{OE}	Output Enable	Input ±	Output ±	C _L = 200pF		15	25	ns
t _{OD}	Output Disable ²	Input ±	Output ±	C _L = 5pF		15	22	ns


AC ELECTRICAL CHARACTERISTICS 0°C \leq T_A \leq +75°C, 4.75 \leq V_{CC} \leq 5.25V, R₁ = 470 Ω , R₂ = 1k Ω

				TEST		LIMITS		
SYMBOL	PARAMETER	FROM	то	CONDITIONS	Min	Typ ¹	Max	UNIT
t _{PD}	Propagation delay	Input ±	Output±	C _L = 30pF		15	25	ns
toE	Output Enable	Input ±	Output –	C _L = 30pF		15	22	ns
t _{OD}	Output Disable ²	Input ±	Output +	C _L = 5pF		15	22	ns


NOTES:

- All typical values are at V_{CC} = 5V. T_A = +25°C.
 High-to-High impedance tests are made at an output voltage of V_{OH} 0.5V with R₁ disconnected from +5V, and Low-to-High impedance tests are made at an output voltage of V_{OL} + 0.5V.

VOLTAGE WAVEFORMS




TEST LOAD CIRCUIT



TIMING DEFINITIONS

SYMBOL	PARAMETER
ŧрD	Propagation delay between input and output.
t _{OD}	Delay between input change and when output is off (Hi–Z or High).
t _{OE}	Delay between input change and when output reflects specified output level

TIMING DIAGRAM



October 1989 178


PLHS473S

LOGIC PROGRAMMING


The PLA can be programmed by means of Logic programming equipment.

With Logic programming the AND/OR/Ex–OR gate input connections necessary to implement the desired logic function are coded directly from logic equations using the Program Table on the following page.


In this table, the logic state of variables I, P and B, associated with each Sum Term S is assigned a symbol which results in the proper fusing pattern of corresponding links, defined as follows



"AND" ARRAY - (I, B)







NOTES:

- 1. This is the initial unprogrammed state of all links.
- Any gate P_n will be unconditionally inhibited if the true and complement of either input (I or B) are both programmed for a connection.

VIRGIN STATE

A factory shipped virgin device contains all fusible links intact, such that:

- All outputs are at "L" polarity.
- 2. All Pn terms are enabled. (Don't Cares.)
- 3. All P_n terms are inactive on all outputs.

PLA PROGRAM TABLE

Signetics Programmable Logic Devices

PLHS473S

																																				,										
CI	ICT		ЛEF	D AI	A M	ıc																				_ A	ND			ļ ——			R													
			ASE																				_							ŀГ	ACTI	VE	A													
																								1	NAC	TIVE	Ţ	0		!	INAC	TIVE	1.	B(0)											
			CS																						. B	-	+	н		L																
CL	JST	ON	<i>N</i> EF	S	ΥM	BC	DLI	ZE	DI	PA	RT	Γ#	t _												. B		-		B(I)			CON	TRO	L												
TC	OTA	LP	NUP	ИВ	ER	OF	FF	PAF	RTS	6_														1 1	-		-	4		, r			_			1										
PF	100	GR/	AΜ	TA	BL	E ;	#_					_ R	RΕ\				_ [TAC	E					L	DON.	T CA	RE -				HGH		H	(PO	L)	<u> </u>					01.45	uT).				
																														į l	.OW		ļL	, .	-,	\vdash			_	T	OLAF	TY	_	_	_	_
												_	ND						-					-	_									_		L_ DR	_	_	_		1	_		_		_
						1				_			NU	_	_	-			D /				-	Į	-	E	_				D				_		0	T		-		B (0			-	-
	10	9	8	T 7	Te	÷	5	4	3	_	2	1	Το	+	. T	7	6	5	B (3	T -	T 1	Το	Ė R M	В	-	8	7	6	5	4	3	2	1	0	В	TA	8	7	6	5	B (0	_	2	1	Το
-	10	9	- 8	+-	+	+	5	4	3	+	2	1	-	+°	+	-	ь	5	4	3	2	+'	10	-	B	A	18	/	6	5	4	3	2	1	0	B	<u> </u>	+°	1	10	+5	+-	3	2	+	+0
_	_		+	+	+	+		-	+	+	+		+	+	+	-		-	\vdash	+	+	+	+	1	+-	+	+	-	-	\vdash	-		-	-	-	-	+	+	+	+	+	+	+	+	\vdash	+
						İ				İ					1									2																						
_			1	1	1	7			-	Ŧ	4			\perp	4	\Box				L	L	\perp	\vdash	3	\vdash										1				_	L	1	1	L		_	L
-		-	+	+	+	+	-		-	+	+		\vdash	+	+			-	-	+-	+-	+	+	5	╀	+	-	-	-	-	-	-	-	-	-	-	+-	\vdash	+-	+	+-	+-	+	+-	+	+
			+	+	+	$^{+}$			\vdash	$^{+}$	+		+	+	+				-	+	+	+-	+	6	+	+-	\vdash		\vdash	-	\vdash	_	_	-	\vdash	\vdash	\vdash	\vdash	+	+	+	+	+	+	+	+
										I				I										7																	I					
-		-	-	+	+	+	-			+	+		-	+	+	-		_	_	-	+-	+	+	8	-	-	-	-	_	-	├-	_	-	-	-	-	-	-	-	+	+	+	+-	+-	+	+-
		-	+-	+	+	+	-		+	+	+		-	+	+	-	_	-	-	+	+-	+	+-	9	+-	+-	-	-	-	-	+-	-	-	-	-	-	+	\vdash	+	+	+	+	+	+	+	+-
				\perp	†	\perp				1	\top			†	†						†			11	1	\vdash															土					土
2				I	I	1				I	\Box			I	I	\Box					\Box	I		12																1	T	\vdash	_	1		1
		-	+	+	+	+	-		+-	+	+		-	+-	+	-		-	_	+	+	+	\vdash	13	+	+-	╀	-	-	-	-	-	-	-	-	-	├	\vdash	\vdash	+	+	+	+	\vdash	-	+
		-	+	+	+-	+	\dashv		+	$^{+}$	+		-	+	+	-		-	-	+	+	+	+-	15	+	-	+	\vdash	-	-	\vdash	-	-	-	-	\vdash	\vdash	\vdash	+	+	+	+	+	+	+	+
5											1				I									16																	I					
		-	-	+	+	+	_		-	+	+		-	+	+	_			_	-	1	+	-	17	1	-	1	-	_	-	-	-	_	-	<u> </u>	-	-	-	⊢	+	+	+	+	+		+
-	-	-	+-	+-	+	+	-		-	+	+		-	+	+	-		-	-	+	+	+-	+-	19	╁	+	+	-	-	\vdash	\vdash	\vdash	-	-	\vdash	\vdash	+	+	+	+	+	+	+	+	+	+
					+	+			1	†	1		\vdash	†	+	1			_	+	+	†		20	\vdash		†																			
1				L	I	1				I	1			I	I						I	I		21		1														1	1	1	1		1	
2		-	-	+	+	+	-		-	+	+	_	-	+	+	-		-	-	+	+	+	+-	22	+	+	+	-	-	-	\vdash	-	-	-	-	-	+	+	+	+	+	+	+	+	+-	+
N	11	10	9	8	+,	+	6	5	4	+	3	2	1	+	+	22	21	20	17	16	15	14	13	-	+	+	+	-	-	\vdash	+	\vdash	-	+	-	19	18	22	120	12	1 20	1,	10	15	14	12
NAME	11	10	9	8			D	5	4		3	2	1	2	3	22	21	20	17	16	15	14	13	NC 1. 2. 3.	TES: The Unu as C All P virgi Unu	FPL sed I con't den	Care ns a	(–) i e ina	n the	on	in sta all ou	ite. tputs	(B,) (O) in	the		18	23	22	1			16	15		

Signetics

PLS100/PLS101 Field-Programmable Logic Array $(16 \times 48 \times 8)$

Signetics Programmable Logic **Product Specification**

Application Specific Products • Series 28

DESCRIPTION

The PLS100 (3-state) and PLS101 (Open Collector) are bipolar, fuse Programmable Logic Arrays (FPLAs). Each device utilizes the standard AND/OR/ Invert architecture to directly implement custom sum of product logic equations.

Each device consists of 16 dedicated inputs and 8 dedicated outputs. Each output is capable of being actively controlled by any or all of the 48 product terms. The True, Complement, or Don't Care condition of each of the 16 inputs can be ANDed together to comprise one P-term. All 48 P-terms can be selectively ORed to each output.

The PLS100 and PLS101 are fully TTL compatible, and chip enable control for expansion of input variables and output inhibit. They feature either Open Collector or 3-state outputs for ease of expansion of product terms and application in bus-organized systems.

Order codes are listed in the Ordering Information Table.


FEATURES

- Field-Programmable (Ni-Cr link)
- Input variables: 16
- Output functions: 8
- Product terms: 48
- I/O propagation delay: 50ns (max.)
- Power dissipation: 600mW (tvp.)
- Input loading: -100μA (max.)
- Chip Enable input
- Output option:
 - PLS100: 3-State
 - PLS101: Open-Collector
- · Output disable function:
 - 3-State: Hi-Z
 - Open-Collector: High


APPLICATIONS

- CRT display systems
- Code conversion
- Peripheral controllers
- Function generators
- Look-up and decision tables
- Microprogramming
- Address mapping
- Character generators
- · Data security encoders
- Fault detectors
- · Frequency synthesizers
- 16-bit to 8-bit bus interface
- Random logic replacement

FUNCTIONAL DIAGRAM




PIN CONFIGURATIONS



PLS100/PLS101

FPLA LOGIC DIAGRAM



PLS100/PLS101

ORDERING INFORMATION

DESCRIPTION	TRI-STATE	OPEN-COLLECTOR
28-pin Plastic DIP 600mil-wide	PLS100N	PLS101N
28-pin Plastic Leaded Chip Carrier	PLS100A	PLS101A

The PLS100 device is also processed to military requirements for operation over the military temperature range. For specifications and ordering information consult the Signetics Military Data Book.

ABSOLUTE MAXIMUM RATINGS¹

SYMBOL	PARAMETER	RATINGS	UNIT
V _{CC}	Supply voltage	+7	V_{DC}
V _{IN}	V _{IN} Input voltage		V _{DC}
Vo	Output voltage	+ 5.5	V _{DC}
I _{IN}	Input current	± 30	mA
lout	Output current	+ 100	mA
T _A	Operating temperature range	0 to +75	°C
T _{STG}	Storage temperature range	-65 to +150	°C

THERMAL RATINGS

TEMPERATURE					
Maximum junction	150°C				
Maximum ambient	75°C				
Allowable thermal rise ambient to junction	75°C				

NOTE:

DC ELECTRICAL CHARACTERISTICS $0^{\circ}C \le T_{A} \le +75^{\circ}C$, $4.75V \le V_{CC} \le 5.25V$

				LIMITS				
SYMBOL	PARAMETER	TEST CONDITION	Min	Typ ¹	Max	UNIT		
Input volt	age ²							
V _{IH}	High	V _{CC} = Max	2			V		
V_{IL}	Low	$V_{CC} = Min$			0.8	V		
V_{IC}	Clamp ^{2, 3}	$V_{CC} = Min, I_{IN} = -12mA$		-0.8	-1.2	V		
Output vo	oltage ²							
		V _{CC} = Min						
V_{OH}	High (PLS100)4	$I_{OH} = -2mA$	2.4			V		
V_{OL}	Low ⁵	$I_{OL} = 9.6 \text{mA}$		0.35	0.45	V		
Input curi	rent							
I _{IH}	High	V _{IN} = 5.5V		< 1	25	μΑ		
I _{IL}	Low	$V_{IN} = 0.45V$		-10	-100	μΑ		
Output cu	irrent							
l _{O(OFF)}	Hi-Z state (PLS100)	CE = High, V _{CC} = Max						
		$V_{OUT} = 5.5V$		1	40	μΑ		
		$V_{OUT} = 0.45V$		-1	-40			
los	Short circuit (PLS100)3, 6	$\overline{CE} = Low, V_{OUT} = 0V$	-15		-70	mA		
Icc	V _{CC} supply current ⁷	V _{CC} = Max		120	170	mA		
Capacitan	ce							
		$\overline{\text{CE}} = \text{High}, \ V_{\text{CC}} = 5.0 \text{V}$						
CIN	Input	$V_{IN} = 2.0V$		8		pF		
C _{OUT}	Output	$V_{OUT} = 2.0V$		17		pF		

Notes on following page.

Stresses above those listed may cause malfunction or permanent damage to the device. This is a stress
rating only. Functional operation at these or any other conditions above those indicated in the operational
and programming specification of the device is not implied.

PLS100/PLS101

AC ELECTRICAL CHARACTERISTICS $R_1 = 470\Omega$, $R_2 = 1k\Omega$, $C_L = 30pF$, $0^{\circ}C \leqslant T_A \leqslant +75^{\circ}C$, $4.75V \leqslant V_{CC} \leqslant 5.25V$

OVERDOL	DADAMETED	T0	FD014		LINUT			
SYMBOL	PARAMETER	то	FROM	Min	Typ ¹	Max	UNIT	
Propagati	on delay							
t _{PD}	Input	Output	Input		35	50	ns	
t _{CE}	Chip enable	Output	Chip enable		15	30	ns	
Disable time								
t _{CD}	Chip disable	Output	Chip enable		15	30	ns	

NOTES

- 1. All values are at $V_{CC} = 5V$, $T_A = + 25$ °C.
- 2. All voltage values are with respect to network ground terminal.
- 3. Test one pin at a time.
- 4. Measured with V_{IL} applied to $\overline{\text{CE}}$ and a logic high stored.
- 5. Measured with a programmed logic condition for which the output test is at a low logic level. Output sink current is applied through a resistor to V_{CC}.
- 6. Duration of short circuit should not exceed 1 second.
- 7. I_{CC} is measured with the chip enable input grounded, all other inputs at 4.5V and the outputs open.

PLS100/PLS101

LOGIC PROGRAMMING

PLS100/PLS101 logic designs can be generated using Signetics' AMAZE PLD design software or one of several other commercially available, JEDEC standard PLD design software packages. Boolean and/or state equation entry is accepted.


PLS100/PLS101 logic designs can also be generated using the program table entry format detailed on the following pages. This program table entry format is supported by the Signetics' AMAZE PLD design software (PTP module). AMAZE is available free of charge to qualified users.

To implement the desired logic functions, the state of each logic variable from logic equations (I, B, O, P, etc.) is assigned a symbol. The symbols for TRUE, COMPLEMENT, INACTIVE, PRESET, etc., are defined below.


OUTPUT POLARITY - (F)



"AND" ARRAY - (I)



"OR" ARRAY - (F)




NOTES


- 1. This is the initial unprogrammed state of all link pairs. It is normally associated with all unused (inactive) AND gates P_{n} .
- 2. Any gate Pn will be unconditionally inhibited if any one of its (I) link pairs is left intact.

PLS100/PLS101


TEST LOAD CIRCUITS



VOLTAGE WAVEFORMS



TIMING DIAGRAM



TIMING DEFINITIONS

SYMBOL	PARAMETER
t _{CE}	Delay between beginning of Chip Enable low (with Input valid) and when Data Output becomes valid.
t _{CD}	Delay between when Chip Enable becomes High and Data Output is in off state (Hi-Z or High).
t _{PD}	Delay between beginning of valid Input (with Chip Enable Low) and when Data Output becomes valid.

VIRGIN STATE

The PLS100/101 virgin devices are factory shipped in an unprogrammed state, with all fuses intact, such that:

- 1. All P_n terms are disabled (inactive), in the AND array.
- 2. All Pn terms are active in the OR array.
- 3. All outputs are active-High.

PLS100/PLS101

FPLA PROGRAM TABLE

	EL	Ф				Polarity programmed once only. Enter (H) for all unused outputs.									ND												P	OLA	RIT	Y		
	OUTPUT ACTIVE LEVEL	Active	-	1		no p	Ţ	<u> </u>	T —		-			INF	TU	(I_m)												0	R			
	EL	ĕ-	1			o pa	E R M	1	1 4	1	1	1	1	L.	-					. –						. – ,		UTP	UT	(F _P)		
	1					Ē 5		5	4	3	2	1	0	9	8	7	6	5	4	3	2	1	0		7	6	5	4	3	2	1	0
	AC		T			ogra or al	0	-	-	_	-	⊢	-	-	_	<u> </u>	_	_	_	\vdash	_	_				_	_		\vdash			_
	7	e _		1		H) fo	1 2	-	-	-	-	\vdash	-	-	_	\vdash	-		-	\vdash	-	-	_	1		-	_	\vdash	\vdash	_	_	_
	15	Active	, 1	-	S	arit)	3		-			\vdash	\vdash			\vdash		_		\vdash			_		_				Н			-
	0	A T			NOTES	E Pol	4																									
				1	ž	- 2	5																									
			T	T		S.	6	-	_	_	_	_	_	_		<u> </u>	_	_		L						_	_		\vdash	_		
		Prod. Term Not Present in Fo	-			term	7	-	-	-	-	\vdash	-	\vdash	-	\vdash	-	-	-	\vdash	-	-	-	1			-		\vdash		_	
S		Prod. Term Not Present in Fo	* (period)	3		arity d P.	9	\vdash	-	-	-	\vdash	\vdash		-	\vdash	-	-		H			_		_				\vdash	_	_	_
RIE	z	Te	Jor	3		pol	10					_	_			\vdash																_
L	0	od.				put	11																									
E	5	4				put	12																									
PROGAM TABLE ENTRIES	OUTPUT FUNCTION		+	-		Entries independent of output polarity. Enter (A) for unused outputs of used P-terms.	13																									
TA	5					nden	14	-	-	_		_	_	-		_	-	_	_	H	_	_					_	_				_
Ā	TPI	Prod. Term Present in Fo				nun	15 16	-	-	-		-	-	-	-	-	-	-	-	\vdash		-			_	-	-		-			-
90	00	Te	4			nde) for	17	-		_			_		_									1		_				-		
PR		od.	1	- 1		er (A)	18																									
		Pre Pre			NOTES	nte	19																									
					2	2.6	20																									
			+	+	_		21		_	_		_				L																_
		e			for unused inputs of used		22	-	_	_		_	_	_		_	_			\vdash							_					_
		Don't Care	- (dash)		jo		23	-	-	-		_	-	-		-	_	-		\vdash			-	-	_		_		\vdash			
		'n	100	1	S		25	-	-	-	-	-	-	-		-	-	-		\vdash	-		_	1	_		-	-	\vdash		_	_
	BL	ă		1	ndu		26		-	-		\vdash	-		_	\vdash	-	-		Н				1	_		-		\vdash		_	-
	INPUT VARIABLE		\perp	4	ъ		27																									
	X			1	nse		28																									
	5	Ε	-	1	5		29																									
	A N				for		30																									
	_			1	NOTE Enter (-) f		31			_		_	_			_		_		\vdash							_		\vdash			
		E	I	.	Ш.	SE	32	-	-	-		\vdash	-	-		\vdash	-	-		\vdash		-					-	-	\vdash			
		=	1		10T	ter	33 34	-	-	-	-	\vdash	-	-	_	\vdash	-	-		Н	-			1			-	\vdash	\vdash	_		_
\perp			_	1	2 ш і		35					\vdash	_			\vdash									_		-	\vdash	Н			_
			1	1			36																	l						_		
						ш	37																									
				į		DATE	38																									
						٦	39		_	_	\vdash	<u> </u>		_		_		_			_						_		_			_
		X					40	-	-	-	\vdash	-	-	-	_	-	-	-			_						-		\vdash		-	_
		X					41		-	-	\vdash	\vdash	-	-		\vdash	-	-	-	\vdash	-	-	-	1			-		\vdash	_	_	-
		CF (XXXX)				REV	43			-	\vdash	\vdash	-		-	\vdash		-		\vdash	-		_	1			-		\vdash	_	_	-
		0	1		1	4	44																									
			T	-			45																									
			2 4 5	7			46																									
			0	2	3TS		47																									
		#= #	1175	7717	- PAR		PIN NO.	2	2	2 2	2	2	2 5	2	2	2	3	4	5	6	7	8	9		1	1	1 2	1 3	1 5	1 6	1 7	1 8
	CUSTOMER NAME	PURCHASE ORDER #	CHISTOMER SYMBOLIZED BART	OMEN STMB	TOTAL NUMBER OF PARTS	PROGRAM TABLE#	VARIABLE NAME		•		3	*	3	3	,										,	•	-	3	J	0	,	0
- (200	PUR		200	TOT,	PRO	>																									

Signetics

Programmable Logic Devices

Section 5 Programmable Logic Sequencer Device Data Sheets

INDEX

Series 20	
PLS155	Programmable Logic Sequencer (16 × 45 × 12); 14MHz 191
PLS157	Programmable Logic Sequencer (16 × 45 × 12); 14MHz 202
PLS159A	Programmable Logic Sequencer (16 \times 45 \times 12); 18MHz 213
Series 24	
PLS167/A	Programmable Logic Sequencers (14 \times 48 \times 6); 14, 20MHz 223
PLS168/A	Programmable Logic Sequencers (12 \times 48 \times 8); 14, 20MHz 234
PLS179	Programmable Logic Sequencer (20 × 45 × 12); 18MHz 245
PLC42VA12	CMOS Programmable Logic Sequencer
	(42 × 105 × 12); 25MHz
Series 28	
PLC415-16	Programmable Logic Sequencer (17 × 68 × 8); 16MHz 275
PLS105/A	Programmable Logic Sequencers (16 \times 48 \times 8); 14, 20MHz 294
PLUS105-40	Programmable Logic Sequencer (16 × 48 × 8); 40MHz 305
PLUS105-55	Programmable Logic Sequencer (16 × 48 × 8); 55MHz 317
PLUS405-37/	45
	Programmable Logic Sequencers (16 \times 64 \times 8); 37, 45MHz 329
PLUS405-55	Programmable Logic Sequencer (16 × 64 × 8); 55MHz 344

Signetics

Document No.	853-0317				
ECN No.	93255				
Date of Issue	May 11, 1988				
Status	Product Specification				
Programmable Logic Devices					

DESCRIPTION

The PLS155 is a 3-State output, registered logic element combining AND/OR gate arrays with clocked J-K flip-flops. These J-K flip-flops are dynamically convertible to D-type via a "fold-back" inverting buffer and control gate F_C. It features 4 registered I/O outputs (F) in conjunction with 8 bidirectional I/O lines (B). These yield variable I/O gate and register configurations via control gates (D, L) ranging from 16 inputs to 12 outputs.

The AND/OR arrays consist of 32 logic AND gates, 13 control AND gates, and 21 OR gates with fusible link connections for programming I/O polarity and direction. All AND gates are linked to 4 inputs (I), bidirectional I/O lines (B), internal flip-flop outputs (Q), and Complement Array output (C). The Complement Array consists of a NOR gate optionally linked to all AND gates for generating and propagating complementary AND terms.


PLS155

Field-Programmable Logic Sequencer $(16 \times 45 \times 12)$

FEATURES

- f_{MAX} = 14MHz
- 18.2MHz clock rate
- Field-Programmable (Ni-Cr link)
- 4 dedicated inputs
- 13 control gates
- 32 AND gates
- 21 OR gates
- 45 product terms:
- 32 logic terms
- 13 control terms
- 8 bidirectional I/O lines
- 4 bidirectional registers
- J-K, T, or D-type flip-flops
- Asynchronous Preset/Reset
- Complement Array
- Active-High or -Low outputs
- Programmable OE control
- Positive edge-triggered clock
- Input loading: -100µA (max.)
- Power dissipation: 750mW (typ.)
- TTL compatible
- 3-State outputs

PIN CONFIGURATIONS



APPLICATIONS

- Random sequential logic
- Synchronous up/down counters
- Shift registers
- Bidirectional data buffers
- Timing function generators
- System controllers/synchronizers
- Priority encoder/registers


Philips Components





PLS155

FUNCTIONAL DIAGRAM



On–Chip T/C buffers couple either True (I, B, Q) or Complement (I, B, Q, C) input polarities to all AND gates, whose outputs can be optionally linked to all OR gates. Any of the 32 AND gates can drive bidirectional I/O lines (B), whose output polarity is individually programmable through a set of Ex–OR gates for implementing AND–OR or AND–NOR logic functions. Similarly, any of the AND gates can drive the J–K

inputs of all flip–flops. The Asynchronous Preset and Reset lines (P, R), are driven from the OR matrix.

All flip—flops are positive edge—triggered and can be used as input, output or I/O (for interfacing with a bidirectional data bus) in conjunction with load control gates (L), steering inputs (I),


(B), (Q) and programmable output select lines (E).

The PLS155 is field programmable, enabling the user to quickly generate custom patterns using standard programming equipment.

Order codes are listed in the Ordering Information Table.

PLS155

FPLS LOGIC DIAGRAM




PLS155

VIRGIN STATE

The factory shipped virgin device contains all fusible links intact, such that:

- 1. OE is always enabled.
- 2. Preset and Reset are always disabled.
- 3. All transition terms are disabled.
- All flip-flops are in D-mode unless otherwise programmed to J-K only or J-K or D (controlled).
- All B pins are inputs and all F pins are outputs unless otherwise programmed.

LOGIC FUNCTION



NOTE:

Similar logic functions are applicable for D and T mode flip-flops.

FLIP-FLOP TRUTH TABLE

ŌE	L	СК	Р	R	J	K	Q	F
Н ,								Hi–Z
L	Х	Х	Н	L	Х	Χ	Н	L
L	Х	Χ	L	Н	Х	Х	L	H
L	L	\uparrow	L	L	L	L	Q	a
L	L	\uparrow	L	L	L	Н	L	Н
L	L	\uparrow	L	L	Н	L	Н	L
L	L	1	L	L	Н	Н	ā	Q
Н	Н	1	L	L	L	Н	L	H*
Н	Н	\uparrow	L	L	Н	L	Н	L*
+10V	Х	\uparrow	Х	Х	L	Н	L	H**
	Х	1	Χ	Χ	Н	L	Н	L**

NOTES:

1. Positive Logic:

- denotes transition from Low to High level.
- 3. X = Don't care
- * = Forced at F_n pin for loading the J–K flipflop in the Input mode. The load control term, L_n must be enabled (HIGH) and the p– terms that are connected to the associated flip–flop must be forced LOW (disabled) during Preload.
- At P = R = H, Q = H. The final state of Q depends on which is released first.
- 5. ** = Forced at F_n pin to load J–K flip–flop independent of program code (Diagnostic mode), 3–State B outputs.

ORDERING INFORMATION

DESCRIPTION	ORDER CODE
20-Pin Plastic DIP (300mil-wide)	PLS155N
20-Pin Plastic Leaded Chip Carrier	PLS155A

ABSOLUTE MAXIMUM RATINGS1

		RATI		
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage		+7	V _{DC}
V _{IN}	Input voltage		+5.5	V _{DC}
V _{OUT}	Output voltage		+5.5	V _{DC}
I _{IN}	Input currents	-30	+30	mA
lout	Output currents		+100	mA
T _A	Operating temperature range	0	+75	°C
T _{STG}	Storage temperature range	-65	+150	°C

NOTES:

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

THERMAL RATINGS

TEMPERATURE	
Maximum junction	150°C
Maximum ambient	75°C
Allowable thermal rise ambient to junction	75°C

PLS155

DC ELECTRICAL CHARACTERISTICS $0^{\circ}C \le T_A \le +75^{\circ}C$, $4.75V \le V_{CC} \le 5.25V$

				LIMITS		
SYMBOL	PARAMETER	TEST CONDITION	Min	Typ1	Max	UNIT
Input volt	age ²					
V _{IH}	High	V _{CC} = Max	2.0			V
V _{IL}	Low	V _{CC} = Min			0.8	V
V _{IC}	Clamp	$V_{CC} = Min, I_{IN} = -12mA$		-0.8	-1.2	V
Output vo	Itage ²					
		V _{CC} = Min				
V _{OH}	High	$I_{OH} = -2mA$	2.4			V
V _{OL}	Low	I _{OL} = 10mA		0.35	0.5	V
Input curr	ent ⁵					
		V _{CC} = Max				
I _{IH}	High	V _{IN} = 5.5V		<1	80	μА
I _{IL}	Low	$V_{IN} = 0.45V$		-10	-100	μА
Output cu	rrent				-	
		V _{CC} = Max				
I _{O(OFF)}	Hi-Z state ^{5, 6}	V _{OUT} = 5.5V		1	80	μΑ
		V _{OUT} = 0.45V		-1	-140	μА
Ios	Short circuit ^{3, 7}	V _{OUT} = 0V	-15		-70	mA
Icc	V _{CC} supply current⁴	V _{CC} = Max		150	190	mA
Capacitan	ce					
		V _{CC} = 5.0V				
CIN	Input	V _{IN} = 2.0V		8		pF
C _{OUT}	Output	V _{OUT} = 2.0V		15		pF

195

- 1. All typical values are at V_{CC} = 5V, T_A = +25°C. 2. All voltage values are with respect to network ground terminal.
- 3. Test one at a time.
- 4. I_{CC} is measured with the OE input grounded, all other inputs at 4.5V and the outputs open.
- 5. Leakage values are a combination of input and output leakage.
- 6. Measured with VIH applied to OE.
- 7. Duration of short circuit should not exceed 1 second.

PLS155

AC ELECTRICAL CHARACTERISTICS $0^{\circ}C \le T_A \le +75^{\circ}C$, $4.75V \le V_{CC} \le 5.25V$, $R_1 = 470\Omega$, $R_2 = 1k\Omega$

					LIMITS			
SYMBOL	PARAMETER	FROM	то	TEST CONDITION	Min	Typ ¹	Max	UNIT
Pulse wid	th	•						
t _{CKH}	Clock ² High	CK+	CK-	C _L = 30pF	25	20		ns
t _{CKL}	Clock Low	CK-	CK+	C _L = 30pF	30	20		ns
t _{CKP}	Period	CK+	CK+	C _L = 30pF	70	50		ns
t _{PRH}	Preset/Reset pulse	(I,B) -	(I,B) +	C _L = 30pF	40	30		ns
Setup time	e ⁵							
t _{IS1}	Input	(I,B) ±	CK+	C _L = 30pF	40	30		ns
t _{IS2}	Input (through F _n)	F±	CK+	C _L = 30pF	20	10		ns
t _{IS3}	Input (through Complement Array) ⁴	(I,B) ±	CK+	C _L = 30pF	65	40		ns
Hold time		•						
t _{IH1}	Input	(I,B) ±	CK+	C _L = 30pF	0	-10		ns
t _{IH2}	Input	F±	CK+	C _L = 30pF	15	10		ns
Propagati	on delays	•				-		
t _{CKO}	Clock	CK+	F±	C _L = 30pF		25	30	ns
t _{OE1}	Output enable	OE -	F-	C _L = 30pF		20	30	ns
t _{OD1}	Output disable ³	ŌĒ +	F+	C _L = 5pF		20	30	ns
t _{PD}	Output	(I,B) ±	В±	C _L = 30pF		40	50	ns
t _{OE2}	Output enable	(I,B) +	В±	C _L = 30pF		35	55	ns
t _{OD2}	Output disable ³	(I,B) -	B +	C _L = 5pF		30	35	ns
t _{PRO}	Preset/Reset	(I,B) +	F±	C _L = 30pF		50	55	ns


NOTES:

- 1. All typical values are at $V_{CC} = 5V$, $T_A = +25^{\circ}C$
- 2. To prevent spurious clocking, clock rise time $(10\% 90\%) \le 10$ ns.
- Measured at V_T = V_{OL} + 0.5V.
 When using the Complement Array t_{CKP} = 95ns (min).
- Limits are guaranteed with 12 product terms maximum connected to each sum term line.
 For test circuits, waveforms and timing diagrams see the following pages.

VOLTAGE WAVEFORMS


+3.0V · +3.0V MEASUREMENTS: All circuit delays are measured at the +1.5V level of inputs and outputs, unless otherwise specified. Input Pulses

TEST LOAD CIRCUIT



PLS155

TIMING DIAGRAMS




TIMING DEFINITIONS

SYMBOL	PARAMETER
t _{CKH}	Width of input clock pulse.
t _{CKL}	Interval between clock pulses.
t _{CKP}	Clock period.
t _{PRH}	Width of preset input pulse.
t _{IS1}	Required delay between beginning of valid input and positive transition of clock.
t _{IS2}	Required delay between beginning of valid input forced at flip-flop output pins, and positive transition of clock.
t _{IH1}	Required delay between positive transition of clock and end of valid input data.
t _{IH2}	Required delay between positive transition of clock and end of valid input data forced at flip—flop output pins.
t _{CKO}	Delay between positive transition of clock and when outputs become valid (with OE Low).
t _{OE1}	Delay between beginning of Output Enable Low and when outputs become valid.
t _{OD1}	Delay between beginning of Output Enable High and when outputs are in the OFF-State.
t _{PD}	Propagation delay between combinational inputs and outputs.
t _{OE2}	Delay between predefined Output Enable High, and when combinational outputs become valid.
t _{OD2}	Delay between predefined Output Enable Low and when combinational outputs are in the OFF–State.
t _{PRO}	Delay between positive transition of predefined Preset/Reset input, and when flip—flop outputs become valid.


PLS155

TIMING DIAGRAMS (Continued)



* The leading edge of preset/reset must occur only when the input clock is "low", and must remain "high" as long as required to override clock. The falling edge of preset/reset can never go "low" when the input clock is "high".





PLS155


LOGIC PROGRAMMING

PLS155 logic designs can be generated using Signetics AMAZE PLD design software or one of several other commercially available, JEDEC standard PLD design software packages. Boolean and/or state equation entry is accepted.


PLS155 logic designs can also be generated using the program table entry format detailed on the following pages. This program table entry format is supported by the Signetics AMAZE PLD design software (PTP module). AMAZE is available free of charge to qualified

To implement the desired logic functions, the state of each logic variable from logic equations (I, B, O, P, etc.) is assigned a symbol. The symbols for TRUE, COMPLEMENT, INACTIVE, PRESET, etc., are defined below.


"AND" ARRAY - (I), (B), (Qp)



"COMPLEMENT" ARRAY - (C)




"OR" ARRAY - (F-F CONTROL MODE)




Notes on following page.

May 11, 1988 199


PLS155




"OR" $ARRAY - (Q_n = J-K Type)$




"OR" ARRAY - (S or B), (P), (R)







"OE" ARRAY - (E)




NOTES:

- 1. This is the initial unprogrammed state of all link pairs. It is normally associated with all unused (inactive) AND gates.
- 2. Any gate (T, F_C, L, P, R, D)_n will be unconditionally inhibited if both of the I, B, or Q links are left intact.
- 3. To prevent oscillations, this state is not allowed for C link pairs coupled to active gates T_n, F_C.
- E_n = O and E_n = are logically equivalent states, since both cause F_n outputs to be unconditionally enabled.
 These states are not allowed for control gates (L, P, R, D)_n due to their lack of "OR" array links.

PLS155

FPLS PROGRAM TABLE



Signetics

Document No.	853-0318			
ECN No.	93255			
Date of Issue	May 11, 1988			
Status	Product Specification			
Programmable Logic Devices				

DESCRIPTION

The PLS157 is a 3–State output, registered logic element combining AND/OR gate arrays with clocked J–K flip–flops. These J–K flip–flops are dynamically convertible to D–type via a "fold–back" inverting buffer and control gate F_C. It features 6 registered I/O outputs (F) in conjunction with 6 bidirectional I/O lines (B). These yield variable I/O gate and register configurations via control gates (D, L) ranging from 16 inputs to 12 outputs.

The AND/OR arrays consist of 32 logic AND gates, 13 control AND gates, and 21 OR gates with fusible link connections for programming I/O polarity and direction. All AND gates are linked to 4 inputs (I), bidirectional I/O lines (B), internal flip—flop outputs (Q), and Complement Array output (C). The Complement Array consists of a NOR gate optionally linked to all AND gates for generating and propagating complementary AND terms.


PLS157

Field-Programmable Logic Sequencer $(16 \times 45 \times 12)$

FEATURES

- f_{MAX} = 14MHz
- 18.2MHz clock rate
- Field-Programmable (Ni-Cr link)
- 4 dedicated inputs
- 13 control gates
- 32 AND gates
- 21 OR gates
- 45 product terms:
 - 32 logic terms
- 13 control terms
- 6 bidirectional I/O lines
- 6 bidirectional registers
- J-K, T, or D-type flip-flops
- 3-State outputs
- Asynchronous Preset/Reset
- Complement Array
- · Active-High or -Low outputs
- Programmable OE control
- Positive edge-triggered clock
- Input loading: -100µA (max.)
- Power dissipation: 750mW (typ.)
- TTL compatible

PIN CONFIGURATIONS



APPLICATIONS

- Random sequential logic
- Synchronous up/down counters
- Shift registers
- Bidirectional data buffers
- Timing function generators
- System controllers/synchronizers
- Priority encoder/registers


Philips Components





PLS157

FUNCTIONAL DIAGRAM



On–chip T/C buffers couple either True (I, B, Q) or Complement (I, B, \overline{Q} , \overline{C}) input polarities to all AND gates, whose outputs can be optionally linked to all OR gates. Any of the 32 AND gates drives bidirectional I/O lines (B), whose output polarity is individually programmable through a set of Ex–OR gates for implementing AND–OR or AND–NOR logic functions. Similarly, any of the 32 AND gates can drive the J–K inputs of all flip–flops. The Asynchronous Preset and Reset lines (P, R), are driven from the ANSD array for 4 of the 8 registers. The Preset and Reset lines (P, R) controlling the lower four registers are driven from the OR matrix.

All flip—flops are positive edge—triggered and can be used as input, output or I/O (for interfacing with a bidirectional data bus) in conjunction with load control gates (L), steering inputs (I), (B), (Q) and programmable output select lines (E).


The PLS157 is field programmable, enabling the user to quickly generate custom patterns using standard programming equipment.

Order codes are listed in the Ordering Informa-

Field-Programmable Logic Sequencer (16 × 45 × 12)

PLS157

FPLS LOGIC DIAGRAM




PLS157

VIRGIN STATE

The factory shipped virgin device contains all fusible links intact, such that:

- 1. OE is always enabled.
- 2. Preset and Reset are always disabled.
- 3. All transition terms are disabled.
- All flip—flops are in D—mode unless otherwise programmed to J—K only or J–K or D (controlled).
- 5. All B pins are inputs and all F pins are outputs unless otherwise programmed.

LOGIC FUNCTION



NOTE:

Similar logic functions are applicable for D and T mode flip-flops.

FLIP-FLOP TRUTH TABLE

ŌĒ	L	СК	Р	R	J	K	Q	F
Н								Hi–Z
L	Х	Х	Н	L	Χ	Χ	Н	L
L	X	X	L	Н	Χ	Χ	L	Н
L	L	\uparrow	L	L	L	L	Q	Q
L	L	\uparrow	L	L	L	Н	L	Н
L	L	\uparrow	L	L	Н	L	Н	L
L	L	\uparrow	L	L	Н	Н	Q	Q
Н	Н	\uparrow	L	L	L	Н	L	H*
Н	Н	\uparrow	L	L	Н	L	Н	L*
+10V	Х	\uparrow	Χ	Χ	L	Н	L	H* *
	X	\uparrow	Χ	Χ	Н	L	Н	L* *

NOTES:

1. Positive Logic:

$$\begin{split} J-K &= T_0 + T_1 + T_2 \dots \qquad \qquad T_{31} \\ T_n &= \overline{C} \cdot \begin{pmatrix} I_0 \cdot I_1 \cdot I_2 \dots \end{pmatrix} \cdot \begin{pmatrix} Q_0 \cdot Q_1 \dots \end{pmatrix} \cdot \begin{pmatrix} B_0 \\ \vdots \end{pmatrix} \\ & \cdot \begin{pmatrix} B_1 \cdot \dots \end{pmatrix} \end{split}$$

- 2. ↑ denotes transition from Low to High level.
- 3. X = Don't care
 - * = Forced at F_n pin for loading the J–K flip– flop in the Input mode. The load control term, L_n must be enabled (HIGH) and the p– terms that are connected to the associated flip–flop must be forced LOW (disabled) during Preload.
- At P = R = H, Q = H. The final state of Q depends on which is released first.
- * * = Forced at F_n pin to load J–K flip–flop independent of program code (Diagnostic mode), 3–State B outputs.

ORDERING INFORMATION

DESCRIPTION	ORDER CODE
20-Pin Plastic DIP (300mil-wide)	PLS157N
20-Pin Plastic Leaded Chip Carrier	PLS157A

ABSOLUTE MAXIMUM RATINGS1

		RATINGS		
SYMBOL	PARAMETER	Min	Max	UNIT
Vcc	Supply voltage		+7	V_{DC}
V _{IN}	Input voltage		+5.5	V _{DC}
V _{OUT}	Output voltage		+5.5	V _{DC}
I _{IN}	Input currents	-30	+30	mA
I _{OUT}	Output currents		+100	mA
TA	Operating temperature range	0	+75	°C
T _{STG}	Storage temperature range	-65	+150	°C

NOTES:

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

THERMAL RATINGS

TEMPERATURE					
Maximum junction	150°C				
Maximum ambient	75°C				
Allowable thermal rise ambient to junction	75°C				

PLS157

DC ELECTRICAL CHARACTERISTICS 0°C \leq T_A \leq +75°C, 4.75V \leq V_{CC} \leq 5.25V

				LIMITS		1
SYMBOL PARAMETER		TEST CONDITION	Min	Typ1	Max	UNIT
Input volt	age ²	-				
V _{IH}	High	V _{CC} = Max	2.0			V
VIL	Low	V _{CC} = Min			0.8	V
V _{IC}	Clamp	$V_{CC} = Min, I_{IN} = -12mA$		-0.8	-1.2	V
Output vo	oltage ²					
		V _{CC} = Min				
V_{OH}	High	$I_{OH} = -2mA$	2.4			V
V_{OL}	Low	I _{OL} = 10mA		0.35	0.5	V
Input cur	rent					
I _{IH}	High	V _{IN} = 5.5V		<1	80	μА
I_{IL}	Low	V _{IN} = 0.45V		-10	-100	μА
Output co	ırrent					
		V _{CC} = Max				
I _{O(OFF)}	Hi-Z state ^{5, 6}	V _{OUT} = 5.5V		1	80	μА
		V _{OUT} = 0.45V		-1	-140	μА
Ios	Short circuit ^{3, 7}	V _{OUT} = 0V	-15		-70	mA
I _{CC}	V _{CC} supply current ⁴	V _{CC} = Max		150	190	mA
Capacita	nce	*				
		V _{CC} = 5.0V				
CIN	Input	V _{IN} = 2.0V		8		pF
C _{OUT}	Output	V _{OUT} = 2.0V		15		pF

NOTES:

- 1. All typical values are at $V_{CC} = 5V$, $T_A = +25^{\circ}C$.
- 2. All voltage values are with respect to network ground terminal.
- 3. Test one at a time.
- 4. I_{CC} is measured with the OE input grounded, all other inputs at 4.5V and the outputs open.
- Leakage values are a combination of input and output leakage.
 Measured with V_{IH} applied to OE.
- 7. Duration of short circuit should not exceed 1 second.

PLS157

AC ELECTRICAL CHARACTERISTICS 0°C \leq T_A \leq +75°C, 4.75V \leq V_{CC} \leq 5.25V, R₁ =470 Ω , R₂ = 1k Ω

						LIMITS		
SYMBOL	PARAMETER	FROM	то	TEST CONDITION	Min	Typ1	Max	UNIT
Pulse wid	th							
t _{CKH}	Clock ² High	CK+	CK-	C _L = 30pF	25	20		ns
t _{CKL}	Clock Low	CK-	CK+	C _L = 30pF	30	20		ns
t _{CKP}	Period	CK+	CK+	C _L = 30pF	70	50		ns
t _{PRH}	Preset/Reset pulse	(I,B) -	(I,B) +	C _L = 30pF	40	30		ns
Setup tim	e ⁵							
t _{IS1}	Input	(I,B) ±	CK+	C _L = 30pF	40	30		ns
t _{IS2}	Input (through F _n)	F±	CK+	C _L = 30pF	20	10		ns
t _{IS3}	Input (through Complement Array) ⁴	(I,B) ±	CK+	C _L = 30pF	65	40		ns
Hold time								
t _{IH1}	Input	(I,B) ±	CK+	C _L = 30pF	0	-10		ns
t _{IH2}	Input	F±	CK +	C _L = 30pF	15	10		ns
Propagati	on delays		•			-	-	
t _{CKO}	Clock	CK+	F±	C _L = 30pF		25	30	ns
t _{OE1}	Output enable	OE -	F-	C _L = 30pF		20	30	ns
t _{OD1}	Output disable ³	ŌĒ +	F+	C _L = 5pF		20	30	ns
t _{PD}	Output	(I,B) ±	В±	C _L = 30pF		40	50	ns
t _{OE2}	Output enable	(I,B) +	В±	C _L = 30pF		35	55	ns
t _{OD2}	Output disable ³	(I,B) -	B +	C _L = 5pF		30	35	ns
t _{PRO}	Preset/Reset	(I,B) +	F±	C _L = 30pF		50	55	ns


NOTES:

- All typical values are at V_{CC} = 5V, T_A = +25°C.
 To prevent spurious clocking, clock rise time (10% 90%) ≤ 10ns.
 Measured at V_T = V_{OL} + 0.5V.
 When using the Complement Array t_{CKP} = 95ns (min).
 Limits are guaranteed with 12 product terms maximum connected to each sum term line.
- 6. For test circuits, waveforms and timing diagrams see the following pages.

VOLTAGE WAVEFORMS


+3.0V +3.0V MEASUREMENTS: All circuit delays are measured at the +1.5V level of inputs and outputs, unless otherwise specified. Input Pulses

TEST LOAD CIRCUIT



PLS157

TIMING DIAGRAMS




TIMING DEFINITIONS

SYMBOL	PARAMETER
t _{CKH}	Width of input clock pulse.
t _{CKL}	Interval between clock pulses.
t _{CKP}	Clock period.
t _{PRH}	Width of preset input pulse.
t _{IS1}	Required delay between beginning of valid input and positive transition of clock.
t _{IS2}	Required delay between beginning of valid input forced at flip—flop output pins, and positive transition of clock.
t _{IH1}	Required delay between positive transition of clock and end of valid input data.
t _{IH2}	Required delay between positive transition of clock and end of valid input data forced at flip—flop output pins.
t _{CKO}	Delay between positive transition of clock and when outputs become valid (with OE Low).
t _{OE1}	Delay between beginning of Output Enable Low and when outputs become valid.
t _{OD1} .	Delay between beginning of Output Enable High and when outputs are in the OFF–State.
t _{PD}	Propagation delay between combinational inputs and outputs.
t _{OE2}	Delay between predefined Output Enable High, and when combinational outputs become valid.
t _{OD2}	Delay between predefined Output Enable Low and when combinational outputs are in the OFF–State.
t _{PRO}	Delay between positive transition of predefined Preset/Reset input, and when flip—flop outputs become valid.


May 11, 1988 208

PLS157

TIMING DIAGRAMS (Continued)



 The leading edge of preset/reset must occur only when the input clock is "low", and must remain "high" as long as required to override clock. The falling edge of preset/reset can never go "low" when the input clock is "high".
 Asynchronous Preset/Reset



May 11, 1988 209

PLS157


LOGIC PROGRAMMING

PLS157 logic designs can be generated using Signetics AMAZE PLD design software or one of several other commercially available, JEDEC standard PLD design software packages. Boolean and/or state equation entry is accepted.


PLS157 logic designs can also be generated using the program table entry format detailed on the following pages. This program table entry format is supported by the Signetics AMAZE PLD design software (PTP module). AMAZE is available free of charge to qualified

To implement the desired logic functions, the state of each logic variable from logic equations (I, B, O, P, etc.) is assigned a symbol. The symbols for TRUE, COMPLEMENT, INACTIVE, PRESET, etc., are defined below.


"AND" ARRAY - (I), (B), (Qp)



"COMPLEMENT" ARRAY - (C)



"OR" ARRAY - (F-F CONTROL MODE)




Notes on following page.


May 11, 1988 210

PLS157







"OR" ARRAY - (Qn = J-K Type)




"OR" ARRAY - (S or B), (P), (R)







"OE" ARRAY - (E)




NOTES:

- This is the initial unprogrammed state of all link pairs. It is normally associated with all unused (inactive) AND gates.
 Any gate (T, F_C, L, P, R, D)_n will be unconditionally inhibited if both of the I, B, or Q links are left intact.
- 3. To prevent oscillations, this state is not allowed for C link pairs coupled to active gates T_n, F_C.
- E_n = O and E_n = are logically equivalent states, since both cause F_n outputs to be unconditionally enabled.
 These states are not allowed for control gates (L, P, R, D)_n due to their lack of "OR" array links.

PLS157

FPLS PROGRAM TABLE



TB013509

May 11, 1988 212

Signetics

Document No.	853–1159				
ECN No.	93255				
Date of Issue	May 11, 1988				
Status	Product Specification				
Programmable Logic Devices					

DESCRIPTION

The PLS159A is a 3-State output, registered logic element combining AND/OR gate arrays with clocked J-K flip-flops. These J-K flip-flops are dynamically convertible to D-type via a "fold-back" inverting buffer and control gate F_C. It features 8 registered I/O outputs (F) in conjunction with 4 bidirectional I/O lines (B). These yield variable I/O gate and register configurations via control gates (D, L) ranging from 16 inputs to 12 outputs.

The AND/OR arrays consist of 32 logic AND gates, 13 control AND gates, and 21 OR gates with fusible link connections for programming I/O polarity and direction. All AND gates are linked to 4 inputs (I), bidirectional I/O lines (B), internal flip—flop outputs (Q), and Complement Array output (C). The Complement Array consists of a NOR gate optionally linked to all AND gates for generating and propagating complementary AND terms.


PLS159A

Field-Programmable Logic Sequencer $(16 \times 45 \times 12)$

FEATURES

- High-speed version of PLS159
- f_{MAX} = 18MHz
- 25MHz clock rate
- Field-Programmable (Ni-Cr link)
- 4 dedicated inputs
- 13 control gates
- 32 AND gates
- 21 OR gates
- 45 product terms:
- 32 logic terms
- 13 control terms
- 4 bidirectional I/O lines
- 8 bidirectional registers
- J-K, T, or D-type flip-flops
- Power—on reset feature on all flip—flops (F_n = 1)
- Asynchronous Preset/Reset
- Complement Array
- Active-High or -Low outputs
- Programmable OE control
- Positive edge-triggered clock
- Input loading: −100µA (max.)
- Power dissipation: 750mW (typ.)
- TTL compatible
- 3-State outputs

PIN CONFIGURATIONS



APPLICATIONS

- Random sequential logic
- Synchronous up/down counters
- Shift registers
- · Bidirectional data buffers
- Timing function generators
- System controllers/synchronizers
- · Priority encoder/registers


Philips Components





PLS159A

FUNCTIONAL DIAGRAM



On–chip T/C buffers couple either True (I, B, Q) or Complement (I, B, Q, \overline{C}) input polarities to all AND gates, whose outputs can be optionally linked to all OR gates. Any of the 32 AND gates can drive bidirectional I/O lines (B), whose output polarity is individually programmable through a set of Ex–OR gates for implementing AND–OR or AND–NOR logic functions. Similarly, any of the 32 AND gates can drive the J–K inputs of all flip–flops. There are 4 AND gates for the Asynchronous Preset/Reset functions.

All flip—flops are positive edge—triggered and can be used as input, output or I/O (for interfacing with a bidirectional data bus) in conjunction with load control gates (L), steering inputs (I), (B), (Q) and programmable output select lines (E).

The PLS159A is field-programmable, enabling the user to quickly generate custom patterns using standard programming equipment.

VIRGIN STATE

The factory shipped virgin device contains all fusible links intact, such that:

- 1. OE is always enabled.
- 2. Preset and Reset are always disabled.
- 3. All transition terms are disabled.
- All flip—flops are in D—mode unless otherwise programmed to J–K only or J–K or D (controlled).
- All B pins are inputs and all F pins are outputs unless otherwise programmed.


FLIP-FLOP TRUTH TABLE

OE	L	CK	Р	R	J	K	Q	F
Н								Hi–Z
L	Х	Χ	L	Χ	Χ	Χ	L	Н
L	X	X	H	L	X	X	H	L H
-	-							
L	L	1	L	L	L	L	Q	ಠ
L	L	\uparrow	L	L	L	Н	L	Н
L	L	\uparrow	L	L	Н	L	Н	L
L	L	<u></u>	L	L	Н	Н	ℚ	Q
Н	Н	\uparrow	L	L	L	Н	L	H*
Н	Н	1	L	L	Н	L	Н	L*
+10V	Х	\uparrow	Χ	Х	L	Н	L	H* *
	Х	1	Χ	Χ	Н	L	Н	L* *

NOTES:

- Positive Logic:
 - $\begin{array}{lll} J-K=T_0+T_1+T_2 & \dots & T_{31} \\ T_n=\overline{C} \cdot (I_0 \cdot I_1 \cdot I_2 \dots) \cdot (Q_0 \cdot Q_1 \dots) \cdot (B_0 \\ \cdot B_1 \cdot \dots) \end{array}$
- 2. ↑ denotes transition from Low to High level.
- 3. X = Don't care
- 4. * = Forced at F_n pin for loading the J–K flipflop in the Input mode. The load control term, L_n must be enabled (HIGH) and the p– terms that are connected to the associated flip–flop must be forced LOW (disabled) during Preload.
- At P = R = H, Q = H. The final state of Q depends on which is released first.
- * * = Forced at F_n pin to load J–K flip–flop independent of program code (Diagnostic mode), 3–State B outputs.

LOGIC FUNCTION



NOTE:


Similar logic functions are applicable for D and T mode flip—flops.

CAUTION: PLS159A PROGRAMMING ALGORITHM

The programming voltage required to program the PLS159A is higher (17.5V) than that required to program the PLS159 (14.5V). Consequently, the PLS159 programming algorithm will not program the PLS159A. Please exercise caution when accessing programmer device codes to insure that the correct algorithm is

PLS159A

FPLS LOGIC DIAGRAM



PLS159A

ORDERING INFORMATION

DESCRIPTION	ORDER CODE
20-Pin Plastic DIP (300mil-wide)	PLS159AN
20-Pin Plastic Leaded Chip Carrier	PLS159AA

ABSOLUTE MAXIMUM RATINGS¹

		RATI		
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage		+7	V _{DC}
V _{IN}	Input voltage		+5.5	V _{DC}
V _{OUT}	Output voltage		+5.5	V _{DC}
I _{IN}	Input currents	-30	+30	mA
I _{OUT}	Output currents		+100	mA
TA	Operating temperature range	0	+75	°C
T _{STG}	Storage temperature range	-65	+150	°C

NOTES:

THERMAL RATINGS

TEMPERATURE							
Maximum junction	150°C						
Maximum ambient	75°C						
Allowable thermal rise ambient to junction	75°C						

DC ELECTRICAL CHARACTERISTICS $0^{\circ}C \le T_A \le +75^{\circ}C$, $4.75V \le V_{CC} \le 5.25V$

				LIMITS			
SYMBOL	PARAMETER	RAMETER TEST CONDITION		Typ ¹	Max	UNIT	
Input volt	age ²						
V _H	High	V _{CC} = Max	2.0		7	V	
VIL	Low	V _{CC} = Min			0.8	V	
V _{IC}	Clamp	V _{CC} = Min, I _{IN} = -12mA		-0.8	-1.2	V	
Output vo	ltage ²			-			
V _{OH}	High	V _{CC} = Min, I _{OH} = -2mA	2.4			V	
V_{OL}	Low	I _{OL} = 10mA		0.35	0.5	V	
Input curi	ent						
I _{IH}	High	V _{CC} = Max, V _{IN} = 5.5V		<1	80	μА	
I _{IL}	Low	V _{IN} = 0.45V		-10	-100	μА	
Output cu	rrent			1	A		
I _{O(OFF)}	Hi-Z state ^{4, 7}	V _{CC} = Max, V _{OUT} = 5.5V		1	80	μΑ	
		V _{OUT} = 0.45V		-1	-140	μΑ	
los	Short circuit ^{3, 5}	V _{OUT} = 0V	-15		-70	mA	
Icc	V _{CC} supply current ⁶	V _{CC} = Max		150	190	mA	
Capacitar	ce						
C _{IN}	Input	V _{CC} = 5.0V, V _{IN} = 2.0V		8		pF	
Cout	Output	V _{OUT} = 2.0V		15		pF	

NOTES:

- 1. All typical values are at $V_{CC} = 5V$, $T_A = +25^{\circ}C$.
- 2. All voltage values are with respect to network ground terminal.
- Test one at a time.
- 4. Measured with VIH applied to OE.
- 5. Duration of short circuit should not exceed 1 second.
- 6. I_{CC} is measured with the $\overline{\text{OE}}$ input grounded, all other inputs at 4.5V and the outputs open.
- 7. Leakage values are a combination of input and output leakage.

May 11, 1988 216

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

PLS159A

AC ELECTRICAL CHARACTERISTICS 0°C \leq T_A \leq +75°C, 4.75V \leq V_{CC} \leq 5.25V, R₁ =470 Ω , R₂ = 1k Ω

						LIMITS		T
SYMBOL	PARAMETER	FROM	то	TEST CONDITION	Min	Typ1	Max	רואט
Pulse wid	th					•		
t _{CKH}	Clock ² High	CK+	CK-	C _L = 30pF	20	15		ns
t _{CKL}	Clock Low	CK-	CK+	C _L = 30pF	20	15		ns
t _{CKP}	Period	CK+	CK+	C _L = 30pF	55	45		ns
t _{PRH}	Preset/Reset pulse	(I,B) -	(I,B) +	C _L = 30pF	35	30		ns
Setup time	e ⁵					•	•	-
t _{IS1}	Input	(I,B) ±	CK+	C _L = 30pF	35	30		ns
t _{IS2}	Input (through F _n)	F±	CK+	C _L = 30pF	15	10		ns
t _{IS3}	Input (through Complement Array) ⁴	(I,B) ±	CK+	C _L = 30pF	55	45		ns
Hold time	•		-			•		-
t _{IH1}	Input	(I,B) ±	CK+	C _L = 30pF	0	-5		ns
t _{IH2}	Input (through F _n)	F±	CK+	C _L = 30pF	15	10		ns
Propagati	on delay	-						
t _{CKO}	Clock	CK+	F±	C _L = 30pF		15	20	ns
t _{OE1}	Output enable	OE -	F-	C _L = 30pF		20	30	ns
t _{OD1}	Output disable ³	OE+	F+	C _L = 5pF		20	30	ns
t _{PD}	Output	(I,B) ±	В±	C _L = 30pF		25	35	ns
t _{OE2}	Output enable	(I,B) +	В±	C _L = 30pF		20	30	ns
t _{OD2}	Output disable ³	(I,B) -	B +	C _L = 5pF		20	30	ns
t _{PRO}	Preset/Reset	(I,B) +	F±	C _L = 30pF		35	45	ns
t _{PPR}	Power-on/preset	V _{CC} +	F-	C _L = 30pF		0	10	ns


NOTES:

- All typical values are at V_{CC} = 5V, T_A = +25°C
- 2. To prevent spurious clocking, clock rise time $(10\% 90\%) \le 10$ ns.
- Measured at V_T = V_{OL} + 0.5V.
- 4. When using the Complement Array t_{CKP} = 75ns (min).
 5. Limits are guaranteed with 12 product terms maximum connected to each sum term line.

VOLTAGE WAVEFORMS


+3.0V +3.0V MEASUREMENTS: All circuit delays are measured at the +1.5V level of inputs and outputs, unless otherwise specified. Input Pulses

TEST LOAD CIRCUIT



PLS159A

TIMING DIAGRAMS




TIMING DEFINITIONS

SYMBOL	PARAMETER
t _{CKH}	Width of input clock pulse.
t _{CKL}	Interval between clock pulses.
t _{CKP}	Clock period.
t _{PRH}	Width of preset input pulse.
t _{IS1}	Required delay between beginning of valid input and positive transition of clock.
t _{IS2}	Required delay between beginning of valid input forced at flip-flop output pins, and positive transition of clock.
t _{IH1}	Required delay between positive transition of clock and end of valid input data.
t _{IH2}	Required delay between positive transition of clock and end of valid input data forced at flip—flop output pins.
tcko	Delay between positive transition of clock and when outputs become valid (with OE Low).
t _{OE1}	Delay between beginning of Output Enable Low and when outputs become valid.
t _{OD1}	Delay between beginning of Output Enable High and when outputs are in the OFF–State.
tppR	Delay between V _{CC} (after power—on) and when flip—flop outputs become preset at "1" (internal Q outputs at "0").
t _{PD}	Propagation delay between combinational inputs and outputs.
t _{OE2}	Delay between predefined Output Enable High, and when combinational outputs become valid.
t _{OD2}	Delay between predefined Output Enable Low and when combinational outputs are in the OFF–State.
t _{PRO}	Delay between positive transition of predefined Preset/Reset input, and when flip—flop outputs become valid.

May 11, 1988 218

PLS159A



Flip-Flop Input Mode

(DIN)

PLS159A


LOGIC PROGRAMMING

PLS159Alogic designs can be generated using Signetics AMAZE PLD design software or one of several other commercially available, JEDEC standard PLD design software packages. Boolean and/or state equation entry is accepted.


PLS159A logic designs can also be generated using the program table entry format detailed on the following pages. This program table entry format is supported by the Signetics AMAZE PLD design software (PTP module). AMAZE is available free of charge to qualified lisers

To implement the desired logic functions, the state of each logic variable from logic equations (I, B, O, P, etc.) is assigned a symbol. The symbols for TRUE, COMPLEMENT, INACTIVE, PRESET, etc., are defined below.


"AND" ARRAY - (I), (B), (Qp)



"COMPLEMENT" ARRAY - (C)




"OR" ARRAY - (F-F CONTROL MODE)



Notes on following page.


"OR" $ARRAY - (Q_n = D-Type)$




CAUTION:


THE PLS159A Programming Algorithm is different from the PLS159.

PLS159A







"OR" ARRAY - (S or B)







"OE" ARRAY - (E)




NOTES:

- 1. This is the initial unprogrammed state of all link pairs. It is normally associated with all unused (inactive) AND gates.
- Any gate (T, F_C, L, P, R, D)_n will be unconditionally inhibited if both of the I, B, or Q links are left intact.
 To prevent oscillations, this state is not allowed for C link pairs coupled to active gates T_n, F_C.
- E_n = O and E_n = are logically equivalent states, since both cause F_n outputs to be unconditionally enabled.
 These states are not allowed for control gates (L, P, R, D)_n due to their lack of "OR" array links.

PLS159A

FPLS PROGRAM TABLE



TB01291S

Signetics

Document No.	853-0314				
ECN No.	97885				
Date of Issue	October 16, 1989				
Status Product Specification					
Programmable Logic Devices					

DESCRIPTION

The PLS167 and PLS167A are bipolar, Programmable Logic State machines of the Mealy type. The Field-Programmable Logic Sequencers (FPLS) contain logic AND/OR gate arrays with user programmable connections which control the inputs of on-chip State and Output Registers. These consist respectively of 8 $\rm Q_P$, and 4 $\rm Q_F$ edge-triggered, clocked S/R flip-flops, with an asynchronous Preset Option.

All flip—flops are unconditionally preset to "1" during power turn—on.

The AND array combines 14 external inputs, I_{0-13} , with 8 internal inputs, P_{0-7} , fed back from the State Register to form up to 48 transition terms (AND terms). In addition, P_0 and P_1 of the internal State Register are brought off—chip to allow extending the Output Register to 6 bits, if so desired.

All transition terms can include True, False, or Don't Care states of the controlling variables, and are merged in the OR array to issue next-state and next-output commands to their respective registers on the Low-to-High transition of the Clock pulse.

Both True and Complement transition terms can be generated by optional use of the internal variable (C) from the Complement Array. Also, if desired, the Preset input can be converted to output—enable function, as an additional user programmable option.

Order codes are listed in the Ordering Information Table.

PLS167/A

Field-Programmable Logic Sequencers $(14 \times 48 \times 6)$


FEATURES

- f_{MAX} = 13.9MHz PLS167 20MHz - PLS167A
- 20MHz clock rate PLS167
 25MHz clock rate PLS167A
- Field-Programmable (Ni-Cr link)
- 14 True/Complement buffered inputs
- 48 programmable AND gates
- 25 programmable OR gates
- 8-bit State Register
- 2-bit shared State/Output Register
- 4-bit Output Register
- Transition Complement Array
- Programmable Asynchronous Preset/Output Enable
- Positive edge-triggered clock
- Power–on preset to logic "1" of all registers
- Automatic logic "HOLD" state via S/R flip-flops
- On-chip Test Array
- Power: 600mW (typ.)
- TTL compatible
- 3-State outputs
- Single +5V supply
- 24-pin DIP 300mil-wide

APPLICATIONS

- Interface protocols
- Sequence detectors
- Peripheral controllers
- Timing generators
- Sequential circuits
- Security locking systems

PIN CONFIGURATIONS




Philips Components





PLS167/A

FUNCTIONAL DIAGRAM




PIN DESCRIPTION

PIN NO.	SYMBOL	NAME AND FUNCTION	POLARITY
1	СК	Clock: The Clock input to the State and Output Registers. A Low-to-High transition on this line is necessary to update the contents of both registers.	Active-High
2 – 7 17 – 23	I ₁ – I ₁₃	Logic Inputs: The 13 external inputs to the AND array used to program jump conditions between machine states, as determined by a given logic sequence.	Active-High/Low
8	I _O	Logic/Diagnostic Input: A 14th external logic input to the AND array, as above, when exercised with standard TTL levels. When I_0 is held at +10V, device outputs F_{0-3} and P_{0-1} reflect the contents of State Register bits P_{2-7} (see Diagnostic Output Mode diagram). The contents of flip–flops P_{0-1} and F_{0-3} remain unaltered.	Active-High/Low
9 – 11 13	F ₀₋₃	Logic/Diagnostic Outputs: Four device outputs which normally reflect the contents of Output Register bits Q_{0-3} , when enabled. When I_0 is held at +10V, $F_{0-3} = (P_{2-5})$.	Active-High
14 – 15	P ₀₋₁	Logic/Diagnostic Outputs: Two register bits with shared function as least Significant State Register bits, or most significant Output Register bits. When I_0 is held at +10V, $P_{0-1} = (P_{6-7})$.	Active-High
16	PR/OE	Preset or Output Enable Input: A user programmable function:	
		 Preset: Provides an Asynchronous Preset to logic "1" of all State and Output Register bits. Preset overrides Clock, and when held High, clocking is inhibited and P₀₋₇ and F₀₋₃ are High. Normal clocking resumes with the first full clock pulse following a High-to-Low clock transition, after Preset goes Low. 	Active-High (H)
		Output Enable: Provides an Output Enable function to all output buffers.	Active-Low (L)

PLS167/A

FPLS LOGIC DIAGRAM



PLS167/A

TRUTH TABLE 1, 2, 3, 4, 5, 6

	ОРТ	ION						
V _{cc}	PR	ŌE	l _o	CK	S	R	Q _{P/F}	F
	Н		*	Х	X	Х	Н	Н
	L		+10V	X	X	X	Qn	(Q _P) _n
	L		X	X	Χ	X	Qn	(Q _F) _n
		Н	*	Χ	X	Χ	Qn	Hi⊢Z
+5V		L	+10V	X	X	X	Qn	(Q _P) _n
		L	X	X	X	Χ	Qn	(Q _F) _n
		L	X	1	L	L	Q _n	(Q _F) _n
		L	X	\uparrow	L	Н	L	L
		L	X	\uparrow	H	L	н	н
		L	X	1	Н	Н	IND.	IND.
1	X	X	Х	Х	X	X	Н	

NOTES:

1. Positive Logic:

S/R = T₀ + T₁ + T₂ + . . . T₄₇

T_n = C(I₀ I₁ I₂ . . .) (P₀ P₁ . . . P₇)

Either Preset (Active–High) or Output Enable (Active–Low) are available, but not both. The desired function is a user-programmable option.

- T denotes transition from Low-to-High level.
- R = S = High is an illegal input condition.
- 5. * = H or L or +10V.
- 6. X = Don't Care (≤5.5V)

ORDERING INFORMATION


DESCRIPTION	ORDER CODE
24-Pin Plastic DIP (300mil-wide)	PLS167N, PLS167AN
28-Pin Plastic Leaded Chip Carrier	PLS167A, PLS167AA

ABSOLUTE MAXIMUM RATINGS¹

		RATI	NGS	
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage		+7	V _{DC}
V _{IN} .	Input voltage		+5.5	V _{DC}
V _{OUT}	Output voltage		+5.5	V _{DC}
I _{IN}	Input currents	-30	+30	mA
I _{OUT}	Output currents		+100	mA
T _A	Operating temperature range	0	+75	°C
T _{STG}	Storage temperature range	-65	+150	°C

1. Stresses above those listed may cause malfunction or permanent damage to the device. This is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

LOGIC FUNCTION



VIRGIN STATE

The factory shipped virgin device contains all fusible links intact, such that:

- 1. PR/OE option is set to PR. Thus, all outputs will be at "1", as preset by initial power-up procedure.
- 2. All transition terms are disabled (0).
- 3. All S/R flip-flop inputs are disabled (0).
- 4. The device can be clocked via a Test Array pre-programmed with a standard test pattern.

NOTE: The Test Array pattern MUST be deleted before incorporating a user program. This is accomplished automatically by any Signetics qualified programming equipment.

THERMAL BATINGS

THE HIMAE HATHING	
TEMPERATURE	
Maximum junction	150°C
Maximum ambient	75°C
Allowable thermal rise ambient to junction	75°C

PLS167/A

DC ELECTRICAL CHARACTERISTICS 0° C \leq T_A \leq +75 $^{\circ}$ C, 4.75V \leq V_{CC} \leq 5.25V

				LIMITS		
SYMBOL	PARAMETER	TEST CONDITION	Min	Typ1	Max	UNIT
Input vol	tage ²			•		
V _H	High	V _{CC} = Max	2.0			V
VIL	Low	V _{CC} = Min			0.8	V
V _{IC}	Clamp ³	$V_{CC} = Min, I_{IN} = -12mA$		-0.8	-1.2	V
Output v	oltage ²					
		V _{CC} = Min				
V_{OH}	High⁴	$I_{OH} = -2mA$	2.4			V
V_{OL}	Low ⁵	I _{OL} = 9.6mA		0.35	0.45	V
Input cur	rent			•		
I _{IH}	High	V _{IN} = 5.5V		<1	80	μΑ
I _{IL}	Low	V _{IN} = 0.45V		-10	-100	μА
IIL	Low (CK input)	V _{IN} = 0.45V		-50	-250	μА
Output c	urrent			-		
		V _{CC} = Max				
I _{O(OFF)}	Hi-Z state ^{5, 6}	V _{OUT} = 5.5V		1	40	μА
		V _{OUT} = 0.45V		-1	-40	μА
los	Short circuit ^{3, 7}	V _{OUT} = 0V	-15		-70	mA
Icc	V _{CC} supply current ⁸	V _{CC} = Max		120	180	mA
Capacita	nce ⁶					
		V _{CC} = 5.0V				
CIN	Input	V _{IN} = 2.0V		8		pF
C _{OUT}	Output	$V_{OUT} = 2.0V$		10		pF

NOTES:

- All typical values are at V_{CC} = 5V, T_A = +25°C.
- 2. All voltage values are with respect to network ground terminal.
- 3. Test one at a time.
- 4. Measured with V_{IL} applied to \overline{OE} and a logic high stored, or with V_{IH} applied to PR.
- 5. Measured with a programmed logic condition for which the output is at a low logic level, and V_{IL} applied to PR/OE Output sink current is
- supplied through a resistor to V_{CC}.

 6. Measured with V_{IH} applied to PR/OE.
- 7. Duration of short circuit should not exceed 1 second.

 8. I_{CC} is measured with the PR/OE input grounded, all other inputs at 4.5V and the outputs open.

PLS167/A


AC ELECTRICAL CHARACTERISTICS R₁ = 470Ω, R₂ = 1kΩ, C_L = 30pF, 0°C ≤ T_A ≤ +75°C, 4.75°CV ≤ V_{CC} ≤ 5.25V

						LIM	ITS			
SYMBOL	PARAMETER	FROM	то		PLS167		- 1	PLS167A		UNIT
				Min	Typ ¹	Max	Min	Typ ¹	Max	
Pulse wi	dth ³						_			
t _{CKH}	Clock ² High	CK+	CK-	25	15		20	15		ns
t _{CKL}	Clock Low	CK-	CK+	25	15		20	15		ns
t _{CKP1} B	Period (without Complement Array)	Output +/-	Input +/-	80	40		50	40		ns
t _{CKP2} B	Period (with Complement Array)	Output +/-	Input +/-	120	60		80	50		ns
t _{PRH}	Preset pulse	PR+	PR –	25	15		25	15		ns
Setup tin	ne ³									
t _{IS1} A	Input	Input ±	CK+	60			40			ns
t _{IS1} B	Input	Input ±	CK+	50			30	70.		ns
t _{IS1} C	Input	Input ±	CK+	42			N/A			ns
t _{IS2} A	Input (through Complement Array)	Input ±	CK+	90			70			ns
t _{IS2} B	Input (through Complement Array)	Input	CK+	80			60			ns
t _{IS2} C	Input (through Complement Array)	Input	CK+	72			N/A		٠.	ns
t _{VS}	Power-on preset	V _{CC} +	CK-	0	-10		0	-10		ns
t _{PRS}	Preset	PR –	CK-	0	-10		0	-10		ns
Hold time	е									
t _{IH}	Input	CK+	Input ±	5	-10		0	-5		ns
Propaga	tion delay									
t _{CKO}	Clock	CK+	Output ±		15	30		15	20	ns
toE	Output enable	OE -	Output –		20	30		20	30	ns
t _{OD}	Output disable	OE +	Output +		20	30		20	30	ns
t _{PR}	Preset	PR+	Output +		18	30		18	30	ns
t _{PPR}	Power–on preset	V _{CC} +	Output +		0	10		0	10	ns
Frequen	cy of operation ³									
f _{MAX} C	Without Complement Array					13.9			20.0	MH
$f_{MAX}C$	With Complement Array					9.8			12.5	MH:


NOTES:

- 1. All typical values are at $V_{CC}=5V$, $T_A=+25^{\circ}C$. 2. To prevent spurious clocking, clock rise time $(10\%-90\%)\leq 30$ ns. 3. See "Speed vs. OR Loading" diagrams.

TEST LOAD CIRCUIT




VOLTAGE WAVEFORMS



PLS167/A

TIMING DIAGRAMS




TIMING DEFINITIONS

SYMBOL	PARAMETER
	Width of input clock pulse.
t _{CKH}	Interval between clock pulses.
t _{CKL}	Clock period — when not using Complement array.
t _{IS1}	Required delay between beginning of valid input and positive transition of clock.
t _{CKP2}	Clock period — when using Complement array.
t _{IS2}	Required delay between beginning of valid input and positive transition of clock, when using optional Complement Array (two passes necessary through the AND array).
t _{VS}	Required delay between V _{CC} (after power–on) and negative transition of clock preceding first reliable clock pulse.
^t PRS	Required delay between negative transition of asynchronous Preset and negative transition of clock preceding first reliable clock pulse.
t _{IH}	Required delay between positive transition of clock and end of valid input data.
t _{CKO}	Delay between positive transition of clock and when outputs become valid (with PR/OE Low).
t _{OE}	Delay between beginning of Output Enable Low and when outputs become valid.
top	Delay between beginning of Output Enable High and when outputs are in the OFF–State.
t _{SRE}	Delay between input I ₀ transition to Diagnostic mode and when the outputs reflect the contents of the State Register.
t _{SRD}	Delay between input I ₀ transition to Logic mode and when the outputs reflect the contents of the Output Register.
t _{PR}	Delay between positive transition of Preset and when outputs become valid at "1".
t _{PPR}	Delay between V _{CC} (after power-on) and when outputs become preset at "1".
t _{PRH}	Width of preset input pulse.
f _{MAX}	Maximum clock frequency.

PLS167/A

TIMING DIAGRAMS (Continued)



SPEED VS. "OR" LOADING

The maximum frequency at which the PLS can be clocked while operating in *sequential mode* is given by:


$$(1/f_{MAX}) = t_{CY} = t_{IS} + t_{CKO}$$


This frequency depends on the number of transition terms T_n used. Having all 48 terms connected in the AND array does not appreciably impact performance; but the number of terms connected to each OR line affects $t_{\rm IS}$, due to capacitive loading. The effect of this loading can be seen in Figure 1, showing the variation of $t_{\rm IS1}$ with the number of terms connected per OR.

The PLS167 AC electrical characteristics contain three limits for the parameters t_{IS1} and t_{IS2} (refer to Figure 1). The first, t_{IS1A} is guaranteed for a device with 48 terms connected to any OR line. t_{IS1B} is guaranteed for a device with 32 terms connected to any OR line. And t_{IS1C} is guranteed for a device with 24 terms connected to any OR line.

The three other entries in the AC table, t_{IS2} A, B, and C are corresponding 48, 32, and 24 term limits when using the on–chip Complement Array.

The PLS167A AC electrical characteristics contain two limits for the parameters $t_{\rm IS1}$ and $t_{\rm IS2}$ (refer to Figure 2). The first, $t_{\rm IS1A}$ is guaranteed for a device with 24 terms connected to any OR line. $t_{\rm IS1B}$ is guaranteed for a device with 16 terms connected to any OR line.






The two other entries in the AC table, $t_{\rm IS2}$ A and B are corresponding 24 and 16 term limits when using the on-chip Complement Array.

The worst case of $t_{\rm IS}$ for a given application can be determined by identifying the OR line with the maximum number of T_n connections. This can be done by referring to the interconnect pattern in the PLS logic diagram, typically illustrated in Figure 3, or by counting the maximum number of "H" or "L" entries in one of the columns of the device Program Table.

This number plotted on the curve in Figure 1 or 2 will yield the worst case t_{IS} and, by implication, the maximum clocking frequency for reliable operation.

Note that for maximum speed all UNUSED transition terms should be disconnected from the OR array.



PLS167/A


LOGIC PROGRAMMING

PLS167/A logic designs can be generated using Signetics AMAZE PLD design software or one of several other commercially available, JEDEC standard PLD design software packages. Boolean and/or state equation entry is accepted.

PLS167/A logic designs can also be generated using the program table entry format detailed on the following pages. This program table entry format is supported by the Signetics AMAZE PLD design software (PTP module). AMAZE is available free of charge to qualified

To implement the desired logic functions, the state of each logic variable from logic equations (I, B, O, P, etc.) is assigned a symbol. The symbols for TRUE, COMPLEMENT, INACTIVE, PRESET, etc., are defined below.


PRESET/OF OPTION - (P/E)




PROGRAMMING:

The PS167/A has a power—up preset feature. This feature insures that the device will power—up in a known state with all register elements (State and Output Register) at logic High (H). When programming the device it is important to realize this is the initial state of the device. You *must* provide a next state jump if you do not wish to use all Highs (H) as the present state.


"AND" ARRAY - (I), (P)



"OR" ARRAY - (N), (F)



"COMPLEMENT" ARRAY - (C)



NOTES:

- 1. This is the initial unprogrammed state of all links.
- 2. Any gate Tn will be unconditionally inhibited if both the true and complement of any input (I, P) are left intact.
- To prevent simultaneous Set and Reset flip-flop commands, this state is not allowed for N and F link pairs coupled to active gates T_n (see flip-flop truth tables).
- 4. To prevent oscillations, this state is not allowed for C link pairs coupled to active gates T_n.

PLS167/A

PLS	S P	R)(ìR.	A۱	/I T	AE	3L	E															PROGRAM TAB	LE EN	TRIES												
	cus	TO	MEE	D NI A	BAE.																	T		AND				-					OR			_		
																							Ti	NACTIVE	0			i	IN.	ACT	TVE	T	0]				
	PUR											CE.	(XXX)	· · ·		_	-						0	ENERATE	A			1	SE	т			Н	1				
	SIGI									-				-		_		-	_	-			F	ROPAGATE	•	Cn		i	RE	SET	Г		L	1	N:	s, F	r	
	CUS	TO	AEF	SY	MB	DLIZ	ED F	PAR	T #	-		_							-	-			1	RANSPARENT !	-			i	NO) CH	IAN	GE	_	1				
	TOT	AL P	lU1	IBEI	N O	F PA	RTS	_		-	-	-											_	INACTIVE 0				Ļ.										_
	PRO	GR/	M.	TAB	LE :	<i>u</i> _		_											_	_			-	I, P H	_							_ OF	OIT	N -				_
	REV	_												_		-				_		1	_	Ĭ, P	_	im, Pa		1	F	RE	SET	Тн						
	DATI																						-	DON'T CARE -	_				7	Æ		L			P	E		
_		_			_	-								_		_						\perp	_	1				Ĺ	_	_	OP	TION	/D/E	=1	_	_	_	_
											AN	D															-	-	-	-	OP	OF		-)	-			-
Ţ						_	1	NPL	JT (I	IM)		_		-		Г	PF	RESI	EN	T ST	ATE	(Ps)		REMA	RKS		N	EXT	ST	ATE	(Ns			_	ou	TPU	T (F	r
E R M	Cn	1 3	1	1	1		Te:	Y = -	TE	TE	77	T =	T 2	17	T = -	3	7-	1=	Τ,	T -	2	T-	Tā				,-	6	F = 1	771	21	2	77	-1	31	2 [-,-,	-,
0		J		-	U	9			В	5			12	L'	U	Ľ	10	5	14		1	<u> </u>	-				Ľ	0	2	*	3		-	1	3	-	_	ľ
1 2							1					8	F	F	F	F	F		F	-	F		F				F		F	H			7	7	1	7	-	_
3				B				B				Ė				E				9	1											ī	\Rightarrow	\exists	\Rightarrow	\Rightarrow		
5		_		_	-		1			-			+		-	-	+	-	+	-	+		-				<u> </u>		-	\vdash	-	-	+	+	+	+	\dashv	-
6			$\overline{}$				7	_		_		-	-	F		F			F	-	-	F					F						1	7	7	7	=	F
8				-				-				9-				L				+														1		\exists		
9		_		-	_	-		_	-	-		1	-	-		H	-	-	\vdash	-	+-	-	\vdash				-	-	-	Н	\vdash	-	+	+	+	\dashv	-	H
11				1				1				B .								T	\downarrow											1	\dashv	1	\Rightarrow	\dashv		Ē
13	Н	_	_	1	-	\vdash		I.	-	\vdash		3	+	-	-	Ͱ	-	\vdash	+	1	+	+	-				-		-			8	_	+	+	\dashv	-	H
14				1_				_								F			F	1	\perp												7	7	1	7		F
16				-				-				-							+	-							\vdash					-	1	1		\exists		
17 18				-				-				-				F			F	-	-	1											\neg	4	7	\neg		F
19				-				E .				8				E				-	\pm												\exists	1				
20	-	_	_	÷	-	-				-		÷	-	-	-	\vdash	-	-	\vdash	÷	+	+	-	-			\vdash		-	\vdash	H	-	+	\dashv	+	-		H
22				-				-				1				F			F	II II												-	_	コ	\Rightarrow	\exists		
23			_	1				B				1								1	\pm						\vdash					10	-	1				
25 26				_									-	-		F	\vdash	H	H	-	\perp	1	H				F					- 0		-	-	\dashv	_	F
27								I —			1	-									\perp												\Rightarrow	\exists		\exists		
28 29	\vdash			-	-	\vdash		-		\vdash		-	+	-	-	Ͱ	+	\vdash	+	-	+	+	\vdash	-			H	-	-		\vdash		+	\dashv	-	\dashv	_	H
30				-							1	H H				F		F	F	+	-	-	F				F				F	-	\dashv	7		7		F
32				Ī				8												Ė													+	J				Ė
33			_	-	-	-	-	1		-			+	-	-	F	-	-	+	F	+	-	+				-	F	-		F	- 1		-	H	7		É
35				L				_												1	\perp											-	\exists	\exists		\exists		
36 37	\vdash	\vdash		_	-	-			\vdash	-		-	+	-	+	-	\vdash	+	+	-	+	+-	-					-	-		-	-		\dashv	+	\dashv	_	H
38			_	-			T	-				-				F			F	-	1												\exists			\exists		F
40				-				-			100					L			1	+													- 1	1				
41								l l		-						F	-	-	F	-			F				H				-		- 1	7				F
43			_	1							_									T	#											8	_					t
44	\vdash	_		8	_	-			\vdash	-			+	-	-	1	+	+	+	1	+-	+	-				-	-	-	-	-	8		\dashv	+	-	_	H
46												B B				F		F	F	1	-	-										- 11		4		\exists		F
PIN	\dashv	1	_	1	2	2	2	2	\vdash	-		r	+		\vdash	H	1		_	-	_		_					1		_	_	Ť	_	1	1	1	1	r
NO.		7		9			2	3	2	3	4	5	6	7	8																					1	0	1
VARIABLE																																						

- NOTES:

 1. The FPLS is shipped with all links initially intact. Thus, a background of "0" for all Terms, and an "H" for the P/E option, exits in the table, shown BLANK instead for clarity.

 2. Unused C_{n.} I_{m.} and P_s bits are normally programmed Don't Care (—).

 3. Unused Transition Terms can be left for future code modification or programmed as (—) for maximum speed.

 4. Letters in variable fields are used as identifiers by logic type programmers.

TB01622S


PLS167/A


TEST ARRAY

The FPLS may be subjected to AC and DC parametric tests prior to programming via an on-chip test array.

The array consists of test transition terms 48 and 49, factory programmed as shown below.

Testing is accomplished by clocking the FPLS and applying the proper input sequence to $\rm l_{0-13}$ as shown in the test circuit timing diagram.






FPLS Under Test

	OPTION (P/E)													
	OR													
	-	NEX	T ST	ATE	(Ns)			01	JTP	JT (I	Fr)			
7	6	5	4	3	2	1	0	3	2	1	0			
L	L	L	L	L	L	L	L							
Н	Н	Н	Н	Н	Н	н								

Test Array Program

Both terms 48 and 49 must be deleted during user programming to avoid interfering with the desired logic function. This is accomplished automatically by any of Signetics' qualified programming equipment.



Test Circuit Timing Diagram

, ·											Α	ND											
E R M	С	1	1	1	1	ļ	, 	NPU	T (in	n)				r			Pi	RESE	NT	STAT	re (F	s)	
		3	2	1	0	9	8	7	6	5	4	3	2	1	0	7	6	5	4	3	2	1	0
48	_	Н	Н	Н	Н	Н	Н	Н	Н	Н	н	Н	Н	Н	н	Н	Н	н	Н	Н	Н	Н	Н
49	•	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L

Test Array Deleted

TB01610S

Signetics

Document No.	853-0322
ECN No.	97853
Date of Issue	October 11, 1989
Status	Product Specification
Programmable	Logic Devices

DESCRIPTION

The PLS168 and tje PLS168A are bipolar, Programmable Logic State machines of the Mealy type. They contain logic AND/ OR gate arrays with user programmable connections which control the inputs of on–chip State and Output Registers These consist respectively of 10 Qp, and 4 QF edge—triggered, clocked S/R flipflops, with an Asynchronous Preset Option.

All flip—flops are unconditionally preset to "1" during power turn—on.

The AND array combines 12 external inputs, I_{0-11} , with 10 internal inputs, P_{0-9} , fed back from the State Register to form up to 48 transition terms (AND terms). In addition, P_0-P_3 of the internal State Register are brought off–chip to allow extending the Output Register to 8 bits, if so desired.

All transition terms can include True, False, or Don't Care states of the controlling variables, and are merged in the OR array to issue next–state and next–output commands to their respective registers on the Low–to–High transition of the Clock pulse.

Both True and Complement transition terms can be generated by optional use of the internal variable (C) from the Complement Array. Also, if desired, the Preset input can be converted to output—enable function, as an additional user programmable option.

Order codes are listed in the Ordering Information Table.

PLS168/A

Field-Programmable Logic Sequencers $(12 \times 48 \times 8)$


FEATURES

- f_{MAX} = 13.9MHz PLS168 20MHz - PLS168A
 - 20MHz clock rate PLS168
 25MHz clock rate PLS168A
- Field-Programmable (Ni-Cr link)
- 12 True/Complement buffered inputs
- 48 programmable AND gates
- 29 programmable OR gates
- 10-bit State Register
- 4-bit shared State/Output Register
- 4-bit Output Register
- Transition Complement Array
- Programmable Asynchronous Preset/Output Enable
- Positive edge-triggered clock
- Power-on preset to logic "1" of all registers
- Automatic logic "HOLD" state via S/R flip-flops
- On-chip Test Array
- Power: 600mW (typ.)
- TTL compatible
- 3-State outputs
- Single +5V supply
- 24-pin DIP 300mil-wide

APPLICATIONS

- Interface protocols
- Sequence detectors
- Peripheral controllers
- Timing generators
- Sequential circuits
- Security locking systems
- Counters
- Shift registers

PIN CONFIGURATIONS




Philips Components





PLS168/A

FUNCTIONAL DIAGRAM




PIN DESCRIPTION

PIN NO.	SYMBOL	NAME AND FUNCTION	POLARITY
1	CK	Clock: The Clock input to the State and Output Registers. A Low-to-High transition on this line is necessary to update the contents of both registers.	Active-High
2 - 6 18 - 23	I ₁ - I ₁₁	Logic Inputs: The 11 external inputs to the AND array used to program jump conditions between machine states, as determined by a given logic sequence.	Active-High/Low
7	I _O	Logic/Diagnostic Input: A 12th external logic input to the AND array, as above, when exercised with standard TTL levels. When I_0 is held at +10V, device outputs $F_2 = F_3$ and $P_0 = P_3$ reflect the contents of State Register bits $P_4 = 9$ (see Diagnostic Output Mode diagram). The contents of flip—flops P_{0-1} and F_{0-3} remain unaltered.	Active-High/Low
13 – 16	P ₀₋₃	Logic/Diagnostic Outputs: Four device outputs which normally reflect the contents of State Register bits P_{0-3} . When I_0 is held at +10V these pins reflect ($P_{6} - P_{9}$).	Active-High
10 – 11	F ₂ - F ₃	Logic/Diagnostic Outputs: Two register bits $(F_2 - F_3)$ which reflect Output register bits $(Q_2 - Q_3)$. When I_0 is held at +10V, these pins reflect $(P_4 - P_5)$.	Active-High
17	PR/OE	Preset or Output Enable Input: A user programmable function:	
		 Preset: Provides an Asynchronous Preset to logic "1" of all State and Output Register bits. Preset overrides Clock, and when held High, clocking is inhibited and P₀₋₉ and F₀₋₃ are High. Normal clocking resumes with the first full clock pulse following a High-to-Low clock transition, after Preset goes Low. 	Active-High (H)
		Output Enable: Provides an Output Enable function to all output buffers.	Active-Low (L)
8, 9	F ₀ - F ₁	Logic Output: Two device outputs which reflect Output Registers Q_0-Q_1 . When I_0 is haeld at +10V, $F_0-F_1=$ Logic "1".	

PLS168/A

FPLS LOGIC DIAGRAM



PLS168/A

TRUTH TABLE 1, 2, 3, 4, 5, 6

	ОРТ	ION						
V _{cc}	PR	ŌĒ	l _o	CK	S	R	Q _{P/F}	F
	Н		*	Х	X	X	Н	Н
	L		+10V	X	X	X	Qn	(Q _P) _n
	L		X	Х	X	X	Qn	(Q _F) _n
		Н	*	X	X	X	Qn	Hi–Z
+5V		L	+10V	X	X	X	Q _n	(Q _P) _n
		L	X	X	X	X	Qn	(Q _F) _n
		L	X	1	L	L	Qn	(Q _F) _n
		L	X	\uparrow	L	Н	L	L
	1	L	×	\uparrow	Н	L	Н	н
		L	X	1	Н	Н	IND.	IND.
1	X	X	X	X	X	X	Н	

NOTES:

1. Positive Logic:

 $S/R = T_0 + T_1 + T_2 + ... + T_{47}$ $T_n = C(I_0 I_1 I_2 ...) (P_0 P_1 ... P_g)$

- 2. Either Preset (Active-High) or Output Enable (Active-Low) are available, but not both. The desired function is a user-programmable option.
- 3. The denotes transition from Low-to-High level.
- 4. R = S = High is an illegal input condition.
- * = H or L or +10V.
- 6. X = Don't Care (≤5.5V)

ORDERING INFORMATION

DESCRIPTION	ORDER CODE
24-Pin Plastic DIP (300mil-wide)	PLS168N, PLS168AN
28-Pin Plastic Leaded Chip Carrier	PLS168A, PLS168AA


ABSOLUTE MAXIMUM RATINGS1

		RAT	NGS	
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage		+7	V _{DC}
V _{IN}	Input voltage		+5.5	V _{DC}
V _{OUT}	Output voltage		+5.5	V _{DC}
I _{IN}	Input currents	-30	+30	mA
l _{out}	Output currents		+100	mA
T _A	Operating temperature range	0	+75	°C
T _{STG}	Storage temperature range	-65	+150	°C

NOTES:

1. Stresses above those listed may cause malfunction or permanent damage to the device. This is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

LOGIC FUNCTION



VIRGIN STATE

The factory shipped virgin device contains all fusible links intact, such that:

- 1. PR/OE option is set to PR. Thus, all outputs will be at "1", as preset by initial power-up procedure.
- 2. All transition terms are disabled (0).
- 3. All S/R flip-flop inputs are disabled (0).
- 4. The device can be clocked via a Test Array pre-programmed with a standard test pattern.

NOTE: The Test Array pattern MUST be deleted before incorporating a user program. This is accomplished automatically by any Signetics qualified programming equipment.

THERMAL RATINGS

TEMPERATURE	
Maximum junction	150°C
Maximum ambient	75°C
Allowable thermal rise ambient to junction	75°C

PLS168/A

DC ELECTRICAL CHARACTERISTICS $0^{\circ}C \le T_{A} \le +75^{\circ}C$, $4.75V \le V_{CC} \le 5.25V$

				LIMITS		
SYMBOL	PARAMETER	TEST CONDITION	Min	Typ1	Max	UNIT
Input vol	tage ²					
V _{IH}	High	V _{CC} = Max	2.0			V
VIL	Low	V _{CC} = Min			0.8	V
V _{IC}	Clamp ³	$V_{CC} = Min, I_{IN} = -12mA$		-0.8	-1.2	V
Output v	oltage ²					
		V _{CC} = Min				
V_{OH}	High⁴	$I_{OH} = -2mA$	2.4			V
V_{OL}	Low ⁵	I _{OL} = 9.6mA		0.35	0.45	V
Input cur	rent		•		•	
I _{IH}	High	V _{IN} = 5.5V		<1	25	μА
I _{IL}	Low	V _{IN} = 0.45V		-10	-100	μА
I_{1L}	Low (CK input)	V _{IN} = 0.45V		-50	-250	μА
Output c	urrent					
		V _{CC} = Max				
I _{O(OFF)}	Hi-Z state ⁶	V _{OUT} = 5.5V		1	40	μА
		V _{OUT} = 0.45V		-1	-40	μА
Ios	Short circuit ^{3, 7}	V _{OUT} = 0V	-15		-70	mA
Icc	V _{CC} supply current ⁸	V _{CC} = Max		120	180	mA
Capacita	nce ⁶	-	•	•		
		V _{CC} = 5.0V				
CIN	Input	$V_{IN} = 2.0V$		8		pF
C _{OUT}	Output	$V_{OUT} = 2.0V$		10		pF

- 1. All typical values are at $V_{CC} = 5V$, $T_A = +25^{\circ}C$.
- 2. All voltage values are with respect to network ground terminal.
- 3. Test one at a time.
- Measured with V_{IL} applied to OE and a logic high stored, or with V_{IH} applied to PR.
 Measured with a programmed logic condition for which the output is at a low logic level, and V_{IL} applied to PR/OE Output sink current is supplied through a resistor to V_{CC}.
- 6. Measured with VIH applied to PR/OE
- 7. Duration of short circuit should not exceed 1 second.
- 8. I_{CC} is measured with the PR/OE input grounded, all other inputs at 4.5V and the outputs open.

PLS168/A

$\textbf{AC ELECTRICAL CHARACTERISTICS} \; R_1 = 470 \Omega, \; R_2 = 1 k \Omega, \; C_L = 30 p F, \; 0^{\circ} C \leq T_A \leq +75^{\circ} C, \; 4.75^{\circ} C V \leq V_{CC} \leq 5.25 V \leq 10 C M_{\odot} C$

						LIM	ITS			
SYMBOL	PARAMETER	FROM	то		PLS168			PLS168A		UNIT
				Min	Typ ¹	Max	Min	Typ ¹	Max	
Pulse wid	dth ³									
t _{CKH}	Clock ² High	CK+	CK-	25	15		20	15		ns
t _{CKL}	Clock Low	CK-	CK+	25	15		20	15		ns
t _{CKP1} B	Period (without Complement Array)	Input +/-	Output +/-	80	40		50	40		ns
t _{CKP2} B	Period (with Complement Array)	Input +/-	Output +/-	120	60		80	50		ns
t _{PRH}	Preset pulse	PR+	PR-	25	15		25	15		ns
Setup tim	ne ³									
t _{IS1} A	Input	Input ±	CK+	60			40			ns
t _{IS1} B	Input	Input ±	CK+	50			30			ns
t _{IS1} C	Input	Input ±	CK+	42			N/A			ns
t _{IS2} A	Input (through Complement Array)	Input ±	CK+	90			70			ns
t _{IS2} B	Input (through Complement Array)	Input	CK+	80			60			ns
t _{IS2} C	Input (through Complement Array)	Input	CK+	72			N/A			ns
t _{VS}	Power-on preset	V _{CC} +	CK-	0	-10		0	-10		ns
t _{PRS}	Preset	PR –	CK-	0	-10		0	-10		ns
Hold time	Ð									
t _{IH}	Input	CK+	Input ±	5	-10		5	-10		ns
Propagat	tion delay									
t _{CKO}	Clock	CK+	Output ±		15	30		15	20	ns
toE	Output enable	OE –	Output –		20	30		20	30	ns
t _{OD}	Output disable	OE +	Output +		20	30		20	30	ns
t _{PR}	Preset	PR+	Output +		18	30		18	30	ns
t _{PPR}	Power–on preset	V _{CC} +	Output +		0	10		0	10	ns
Frequenc	cy of operation ³									
f _{MAX} C	Without Complement Array					13.9			20.0	MHz
f _{MAX} C	With Complement Array					9.8			12.5	MHz


NOTES:

- 1. All typical values are at $V_{CC}=5V$, $T_A=+25^{\circ}C$. 2. To prevent spurious clocking, clock rise time $(10\%-90\%)\leq 30$ ns. 3. See "Speed vs. OR Loading" diagrams.

TEST LOAD CIRCUIT


VCC P₃ P₀ F₀ F₃ 111 PR/OF (INCLUDES SCOPE AND JIG CAPACITANCE) GND

VOLTAGE WAVEFORMS



PLS168/A

TIMING DIAGRAMS




	EFINITIONS
SYMBOL	PARAMETER
t _{CKH}	Width of input clock pulse.
t _{CKL}	Interval between clock pulses.
t _{CKP1}	Clock period — when not using Complement array.
t _{IS1}	Required delay between beginning of valid input and positive transition of clock.
t _{CKP2}	Clock period — when using Complement array.
t _{IS2}	Required delay between beginning of valid input and positive transition of clock, when using optional Complement Array (two passes necessary through the AND array).
t _{VS}	Required delay between V _{CC} (after power–on) and negative transition of clock preceding first reliable clock pulse.
t _{PRS}	Required delay between negative transition of asynchronous Preset and negative transition of clock preceding first reliable clock pulse.
t _{IH}	Required delay between positive transition of clock and end of valid input data.
t _{CKO}	Delay between positive transition of clock and when outputs become valid (with PR/OE Low).
toe	Delay between beginning of Output Enable Low and when outputs become valid.
t _{OD}	Delay between beginning of Output Enable High and when outputs are in the OFF—State.
t _{SRE}	Delay between input I ₀ transition to Diagnostic mode and when the outputs reflect the contents of the State Register.
t _{SRD}	Delay between input I ₀ transition to Logic mode and when the outputs reflect the contents of the Output Register.
t _{PR}	Delay between positive transition of Preset and when outputs become valid at "1".
t _{PPR}	Delay between V _{CC} (after power-on) and when outputs become preset at "1".
t _{PRH}	Width of preset input pulse.
f_{MAX}	Maximum clock frequency.

October 11, 1989

240

TIMING DIAGRAMS (Continued)



SPEED VS. "OR" LOADING

The maximum frequency at which the PLS can be clocked while operating in *sequential mode* is given by:

$$(1/f_{MAX}) = t_{CY} = t_{IS} + t_{CKO}$$

This frequency depends on the number of transition terms T_n used. Having all 48 terms connected in the AND array does not appreciably impact performance; but the number of terms connected to each OR line affects $t_{\rm IS}$, due to capacitive loading. The effect of this loading can be seen in Figure 1, showing the variation of $t_{\rm IS1}$ with the number of terms connected per OR.

The PLS168 AC electrical characteristics contain three limits for the parameters $t_{\rm IS1}$ and $t_{\rm IS2}$ (refer to Figure 1). The first, $t_{\rm IS1A}$ is guaranteed for a device with 48 terms connected to any OR line. $t_{\rm IS1B}$ is guaranteed for a device with 32 terms connected to any OR line. And $t_{\rm IS1C}$ is guranteed for a device with 24 terms connected to any OR line.

The three other entries in the AC table, t_{IS2}A, B, and C are corresponding 48, 32, and 24 term limits when using the on–chip Complement Array.

The PLS168A AC electrical characteristics contain two limits for the parameters $t_{\rm IS1}$ and $t_{\rm IS2}$ (refer to Figure 2). The first, $t_{\rm IS1A}$ is guaranteed for a device with 24 terms connected to any OR line. $t_{\rm IS1B}$ is guaranteed for a device with 16 terms connected to any OR line.




Figure 1. PLS168 t_{IS1} vs. Terms/OR Connected





Figure 2. PLS168A t_{IS1} vs. Terms/OR Connected

The two other entries in the AC table, $t_{\rm IS2}$ A and B are corresponding 24 and 16 term limits when using the on-chip Complement Array.

The worst case of $t_{\rm IS}$ for a given application can be determined by identifying the OR line with the maximum number of $T_{\rm n}$ connections. This can be done by referring to the interconnect pattern in the PLS logic diagram, typically illustrated in Figure 3, or by counting the maximum number of "H" or "L" entries in one of the columns of the device Program Table.

This number plotted on the curve in Figure 1 or 2 will yield the worst case t_{IS} and, by implication, the maximum clocking frequency for reliable operation.

Note that for maximum speed all UNUSED transition terms should be disconnected from the OR array.



PLS168/A


LOGIC PROGRAMMING

PLS168/A logic designs can be generated using Signetics AMAZE PLD design software or one of several other commercially available, JEDEC standard PLD design software packages. Boolean and/or state equation entry is accepted.

PLS168/A logic designs can also be generated using the program table entry format detailed on the following pages. This program table entry format is supported by the Signetics AMAZE PLD design software (PTP module). AMAZE is available free of charge to qualified

To implement the desired logic functions, the state of each logic variable from logic equations (I, B, O, P, etc.); a sassigned a symbol. The symbols for TRUE, COMPLEMENT, INACTIVE, PRESET, etc., are defined below.


PRESET/OE OPTION - (P/E)




PROGRAMMING:

The PS168/A has a power–up preset feature. This feature insures that the device will power–up in a known state with all register elements (State and Output Register) at logic High (H). When programming the device it is important to realize this is the initial state of the device. You *must* provide a next state jump if you do not wish to use all Highs (H) as the present state.


"AND" ARRAY - (I), (P)



"OR" ARRAY - (N), (F)



"COMPLEMENT" ARRAY - (C)



NOTES:

- 1. This is the initial unprogrammed state of all links.
- 2. Any gate T_n will be unconditionally inhibited if both the true and complement of any input (I or P) are left intact.
- To prevent simultaneous Set and Reset flip-flop commands, this state is not allowed for N and F link pairs coupled to active gates T_n (see flip-flop truth tables).
- 4. To prevent oscillations, this state is not allowed for C link pairs coupled to active gates T_n.

PLS168/A

FPLS PROGRAM TABLE

CUS PUR SIGN CUS TOTA PRO REV	CHA NETI TOA AL A GRA	ASE ICS IER	OR DE SY	DEF VICI MB	E # OLI F P	ZEC) PA				()										-			AND IMACTIVE O QRINERATE A PPOOPAGATE TRANSPRISE O IMACTIVE O I, P L DON'T CARE —		C _n				MAC SET RESE NO C	HAN	GE	OPT L	TION	н,	PE		
											AND	,													L					OPT	OR		E)					4
Ţ		_			NAME OF TAXABLE PARTY.			consten	and the last	1	Algorithm .				0)	00	505	MY	STA	YE	(Ps)	SECTION .		REMARKS	┝	NEX	T ST	ATE	(Ns)	-	OH	-	OL	JTPL	IT (F	r)	on the last	٦
E R M	C _n	1	1					T(Im										(F	ex)						ı		(P	Px)		_				П				
И	L	1	0	9	8	7	6	5	4	3	2	1	0	9	8	7	6	5	4	3	2	1	٥		9	8	7	6	5	4	3	2	7	٥	3	2	1	0
0					L	H				L				Н		4	4	L	L	Ŀ	+	1	L		L	╀	L	L	Н	÷	4	+	+	4	+	+	+	4
2	Н	H	\vdash	H	\vdash	H	\vdash	\vdash		H	\vdash	Н	Н	Н	Н	\dashv	\dashv	-		-	+	\vdash	\vdash		H	╁	Н	Н	H	÷	+	+	+	+	+	+	+	┥
3	H		\vdash	Н		ŀ	\vdash			H		Н	Н	Н		+	\dashv	\vdash		H	+	\vdash	\vdash		t	t		Н	\forall	+	+	+	+	+	†	†	†	7
4										H										H					L					‡	I	I	1	1		I	I	
5	L					-	L			-				Н	4	4	_			Ŀ	\perp	L	L		L	╀		Н	Н	-	4	+	4	4	+	+	+	4
7	Н	H	H	H	\vdash	H	\vdash	-	H	H	\vdash	\vdash	H	Н	\dashv	+	\dashv	-	H	H	╀	⊢	\vdash		Ͱ	+	-	Н	Н	Ť	+	+	+	+	+	+	+	4
-	H		H	-		1	1			۲			H	Н	\dashv	+	٦	-		-	+	1			t	+		Н	H	+	+	+	1	+	\dagger	+	\dagger	4
9					1	H				-										L	İ				İ					‡	1	Ì	I		İ	Ì	I	J
10						F				F				П		1				F					L	F			Ц	-	4	1	4	4	T	1	7	
11	H	-	-	-	-	i-	-	\vdash		ŀ	-	H	H	Н	\dashv	+	-	-		ŀ	+	+	+	-	+	+	-	H	H	÷	+	+	+	+	+	+	+	\dashv
13		-	1	-	-	۲				۲	+			H	\dashv	+	-	-		-	1		-		+	+	-			+	+	+	+	+	+	+	+	\forall
14						L				H										H	İ				L					7	1	1		1	Ì	I	Ì	
15					ı.	H				F				П		\Box	4			F	F	L	F		L	F			Д	-	4	4	4	4	4	4	4	_
16	H	H	-	H		i	-	-		i	\vdash	H	H	Н	Н	\dashv	-	_	H	i	╀	-	\vdash		₽	╀	\vdash	Н	Н	+	+	+	+	-	+	+	+	4
18	H	H	\vdash	\vdash		۰	-	\vdash		-	-	\vdash	Н	Н	Н	\dashv	\dashv	Н		H	+	╁	╁		╁	+		Н	Н	+	+	+	+	+	+	+	+	Н
19	H	Н				۲	\vdash			۲				Н		\forall		Т		H	t		\vdash		t	†		Н	H	†	7	+	7	7	\dagger	\dagger	+	٦
20						-				H										F					Г					⇉	I	I	I	I	I	I	I	
21	L	L	L	L		Ļ	L	H		ŀ	L	L		Н	-	4	4	L		i	╀	\vdash	L		H	╀	H	L	Н	4	4	4	+	4	+	+	+	4
22	H	\vdash	\vdash	H		-	\vdash	\vdash	\vdash	H	\vdash	\vdash	Н	Н	-	\dashv	\dashv	-		i	╁	+	\vdash		Ͱ	+	-	Н	Н	+	+	+	+	+	+	+	+	\dashv
24	Н		\vdash			!		\vdash		۲	\vdash	\vdash		Н		\forall	٦	\vdash		F	†	\vdash	\vdash		t	1			H	+	1	\dagger	1	1	\dagger	†	\dagger	٦
25						t				-										F										7	I	I	\Box	1	1	I	I	
26	L		_		-	i	_	1		ŀ	-			Н	Н	4	4	_		ŀ	+	┞	-		┞	╀		Н	H	i	4	+	4	4	+	4	+	4
27	Н	H	\vdash	H		H	┝	\vdash	-	H	\vdash	H	Н	Н	\vdash	\dashv	\dashv	H		ŀ	╁	⊢	⊢	-	┞	+	H	H	H	+	+	+	+	+	+	+	+	4
29	Н	\vdash	-	\vdash		۰	\vdash	-		H	-	H		Н	Н	\forall	\dashv	-		۲	+	+	\vdash	-	t	$^{+}$			H	+	+	+	+	+	+	+	$^{+}$	-
30			1			-				H										-	I				I					‡	1	1	I	1	I	I	1	
31	L		L			-		L		Ŀ				Ц		4				Ŀ	\perp	1			L	1	L	L	Ц	4	4	4	4	4	4	1	4	_
32	H	\vdash	⊢	H	⊢	i	\vdash	\vdash	\vdash	i	\vdash	H	Н	Н	Н	+	-	_		i	+	+	\vdash	-	₽	+	\vdash	H	Н	Ť	+	+	+	+	+	+	+	-
34						-				H				H		1				-	1	\perp			t	1				+	1	_		7	1	+	+	_
35						-				-										H	I				L	I			口	+	1	I	1	1	1	1	1	
36	H	H	-	H		H	-	-		Ļ	-	-	H	Н	\vdash	4	4	L		ŀ	+	+	1		1	+	-	-	H	÷	4	+	4	4	+	+	4	_
37	H	-	-	-		ŀ	-	-		-	-	-	H	Н	H	\dashv	\dashv	-		ŀ	+	+	+		t	+	\vdash		H	+	+	+	+	+	+	+	+	-
39										H										-	1				İ	İ				+	1	1	1	1	1	\pm	1	
40										- -	Г									-	F	Г	F		L	F			Д	7	I	1	1	I	I	I	I	
41	H	-	-	H		-	-	-		-	-	H	H	Н	\Box	4	_	L		i	+	-	1		H	+	-	-	Н	4	4	+	4	4	4	+	4	
42	\vdash	-	\vdash	H	H	-	\vdash	\vdash	\vdash	-	\vdash	H	H	Н	Н	\dashv	-	-		ŀ	+	+	+		╁	+	\vdash	\vdash	Н	+	+	+	+	+	+	+	+	-
44						-				H			H	Н		+				ŀ	+	1	\perp		T	1			H	+	+	+	+	1	+	+	+	_
45						-				- -										-	I	L	L		I	L	L			7	1	1	コ	口	1	1	1	
48	H	-	H	H		-	-	-		Ŀ	-	H	H	Н	Н	4	4	H		ŀ	+	+	+		1	+	-	-	Н	÷	4	+	+	-	+	+	+	_
	-	-	-	-	-	۲	-	-	-	-	-	-	-	٢				-	_		-	-	_		-		_		_	+	+	+	+	+	+	+	+	
PIN NO		8	9	0	1	2 2	3	2	3	Ŀ	5	6	7																		6	5	4	3	;	0	9	8
VARIA NAM	BLE €																																					


PLS168/A


TEST ARRAY

The FPLS may be subjected to AC and DC parametric tests prior to programming via an on-chip test array.

The array consists of test transition terms 48 and 49, factory programmed as shown below.

Testing is accomplished by clocking the FPLS and applying the proper input sequence to $l_{0.11}$ as shown in the test circuit timing diagram.






State Diagram

FPLS Under Test

	the same of							To palogarity		-							9/4									Г	Name of Street	-			0	PTIC	N (F	E)				н
											ANI	D																				0	R					
T E B	c,	-	1	1			INPL	T(In	١)					Γ			PRE	ESE	NT (P		TE (Ps)			REMARKS		NE)		TATE Px)	(Ns)			0	UTP	UT (Fr)	
М		1	0	9	8	7	6	5	4	3	2	1	0	9	1	I	7	6	5	4	3	2	1	0		9	8	7	6	5	4	3	2	1	0	3	2	1 0
48	A	H	H	H	H	P	H	H	Н	Н	H	Н	Н	H	H	11	1	H	H	Н	Н	Н	Н	Н		L	L	L	L	L	L	L	L	L	٢	L	L	LL
49	1.	L	L	L	L	L	L	L	L	L	L	L	L	L	L	1	. [L	L	L	L	L	L		۲	H	H	H	Н	H	н	H	H	H	H	H	H H

Test Array Program

Both terms 48 and 49 must be deleted during user programming to avoid interfering with the desired logic function. This is accomplished automatically by any of Signetics' qualified programming equipment.



Test Circuit Timing Diagram

											AND														L					OF	PTIO		E)	_	-	-	1	1
T E R																REMARKS		NEX	T ST	ATE	(Ns			H	0	UTP	UT (Fr)										
м	L	,	0	9	8	7	6	5	4	3	2	1	0	9	8	7	6	5	1	3	2	1	0		9	8	7	6	5	4	3	2	1	0	3	2	1	0
48	F	H	Н	Н	Н	Н	H	H	н	н	н	H	H	H	H	H	Н	Н	Н	Н	Н	Н	H		-	-	-	-	-	-	-	-	-	-	-	-	-	-
49	ŀ	L	L	L	L	L	L	L	L	7	L	L	L	L	L	L	L	L	L	L	L	L	L		-	-	-	-	-	-	-	-	-	-	-	-	-	-

Test Array Deleted

Signetics

Document No.	853-0862		
ECN No.	93255		
Date of Issue	May 11, 1988		
Status Product Specification			
Programmable Logic Devices			

DESCRIPTION

The PLS179 is a 3–State output, registered logic element combining AND/OR gate arrays with clocked J–K flip–flops. These J–K flip–flops are dynamically convertible to D–type via a "foldback" inverting buffer and control gate F_C. It features 8 registered I/O outputs (F) in conjunction with 4 bidirectional I/O lines (B). There are 8 dedicated inputs. These yield variable I/O gate and register configurations via control gates (D, L) ranging from 20 inputs to 12 outputs.

The AND/OR arrays consist of 32 logic AND gates, 13 control AND gates, and 21 OR gates with fusible link connections for programming I/O polarity and direction. All AND gates are linked to 8 inputs (I), bidirectional I/O lines (B), internal flip-flop outputs (Q), and Complement Array output (C). The Complement Array consists of a NOR gate optionally linked to all AND gates for generating and propagating complementary AND terms.

PLS179

Field-Programmable Logic Sequencer $(20 \times 45 \times 12)$


FEATURES

- f_{MAX} = 18.2MHz25MHz clock rate
- Field-Programmable (Ni-Cr link)
- 8 dedicated inputs
- 13 control gates
- 32 AND gates
- 21 OR gates
- 45 product terms:
- 32 logic terms
- 13 control terms
- 4 bidirectional I/O lines
- 8 bidirectional registers
- J/K, T, or D-type flip-flops
- Asynchronous Preset/Reset
- Complement Array
- · Active-High or -Low outputs
- Programmable OE control
- Positive edge-triggered clock
- Power-on reset on flip-flop (F_n = "1")
- Input loading: 100μA (max.)
- Power dissipation: 750mW (typ.)
- TTL compatible
- 3-State outputs

APPLICATIONS

- Random sequential logic
- Synchronous up/down counters
- Shift registers
- Bidirectional data buffers
- Timing function generators
- System controllers/synchronizers
- Priority encoder/registers

PIN CONFIGURATIONS




Philips Components





PLS179

FUNCTIONAL DIAGRAM



On–chip T/C buffers couple either True (I, B, Q) or Complement (I, B, Ω , \mathcal{O}) input polarities to all AND gates, whose outputs can be optionally linked to all OR gates. Any of the 32 AND gates can drive bidirectional I/O lines (B), whose output polarity is individually programmable through a set of Ex–OR gates for implementing AND–OR or AND–NOR logic functions. Similarly, any of the 32 AND gates can drive the

J-K inputs of all flip-flops. Four AND gates have been dedicated for the Asynchronous Preset/Reset functions.

All flip—flops are positive edge—triggered and can be used as input, output or I/O (for interfacing with a bidirectional data bus) in conjunction with load control gates (L), steering inputs (I),


(B), (Q) and programmable output select lines (E).

The PLS179 is field programmable, enabling the user to quickly generate custom patterns using standard programming equipment.

Order codes are listed in the Ordering Information Table.

PLS179

FPLS LOGIC DIAGRAM




PLS179

VIRGIN STATE

The factory shipped virgin device contains all fusible links intact, such that:

- 1. OE is always enabled.
- 2. Preset and Reset are always disabled.
- 3. All transition terms are disabled.
- All flip—flops are in D—mode unless otherwise programmed to J–K only or J–K or D (controlled).
- 5. All B pins are inputs and all F pins are outputs unless otherwise programmed.

LOGIC FUNCTION



NOTE:

Similar logic functions are applicable for D and T mode flip-flops.

FLIP-FLOP TRUTH TABLE

ŌE	L	СК	Р	R	J	K	Q	F
Н								H/Hi–Z
L	Х	Χ	Χ	Χ	Χ	Χ	L	Н
L	X	X	Н	L	X	X	Н	· L
L	X	X	L	Н	Χ	X	L	Н
L	L	\uparrow	L	L	L	L	Q	ā
L	L	\uparrow	L	L	L	Н	L	Н
L	L	\uparrow	L	L	Н	L	Н	L
L	L	\uparrow	L	L	Н	Н	ಠ	Q
Н	Н	\uparrow	L	L	L	Н	L	H*
Н.	Н	\uparrow	L	L	Н	L	Н	L*
+10V	X	\uparrow	Χ	Χ	L	Н	L	H* *
	Х	1	Χ	Χ	Н	L	Н	L* *

NOTES:

Positive Logic:

$$\begin{array}{lll} J-K=T_0+T_1+T_2 & \dots & T_{31} \\ T_n=\overline{C} \cdot \left(I_0 \cdot I_1 \cdot I_2 \, \dots \right) \cdot \left(Q_0 \cdot Q_1 \, \dots \right) \cdot \\ \left(B_0 \cdot B_1 \cdot \dots \right) \end{array}$$

- 2. The denotes transition from Low to High level.
- 3. X = Don't care
- * = Forced at F_n pin for loading the J-K flipflop in the Input mode. The load control term, L_n must be enabled (HIGH) and the p-terms that are connected to the associated flip-flop must be forced LOW (disabled) during Preload.
- At P = R = H, Q = H. The final state of Q depends on which is released first.
- * * = Forced at F_n pin to load J–K flip–flop independent of program code (Diagnostic mode), 3–State B outputs.

ORDERING INFORMATION

DESCRIPTION	ORDER CODE	
24-Pin Plastic DIP (300mil-wide)	PLS179N	
28-Pin Plastic Leaded Chip Carrier	PLS179A	

ABSOLUTE MAXIMUM RATINGS1

		RATINGS		
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage		+7	V _{DC}
V _{IN}	Input voltage		+5.5	V _{DC}
V _{OUT}	Output voltage		+5.5	V _{DC}
I _{IN}	Input currents	-30	+30	mA
l _{out}	Output currents		+100	mA
T _A	Operating temperature range	0	+75	°C
T _{STG}	Storage temperature range	-65	+150	°C

NOTES:

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

THERMAL RATINGS

THE THINK E THAT THE GO				
TEMPERATURE				
Maximum junction	150°C			
Maximum ambient	75°C			
Allowable thermal rise ambient to junction	75°C			

PLS179


DC ELECTRICAL CHARACTERISTICS $0^{\circ}C \le T_A \le +75^{\circ}C$, $4.75V \le V_{CC} \le 5.25V$

				LIMITS			
SYMBOL	PARAMETER	TEST CONDITION	Min	Typ1	Max	UNIT	
Input volta	age ²						
V _{IH}	High	V _{CC} = Max	2.0			V	
V _{IL}	Low	V _{CC} = Min			0.8	V	
V _{IC}	Clamp	V _{CC} = Min, I _{IN} = -12mA		-0.8	-1.2	V	
Output vo	Itage ²					A	
V _{OH}	High	V _{CC} = Min, I _{OH} = -2mA	2.4			V	
V_{OL}	Low ⁵	I _{OL} = 10mA		0.35	0.5	V	
Input curr	ent			•		A	
I _{IH}	High	V _{CC} = Max, V _{IN} = 5.5V		<1	40	μА	
I _{IL}	Low	V _{IN} = 0.45V		-10	-100	μА	
Output cu	rrent			•			
I _{O(OFF)}	Hi-Z state ^{4, 7}	V _{CC} = Max, V _{OUT} = 5.5V		1	80	μА	
		V _{OUT} = 0.45V			-140	μА	
Ios	Short circuit ^{3, 5}	V _{OUT} = 0V	-15		-70	mA	
Icc	V _{CC} supply current ⁶	V _{CC} = Max		150	210	mA	
Capacitan	ce		-		A		
C _{IN}	Input	V _{CC} = 5.0V, V _{IN} = 2.0V		8		pF	
C _{OUT}	Output	V _{OUT} = 2.0V		15		pF	

- 1. All typical values are at V_{CC} = 5V, T_A = +25°C.
- All voltage values are with respect to network ground terminal.
- Test one at a time.
- Measured with V_{IH} applied to OE.
- 5. Duration of short circuit should not exceed 1 second.
- 6. I_{CC} is measured with the OE input grounded, all other inputs at 4.5V and the outputs open.
- 7. Leakage values are a combination of input and output leakage.

VOLTAGE WAVEFORMS +3.0V -10% +3.0V MEASUREMENTS: All circuit delays are measured at the +1.5V level of inputs and outputs, unless otherwise specified. Input Pulses

TEST LOAD CIRCUIT



May 11, 1988 249

PLS179

$\textbf{AC ELECTRICAL CHARACTERISTICS} \ \ R_1 = 470\Omega, \ \ R_2 = 1 \text{k}\Omega, \ C_L = 30 \text{pF}, \ 0^{\circ}\text{C} \le T_A \le +75 ^{\circ}\text{C}, \ 4.75 ^{\circ}\text{CV} \le V_{CC} \le 5.25 \text{V}$

SYMBOL	PARAMETER	FROM	то	TEST	LIMITS			UNIT
				CONDITION	Min ⁵	Typ1	Max	
Pulse widt	th ³							
t _{CKH}	Clock ² High	CK+	CK-	C _L = 30pF	20	15		ns
t _{CKL}	Clock Low	CK-	CK+	C _L = 30pF	20	15		ns
t _{CKP}	Period	CK+	CK+	C _L = 30pF	55	45		ns
t _{PRH}	Preset/Reset pulse	(I, B) -	(I, B) +	C _L = 30pF	35	30		ns
Setup time	9							
t _{IS1}	Input	(I, B) ±	CK+	C _L = 30pF	35	30		ns
t _{IS2}	Input (through F _n)	F±	CK+	C _L = 30pF	15	10		ns
t _{IS3}	Input (through Complement Array)4	(I, B) ±	CK+	C _L = 30pF	55	45		ns
Hold time		•					-	
t _{IH1}	Input	(I, B) ±	CK+	C _L = 30pF	0	-5		ns
t _{IH2}	Input (through F _n)	F±	CK+	C _L = 30pF	15	10		ns
Propagation	on delay	•						
t _{CKO}	Clock	ck±	F±	C _L = 30pF		15	20	ns
t _{OE1}	Output enable	OE -	F-	C _L = 30pF		20	30	ns
t _{OD1}	Output disable ³	ŌĒ +	F+	C _L = 5pF		20	30	ns
t _{PD}	Output	(I, B) ±	В±	C _L = 30pF		25	35	ns
t _{OE2}	Output enable	(I, B) +	В±	C _L = 30pF		20	30	ns
t _{OD2}	Output disable ³	(I, B) -	B +	C _L = 5pF		20	30	ns
t _{PRO}	Preset/Reset	(I, B) +	F±	C _L = 30pF		35	45	ns
t _{PPR}	Power-on preset	V _{CC} +	F-	C _L = 30pF		0	10	ns


NOTES:

All typical values are at V_{CC} = 5V, T_A = +25°C.
 To prevent spurious clocking, clock rise time (10% – 90%) ≤ 10ns.
 Measured at V_T = V_{OL} + 0.5V.
 When using the Complement Array t_{CKP} = 75ns (min).
 Limits are guaranteed with 12 product terms maximum connected to each sum term line.

May 11, 1988 250

PLS179


TIMING DIAGRAMS



TIMING DEFINITIONS


SYMBOL	PARAMETER
t _{CKH}	Width of input clock pulse.
t _{CKL}	Interval between clock pulses.
t _{CKP}	Clock period.
t _{PRH}	Width of preset input pulse.
t _{IS1}	Required delay between beginning of valid input and positive transition of clock.
t _{IS2}	Required delay between beginning of valid input forced at flip–flop output pins, and positive transition of clock.
t _{IH1}	Required delay between positive transition of clock and end of valid input data.
t _{IH2}	Required delay between positive transition of clock and end of valid input data forced at flip—flop output pins.
tcko	Delay between positive transition of clock and when outputs become valid (with OE Low).
t _{OE1}	Delay between beginning of Output Enable Low and when outputs become valid.
t _{OD1}	Delay between beginning of Output Enable High and when outputs are in the OFF–State.
tppR	Delay between V _{CC} (after power-on) and when flip-flop outputs become preset at "1" (internal Q outputs at "0").
t _{PD}	Propagation delay between combinational inputs and outputs.
t _{OE2}	Delay between predefined Output Enable High, and when combinational Outputs become valid.
t _{OD2}	Delay between predefined Output Enable Low and when combinational Outputs are in the OFF-State.
t _{PRO}	Delay between positive transition of predefined Preset/Reset input, and when flip-flop outputs become valid.

TIMING DIAGRAMS (Continued)



Preset and Reset functions override Clock. However, F outputs may glitch with the first positive Clock Edge if T_{IS1} cannot be guaranteed by the user.

Asynchronous Preset/Reset



PLS179


LOGIC PROGRAMMING

PLS179 logic designs can be generated using Signetics AMAZE PLD design software or one of several other commercially available, JEDEC standard PLD design software packages. Boolean and/or state equation entry is accepted.


PLS179 logic designs can also be generated using the program table entry format detailed on the following pages. This program table entry format is supported by the Signetics AMAZE PLD design software (PTP module). AMAZE is available free of charge to qualified USERS

To implement the desired logic functions, the state of each logic variable from logic equations (I, B, O, P, etc.) is assigned a symbol. The symbols for TRUE, COMPLEMENT, INACTIVE, PRESET, etc., are defined below.


"AND" ARRAY - (I), (B), (Qp)




"COMPLEMENT" ARRAY - (C)



"OR" ARRAY - (F-F CONTROL MODE)









Notes on following page.

PLS179







"OR" ARRAY - (S or B)







"OE" ARRAY - (E)




- This is the initial unprogrammed state of all link pairs. It is normally associated with all unused (inactive) AND gates.
 Any gate (T, F_C, L, P, R, D)_n will be unconditionally inhibited if any one of the I, B, or Q link pairs are left intact.
- 3. To prevent oscillations, this state is not allowed for C link pairs coupled to active gates Tn, Fc.
- E_n = O and E_n = are logically equivalent states, since both cause F_n outputs to be unconditionally enabled.
 These states are not allowed for control gates (L, P, R, D)_n due to their lack of "OR" array links.

May 11, 1988 254

PLS179

FPLS PROGRAM TABLE



Signetics

Document No.			
ECN No.			
Date of Issue	January 1989		
Status	Preliminary Specification		
Programmable Logic Devices			

DESCRIPTION

The new PLC42VA12 CMOS PLD from Signetics exhibits a unique combination of the two architectural concepts that revolutionized the PLD marketplace.

The Signetics unique Output Macro Cell (OMC) embodies all the advantages and none of the disadvantages associated with the "V" type Output Macro Cell devices. This new design, combined with added functionality of two programmable arrays, represents a significant advancement in the configurability and efficiency of multi-function PLDs.

The most significant improvement in the Output Macro Cell structure is the implementation of the register bypass function. Any of the 10 J-K/D registers can be individually bypassed, thus creating a combinatorial I/O path from the AND array to the output pin. Unlike other "V" type devices, the register in the PLC42VA12 Macro Cell remains fully functional as a buried register. Both the combinatorial I/O and buried register have separate input paths (from the AND array). In most V-type architectures, the register is lost as a resource when the cell is configured as a combinatorial I/O. This feature provides the capability to operate the buried register independently from the combinatorial I/O.

PLC42VA12 CMOS Programmable Logic

Sequencer $(42 \times 105 \times 12)$


FEATURES

- High-speed EPROM-based CMOS Multi-Function PLD
 - Super set of 22V10, 32VX10 and 20RA10 PAL® ICs
- Two fully programmable arrays eliminate "P-term Depletion"
 - Up to 64 P-terms per OR function
- Improved Output Macro Cell Structure
 - Individually programmable as:
 - * Registered Output
 - * Registered Input
 - Combinatorial I/O with Buried Register
 - Bypassed Registers are 100% functional with separate input and feedback paths
 - Individual Output Enable control functions
 - * From pin or AND array
- Eleven clock sources
- Register Preload and Diagnostic Test Mode Features
- Security fuse

APPLICATIONS

- Mealy or Moore State Machines
 - Synchronous
 - Asynchronous
- Multiple, independent State Machines
- 10-bit ripple cascade
- Sequence recognition
- Bus Protocol generation
- Industrial control
- A/D Scanning

PIN CONFIGURATIONS



PAL is a registered trademark of Monolithic Memories, Inc., a wholly owned subsidiary of Advanced Micro Devices, Inc.


Philips Components





PLC42VA12


FUNCTIONAL DIAGRAM



January 1989 257

PLC42VA12


LOGIC DIAGRAM



Programmable Connection

PLC42VA12

LOGIC DIAGRAM (Continued)



PLC42VA12

ORDERING INFORMATION

DESCRIPTION	ORDER CODE
24-Pin Ceramic Dual In-Line with window, Reprogrammable (300mil-wide)	PLC42VA12FA
24–Pin Plastic Dual In–Line, One Time Programmable (300mil–wide)	PLC42VA12N
28-Pin Plastic Leaded Chip Carrier, One Time Programmable (450mil-wide)	PLC42VA12A

ABSOLUTE MAXIMUM RATINGS1


SYMBOL	PARAMETER	RATINGS	UNIT
V _{CC}	Supply voltage	-0.5 to +7	V _{DC}
V _{IN}	Input voltage	-0.5 to V _{CC} +0.5	V _{DC}
V _{OUT}	Output voltage	-0.5 to V _{CC} +0.5	V _{DC}
I _{IN}	Input currents	-10 to +10	mA
lout	Output currents	+24	mA
T _A	Operating temperature range	0 to +75	°C
T _{STG}	Storage temperature range	-65 to +150	°C

THERMAL RATINGS


TEMPERATURE					
Maximum junction	150°C				
Maximum ambient	75°C				
Allowable thermal rise ambient to junction	75°C				

NOTE:

AC TEST CONDITIONS



VOLTAGE WAVEFORMS



January 1989 260

^{1.} Stresses above those listed may cause malfunction or permanent damage to the device. This is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.


PLC42VA12


DC ELECTRICAL CHARACTERISTICS 0°C ≤ T_A ≤ +75°C, 4.75V ≤ V_{CC} ≤ 5.25V

	N - 7 *					
SYMBOL	PARAMETER	TEST CONDITION	Min	Typ1	Max	UNIT
Input volta	age ²			•		
V _{IL}	Low	V _{CC} = Min	-0.3		0.8	V
VIH	High	V _{CC} = Max	2.0		V _{CC} + 0.3	V
Output vo	Itage ²					
V _{OL}	Low	V _{CC} = Min I _{OL} = 16mA			0.5	V
V _{OH}	High	I _{OH} = -3.2mA	2.4			V
Input curr	ent			•	•	
I _{IL}	Low	V _{IN} = GND			-10	μΑ
I _{IH}	High	$V_{IN} = V_{CC}$			10	μА
Output cu	rrent					
la arr	Hi–Z state	V _{OUT} = V _{CC}			10	μА
I _{O(OFF)}	TIPE State	V _{OUT} = GND			-10	μΑ
los	Short-circuit ^{3,6}	V _{OUT} = GND			-130	mA
Icc	V _{CC} supply current (Active) ⁴	I _{OUT} = 0mA, f = 15MHz ⁵ , V _{CC} = Max			90	mA
Capacitan	се					
Cı	Input	V _{CC} = 5V V _{IN} = 2.0V		12		pF
C _B	1/0	V _B = 2.0V		15		pF

NOTES:

- 1. All typical values are at $V_{CC} = 5V$. $T_A = +25$ $^{\circ}C$.
- 2. All voltage values are with respect to network ground terminal.
- 3. Duration of short-circuit should not exceed one second. Test one at a time.
- 4. Tested with TTL input levels: $V_{IL} = 0.45V$, $V_{IH} = 2.4V$. Measured with all inputs and outputs switching.
- 5. Refer to Figure 1, ΔI_{CC} vs Frequency (worst case). (Referenced from 15MHz)
- 6. Refer to Figure 2 for Δt_{PD} vs output capacitance loading





PLC42VA12

AC ELECTRICAL CHARACTERISTICS 0°C \leq T_A \leq +75°C, 4.75V \leq V_{CC} \leq 5.25V; R₁ = 238 Ω , R₂ = 170 Ω

					F			
SYMBOL	PARAMETER	FROM	то	TEST ² CONDITION (C _L (pF))	Min	Typ ¹	Max	UNIT
Set-up Ti	me							
t _{IS1}	Input; dedicated clock	(I, B, M) +/-	CK+	50	25			ns
t _{IS2}	Input; P-term clock	(I, B, M) +/-	(I, B, M) +/-	50	15			ns
t _{IS3}	Preload; dedicated clock	(M) +/-	CK+	50	10			ns
t _{IS4}	Preload; P-term clock	(M) +/-	(I, B, M) +/-	50	0			ns
t _{IS5}	Input through complement array; dedicated clock	(I, B, M) +/-	CK+	50	50			ns
t _{IS6}	Input through complement array; P-term clock	(I, B, M) +/-	(I, B, M) +/-	50	40			ns
Propagati	on Delay							
t _{PD}	Propagation Delay	(I, B, M) +/-	(I, B, M) +/-	50			35	ns
t _{CKO1}	Clock to Output; Dedicated clock	CK+	(M) +/-	50			15	ns
t _{CKO2}	Clock to output; P-term clock	(I, B, M) +/-	(M) +/-	50			30	ns
t _{CKP1}	Registered operating period; Dedicated clock (f _{IS1} + f _{CKO1})	(I, B, M) +/-	(M) +/-	50			40	ns
t _{CKP2}	Registered operating period; P-term clock (t _{IS2} + t _{CKO2})	(I, B, M) +/-	(M) +/-	50			45	ns
t _{CKP3}	Register preload operating period; dedicated clock (tls3 + tcko1)	(M) +/-	(M) +/-	50			25	ns
t _{CKP4}	Register preload operating period; P-term clock (t _{IS4} + t _{CKO2})	(M) +/-	(M) +/-	50			30	ns
t _{CKP5}	Registered operating period with complement array; dedicated clock (t _{IS5} + t _{CKO1})	(I, B, M) +/-	(M) +/-	50			65	ns
t _{CKP6}	Registered operating period with complement array; P-term clock (tise + tcko2)	(I, B, M) +/-	(M) +/-	50			70	ns
t _{OE1}	Output Enable; from /OE pin	/OE -	(M) +/-	50			20	ns
t _{OE2}	Output Enable; from P- term	(I, B, M) +/-	(B, M) +/-	50			30	ns
t _{OD1}	Output Disable; from /OE pin	/OE +	Outputs disabled	5			20	ns
t _{OD2}	Output Disable; from P-term	(I, B, M) +/-	Outputs disabled	5			30	ns
t _{PRO}	Preset to Output	(I, B, M) +/-	(M) +/-	50			30	ns
t _{PPR}	Power-on Reset (Mn = 1)	V _{CC} +	(M) +/-	50			15	ns
Hold Time								
t _{IH1}	Input (Dedicated clock)	CK+	(I, B, M) +/-	50	0			ns
t _{IH2}	Input (P- term clock)	(I, B, M) +/-	(I, B, M) +/-	50	10			ns
t _{IH3}	Input; from Mn (Dedicated clock)	CK+	(M) +/-	50	15			ns
t _{IH4}	Input; from Mn (P- term clock)	(I, B, M) +/-	(M) +/-	50	25			ns
Pulse Wid	dth		*		•	*		•
t _{CKH1}	Clock High; Dedicated clock	CK+	CK-	50	15			ns
t _{CKL1}	Clock Low; Dedicated clock	CK-	CK+	50	15			ns
t _{CKH2}	Clock High; P- term clock	CK+	CK-	50	20			ns
t _{CKL2}	Clock Low; P- term clock	CK-	CK+	50	20			ns
t _{PRH}	Width of preset/reset input pulse	(I, B, M) +/-	(I, B, M) +/-	50	30			ns

262

January 1989


PLC42VA12

AC ELECTRICAL CHARACTERISTICS (Continued) 0°C \leq T_A \leq +75°C, 4.75V \leq V_{CC} \leq 5.25V; ; R₁ = 238 Ω , R₂ = 170 Ω

					F			
SYMBOL	PARAMETER	FROM	то	TEST ² CONDITION (C _L (pF))	Min	Typ ¹	Max	UNIT
Frequenc	y of Operation							
f _{CK1}	Dedicated clock frequency	C+	C+	50			33	MHz
f _{CK2}	P- term clock frequency	C+	C+	50			25	MHz
f _{MAX1}	Registered operating frequency; Dedicated clock (t _{IS1} + t _{CKO1})	(I, B, M) +/-	(M) +/-	50			25	MHz
f _{MAX2}	Registered operating frequency; P- term clock (t _{IS2} + t _{CKO2})	(I, B, M) +/-	(M) +/-	50			22.2	MHz
f _{MAX3}	Register preload operating frequency; Dedicated clock (t _{IS3} + t _{CKO1})	(M) +/-	(M) +/-	50			40	MHz
f _{MAX4}	Register preload operating frequency; P- term clock (t _{IS4} + t _{CKO2})	(M) +/-	(M) +/-	50			33	MHz
f _{MAX5}	Registered operating frequency with complement array; Dedicated clock (tls5 + tcko1)	(I, B, M) +/-	(M) +/-	50			15.4	MHz
f _{MAX6}	Registered operating frequency with complement array; P- term clock (t _{IS6} + t _{CKO2})	(I, B, M) +/-	(M) +/-	50			14.3	MHz


- 1. All typical values are at V_{CC} = 5V, T_A = +25°C. 2. Refer also to AC Test Conditions (Test Load Circuit).

BLOCK DIAGRAM



PLC42VA12

OUTPUT MACRO CELL (OMC)



Output Macro Cell Configuration

Signetics unique Output Macro Cell design represents a significant advancement in the configurability of multi-function Programmable Logic Devices.

The PLC42VA12 has 10 programmable Output Macro Cells. Each can be individually programmed in any of 5 basic configurations:

- Dedicated I/O (combinatorial) with feedback to AND array
- Dedicated Input
- Combinatorial I/O with feedback and Buried Register with feedback (register bypass)
- Registered Input
- · Registered Output with feedback

Each of the registered options can be further customized as J–K type or D–type, with either an internally derived clock (from the AND array)

or clocked from an external source. With these additional programmable options, it is possible to program each Output Macro Cell in any one of 20 different configurations.

These 20 configurations, combined with the fully programmable OR array, make the PLC42VA12 the most versatile and silicon efficient of all the Output Macrocell—type PLDs.


The most significant Output Macro Cell (OMC) feature is the implementation of the register bypass function. Any of the 10 J–K/D registers can be individually bypassed, thus creating a combinatorial I/O path from the AND array to the output pin. Unlike other Output Macrocell-type devices, the register in the OMC is fully functional as a buried register. Furthermore, both the combinatorial I/O and the buried register have separate input paths (from the AND array) and separate feedback paths (to the AND array). This feature provides the capability to operate the buried register independently from the combinatorial I/O.

The PLC42VA12 is ideally suited for both synchronous and asynchronous logic functions. Eleven clock sources – 10 driven from the AND array and one from an external source – make it possible to design synchronous state machine functions, event–driven state machine functions and combinatorial (asynchronous) functions all on the same chip.


Output Polarity for the combinatorial I/O paths is configurable via 12 programmable EX–OR gates. The output of each register can be configured as inverting (active Low) or non–inverting (active High) via manipulation of the logic equations

PLC42VA12

OUTPUT MACRO CELL PROGRAMMABLE OPTIONS



ARCHITECTURAL OPTIONS REGISTER SELECT OPTIONS



Notes on page 270.

OMC Programmable Options

For purposes of programming, the Output Macro Cell should be considered to be partitioned in to five separate blocks. As shown in the drawing titled "Output Macro Cell Programmable Options", the programmable blocks are: Register Select Options, Polarity Options, Clock Options, OMC Configuration Options and Output Enable Control Options.

There is one programmable location associated with each block except the Output Enable Control block which has two programmable fuse locations per OMC.

The following drawings detail the options associated with each programmable block. The associated programming codes are also included. The table titled "Output Macro Cell Configurations" lists all the possible combinations of the five programmable options.

Register Select Options


Each OMC Register can be configured either as a D-type or a J-K flip-flop. The Flip-Flop Control term, Fc, provides the option to control each Register dynamically—switching from D-type to J-K type based on the Fc control signal.

Register Preset and Reset are controlled from the AND array. Each OMC has an individual Reset Control term (RMn). The Register Preset function is controlled in two banks of 4 for OMCs M_1-M_3 and M_4-M_8 (via the control terms PA and PB). OMCs M_0 and M_9 have individual control terms (PM $_0$ and PM $_0$ respectively).


PLC42VA12

ARCHITECTURAL OPTIONS (Continued)

REGISTER SELECT OPTIONS (Continued)



POLARITY OPTIONS (for Combinatorial I/O Configurations Only 1)




Polarity Options

When an OMC is configured as a Combinatorial I/O with Buried Register, the polarity of the combinatorial path can be programmed as Active-High or Active-Low. A configurable EX-OR gate provides polarity control.

If an OMC is configured as a Registered Output, /Q is propagated to the output pin. Note that either Q or /Q can be fedback to the AND array by manipulating the feedback logic equations. (TRUE or COMPLEMENT).

CLOCK OPTIONS



Clock Options


In the unprogrammed state, all Output Macro Cell clock sources are connected to the External Clock pin (I₀/CLK pin 1). Each OMC can be individually programmed such that its P-term Clock (CKn) is enabled, thus disabling it from the External Clock and providing event-driven clocking capability.


This feature supports multiple state machines, clocked at several different rates, all on one chip, or the ability to collect large amounts of random logic, including 10 separately clocked flip-flops.

Notes on page 270

PLC42VA12

OUTPUT MACRO CELL CONFIGURATION OPTIONS





Notes on page 270.

OMC Configuration Options


Each OMC can be configured as a Registered Output with feedback, a Registered Input or a Combinatorial I/O with Buried Register. Dedicated Input and dedicated I/O configurations are also possible.

When the Combinatorial I/O option is selected, (the Register Bypass option), the Buried Register remains 100% functional, with its own inputs from the AND array and a separate feedback path. This unique feature is ideal for designing any type of state machine; synchronous Mealytypes that require both Buried and Output Registers, or asynchronous Mealy—types that require buried registers and combinatorial output functions. Both synchronous and asynchronous Moore—type state machines can also be easily accomodated with the flexible OMC structure.

Note that an OMC can be configured as either a Combinatorial I/O (with Buried Register) or a Registered Output with feedback and it can still be used as a Registered Input. By disabling the outputs via any OE control function, the M pin can be used as an input. When the Load Control P-term is asserted HIGH, the register is preloaded from the M pin(s). When the Lo P-term is Active-Low and the output is enabled, the OMC will again function as configured (either a combinatorial I/O or a registered output with feedback). This feature is suited for synchronizing input signals prior to commencing a state sequence.

PLC42VA12


OUTPUT CONTROL OPTIONS




Output Enable Control Options


Similar to the Clock Options, the Output Enable Control for each OMC can be connected either to an external source (I₉/OE, pin 13) or controlled from the AND array (P-terms DM_n). Each Output can also be permanently enabled

Output Enable control for the two bi-directional I/O (B pins 10 and 11) is from the AND array only (P-terms DB0 and DB1 respectively).





COMPLEMENT ARRAY DETAIL



Complement Array Detail

The complement array is a special sequencer feature that is often used for detecting illegal states. It is also ideal for generating IF—THEN—ELSE logic statements with a minimum number of product terms.

The concept is deceptively simple. If you subscribe to the theory that the expressions (/A */B */C) and $(\overline{A} + \overline{B} + \overline{C})$ are equivalent, you will begin to see the value of this single term NOR array.

The complement array is a single OR gate with inputs from the AND array. The output of the complement array is inverted and fedback to the AND array (NOR function). The output of the array will be LOW if any one or more of the AND terms connected to it are active (HIGH). If, however, all the connected terms are inactive (LOW), which is a classic unknown state, the output of the complement array will be HIGH.

Consider the product terms A, B and D that represent defined states. They are also connected to the input of the complement array. When the condition (not A and not B and not D) exists, the Complement Array will detect this and propagate an Active—High signal to the AND array. This signal can be connected to product term E, which could be used in turn to reset the state machine to known state. Without the complement array, one would have to generate product terms for all unknown or illegal states. With very complex state machines, this approach can be prohibitive, both in terms of time and wasted resources.

Notes on page 270

PLC42VA12

LOGIC PROGRAMMING


PLC42VA12 logic designs can be generated using Signetics AMAZE PLD design software or one of several other commercially available, JEDEC standard PLD design software packages. Boolean and/or state equation entry is accepted. Schematic capture entry is also supported via FutureNet and OrCAD Schematic Entry Packages.

PLC42VA12 logic designs can also be generated using the program table entry format detailed on the following pages. This program table entry format is supported by the Signetics AMAZE PLD design software (PTE module). AMAZE is available free of charge to qualified users.


To implement the desired logic functions, the state of each logic variable from logic equations (I, B, O, P, etc.) is assigned a symbol. The symbols for TRUE, COMPLEMENT, INACTIVE, PRESET, etc., are defined below. Symbols for OMC configuration have been previously defined in the Architectural Options section.

LOGIC IMPLEMENTATION






"COMPLEMENT" ARRAY - (C)




"OR" ARRAY - (J - K Type)




269





"OR" ARRAY - (D - Type)



Notes on page 270.

PLC42VA12

LOGIC IMPLEMENTATION (Continued)

OUTPUT MACRO CELL CONFIGURATIONS

	PROGRAMMING CODES							
OUTPUT MACRO CELL CONFIGURATION	REGISTER SELECT FUSE	OMC CONFIGURATION FUSE	POLARITY FUSE	CLOCK FUSE				
Combinatorial I/O with Buried D-type	e register							
External clock source	A	•	H or L	А				
P-term clock source	А	•	H or L	•				
Combinatorial I/O with Buried J-K ty	pe register	•						
External clock source	•	•	H or L	А				
P-term clock source	•	•	H or L	•				
Registered Output (D-type) with feed	dback		•					
External clock source	А	A	N/A	А				
P-term clock source	A	A	N/A	•				
Registered Output (J–K type) with fe	edback							
External clock source	•	A	N/A	А				
P-term clock source		A	N/A	•				
Registered Input (Clocked Preload) v	vith feedback		•					
External clock source	А	A or ● ⁵	Optional ⁵	А				
P-term clock source	Α	A or ● ⁵	Optional ⁵	•				

	OUTPUT CON	TROL FUSES	
OUTPUT ENABLE CONTROL CONFIGURATION	OE CONTROL FUSE	En FUSES	CONTROL SIGNAL
I/O controlled by /OE pin	A ⁷	•	
Output Enabled			Low
Output Disabled			High
I/O controlled by P-term	•7	A or ●	
Output Enabled			High
Output Disabled			Low
Output always Enabled	A ⁷	А	Not Applicable


NOTES:

- 1. This is the initial (unprogrammed) state of the device.
- 2. Any gate will be unconditionally inhibited if both the TRUE and COMPLEMENT fuses are left intact.
- 3. To prevent oscillations, this state is not allowed for Complement Array fuse pairs that are coupled to active product terms.
- 4. The OMC Configuration fuse must be programmed as Combinatorial I/O in order to make use of the Polarity Option.
- 5. Regardless of the programmed state of the OMC Configuration fuse, an OMC can be used as a Registered Input. Note that the Load Control P-term must be asserted active—High.
- 6. Output must be disabled.
- 7. For OMCs M0 and M9, the programming codes must be reversed to obtain this function (i.e., A = and = A).
- 8. Program code definitions:
 - A = Active (unprogrammed fuse)
 - = Inactive (programmed fuse)
 - = Don't Care (both TRUE and COMPLEMENT fuses unprogrammed)
 - H = Active-High connection
 - L = Active-Low connection


January 1989 270

PLC42VA12


TIMING DIAGRAMS



Flip-Flop Outputs with P-term Clock



Flip-Flop Outputs with External Clock




TIMING DEFINITIONS

SYMBOL	PARAMETER						
f _{CK1}	Clock Frequency; External Clock						
f _{CK2}	Clock Frequency; P-term Clock						
t _{CKH1}	Width of Input Clock Pulse; External Clock						
t _{CKH2}	Width of Input Clock Pulse; P-term Clock						
t _{CKL1}	Interval between Clock pulses; External Clock						
t _{CKL2}	Interval between Clock Pulses; P-term Clock						
t _{CKO1}	Delay between the Positive Transition of External Clock and when M Outputs become valid.						
t _{CKO2}	Delay between the Positive Transition of P-term Clock and when M Outputs become valid.						
t _{CKP1}	Delay between beginning of Valid Input and when the Moutputs be- come Valid when using External Clock.						
t _{CKP2}	Delay between beginning of Valid Input and when the Moutputs be- come Valid when using P-term Clock.						
t _{CKP3}	Delay between beginning of Valid Input and when the Moutputs be- come Valid when using Preload Inputs (from Mpins) and External Clock.						
t _{CKP4}	Delay between beginning of Valid Input and when the Moutputs be- come valid when using Preload inputs (from M pins) and P-term Clock.						
t _{CKP5}	Delay between beginning of Valid Input and when the Moutputs be- come Valid when using Comple- ment Array and External clock.						
t _{CKP6}	Delay between beginning of Valid Input and when the Moutputs be- come Valid when using Comple- ment Array and P-term Clock.						
f _{MAX1}	Minimum guaranteed Operating Frequency; Dedicated Clock						
f _{MAX2}	Minimum guaranteed Operating Frequency; P-term Clock						
f _{MAX3}	Minimum guaranteed Operating Frequency using Preload; Dedicated Clock						
f _{MAX4}	Minimum guaranteed Operating Frequency using Preload; P-term Clock						
f _{MAX5}	Minimum guaranteed Operating Frequency using Complement Array; Dedicated Clock						
f _{MAX6}	Minimum Operating Frequency using Complement Array; P-term Clock						
t _{IH1}	Required delay between positive transition of External Clock and end of valid input data.						

PLC42VA12

TIMING DIAGRAMS (Continued)




TIMING DEFINITIONS (Continued)

SYMBOL	PARAMETER
t _{IH2}	Required delay between positive transition of P-term Clock and end of valid input data.
t _{IH3}	Required delay between positive transition of External Clock and end of valid input data when using Preload Inputs (from M pins).
t _{IH4}	Required delay between positive transition of P-term Clock and end of valid input data when using Preload Inputs (from M pins).
t _{IS1}	Required delay between begin- ning of valid input and positive transition of External Clock.
t _{IS2}	Required delay between beginning of valid input and positive transition of P-term Clock input.
t _{IS3}	Required delay between begin- ning of valid Preload input (from M pins) and positive transition of External Clock.
t _{IS4}	Required delay between begin- ning of valid Preload input (from M pins) and positive transition of P-term Clock input.
t _{IS5}	Required delay between begin- ning of valid input through Com- plement Array and positive tran- sition of External Clock.
t _{IS6}	Required delay between begin- ning of valid input through Com- plement Array and positive tran- sition of P-term Clock input.
t _{OE1}	Delay between beginning of Output Enable signal (Low) from /OE pin and when Outputs become valid.
t _{OE2}	Delay between beginning of Output Enable signal (High or Low) from OE P-term and when Outputs become valid.
t _{OD1}	Delay between beginning of Output Enable signal (HIGH) from /OE pin and when Outputs become disabled.
t _{OD2}	Delay between beginning of Output Enable signal (High or Low) from OE P-term and when Outputs become disabled.
t _{PD}	Delay between beginning of valid input and when the Outputs become valid (Combinatorial Path).
t _{PRH}	Width of Preset/Reset Pulse.
t _{PRO}	Delay between beginning of valid Preset/Reset Input and when the registered Outputs become Pre- set ("1") or Reset ("0").
t _{PPR}	Delay between V _{CC} (after pow- er-up) and when flip-flops be- come Reset to "0". Note: Signal at Output (M pin) will be inverted.

January 1989 272

PLC42VA12

LOGIC FUNCTION



NOTE:

Similar logic functions are applicable for D mode flip-flops.

FLIP-FLOP TRUTH TABLE

ŌĒ	Ln	CK _n	Pn	Rn	J	K	Q	М
Н								Hi–Z
L	X	Χ	Χ	Χ	Χ	Χ	L	Н
L	X	Χ	Н	L	Χ	Χ	Н	L
L	Χ	Χ	L	Н	Χ	Χ	L	Н
L	L	\uparrow	L	L	L	L	Q	۵
L	L	\uparrow	L	L	L	Н	L	Н
L	L	\uparrow	L	L	Н	L	Н	L
L	L	\uparrow	L	L	Н	Н	ℚ	Q
Н	Н	\uparrow	L	L	L	Н	L	H*
Н	Н	\uparrow	L	L	Н	L	Н	Ľ*
+10V	Х	1	Χ	Χ	L	Н	L	H**
	Х	1	Χ	Χ	Н	L	Н	L**

NOTES:

- 1. Positive Logic: J-K = T₀ + T₁ + T₂ + ... + T₃₁ T_n = C · (I₀ · I₁ · I₂...) · (Q₀ · Q₁...) · (B₀ · B₁...)
 - denotes transition for Low to High level.
- 3. X = Don't care
- 4. * = Forced at M_n pin for loading the J–K flip–flop in the Input mode. The load control term, L_n must be enabled (HIGH) and the p–terms that are connected to the associated flip–flop must be forced LOW (disabled) during Preload.
- At P = R = H, Q = H. The final state of Q depends on which is released first.
- ** = Forced at F_n pin to load J/K flip-flop (Diagnostic mode).

PLC42VA12 UNPROGRAMMED STATE

A factory shipped unprogrammed device is configured such that all cells are in a conductive state

The following are:

ACTIVE:

- OR array logic terms
- Output Macro Cells M1 M8;
 - D-type registered outputs
- External clock path
- Inputs: B₀, B₁, M₀, M₉

INACTIVE

- AND array logic and control terms (except flip-flop mode control term, F_C)
- Bidirectional I/O (B₀, B₁);
- Inputs are active. Outputs are 3-Stated via the OE P-terms, D₀ and D₁.
- Output Macro Cells Mo and Ma;
 - Bidirectional I/O, 3–Stated via the OE P-terms, DM₀ and DM₉. The inputs are active.
- P-term clocks
- Complement Array
- J-K Flip-Flop mode

ERASURE CHARACTERISTICS (For Quartz Window Packages Only)


The erasure characteristics of the PLC42VA12 devices are such that erasure begins to occur upon exposure to light with wavelength shorter than approximately 4000 Angstroms (Å). It should be noted that sunlight and certain types of fluorescent lamps have wavelengths in the 3000 - 4000 Å range. Data shows that constant exposure to room level fluorescent lighting could erase a typical PLC42VA12 in approximately three years, while it would take approximately one week to cause erasure when exposed to direct sunlight. If the PLC42VA12 is to be exposed to these types of lighting conditions for extended periods of time, opaque labels should be placed over the window to prevent unintentional erasure.

The recommended erasure procedure for the PLC42VA12 is exposure to shortwave ultraviolet light which has a wavelength of 2537 Angstroms (Å). The integrated dose (i.e., UV intensity × exposure time) for erasure should be a minimum of 15Wsec/cm². The erasure time with this dosage is approximately 30 to 35 minutes using an ultraviolet lamp with a 12,000µW/cm² power rating. The device should be placed within one inch of the lamp tubes during erasure. The maximum integrated dose a CMOS EPLD can be expose to without damage is 7258Wsec/cm2 (1 week @ 12000µW/cm²). Exposure of these CMOS EPLDs to high intensity UV light for longer periods may cause permanent damage.

The maximum number of guaranteed erase/ write cycles is 50. Data retentions exceeds 20 years.

PLC42VA12

FPLS PROGRAM TABLE



January 1989 274

Signetics

Document No.	853–1382					
ECN No.	97884					
Date of Issue	October 16, 1989					
Status	Product Specification					
Programmable Logic Devices						

PLC415–16 CMOS Programmable Logic Sequencer $(17 \times 68 \times 8)$

DESCRIPTION

The PLC415–16 PLD is a CMOS Programmable Logic Sequencer of the Mealy type. The PLC415–16 is a pin–for–pin compatible, functional superset of the PLS105 and PLUS405 Bipolar Programmable Logic Sequencer devices.

The PLC415 is ideally suited for high density, power sensitive controller functions. The Power Down feature provides true CMOS standby power levels of less than 100µA. The EPROMbased process technology supports operating frequencies of 16 to 20MHz. The PLC415–16 has been designed to accept both CMOS and TTL input levels to facilitate logic integration in almost any system environment.

The PLC415 architecture has been tailored for state machine functions. Both arrays are programmable, thus providing full interconnectability. Any one or all of the 64 AND transition terms can be connected to any (or all) of the 8 buried state and 8 output registers.

Two clock sources enable the design of 2 state machines on one chip. The J–K flip-flops provide the added flexibility of the toggle function which is indeterminate on S–R flip-flops. The programmable Initialization feature supports asynchronous initialization of the state machine to any user defined pattern. Separate INIT functions and Output Enable functions are controllable either from the array or from an external pin.

The unique Complement Array feature' supports complex ELSE transition statements with a single product term. The PLC415–16 has 2 Complement Arrays which allows the user to design two independent complement functions. This is particularly useful if two state machines have been implemented on one chip.


FEATURES

- Pin-for-Pin compatible, functional superset of PLS105/A and PLUS405 Logic Sequencers
- Zero standby power of less than 100μA (worst case)
 - Power dissipation at f_{MAX} = 80mA (worst case)
- . CMOS and TTL compatible
- Programmable asynchronous Initialization and OE functions
 - Controllable from AND Array or external source
- 17 input variables
- 8 output functions
- 68 Product Terms
- 64 transition terms
- 4 control terms
- 8-bit State Register
- 8-bit Output Register
- 2 Transition Complement Arrays
- Multiple clocks
- Diagnostic test modes features for access to state and output registers
- Power-on preset of all registers to "1"
- · J-K flip-flops
 - Automatic Hold states
- Security Fuse
- 3-State outputs

APPLICATIONS

- Interface protocols
- Sequence detectors
- · Peripheral controllers
- Timing generators
- · Sequential circuits
- Elevator controllers
- Security locking systems
- Counters
- Shift Registers

PIN CONFIGURATIONS



Philips Components





PLC415-16

PIN DESCRIPTION

PIN NO.	SYMBOL	NAME AND FUNCTION	POLARITY
1	CLK1	Clock: The Clock input to the State and Output Registers. A Low–to–High transition on this line is necessary to update the contents of both registers. Pin 1 only clocks P_{0-3} and F_{0-3} if Pin 4 is also being used as a clock.	Active-High (H)
2, 3, 5–9, 26–27 20–22		Logic Inputs: The 12 external inputs to the AND array used to program jump conditions between machine states, as determined by a given logic sequence. True and complement signals are generated via use of "H" and "L".	Active-High/Low (H/L)
4	I ₅ /CLK2	Logic Input/Clock: A user programmable function:	
9		Logic Input: A 13th external logic input to the AND array, as above.	Active-High/Low (H/L)
		 Clock: A 2nd clock for the State Registers P₄₋₇ and Output Registers F₄₋₇, as above. Note that input buffer I₅ must be deleted from the AND array (i.e., all fuse locations "Don't Care") when using Pin 4 as a Clock. 	Active-High (H)
23	l ₁₂	Logic/Diagnostic Input: A 14th external logic input to the AND array, as above, when exercising standard TTL or CMOS levels. When I_{12} is held at +11V, device outputs $F_0 - F_7$ reflect the contents of State Register bits $P_0 - P_7$. The contents of each Output Register remains unaltered.	Active-High/Low (H/L)
24	I ₁₁	Logic/Diagnostic Input: A 15th external logic input to the AND array, as above, when exercising standard TTL or CMOS levels. When l_{11} is held at +11V, device outputs $F_0 - F_7$ become direct inputs for State Register bits $P_0 - P_7$: a Low-to-High transition on the appropriate clock line loads the values on pins $F_0 - F_7$ into the State Register bits $P_0 - P_7$. The contents of each Output Register remains unaltered.	Active-High/Low (H/L)
25	110	Logic/Diagnostic Input: A 16th external logic input to the AND array, as above, when exercising standard TTL or CMOS levels. When I_{10} is held at +11V, device outputs $F_0 - F_7$ become direct inputs for Output Register bits $Q_0 - Q_7$; a Low-to-High transition on the appropriate clock line loads the values on pins $F_0 - F_7$ into the Output Register bits $Q_0 - Q_7$. The contents of each State Register remains unaltered.	Active-High/Low (H/L)
10–13 15–18	F ₀ – F ₇	Logic Outputs/Diagnostic Outputs/Diagnostic Inputs: Eight device outputs which normally reflect the contents of Output Register Bits Q_0-Q_7 , when enabled. When I_{12} is held at +11V, F_0-F_7 become inputs to State Register bits P_0-P_7 . When I_{11} is held at +11V, F_0-F_7 become inputs to Output Register bits Q_0-Q_7 .	Active-High (H)
19	INIT/OE I ₁₆ /PD	External Initialization, External /OE, PD or I ₁₆ : A user programmable function: Only one of the four options below may be selected. Note that both Initialization and /OE options are alternately available via the AND array. (P-terms INA, INB, OEA, and OEB.)	
		• External Initialization: Provides an asynchronous Preset to logic "1" or Reset to logic "0" of any or all State and Output Registers, determined individually on a register–by–register basis. INIT overrides the clock, and when held High, clocking is inhibited. Normal clocking resumes with the first full clock pulse following a High—to—Low clock transition, after the INIT pulse goes Low. See timing diagrams for the theorem of the that if the External Initialization option is selected, Ins is disabled automatically via the design software and the Power Down and External OE options are not available. Internal OE is available via P—Terms OEA and/or OEB. This option can be selected for one or both banks of registers.	Active—High (H)
		• External Output Enable: Provides an Output Enable/Disable function for Output Registers. Note that if the External OE option is selected, I ₁₆ is disabled automatically via the design software and the Power Down and External INIT options are not available. Internal INIT is available via P-terms INA and/or INB. This option can be selected for one or both banks of registers.	Active-Low (L)
		• Power Down: When invoked, provides a Power Down (zero power) mode. The contents of all Registers is retained, despite the toggling of the Inputs or the clocks. To obtain the lowest possible power level, all Inputs should be static and at CMOS input levels. Note that if the PD options is selected, I16 is disabled automatically via the design software and the External INIT and External OE options are not available. Internal INIT is available via P-terms INA and/or INB and Internal OE is available via P-terms OEA and/or OEB.	Active-High (H)
		 Logic Input: The 17th external logic input to the AND array as above. Note that when the I₁₆ option is selected, the Power Down, External /OE and External INIT are not avail- able. Internal OE and Internal INIT are available from P-Terms OEA/OEB and INA/INB, respectively. 	Active-High/Low (H/L)

PLC415-16

TRUTH TABLE 1, 2, 3, 4, 5, 6

	ОРТ	ION									
V _{cc}	INIT	ŌĒ	I ₁₀	I ₁₁	I ₁₂	CK	J	K	Q _P	Q _F	F
	Н		X	Χ	X	Х	X	Х	H/L	H/L	Q _F
	×		+11V	X	X	\uparrow	X	X	Q _P	L	L
	X		+11V	X	X	\uparrow	X	X	Q _P	Н	н
	X		×	+11V	X	\uparrow	X	X	L	Q _F	L
	X		×	+11 V	X	\uparrow	X	X	н	Q _F	н
	X		X	X	+11V	X	X	X	Q_P	Q_F	Q _P
	L		X	Χ	Χ	X	X	X	Q _P	Q _F	Q _F
+5V		Н	X	X	X	X	X	X	Q _P	Q _F	Hi–Z
		×	+11V	X	X	\uparrow	X	X	Q _P	L	L
		X	+11V	X	X	\uparrow	X	X	Qp	Н	н
		×	×	+11V	X	\uparrow	X	X	L	Q _F	L
		X	X	+11V	X	\uparrow	X	X	Н	Q _F	н
		L	X	X	+11V	X	X	X	Qp	Q _F	Qp
		L	X	X	X	X	X	X	Qp	Q _F	Q _F
		L	X	Χ	X	\uparrow	L	L	Qp	Q _F	QF
		L	×	Χ	X	\uparrow	L	Н	L	L	L
		L	×	Χ	X	\uparrow	Н	L	Н	Н	н
		L	X	Χ	X	1	Н	Н	Q _P	Q _F	Q _F
1	L	L	X	Χ	X	X	X	X	Н	Н	Н

NOTES:

1. Positive Logic:

- S/R (or J/K) = T₀ + T₁ + T₂ + ... T₆₃

 T_n = (C₀, C₁)(I₀, I₁, I₂, ...) (P₀, P₁ ... P₇)


 Either Initialization or Output Enable are available, but not both. The desired function is a user–programmable option.
- 3. ↑ denotes transition from Low-to-High level.
- 4. X = Don't Care (≤5.5V)
- 5. H/L implies that either a High or a Low can occur, depending upon user-programmed Initialization selection (each State and Output Register individually programmable)
- 6. When using the F_n pins as inputs to the State and Output Registers in diagnostic mode, the F buffers are 3–Stated and the indicated levels on the output pins are forced by the user.

VIRGIN STATE

A factory-shipped virgin device contains all fusible links intact, such that:


- 1. INIT/OE/PD/I₁₆ is set to INIT. In order to use the INIT function, the user must select either the PRESET or the RESET option for each flip-flop. Note that regardless of the user-programmed initialization, or even if the INIT function is not used, all registers are preset to "1" by the powerup procedure.
- 2. All transition terms are inactive (0).
- 3. All J/K flip-flop inputs are disabled (0).
- 4. The Complement Arrays are inactive.
- 5. Clock 1 is connected to all State and Output Registers.

LOGIC FUNCTION




PLC415-16

FUNCTIONAL DIAGRAM




PLC415-16


LOGIC DIAGRAM





PLC415-16

DETAILS FOR PLC415-16 LOGIC DIAGRAM










PLC415-16

DETAILS FOR PLC415-16 LOGIC DIAGRAM (Continued)



The Complement Array is a special sequencer feature that is often used for detecting illegal states. It is also ideal for generating IF—THEN—ELSE logic statements with a minimum number of product terms.

The concept is deceptively simple. If you subscribe to the theory that the expressions (/A */B */C) and $(\overline{A} + \overline{B} + \overline{C})$ are equivalent, you will begin to see the value of this single term NOR array.

The Complement Array is a single OR gate with inputs from the AND array. The output of the

Complement Array is inverted and fed back to the AND array (NOR). The output of the array will be Low if any one or more of the AND terms connected to it are active (High). If, however, all the connected terms are inactive (Low), which is a classic unknown state, the output of the Complement Array will be High.

Consider the Product Terms A, B and D that represent defined states. They are also connected to the input of the Complement Array. When the condition (not A and not B and not D exists, the Complement Array will detect this and propagate an Active—High signal to the

AND array. This signal can be connected to Product Term E, which could be used in turn to reset the state machine to a known state. Without the Complement Array, one would have to generate product terms for all unknown or illegal states. With very complex state machines, this approach can be prohibitive, both in terms of time and wasted resources.

Note that the PLC415–16 has 2 Complement Arrays which allow the user to design 2 independentComplement functions. This is particularly useful if 2 independent state machines have been implemented on one device.

PLC415-16

ORDERING INFORMATION

DESCRIPTION	OPERATING FREQUENCY	ORDER CODE
28-Pin Ceramic DIP with window; Reprogrammable (600mil-wide)	f _{MAX} = 16MHz	PLC415-16FA
28-Pin Plastic DIP; One-Time Programmable (600mil-wide)	f _{MAX} = 16MHz	PLC415-16N
28-Pin Plastic Leaded Chip Carrier; One-Time Programmable (450mil-wide)	f _{MAX} = 16MHz	PLC415-16A

ABSOLUTE MAXIMUM RATINGS¹

SYMBOL	PARAMETER	RATINGS	UNIT
V _{CC}	Supply voltage	+7	V _{DC}
V _{IN}	Input voltage	+5.5	V _{DC}
V _{OUT}	Output voltage	+5.5	V _{DC}
I _{IN}	Input currents	-30 to +30	mA
l _{out}	Output currents	+100	mA
TA	Operating temperature range	0 to +75	°C
T _{STG}	Storage temperature range	-65 to +150	°C

NOTES

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.


PLC415-16


DC ELECTRICAL CHARACTERISTICS 0°C ≤ T_A ≤ +75°C, 4.75 ≤ V_{CC} ≤ 5.25V

					LIMITS		
SYMBOL	PARAMETER	TEST CO	NDITION	Min	Typ ¹	Max	UNIT
Input volt	age ²						
V _{IL}	Low	V _{CC} =	-0.3		0.8	V	
V _{IH}	High	V _{CC} =	2.0		V _{CC} + 0.3	V	
Output vo	oltage ²			•			
V _{OL}	Low	V _{CC} = I _{OL} =				0.5	٧
V _{OH}	High	I _{OH} = -	-3.2mA	2.4			V
Input curr	ent				*		
I _{IL}	Low	V _{IN} =			-10	μΑ	
I _{IH}	High	V _{IN} =	· V _{CC}			10	μΑ
Output cu	irrent						
I _{O(OFF)}	Hi–Z state	$V_{OUT} = V_{CC}$ $V_{OUT} = GND$				10 -10	μA μA
I _{OS}	Short-circuit 3, 6	V _{OUT} =	= GND			-130	mA
I _{CCSB}	V _{CC} supply current with PD asserted ⁷	V _{CC} = V _{IN} = 0	MAX or V _{CC}		50	100	μА
Icc	V _{CC} supply current Active ^{4, 5}	I _{OUT} = 0mA	at f = 1MHz			55	mA
	(TTL or CMOS Inputs)	V _{CC} = MAX at f = MAX				80	mA
Capacitan	nce						
C ₁	Input	$V_{CC} = 5V$ $V_{IN} = 2.0V$			12		pF
C _B	1/0	V _B =	2.0V		15		pF

NOTES:

- 1. All typical values are at $V_{CC} = 5V$. $T_A = +25^{\circ}C$
- 2. All voltage values are with respect to network ground terminal.
- 3. Duration of short-circuit should not exceed one second. Test one at a time.
- 4. Tested with TTL input levels: $V_{IL} = 0.45V$, $V_{IH} = 2.4V$. Measured with all inputs and outputs switching.
- 5. Refer to Figure 1, I_{CC} vs Frequency (worst case).
- 6. Refer to Figure 2 for $\Delta t_{\mbox{\scriptsize PD}}$ vs output capacitance loading.
- 7. The outputs are automatically 3–Stated when the device is in the Power Down mode. To achieve the lowest possible current, the inputs and clocks should be at CMOS static levels.





PLC415-16

AC ELECTRICAL CHARACTERISTICS $R_1 = 252\Omega$, $R_2 = 178\Omega$, $0^{\circ}C \le T_A \le +75^{\circ}C$, $4.75 \le V_{CC} \le 5.25V$

				TEST	LIMITS			
SYMBOL	PARAMETER	FROM	то	CONDITION	Min	Тур	Max	UNIT
Pulse wid	lth							
t _{CKH}	Clock High	CK+	CK-	30pF	25	10		ns
t _{CKL}	Clock Low	CK-	CK+	30pF	25	10		ns
t _{INITH}	Initialization Input pulse	INIT+	INIT-	30pF	20			ns
Set-up tir	me							
t _{IS1}	Input	(1) +/-	CK+	30pF	38	25		ns
t _{IS2} 1	Input through Complement array	(1) +/-	CK+	30pF	60	40		ns
t _{ISPD}	Power Down Setup (from PD pin)	PD+	CK+	30pF	38	15		ns
t _{ISPU}	Power Up Setup (from PD pin)	PD-	First Valid CK+	30pF	38	30		ns
t _{VS} 1	Power on Preset Setup	V _{CC} +	CK-	30pF	0			ns
t _{VCK1}	Clock resume (after INIT) when using INIT pin (pin 19)	INIT-	CK-	30pF	10	-5		ns
t _{VCK2} 1	Clock resume (after INIT) when using P-term INIT (from AND array)	(1) +/-	CK-	30pF	20	8		ns
t _{NVCK1}	Clock lockout (before INIT) when using INIT pin (pin 19)	CK-	INIT-	30pF	10	-3		ns
t _{NVCK2} 1	Clock lockout (before INIT) when using P-term INIT (from AND array)	CK-	INIT-	30pF	0	-5		ns
Propagat	ion delays							
t _{CKO}	Clock to Output	CK+	(F) +/-	30pF		15	22	ns
t _{PDZ}	Power Down to outputs off	PD+	Outputs Off	5pF		25	30	ns
t _{PUA1}	Power Up to outputs Active with dedicated Output Enable	PD-	Outputs Active	30pF		20	35	ns
t _{PUA2} 1	Power Up to outputs Active with P-term Output Enable ¹	PD-	Outputs Active	30pF		37	55	ns
t _{IHPU}	Last valid clock to Power Down delay (Hold)	Last Valid Clock	PD+	30pF	25	15		ns
t _{IHPD}	First valid clock cycle before Power Up	Beginning of First Valid Clock Cycle	PD-	30pF	0	-25		ns
t _{OE1}	Output Enable: from /OE pin	OE-	Output Enabled	30pF		15	30	ns
t _{OE2} 1	Output Enable; from P-term	(1) +/-	Output Enabled	30pF		25	40	ns
t _{OD1}	Output Disable; from /OE pin	OE+	Output Disabled	5pF		20	30	ns
t _{OD2}	Output Disable; from P-term	(1) +/-	Output Disabled	5pF		30	40	ns
t _{INIT1}	INIT to output when using INIT pin	INIT+	(F) +/-	30pF		22	35	ns
t _{INIT2}	INIT to output when using P-term INIT	(1) +/-	(F) +/-	30pF		35	45	ns
t _{PPR} 1	Power–on Preset (F _n = 1)	V _{CC} +	(F) +	30pF			15	ns
t _{CKP1}	Registered operating period; (t _{IS1} + t _{CKO1})	(1) +/-	(F) +/-	30pF		40	60	ns
t _{CKP2} 1	Registered operating period with Complement Array (t _{IS2} + t _{CKO1})	(1) +/-	(F) +/-	30pF		55	75	ns

NOTE:

^{1.} Not 100% tested, but guaranteed by design/characterization.


PLC415-16

AC ELECTRICAL CHARACTERISTICS (Continued) $R_1 = 252\Omega$, $R_2 = 178\Omega$, $0^{\circ}C \le T_A \le +75^{\circ}C$, $4.75 \le V_{CC} \le 5.25V$

				TEST	LIMITS		-	
SYMBOL	PARAMETER	FROM	то	CONDITION	Min	Тур	Max	UNIT
Hold time								
t _{IH}	Input Hold	CK+	(F) +/-	30pF		-10	0	ns
Frequency of operation								
f _{CLK} ¹	Clock (toggle) frequency	C+	C+	30pF	20	50		MHz
f _{MAX1}	Registered operating frequency (t _{IS1} + t _{CKO1})	(1) +/-	(F) +/-	30pF	16.7	25		MHz
f _{MAX2}	Registered operating frequency with Complement Array (t _{IS2} + t _{CKO1})	(1) +/-	(F) +/-	30pF	13.3	18.2		MHz

NOTE:

TIMING DIAGRAMS



^{1.} Not 100% tested, but guaranteed by design/characterization.


PLC415-16

The PLC415-16 has a unique power down feature that is ideal for power sensitive controller and state machine applications. During idle periods, the PLC415 can be powered down to a near zero power consumption level of less than 100 micro Amps. Externally controlled from Pin 19, the power down sequence first saves


the data in all the State and Output registers. In order to insure that the last valid states are saved, there are certain hold times associated with the first and last valid clock edges and the Power Down input pulse. The Outputs are then automatically 3-Stated and power consumption is reduced to a minimum.

Once in the power down mode, any or all of the inputs, including the clocks, may be toggled without the loss of data. To obtain the lowest possible power level, the inputs should be at static CMOS input levels during the power down period.

TIMING DIAGRAMS (Continued)



PLC415-16



PLC415-16

TIMING DEFINITIONS


SYMBOL	PARAMETER			
f _{CLK}	Minimum guaranteed toggle frequency of the clock (from Clock HIGH to Clock HIGH).			
f _{MAX1, 2}	Minimum guaranteed operating frequency.			
tckH	Width of input clock pulse.			
t _{CKL}	Interval between clock pulses.			
t _{CKP1}	Minimum guaranteed operating period – when not using Complement Array.			
t _{CKP2}	Minimum guaranteed operating period – when using Complement Array.			
t _{CKO}	Delay between positive transition of Clock and when Outputs become valid (with outputs enabled).			
t _{IH}	Required delay between positive transition of Clock and end of valid Input data.			
t⊪PD	Required delay between the positive transition of the beginning of the first valid clock cycle to the beginning of Power Down LOW to insure that the last valid states are intact and that the next positive transition of the clock is valid.			
t⊪₽U	Required delay between the positive transition of the last valid clock and the beginning of Power Down HIGH to insure that last valid states are saved.			
t _{INITH}	Width of initialization input pulse.			
t _{INIT1}	Delay between positive transition of Initialization and when Outputs become valid when using external INIT control (from pin 19).			
t _{INIT2}	Delay between positive transition of Initialization and when outputs become valid when using internal INIT control (from P-terms INA and INB).			
t _{ISPD}	Required delay between the beginning of Power Down HIGH (from pin 19) and the positive transition of the next clock to insure that the clock edge is not detected as a valid Clock and that the last valid states are saved.			

SYMBOL	PARAMETER
t _{ISPU}	Required delay between the beginning of Power Down LOW and the positive transition of the first valid clock.
t _{IS1}	Required delay between beginning of valid input and positive transition of Clock.
t _{IS2}	Required delay between beginning of valid input and positive transition of Clock, when using optional Complement Array (two passes necessary through the AND Array).
t _{NVCK1}	Required delay between the negative transition of the clock and the negative transition of the Asynchronous Initialization when using external INIT control (from pin 19) to guarantee that the clock edge is not detected as a valid negative transition.
t _{NVCK2}	Required delay between the negative transition of the clock and the negative transition of the Asynchronous Initialization, when using the internal INIT control (from P-terms INA and INB), to guarantee that the clock edge is not detected as a valid negative transition.
[‡] OD1	Delay between beginning of Output Enable High and when Outputs are in the OFF-state, when using external OE control (from pin 19).
t _{OD2}	Delay between beginning of Output Enable High and when outputs are in the OFF-State when using internal OE control (from P-terms OEA and OEB).
^t OE1	Delay between beginning of Output Enable Low and when Outputs become valid when using external OE control from pin 19.
[†] OE2	Delay between beginning of Output Enable Low and when outputs become valid when using internal OE control (from P-terms OEA and OEB).
t _{PDZ}	Delay between beginning of Power Down HIGH and when outputs are in OFF—State and the circuit is "powered down".


SYMBOL	PARAMETER
t _{PPR}	Delay between V _{CC} (after power–on) and when Outputs become preset at "1".
t _{PUA1,2}	Delay between beginning of Power Down LOW and when outputs become Active (valid) and the circuit is "powered up". See AC Specifications.
t _{RH}	Required delay between positive transition of Clock and end of valid Input data when jamming data into State or Output Registers in diagnostic mode.
t _{RJH}	Required delay between positive transition of Clock and end of inputs I ₁₁ or I ₁₀ transition to State and Output Register Input Jam Diagnostic Modes, respectively.
t _{RJS}	Required delay between when inputs I ₁₁ or I ₁₀ transition to State and Output Register Input Jam Diagnostic Modes, respectively, and when the output pins become available as inputs.
t _{SRD}	Delay between input I ₁₂ transition to Logic mode and when the Outputs reflect the contents of the Output Register.
t _{SRE}	Delay between input I ₁₂ transition to Diagnostic Mode and when the Outputs reflect the contents of the State Register.
t _{VCK1}	Required delay between negative transition of Asynchronous Initialization and negative transition of Clock preceding the first valid clock pulse when using external INIT control (pin 19).
t _{VCK2}	Required delay between the negative transition of the Asynchronous Initialization and the negative transition of the clock preceding the first valid clock pulse when using internal INIT control (from P—terms INA and INB).
t _{VS}	Required delay between V _{CC} (after power–on) and negative transition of Clock preceding first reliable clock pulse.

PLC415-16

TEST LOAD CIRCUIT



VOLTAGE WAVEFORMS




LOGIC PROGRAMMING

PLC415–16 logic designs can be generated using Signetics AMAZE design software or several other commercially available, JEDEC standard PLD design software packages. Boolean and/or state equation entry format is accepted. Schematic capture entry formats are also supported.


PLC415–16 logic designs can also be generated using the program table format detailed on the following page(s). This Program Table Entry format (PTE) is supported by the Signetics AMAZE PLD design software. AMAZE is available free of charge to qualified users.

To implement the desired logic functions, each logic variable (I, B, P, S, T, etc.) from the logic equations if assigned a symbol. TRUE, COMPLEMENT, PRESET, RESET, OUTPUT ENABLE, INACTIVE, etc., symbols are defined below.

INITIALIZATION (PRESET/RESET)11 OPTION - (P/R)



"AND" ARRAY - (I), (P)




289


Notes are on page 291.


PLC415-16


LOGIC PROGRAMMING (Continued)


PIN 19 FUNCTION: POWER DOWN, INIITALIZATION, OE, OR INPUT












Notes are on page 291.


PLC415-16

LOGIC PROGRAMMING (Continued)


"OR" ARRAY - J-K FUNCTION - (N), (F)



"COMPLEMENT" ARRAY - (C)



CLOCK OPTION - (CLK1/CLK2)




NOTES:

- This is the initial unprogrammed state of all links.
- 2. Any gate T_n will be unconditionally inhibited if any one of its I or P link pairs is left intact.
- 3. To prevent oscillations, this state is not allowed for C link pairs coupled to active gates Tn-
- 4. These states are not allowed when using PRESET/RESET option.
- 5. Input buffer I₅ must be deleted from the AND array (i.e., all fuse locations "Don't Care") when using second clock option.
- 6. When using Power Down feature, INPUT 16 is automatically disabled via the design software.
- If the internal (P-term) control fuse for INIT and/or OE is programmed as Active High, the associated External Control function will be permanently disabled, regardless of the state of the External INIT/OE fuse.
- One internal control fuse exists for each group of 8 registers. P₀₋₃ and F₀₋₃ are banked together in one group, as are P₄₋₇ and F₄₋₇.
 Control can be split between the INIT/OE pin (Pin 19) and P-terms INA, INB, OEA and OEB.
- 9. The PLC415–16 also has a power–up preset feature. This feature insures that the device will power–up in a known state with all register elements (State and Output Register) at a logic High (H). When programming the device it is important to realize this is the initial state of the device. You *must* provide a next state jump if you do not wish to use all Highs (H) as the present state.
- 10. L = cell unprogrammed.
 - H = cell programmed.
- 11. Inputs 10, 11 and 12 (pins 25, 24, & 23) can be used for supervoltage diagnostic mode tests. It is recommended that these inputs not be connected to product terms INA, INB, OEA or OEB if you intend to make use of the diagnostic modes due to the fact that the patterns associated with the internal INIT and OE control product terms may interfere with the diagnostic mode data loading and reading.

PLC415-16

PROGRAM TABLE



NOTES:

1. In the unprogrammed state all cells are conducting. Thus, the program table for an unprogrammed device would contain "0"s for all product terms (inactive) and initialization states (indeterminate). The default or unprogrammed state of all other options is "L".

2. Unused Cn, Im and Ps cells are normally programmed as Don't Care (-).

3. Unused product terms can be left blank (inactive) for future code modification.

PLC415-16

ERASURE CHARACTERISTICS (For Quartz Window Packages Only)

The erasure characteristics of the PLC415 Series devices are such that erasure begins to occur upon exposure to light with wavelengths shorter than approximately 4000 Angstroms (Å). It should be noted that sunlight and certain types of fluorescent lamps has wavelengths in the 3000 – 4000Å range. Data shows that constant exposure to room level fluorescent lighting could erase a typical PLC415 in approximately three years, while it would take

approximately one week to cause erasure when exposed to direct sunlight. If the PLC415 is to be exposed to these types of lighting conditions for extended periods of time, opaque labels should be placed over the window to prevent unintentional erasure.

The recommended erasure procedure for the PLC415 is exposure to shortwave ultraviolet light which has a wavelength of 2537 Angstroms (Å). The integrated dose (i.e., UV intensity × exposure time) for erasure should be a minimum of 15Wsec/cm². The erasure time with this dosage is approximately 30 to 35

minutes using an ultraviolet lamp with a 12,000μW/cm² power rating. The device should be placed within one inch of the lamp tubes during erasure. The maximum integrated dose a CMOS EPLD can be exposed to without damage is 7258Wsec/cm² (1 week @ 12000μW/cm²). Exposure of these CMOS EPLDs to high intensity UV light for longer

periods may cause permanent damage.

The maximum number of guaranteed erase/write cycles is 50. Data retention exceeds 20

Signetics

Document No.	853-0310				
ECN No.	97888				
Date of Issue	October 16, 1989				
Status	Product Specification				
Programmable Logic Devices					

DESCRIPTION

The PLS105and the PLS105A are bipolar Programmable Logic State machines of the Mealy type. They contain logic AND—OR gate arrays with user programmable connections which control the inputs of on-chip State and Output Registers. These consist respectively of 6 $\rm Q_P$, and 8 $\rm Q_F$ edge-triggered, clocked S/R flip-flops, with an Asynchronous Preset option. all flip-flops are unconditionally preset to "1" during power turn on.

The AND array combines 16 external inputs $I_0 - I_{15}$ with six internal inputs P_{0-5} , which are fed back from the State Registers to form up to 48 transition terms (AND terms). All transition terms can include True, False, or Don't Care states of the controlling variables, and are merged in the OR array to issue next-state and next-output commands to their respective registers on the Low-to-High transition of the Clock pulse. Both True and Complement transition terms can be generated by optional use of the internal input variable (C) from the Complement Array. Also, if desired, the Preset input can be converted to Output Enable function, as an additional user-programmable option.

Order codes are listed in the Ordering Information Table.

PLS105/A

Field-Programmable Logic Sequencers $(16 \times 48 \times 8)$


FEATURES

- PLS105 f_{MAX} = 13.9MHz
 - 20MHz clock rate
- PLS105A fMAX = 20MHz
- 25MHz clock rate
- Field-Programmable (Ni-Cr link)
- 16 input variables
- 8 output functions
- 48 transition terms
- 6-bit State Register
- 8-bit Output Register
- Transition complement array
- Positive edge-triggered clocked flip-flops
- Programmable Asynchronous Preset or Output Enable
- Power-on preset to all "1" of internal registers
- Power dissipation: 600mW (typ.)
- TTL compatible
- Single +5V supply
- 3-State outputs

APPLICATIONS

- Interface protocols
- Sequence detectors
- Peripheral controllers
- Timing generators
- Sequential circuits
- Elevator controllers
- · Security locking systems
- Counters
- Shift registers

PIN CONFIGURATIONS




Philips Components





PLS105/A

FUNCTIONAL DIAGRAM




PIN DESCRIPTION

PIN NO.	SYMBOL	NAME AND FUNCTION	POLARITY
1	CK	Clock: The Clock input to the State and Output Registers. A Low-to-High transition on this line is necessary to update the contents of both registers.	Active-High
2 - 8 20 - 27	I ₁ – I ₁₅	Logic Inputs: The 15 external inputs to the AND array used to program jump conditions between machine states, as determined by a given logic sequence.	Active-High/Low
9	I ₀	Logic/Diagnostic Input: A 16th external logic input to the AND array, as above, when exercised with standard TTL levels. When l_0 is held at +10V, device outputs F_{0-5} reflect the contents of State Register bits P_{0-5} . The contents each Output Register remains unaltered.	Active-High/Low
10 – 13 15 – 18	F ₀₋₇	Logic/Diagnostic Outputs: Eight device outputs which normally reflect the contents of Output Register bits Q_{0-7} , when enabled. When I_0 is held at +10V, $F_{0-5} = (P_{0-5})$, and $F_{6,7} = \text{Logic}$ "1".	Active-High
19	PR/OE	Preset or Output Enable Input: A user programmable function:	
		 Preset: Provides an Asynchronous Preset to logic "1" of all State and Output Register bits. Preset overrides Clock, and when held High, clocking is inhibited and F₀₋₇ are High. Normal clocking resumes with the first full clock pulse following a High-to-Low clock transition, after Preset goes Low. 	Active-High (H)
		Output Enable: Provides an Output Enable function to all output buffers F ₀₋₇ from the Output Register.	Active-Low (L)

PLS105/A

FPLS LOGIC DIAGRAM



PLS105/A

TRUTH TABLE 1, 2, 3, 4, 5, 6

	ОРТ	ION						
V _{cc}	PR	ŌE	l _o	CK	S	R	Q _{P/F}	F
	Н		*	X	X	Χ	Н	Н
	L		+10V	X	X	X	Qn	(Q _P) _n
	L		X	X	X	Χ	Qn	(Q _F) _n
		Н	*	X	X	X	Qn	Hi–Z
+5V		L	+10V	X	X	X	Qn	(Q _P) _n
		L	X	X	X	X	Qn	(Q _F) _n
		L	X	\uparrow	L	L	Qn	(Q _F) _n
		L	ı, X	\uparrow	L	Н	L	L
	,	L	X	\uparrow	Н	L	н	Н
		L	X	1	Н	Н	IND.	IND.
1	X	X	X	X	X	X	Н	

NOTES:

1. Positive Logic:

 $S/R = T_0 + T_1 + T_2 + ... + T_{47}$

 $T_n = C(I_0 \ I_1 \ I_2 \dots) \ (P_0 \ P_1 \dots P_5)$ 2. Either Preset (Active—High) or Output Enable (Active

- Either Preset (Active—High) or Output Enable (Active—Low) are available, but not both. The
 desired function is a user—programmable option.
- 3. ↑ denotes transition from Low-to-High level.
- 4. R = S = High is an illegal input condition.
- 5. * = H or L or +10V.
- 6. X = Don't Care (<5.5V).

ORDERING INFORMATION

DESCRIPTION	ORDER CODE
28-Pin Plastic DIP (600mil-wide)	PLS105N, PLS105AN
28-Pin Plastic Leaded Chip Carrier	PLS105A, PLS105AA


ABSOLUTE MAXIMUM RATINGS¹

		RATI	NGS	
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage		+7	V _{DC}
V _{IN}	Input voltage		+5.5	V _{DC}
V _{OUT}	Output voltage		+5.5	V _{DC}
I _{IN}	Input currents	-30	+30	mA
I _{OUT}	Output currents		+100	mA
T _A	Operating temperature range	0	+75	°C
T _{STG}	Storage temperature range	-65	+150	°C

NOTES:

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

LOGIC FUNCTION



VIRGIN STATE

The factory shipped virgin device contains all fusible links intact, such that:

- PR/OE option is set to PR. Thus, all outputs will be at "1", as preset by initial power-up procedure.
- 2. All transition terms are disabled (0).
- 3. All S/R flip-flop inputs are disabled (0).
- The device can be clocked via a Test Array pre-programmed with a standard test pattern.

NOTE: The Test Array pattern MUST be deleted before incorporating a user program. This is accomplished automatically by any Signetics qualified programming equipment.

THERMAL RATINGS

TEMPERATURE	
Maximum junction	150°C
Maximum ambient	75°C
Allowable thermal rise ambient to junction	75°C

PLS105/A

DC ELECTRICAL CHARACTERISTICS 0° C \leq T_A \leq +75 $^{\circ}$ C, 4.75V \leq V_{CC} \leq 5.25V

				LIMITS		
SYMBOL	PARAMETER	TEST CONDITION	Min	Typ1	Max	UNIT
Input volt	age ²			1		
V _{IH}	High	V _{CC} = Max	2.0			V
V _{IL}	Low	V _{CC} = Min	-		0.8	V
V _{IC}	Clamp ³	$V_{CC} = Min, I_{IN} = -12mA$		-0.8	-1.2	V
Output vo	oltage ²					
		V _{CC} = Min				
V_{OH}	High⁴	$I_{OH} = -2mA$	2.4			V
V _{OL}	Low ⁵	I _{OL} = 9.6mA		0.35	0.45	V
Input cur	rent	-				
I _{IH}	High	V _{IN} = 5.5V		<1	25	μА
I _{IL}	Low	V _{IN} = 0.45V		-10	-100	μА
$I_{\rm IL}$	Low (CK input)	V _{IN} = 0.45V		-50	-250	μА
Output cu	ırrent				•	
		V _{CC} = Max				
I _{O(OFF)}	Hi-Z state ⁶	V _{OUT} = 5.5V		1 -	40	μА
		V _{OUT} = 0.45V		-1	-40	μА
Ios	Short circuit ^{3, 7}	V _{OUT} = 0V	-15		-70	mA
Icc	V _{CC} supply current ⁸	V _{CC} = Max		120	180	mA
Capacita	nce ⁶			-		
		V _{CC} = 5.0V				
CIN	Input	$V_{IN} = 2.0V$		8		pF
C _{OUT}	Output	V _{OUT} = 2.0V		10		pF

- 1. All typical values are at $V_{CC} = 5V$, $T_A = +25^{\circ}C$.
- 2. All voltage values are with respect to network ground terminal.
- 3. Test one at a time.
- 4. Measured with V_{IL} applied to \overline{OE} and a logic high stored, or with V_{IH} applied to PR.
- 5. Measured with a programmed logic condition for which the output is at a low logic level, and V_{IL} applied to PR/OE Output sink current is supplied through a resistor to V_{CC}.

 6. Measured with V_{IH} applied to PR/OE.
- 7. Duration of short circuit should not exceed 1 second.
- 8. I_{CC} is measured with the PR/OE input grounded, all other inputs at 4.5V and the outputs open.


PLS105/A

AC ELECTRICAL CHARACTERISTICS R₁ = 470Ω, R₂ = 1kΩ, C₁ = 30pF, 0°C ≤ T_A ≤ +75°C, 4.75V ≤ V_{CC} ≤ 5.25V


						LIM	IITS			
SYMBOL	PARAMETER	FROM	то		PLS105			PLS105A	١	UNIT
				Min	Typ ¹	Max	Min	Typ1	Max	
Pulse wid	dth									
t _{CKH}	Clock ² High	CK+	CK-	25	15		20	15		ns
t _{CKL}	Clock Low	CK-	CK+	25	15		20	15		ns
t _{CKP1} B	Period (without Complement Array)	Output +/-	Input +/-	80	40		50	40		ns
t _{CKP2} B	Period (with Complement Array)	Output +/-	Input +/-	120	60		80	50		ns
t _{PRH}	Preset pulse	PR+	PR-	25	15		25	15		ns
Setup tin	ne ³									
t _{IS1} A	Input	Input ±	CK+	60			40			ns
t _{IS1} B	Input	Input ±	CK+	50			30			ns
t _{IS1} C	Input	Input ±	CK+	42			N/A			ns
t _{IS2} A	Input (through Complement Array)	Input ±	CK+	90			70			ns
t _{IS2} B	Input (through Complement Array)	Input	CK+	80			60			ns
t _{IS2} C	Input (through Complement Array)	Input	CK+	72			N/A			ns
t _{VS}	Power–on preset	V _{CC} +	CK -	0	-10		0	-10		ns
tprs	Preset	PR –	CK-	0	-10		0	-10		ns
Hold time	9									
t _{IH}	Input	CK+	Input ±	5	-10		5	-10		ns
Propagat	tion delay									
t _{CKO}	Clock	CK+	Output ±		15	30		15	20	ns
toE	Output enable	OE -	Output -		20	30		20	30	ns
t _{OD}	Output disable	OE +	Output +		20	30		20	30	ns
t _{PR}	Preset	PR +	Output +		18	30		18	30	ns
t _{PPR}	Power-on preset	V _{CC} +	Output +		0	10		0	10	ns
Frequenc	cy of operation ³									
f _{MAX} C	Without Complement Array				-	13.9			20.0	MHz
f _{MAX} C	With Complement Array					9.8			12.5	MHz

- 1. All typical values are at $V_{CC}=5V$, $T_A=+25^{\circ}C$. 2. To prevent spurious clocking, clock rise time $(10\%-90\%)\leq 30$ ns. 3. See "Speed vs. OR Loading" diagrams.

TEST LOAD CIRCUIT




VOLTAGE WAVEFORMS



PLS105/A

TIMING DIAGRAMS




TIMING DEFINITIONS

SYMBOL	PARAMETER
t _{CKH}	Width of input clock pulse.
t _{CKL}	Interval between clock pulses.
t _{CKP1}	Clock period — when not using Complement array.
t _{IS1}	Required delay between beginning of valid input and positive transition of clock.
t _{CKP2}	Clock period — when using Complement array.
t _{IS2}	Required delay between beginning of valid input and positive transition of Clock, when using optional Complement Array (two passes necessary through the AND array).
t _{VS}	Required delay between V _{CC} (after power–on) and negative transition of Clock preceding first reliable clock pulse.
t _{PRS}	Required delay between negative transition of Asynchronous Preset and negative transition of Clock preceding first reliable clock pulse.
t _{IH}	Required delay between positive transition of Clock and end of valid input data.
t _{CKO}	Delay between positive transition of clock and when outputs become valid (with PR/OE Low).
toE	Delay between beginning of Output Enable Low and when outputs become valid.
t _{OD}	Delay between beginning of Output Enable High and when outputs are in the OFF–State.
t _{SRE}	Delay between input I ₀ transition to Diagnostic mode and when the outputs reflect the contents of the State Register.
t _{SRD}	Delay between input I ₀ transition to Logic mode and when the outputs reflect the contents of the Output Register.
t _{PR}	Delay between positive transition of Preset and when outputs become valid at "1".
t _{PPR}	Delay between V _{CC} (after power-on) and when outputs become preset at "1".
t _{PRH}	Width of preset input pulse.
f _{MAX}	Maximum clock frequency.

October 16, 1989 300

PLS105/A

TIMING DIAGRAMS (Continued)



SPEED VS. "OR" LOADING

The maximum frequency at which the PLS can be clocked while operating in *sequential mode* is given by:


$$(1/f_{MAX}) = t_{CY} = t_{IS} + t_{CKO}$$

This frequency depends on the number of transition terms T_n used. Having all 48 terms connected in the AND array does not appreciably impact performance; but the number of terms connected to each OR line affects t_{iS} , due to capacitive loading. The effect of this loading can be seen in Figure 1, showing the variation of t_{iS1} with the number of terms connected per OR.

The PLS105 AC electrical characteristics contain three limits for the parameters t_{IS1} and t_{IS2} (refer to Figure 1). The first, t_{IS1A} is guaranteed for a device with 48 terms connected to any OR line. t_{IS1B} is guaranteed for a device with 32 terms connected to any OR line. And t_{IS1C} is guranteed for a device with 24 terms connected to any OR line.

The three other entries in the AC table, $t_{\rm IS2}$ A, B, and C are corresponding 48, 32, and 24 term limits when using the on–chip Complement Array.

The PLS105A AC electrical characteristics contain two limits for the parameters $t_{\rm IS1}$ and $t_{\rm IS2}$ (refer to Figure 2). The first, $t_{\rm IS1A}$ is guaranteed for a device with 24 terms connected to any OR line. $t_{\rm IS1B}$ is guaranteed for a device with 16 terms connected to any OR line.



Terms/OR Connected




Figure 2. PLS105A t_{IS1} vs. Terms/OR Connected

The two other entries in the AC table, $t_{\rm IS2}$ A and B are corresponding 24 and 16 term limits when using the on-chip Complement Array.

The worst case of $t_{\rm IS}$ for a given application can be determined by identifying the OR line with the maximum number of T_n connections. This can be done by referring to the interconnect pattern in the PLS logic diagram, typically illustrated in Figure 3, or by counting the maximum number of "H" or "L" entries in one of the columns of the device Program Table.

This number plotted on the curve in Figure 1 or 2 will yield the worst case $t_{\rm IS}$ and, by implication, the maximum clocking frequency for reliable operation.

Note that for maximum speed all UNUSED transition terms should be disconnected from the OR array.




Figure 3. Typical OR Array Interconnect Pattern

PLS105/A


LOGIC PROGRAMMING

PLS105/A logic designs can be generated using Signetics AMAZE PLD design software or one of several other commercially available, JEDEC standard PLD design software packages. Boolean and/or state equation entry is accepted.

PLS105/A logic designs can also be generated using the program table entry format detailed on the following pages. This program table entry format is supported by the Signetics AMAZE PLD design software (PTP module). AMAZE is available free of charge to qualified users.

To implement the desired logic functions, the state of each logic variable from logic equations (I, B, O, P, etc.) is assigned a symbol. The symbols for TRUE, COMPLEMENT, INACTIVE, PRESET, etc., are defined below.


PRESET/OE OPTION - (P/E)




PROGRAMMING:

The PLS105/A has a power—up preset feature. This feature insures that the device will power—up in a known state with all register elements (State and Output Register) at logic High (H). When programming the device it is important to realize this is the initial state of the device. You *must* provide a next state jump if you do not wish to use all Highs (H) as the present state.


"AND" ARRAY - (I), (P)



"OR" ARRAY - (N), (F)



"COMPLEMENT" ARRAY - (C)



NOTES

- 1. This is the initial unprogrammed state of all links.
- 2. Any gate T_n will be unconditionally inhibited if both the true and complement of any input (I or P) are left intact.
- To prevent simultaneous Set and Reset flip-flop commands, this state is not allowed for N and F link pairs coupled to active gates T_n (see flip-flop truth tables).
- To prevent oscillations, this state is not allowed for C link pairs coupled to active gates T_n.

PLS105/A

PROGRAM TABLE ENTRIES **FPLS PROGRAM TABLE** AND OR CUSTOMER NAME INACTIVE 0 INACTIVE 0 PURCHASE ORDER# _ GENERATE SET Cn SIGNETICS DEVICE# __ PROPAGATE RESET L CUSTOMER SYMBOLIZED PART # _ TRANSPARENT NO CHANGE TOTAL NUMBER OF PARTS _ INACTIVE 0 OPTION PROGRAM TABLE_ н lm. Ps REV PRESET H L DIE ŌĒ DATE DON'T CARE OPTION (P/E) NEXT STATE (Ns) OUTPUT (Fri INPUT (Im) PRESENT STATE (Ps) REMARKS 7 6 5 4 3 2 1 0 1 ı. 8 1 1 . . 33 34 35 36 1 . 45 46 47 PIN 1 1 6 2 8 NO. VARIABLE NAME

- NOTES:

 1. The FPLS is shipped with all links initially intact. Thus, a background of "0" for all Terms, and an "H" for the P/E option, exits in the table, shown BLANK instead for clarity.

 2. Unused C_n, I_m, and P_s bits are normally programmed Don't Care (-).

 3. Unused Transition Terms can be left blank for future code modification, or programmed as (-) for maximum speed.

 4. Letters in variable fields are used as identifiers by logic type programmers.


PLS105/A


TEST ARRAY

The FPLS may be subjected to AC and DC parametric tests prior to programming via an on-chip test array.

The array consists of test transition terms 48 and 49, factory programmed as shown below.

Testing is accomplished by clocking the FPLS and applying the proper input sequence to ${\rm I}_{0.15}$ as shown in the test circuit timing diagram.






FPLS Under Test

TEST ARRAY PROGRAM

-	-											Α	ND											
	Ė										1	NPL	T (Ir	n)					PR	ESE	NT	STA	TE (Ps)
	M	С	1	1	1	1	1	1	L															
			5	4	3	2	1	0	9	8	7	6	5	4	3	2	1	0	5	4	3	2	1	0
	48	А	н	н	н	н	н	н	н	н	н	н	н	н	н	н	н	н	н	н	н	н	н	н
	49	•	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L

				(OPT	ON	(P/E	Ξ)					н	
						OR								
-	NEX	T ST	ATE	(Ns)	OUTPUT (Fr)								
5	4	3	2	1	0	7	6	5	4	3	2	1	0	
L	L	L	L	L	L	L	L	L	L	L	L	L	L	
Н	н	н	н	н	н	н	н	н	н	н	н	н	н	

Test Array Program



Both terms 48 and 49 must be deleted during user programming to avoid interfering with the desired logic function. This is accomplished automatically by any of Signetics' qualified programming equipment.

TEST ARRAY DELETED

т.												AND											
E											INP	UT (m)					PRESENT STATE (Ps)					
R	С	1	1	1	1	1	1																
100		5	4	3	2	1	0	9	8	7	6	5	4	3	2	1	0	5	4	3	2	1	0
48	_	н	н	н	н	н	н	н	н	н	н	н	н	н	н	н	н	н	н	н	н	н	н
49	•	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L

	OPTION (P E)														
						OR									
-	NEX	TST	ATE	(Ns)	OUTPUT (Fr)									
	Τ	Γ.	2	T-	0	7	6	5	17-	3	2	T.	0		
5	4	3	~		-	,	0	5	-	3	2	1	O		
-	-		_	-	-	-	_	-	-	_	_	-	_		

Test Array Deleted

TB01750S

Signetics

Document No.	853–1351
ECN No.	97355
Date of Issue	August 11, 1989
Status	Product Specification
Programmable	Logic Devices

DESCRIPTION

The PLUS105–40 is a bipolar programmable state machine of the Mealy type. Both the AND and the OR array are user–programmable. All 48 AND gates are connected to the 16 external dedicated inputs (I_0 - I_{15}) and to the feedback paths of the 6 buried State Registers (Q_{P0} - Q_{P5}). Because the OR array is programmable, any one or all of the 48 transition terms can be connected to any or all of the State and Output Registers.

All state transition terms can include True, False and Don't Care states of the controlling state variables. A Complement Transition Array supports complex IF THEN ELSE state transitions with a single product term.

All buried State and Output registers are edge-triggered S-R flip-flops. Asynchronous Preset/Output Enable functions are available.

To facilitate testing of state machine designs, diagnostic mode features for register preset and buried state register observability have been incorporated into the PLUS105–40 device architecture.

Ordering codes are listed in the Ordering Information Table.

PLUS105-40

Field-Programmable Logic Sequencer $(16 \times 48 \times 8)$


FEATURES

- Functionally equivalent to, but faster than TI105BC and AmPLS105-37
- 300 and 600mil-wide Plastic DIP packages
- 50MHz clock rate
- 40MHz operating frequency
- Field-Programmable (TiW link)
- 16 input variables
- 8 output functions
- 48 transition terms
- 6-bit State Register
- 8-bit Output Register
- Transition complement array
- Positive edge-triggered clocked flip-flops
- · Security fuse
- Programmable Asynchronous Preset or Output Enable
- Power-on preset to all "1" of internal registers
- . Power dissipation: 800mW (typ.)
- TTL compatible
- Single +5V supply
- 3-State outputs

APPLICATIONS

- Interface protocols
- · Sequence detectors
- · Peripheral controllers
- Timing generators
- Sequential circuits
- · Elevator controllers
- · Security Locking systems
- Counters
- Shift registers

PIN CONFIGURATIONS




Philips Components





FUNCTIONAL DIAGRAM



PIN DESCRIPTION

PIN NO.	SYMBOL	NAME AND FUNCTION	POLARITY
1	СК	Clock: The Clock input to the State and Output Registers. A Low-to-High transition on this line is necessary to update the contents of both registers.	Active- High (H)
2-9, 26, 27 20-22	l ₀ - l ₉ , l ₁₃ - l ₁₅	Logic Inputs: The 13 external inputs to the AND array used to program jump conditions between machine states, as determined by a given logic sequence. True and complement signals are generated via use of "H" and "L".	Active-High/ Low (H/L)
23	I ₁₂	Logic/Diagnostic Input : A 14th external logic input to the AND array, as above, when exercising standard TTL levels. When I_{12} is held at +10V, device outputs F_0 - F_5 reflect the contents of State Register bits P_0 - P_5 . The contents of each Output Register remains unaltered.	Active-High/ Low (H/L)
24	I ₁₁	Logic/Diagnostic Inputs: A 15th external logic input to the AND array, as above, when exercising standard TTL levels. When I_{11} is held at +10V, device outputs F_0 - F_5 become direct inputs for State Register bits P_0 - P_5 ; a Low-to-High transition on the appropriate clock line loads the values on pins F_0 - F_5 into the State Register bits P_0 - P_5 . The contents of each Output Register remains unaltered.	Active-High/ Low (H/L)
25	l ₁₀	Logic/Diagnostic Input: A 16th external logic input to the AND array, as above, when exercising standard TTL levels. When I_{10} is held at +10V, device outputs F_0 - F_7 become direct inputs for Output Register bits Q_0 - Q_7 ; a Low-to-High transition on the appropriate clock line loads the values on pins F_0 - F_7 into the Output Register bits Q_0 - Q_7 . The contents of each State Register remains unaltered.	Active-High/ Low (H/L)
10-13 15-18	F ₀ - F ₇	Logic Outputs/Diagnostic Outputs/Diagnostic Inputs : Eight device outputs which normally reflect the contents of Output Register bits Q_0 - Q_7 , when enabled. When I_{12} is held at +10V, F_0 - F_5 = $(P_0$ - $P_5)$. When I_{11} is held at +10V, F_0 - F_5 become inputs to State Register bits P_0 - P_5 . When I_{10} is held at +10V, F_0 - F_7 become inputs to Output Register bits Q_0 - Q_7 .	Active- High (H)
19	PR/OE	Preset or Output Enable Input: A user programmable function:	
		 Preset: Provides an asynchronous preset to logic "1" of all State and Output Register bits. PR overrides Clock, and when held High, clocking is inhibited and F₀ - F₇ are High. Normal clocking resumes with the first full clock pulse following a High-to-Low clock transition, after the Preset signal goes low. See timing definitions. 	Active- High (H)
		 Output Enable: Provides an output enable function to buffers F₀ - F₇ from the Output Registers. 	Active- Low (L)

306

August 11, 1989

PLUS105-40

TRUTH TABLE 1, 2, 3, 4, 5, 6, 7

	ОРТ	ION									
V _{cc}	PR	ŌE	I ₁₀	I ₁₁	I ₁₂	CK	S	R	Q _P	Q _F	F
	Н		*	*	*	Х	X	Х	Н	Н	Q _F
	L		+10V	X	X	\uparrow	X	X	Qp	L	L
	L		+10V	X	X	$\uparrow \uparrow$	X	×	Qp	н	н
	L		×	+10V	X	\uparrow	X	X	L	QF	L
	L		×	+10V	X	\uparrow	X	X	н	QF	Н
	L		×	X	+10V	X	X	X	Q _P	QF	Q _P
	L		×	X	X	X	X	X	Q _P	Q _F	Q _F
		Н	×	X	*	X	X	X	Q _P	Q _F	Hi-Z
+5V		×	+10V	X	X	\uparrow	X	X	Qp	L	L
		×	+10V	X	X	1	X	X	Q _P	н	Н
		×	×	+10V	X	\uparrow	X	×	L	Q _F	L
		×	×	+10V	×	\uparrow	X	X	н	QF	Н
		L	×	X	+10V	X	X	X	Q _P	QF	Q _P
	1 2	L	×	X	X	X	X	X	Q _P	QF	Q _F
		L ·	×	X	X	\uparrow	L	L	Q _P	Q _F	Q _F
		L	×	X	X	1	L	Н	L	L	L
		L	×	Χ	X	\uparrow	Н	L	н	н	Н
		L	Х	X	X	\uparrow	Н	Н	IND.	IND.	IND.
1	×	Х	X	X	X	Χ	Х	Χ	н	H	N. A.

NOTES:

1. Positive Logic:

 $S/R (or J/K) = T_0 + T_1 + T_2 + ... T_{48}$

 $T_n = (C_0, C_1) (I_0, I_1, I_2, ...) (P_0, P_1, ...P_5)$


- 2. Either Preset (Active High) or Output Enable (Active Low) are available, but not both. The desired function is a user-programmable option.
- 3. The denotes transition from Low-to-High level.
- 4. * = H or L or +10V
- 5. X = Don't Care (≤ 5.5V)
- When using the F_n pins as inputs to the State and Output Registers in diagnostic mode, the F buffers are 3-stated and the indicated levels on the output pins are forced by the user.
- 7. IND. = Indeterminent

VIRGIN STATE

A factory-shipped virgin device contains all fusible links intact, such that:

- PR/OE option is set to PR. Note that even if the PR function is not used, all registers are preset to "1" by the power-up procedure.
- 2. All transition terms are disabled (0).
- 3. All S/R flip-flop inputs are disabled (0).
- The device can be clocked via a Test Array preprogrammed with a standard test pattern. NOTE: The Test Array pattern must be deleted before incorporating a user program.

FPLS LOGIC DIAGRAM



Field-Programmable Logic Sequencer (16 × 48 × 8)

PLUS105-40

ORDERING INFORMATION

DESCRIPTION	ORDER CODE
28-pin Plastic Dual-In-Line, 600mil-wide	PLUS105-40N
28-pin Plastic Dual-In-Line, 300mil-wide	PLUS105-40N3
28-pin Plastic Leaded Chip Carrier, 450mil-square	PLUS105-40A

THERMAL RATINGS


TEMPERATURE											
Maximum junction	150°C										
Maximum ambient	75°C										
Allowable thermal rise ambient to junction	75°C										

ABSOLUTE MAXIMUM RATINGS¹

		RATI		
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage		+7	V _{DC}
V _{IN}	Input voltage		+5.5	V _{DC}
V _{OUT}	Output voltage		+5.5	V _{DC}
I _{IN}	Input currents	-30	+30	mA
I _{OUT}	Output currents		+100	mA
T _A	Operating temperature range	0	+75	°C
t _{STG}	Storage temperature range	-65	+150	°C

NOTE:

LOGIC FUNCTION



Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those
indicated in the operational and programming specification of the device is not implied.

PLUS105-40

DC ELECTRICAL CHARACTERISTICS $0^{\circ}C \le T_{A} \le 75^{\circ}C$, $4.75V \le V_{CC} \le 5.25V$

			1 7 7	LIMITS			
SYMBOL	PARAMETER	TEST CONDITION	Min	Typ1	Max	UNIT	
Input volta	ge ²						
V _{IH}	High	V _{CC} = Max	2.0			V	
V_{IL}	Low	V _{CC} = Min			0.8	V	
V_{IC}	Clamp ³	$V_{CC} = Min, I_{IN} = -12mA$		-0.8	-1.2	V	
Output vol	tage ²						
	4	V _{CC} = Min					
V_{OH}	High	$I_{OH} = -2mA$	2.4			V	
V _{OL}	Low	I _{OL} = 9.6mA		0.35	0.45	. V	
Input curre	nt						
		V _{CC} = Max					
I _{IH}	High	$V_{IN} = V_{CC}$		<1	25	μА	
I _{IL}	Low	$V_{IN} = 0.45V$		-20	-250	μА	
Output cur	rent				-		
		V _{CC} = Max					
I _{O(OFF)}	Hi-Z state	V _{OUT} = 5.5V		1	40	μΑ	
		V _{OUT} = 0.45V		-1	-40	μΑ	
los	Short circuit ^{3, 4}	V _{OUT} = 0V	-15		-70	μΑ	
Icc	V _{CC} supply current ⁵	V _{CC} = Max		160	200	mA	
Capacitano	e	-	•			***************************************	
		V _{CC} = 5.0V		7.4	1		
CIN	Input	$V_{IN} = 2.0V$		8		pF	
Cout	Output	$V_{OUT} = 2.0V$		10		pF	

NOTES

- 1. All typical values are at $V_{CC} = 5V$, $T_A = +25^{\circ}C$.
- 2. All voltage values are with respect to network ground terminal.
- 3. Test one at a time.
- 4. Duration of short circuit should not exceed 1 second.
- 5. I_{CC} is measured with the PR/OE input grounded, all other inputs at 4.5V and the outputs open.

PLUS105-40

$\textbf{AC ELECTRICAL CHARACTERISTICS} \ R_1 = 470\Omega, \ R_2 = 1k\Omega, \ C_L = 30pF, \ 0^{\circ}C \leq \ T_A \leq +75^{\circ}C, \ 4.75V \leq V_{CC} \leq 5.25V$


					LIMITS			
SYMBOL	PARAMETER	FROM	то	Min	Typ1	Max	UNIT	
Pulse Width		1		-				
t _{CKH}	Clock High	CK+	CK-	10	8		ns	
t _{CKL}	Clock Low	CK-	CK+	10	8		ns	
t _{CKP1}	Period (without Complement Array)	Input ±	Output ±	25	20		ns	
t _{CKP2}	Period (with Complement Array)	Input ±	Output ±	35	28		ns	
t _{PRH}	Preset pulse	PR+	PR -	15	8		ns	
Setup Time			-		•			
t _{IS1}	Input	Input ±	CK+	15	12		ns	
t _{IS2}	Input (through Complement Array)	Input ±	CK+	25	20		ns	
t _{VS}	Power-on preset	V _{CC} +	CK-	0	-10		ns	
tPRS	Clock resume (after preset)	PR-	CK-	0	-5		ns	
t _{NVCK}	Clock lockout (before preset)	CK-	PR-	15	5		ns	
Hold Time								
t _{IH}	Input	CK+	Input ±	5	-10		ns	
Propagation	Delay ³							
tско	Clock	CK+	Output ±		8	10	ns	
toe	Output enable	OE -	Output –		8	10	ns	
top	Output disable ²	OE +	Output +		8	10	ns	
t _{PR}	Preset	PR+	Output +		15	20	ns	
t _{PPR}	Power-on preset	V _{CC} +	Output +		0	10	ns	
Frequency o	of Operation							
f _{MAX}	Without Complement Array	Input ±	Output ±	40.0	50.0		MHz	
f _{MAX}	With Complement Array	Input ±	Output ±	28.5	35.7		MHz	
f _{CLK}	Clock period	CK+	CK+	50.0	62.5		MHz	

NOTES:


^{1.} All typical values are at $V_{CC}=5V$, $T_A=+25^{\circ}C$. 2. $C_L=5pF$; $V_T=V_{OL}+0.5V$. 3. Propagation delays measured with all outputs switching.

PLUS105-40

TIMING DIAGRAMS



TIMING DIAGRAMS (Continued)




TIMING DEFINITIONS

SYMBOL	PARAMETER
t _{CKH}	Width of input clock pulse
t _{CKL}	Interval between clock pulses.
t _{CKP2}	Operating period — when using Complement Array.
t _{IS1}	Required delay between begin- ning of valid input and positive transition of Clock.
t _{IS2}	Required delay between begin- ning of valid Input and positive transition of Clock, when using optional Complement Array (two passes necessary through the AND Array).
t _{VS}	Required delay between V _{CC} (after power-on) and negative transition of Clock preceding first reliable clock pulse.
t _{PRS}	Required delay between negative transition of Asynchronous Preset and the first positive transition of Clock.


SYMBOL	PARAMETER
t⊪	Required delay between positive transition of Clock and end of valid Input data.
t _{CKO}	Delay between positive transition of Clock and when Outputs become valid (with PR/OE Low).
toE	Delay between beginning of Output Enable Low and when Outputs become valid.
top	Delay between beginning of Output Enable High and when Outputs are in the OFF-state.
t _{SRE}	Delay between input I ₁₂ transition to Diagnostic Mode and when the Outputs reflect the contents of the State Register.
t _{SRD}	Delay between input I ₁₂ transition to Logic mode and when the Outputs reflect the contents of the Output Register.

SYMBOL	PARAMETER
t _{CKP1}	Operating period — without the Complement Array.
tpR	Delay between positive transition of Preset and when Outputs become valid at "1".
tppR	Delay between V _{CC} (after) power-on) and when Outputs become preset at "1".
t _{PRH}	Width of preset input pulse.
f _{MAX}	Min. guaranteed operating frequency.
tnvck	Required delay between the negative transition of the clock and the negative transition of the Asynchronous PRESET to guarantee that the clock edge is not detected as a valid negative transition.

TIMING DIAGRAMS (Continued)



TEST LOAD CIRCUITS



LOGIC PROGRAMMING

PLUS105-40 logic designs can be generated using Signetics AMAZE PLD design software or one of several other commercially available, JEDEC standard PLD design software packages. Boolean and/or state equation entry is accepted.

PLUS105-40 logic designs can also be generated using the program table entry format detailed on the following pages. This program table entry format is supported by the Signetics AMAZE PLD design software (PTE module). AMAZE is available free of charge to qualified users


To implement the desired logic functions, the state of each logic variable from logic equations (I, B, O, P, etc.) is assigned a symbol. The symbols for TRUE, COMPLEMENT, INACTIVE, PRESET, etc., are defined below.

PROGRAMMING THE

PLUS 105-40


The PLUS105-40 has a power-up preset feature. This feature insures that the device will power-up in a known state with all register elements (state and output register) at a logic High (H). When programming the device it is important to realize this is the initial state of the device. You must provide a next state jump if you do not wish to use all Highs (H) as the present state.

VOLTAGE WAVEFORMS




PLUS105-40


PRESET/OE OPTION - (P/E)




"AND" ARRAY - (I), (P)



"OR" ARRAY - (N), (F)



"COMPLEMENT" ARRAY - (C)



NOTES:

- 1. This is the initial unprogrammed state of all link pairs. It is normally associated with all unused (inactive) AND gates T_n .
- 2. Any gate Tn will be unconditionally inhibited if both the true and complement fuses of any input (I,P) are left intact.
- To prevent simultaneous Set and Reset flip-flop commands, this state is not allowed for N and F link pairs coupled to active gates T_n (see flip-flop truth tables).
- 4. To prevent oscillations, this state is not allowed for C link pairs coupled to active gates T_n.

PLUS105-40

FPLS PROGRAM TABLE

PROGRAM TABLE ENTRIES

	CUSTOMER NAME											I	AND						OR																		
	PURCHASE ORDER #													IN	ACTIVE	. 0			- !	10	ACT	IVE	ĭ	0	1												
	SIC	7		100	0	700	en er	# . #					E	(YY	/YY	1		-		_		1	GI	ENERATE	A		Cn	į.	S	ET		1	н			_	
																				-			PF	ROPAGATE				1	R	ESE	Γ	1	Ł	1	Ns,	Fr	
	CUSTOMER SYMBOLIZED PART#													TF	RANSPARENT	-			1	N	0 CF	ANC	E	_													
	TOTAL NUMBER OF PARTS													TH.	NACTIVE	0			-				0 D	Ŧ.ō													
	PROGRAM TABLE												_	-	Н	Im	, Ps	ŀ				OP	110	PN .													
	RE	٧		_			_													_			ī	P	L		,	i			SET H						
	DA	TE	_																	_			0	ON'T CARE	\exists			- 1		ŌΕ		1	.]		* //	-	- 1
-																					OPTI	ON (P/E)			_	1	$\overline{}$									
	AND INPUT (Im) PRESENT STATI																						(R													
E R M	-	7.1	-11	-	71	-	73																	REMARK	S	"	EXT	STA	TE (N	(8)			OU	TPU	(Fr)	
R M	Cn	5	4	3	2	1	0	9	8	7	6	5	4	3	2	1	0	5	4	3	2	1	0			5	4	3	2 1	To	7	6	5	4	3	2 1	To
0		-	_		-		-	_			-	-	-		-	-	\dashv	Н				\vdash	Н			\vdash	+	+	+	+	Н	-	-	÷	+	+	+
2												\Rightarrow																1	1	1			-	-	#	1	
3																												1	1					+	\pm		\pm
6		-			-	-	-	_			-	-	-	-	-	-	-	Н		-		\vdash	\vdash			\vdash	\rightarrow	+	+	+	\vdash	\vdash	-	- 10	+	+	+
7		_			=																							+	+	1				-	#	-	
9					=								7																					-	1		
10		-		-	-		-	_	-		-		-		-	_	-	H	-		\vdash		-	-		\vdash	-		+	+	Н		-	÷	+	+	+
12			-		_								-				_												1					-	#		
14																												+	\pm					- 1	1		
15		-			-	-		_						_		_	_									\vdash			-	+				-	+	+	\vdash
17					=								_	_														\Rightarrow		1					#	1	
18					-					- 1		-					_		1							+								-	+	+	+
20			_		7								-			_	_	H	-				=			-		-					-	_	+	-	\vdash
21																																		-	#	\pm	
23													-				-	Н	-	-						+		+	-	+	\vdash			÷	+	+	+-
24 25 26					-	-			-!				_							-			=			\vdash				-					7	-	
27																														1				ī	#		
28	-	-	-	-	-	-	-	_	-	Н	\dashv	-	-	-	_	_	-	Н	-	-	-	-	\vdash			╁	-	-	-	+	\vdash			+	+	+	+
30					=								_																-	-					#	1	
31 32																														+-				-	\pm	1	\Box
33 34		-	_		-		-		_		-		7					H					\Box			F		_	-		F			-	+	-	+
35 36		_							_!																										#	1	\Box
36 37 38													-				-	H					Н			+					\vdash			Ť	- 1		
38		-																					\Box			-		-	-	-				-	-	-	=
40					=					-																		1	1						\pm	+	
41		-			-	-	-	_	_	-	-				-	_	_	H	-		-		Н			╁		-	+	+	\vdash			-	+	+	+
43		_			_																		\Box					_	1	-					#		\Box
45					7													E																+	#		\pm
46				-	-		-	_					-		-		_	-	-	-			\vdash			\vdash		-	+	+	\vdash			-	-	+	+
PII		2	2	2 2	2	2 4	2 5	2	2 7	2	3	4	5	6	7	8	9									-					1 0	1	1 2	1 3	1 1	1 1	
VARIABLE	NAME																																				

- 1. The FPLS is shipped with all links initially intact. Thus, a background of "0" for all Terms, and an "H" for the P/E option, exists in the table, shown BLANK instead for clarity.

 2. Unused C_n, I_m, and P_s bits are normally programmed Don't Care (-).

 3. Unused Transition Terms can be left blank for future code modification, or programmed as (-) for maximum speed.

- 4. Letters in variable fields are used as identifiers by logic type programmers.

Signetics

Document No.	
ECN No.	
Date of Issue	November 1989
Status	Preliminary Specification
Programmable	Logic Devices

DESCRIPTION

The PLUS105–55 is a bipolar programmable state machine of the Mealy type. Both the AND and the OR array are user–programmable. All 48 AND gates are connected to the 16 external dedicated inputs (I_0 - I_{15}) and to the feedback paths of the 6 buried State Registers (Q_{P0} - Q_{P5}). Because the OR array is programmable, any one or all of the 48 transition terms can be connected to any or all of the State and Output Registers.

All state transition terms can include True, False and Don't Care states of the controlling state variables. A Complement Transition Array supports complex IF THEN ELSE state transitions with a single product term

All buried State and Output registers are edge-triggered S-R flip-flops. Asynchronous Preset/Output Enable functions are available.

To facilitate testing of state machine designs, diagnostic mode features for register preset and buried state register observability have been incorporated into the PLUS105–55 device architecture.

Ordering codes are listed in the Ordering Information Table.

PLUS105-55

Field-Programmable Logic Sequencer $(16 \times 48 \times 8)$


FEATURES

- Functionally equivalent to, but faster than TI105BC and AmPLS105-37
- 62.5MHz clock rate
 - 55MHz operating frequency
- Available in 300 and 600mil—wide Plastic DIP packages
- Field-Programmable (TiW link)
- 16 input variables
- 8 output functions
- 48 transition terms
- 6-bit State Register
- 8-bit Output Register
- Transition complement array
- Positive edge-triggered clocked flip-flops
- · Security fuse
- Programmable Asynchronous Preset or Output Enable
- Power-on preset to all "1" of internal registers
- · Power dissipation: 800mW (typ.)
- TTL compatible
- Single +5V supply
- 3-State outputs

APPLICATIONS

- Interface protocols
- Sequence detectors
- · Peripheral controllers
- Timing generators
- · Sequential circuits
- Elevator controllers
- · Security Locking systems
- Counters
- Shift registers

PIN CONFIGURATIONS




Philips Components





PLUS105-55

FUNCTIONAL DIAGRAM



PIN DESCRIPTION

PIN NO.	SYMBOL	NAME AND FUNCTION	POLARITY
1	CK	Clock: The Clock input to the State and Output Registers. A Low-to-High transition on this line is necessary to update the contents of both registers.	Active- High (H)
2-9, 26, 27 20-22	l ₀ - l ₉ , l ₁₃ - l ₁₅	Logic Inputs: The 13 external inputs to the AND array used to program jump conditions between machine states, as determined by a given logic sequence. True and complement signals are generated via use of "H" and "L".	Active-High/ Low (H/L)
23	I ₁₂	Logic/Diagnostic Input: A 14th external logic input to the AND array, as above, when exercising standard TTL levels. When I_{12} is held at +10V, device outputs $F_0 - F_5$ reflect the contents of State Register bits $P_0 - P_5$. The contents of each Output Register remains unaltered.	Active-High/ Low (H/L)
24	I ₁₁	Logic/Diagnostic Inputs: A 15th external logic input to the AND array, as above, when exercising standard TTL levels. When I ₁₁ is held at +10V, device outputs F ₀ - F ₅ become direct inputs for State Register bits P ₀ - P ₅ ; a Low-to-High transition on the appropriate clock line loads the values on pins F ₀ - F ₅ into the State Register bits P ₀ - P ₅ . The contents of each Output Register remains unaltered.	Active-High/ Low (H/L)
25	I ₁₀	Logic/Diagnostic Input: A 16th external logic input to the AND array, as above, when exercising standard TTL levels. When I_{10} is held at +10V, device outputs $F_0 - F_7$ become direct inputs for Output Register bits $Q_0 - Q_7$; a Low-to-High transition on the appropriate clock line loads the values on pins $F_0 - F_7$ into the Output Register bits $Q_0 - Q_7$. The contents of each State Register remains unaltered.	Active-High/ Low (H/L)
10-13 15-18	F ₀ - F ₇	Logic Outputs/Diagnostic Outputs/Diagnostic Inputs: Eight device outputs which normally reflect the contents of Output Register bits Q_0 - Q_7 , when enabled. When I_{12} is held at +10V, F_0 - F_5 ecome inputs to State Register bits P_0 - P_5 . When I_{10} is held at +10V, P_0 - P_5 become inputs to Output Register bits P_0 - P_5 . When P_0 is held at +10V, P_0 - P_5 become inputs to Output Register bits P_0 - P_5 .	Active- High (H)
19	PR/OE	Preset or Output Enable Input: A user programmable function:	
		 Preset: Provides an asynchronous preset to logic "1" of all State and Output Register bits. PR overrides Clock, and when held High, clocking is inhibited and F₀ - F₇ are High. Normal clocking resumes with the first full clock pulse following a High-to-Low clock transi- tion, after the Preset signal goes Low. See timing definitions. 	Active- High (H)
		 Output Enable: Provides an output enable function to buffers F₀ - F₇ from the Output Registers. 	Active- Low (L)

318

PLUS105-55

TRUTH TABLE 1, 2, 3, 4, 5, 6, 7

	OP1	TION									
V _{CC}	PR	ŌĒ	I ₁₀	I ₁₁	l ₁₂	CK	S	R	Q _P	Q _F	F
	Н		*	*	*	Х	X	Х	Н	Н	Q_F
	L		+10V	X	X	\uparrow	X	X	Q _P	L	L
	L		+10V	X	X	\uparrow	X	X	Q _P	н	Н
	L		×	+10V	X	\uparrow	X	X	L	QF	L
	L		×	+10V	X	\uparrow	X	X	н	Q _F	Н
	L		X	X	+10V	X	X	X	Qp	Q _F	Qp
	L		×	X	X	X	X	X	Qp	Q _F	Q_F
		н	×	X	*	X	X	X	Qp	Q _F	Hi-Z
+5V		×	+10V	X	X	\uparrow	X	X	Qp	L	L
		×	+10V	X	X	\uparrow	X	X	Qp	н	н
		×	×	+10V	X	\uparrow	X	X	L	Q _F	L
		×	×	+10V	X	\uparrow	X	X	н	Q _F	н
		L.	×	X	+10V	X	X	X	Qp	Q _F	Q _P
		L	×	X	X	X	X	X	Q _P	Q _F	Q _F
		L	×	X	X	\uparrow	L	L	Q _P	Q _F	Q _F
		L	×	X	X	\uparrow	L	Н	L	L	L
		L	×	X	X	\uparrow	Н	L	н	н	Н
		L	×	X	X	\uparrow	Н	Н	IND.	IND.	IND.
1	Х	Х	X	X	X	Χ	Х	X	н	Н	

NOTES:

1. Positive Logic:

S/R (or J/K) = $T_0 + T_1 + T_2 + ... T_{48}$

 $T_n = (C_0, C_1) (I_0, I_1, I_2, ...) (P_0, P_1, ...P_5)$

- 2. Either Preset (Active High) or Output Enable (Active Low) are available, but not both. The desired function is a user-programmable option.
- 3. ↑ denotes transition from Low-to-High level.
- 4. * = H or L or +10V
- 5. X = Don't Care (≤ 5.5V)
- When using the F_n pins as inputs to the State and Output Registers in diagnostic mode, the F buffers are 3-stated and the indicated levels on the output pins are forced by the user.
- 7. IND. = Indeterminent


VIRGIN STATE

A factory-shipped virgin device contains all fusible links intact, such that:

- PR/OE option is set to PR. Note that even if the PR function is not used, all registers are preset to "1" by the power-up procedure.
- 2. All transition terms are disabled (0).
- 3. All S/R flip-flop inputs are disabled (0).
- The device can be clocked via a Test Array preprogrammed with a standard test pattern. NOTE: The Test Array pattern must be deleted before incorporating a user program.

PLUS105-55

FPLS LOGIC DIAGRAM



PLUS105-55

ORDERING INFORMATION

DESCRIPTION	ORDER CODE
28-pin Plastic Dual-In-Line, 600mil-wide	PLUS105-55N
28-pin Plastic Dual-In-Line, 300mil-wide	PLUS105-55N3
28-pin Plastic Leaded Chip Carrier, 450mil-square	PLUS105-55A

THERMAL RATINGS


TEMPERATUR	E
Maximum junction	150°C
Maximum ambient	75°C
Allowable thermal rise ambient to junction	75°C

ABSOLUTE MAXIMUM RATINGS¹

SYMBOL	PARAMETER	RATI	NGS	UNIT
		Min	Max	
V _{CC}	Supply voltage		+7	V_{DC}
V _{IN}	Input voltage		+5.5	V _{DC}
V _{OUT}	Output voltage		+5.5	V _{DC}
I _{IN}	Input currents	-30	+30	mA
I _{OUT}	Output currents		+100	mA
T _A	Operating temperature range	0	+75	°C
t _{STG}	Storage temperature range	-65	+150	°C

NOTE:

LOGIC FUNCTION



November 1989 321

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

PLUS105-55

DC ELECTRICAL CHARACTERISTICS $0^{\circ}C \le T_{A} \le 75^{\circ}C$, $4.75V \le V_{CC} \le 5.25V$

		174.	5	LIMITS						
SYMBOL	PARAMETER	TEST CONDITION	Min	Typ1	Max	UNIT				
Input voite	nge ²			•						
V _{IH}	High	V _{CC} = Max	2.0			V				
V _{IL}	Low	V _{CC} = Min			0.8	V				
V _{IC}	Clamp ³	$V_{CC} = Min, I_{IN} = -12mA$		-0.8	-1.2	V				
Output vo	ltage ²									
		V _{CC} = Min								
V _{OH}	High	$I_{OH} = -2mA$	2.4			V				
V_{OL}	Low	$I_{OL} = 9.6 \text{mA}$		0.35	0.45	V				
Input curre	ent									
		V _{CC} = Max								
I _{IH}	High	V _{IN} = V _{CC}		<1	25	μА				
I _{IL}	Low	V _{IN} = 0.45V		-20	-250	μА				
Output cu	rrent									
		V _{CC} = Max								
I _{O(OFF)}	Hi-Z state	V _{OUT} = 5.5V		1	40	μА				
		V _{OUT} = 0.45V		-1	-40	μА				
los	Short circuit ^{3, 4}	V _{OUT} = 0V	-5		-70	μА				
Icc	V _{CC} supply current ⁵	V _{CC} = Max		160	200	mA				
Capacitan	ce			5 1 1	*18.1.					
		V _{CC} = 5.0V								
CIN	Input	$V_{IN} = 2.0V$		8		pF				
C _{OUT}	Output	V _{OUT} = 2.0V		10		рF				

NOTES:

- 1. All typical values are at V_{CC} = 5V, T_A = +25°C. 2. All voltage values are with respect to network ground terminal.
- 3. Test one at a time.
- 4. Duration of short circuit should not exceed 1 second.
- 5. I_{CC} is measured with the PR/OE input grounded, all other inputs at 4.5V and the outputs open.

PLUS105-55

$\textbf{AC ELECTRICAL CHARACTERISTICS} \; \mathsf{R}_1 = 470\Omega, \; \mathsf{R}_2 = 1 \text{k}\Omega, \; \mathsf{C}_L = 30 \text{pF}, \, 0^{\circ} \text{C} \leq \; \mathsf{T}_{A} \leq +75^{\circ} \text{C}, \, 4.75 \text{V} \leq \text{V}_{CC} \leq 5.25 \text{V}$


					LIMITS					
SYMBOL	PARAMETER	FROM	то	Min	Typ ¹	Max	UNIT			
Pulse Width	1	•	A							
t _{CKH}	Clock High	CK+	CK-	8			ns			
t _{CKL}	Clock Low	CK-	CK+	8			ns			
t _{CKP1}	Period (without Complement Array)	Input ±	Output ±	18			ns			
t _{CKP2}	Period (with Complement Array)	Input ±	Output ±	28			ns			
t _{PRH}	Preset pulse	PR+	PR-	10			ns			
Setup Time										
t _{IS1}	Input	Input ±	CK+	10			ns			
t _{IS2}	Input (through Complement Array)	Input ±	CK+	20			ns			
t _{VS}	Power-on preset	V _{CC} +	CK-	0			ns			
tprs	Clock resume (after preset)	PR –	CK-	0			ns			
t _{NVCK}	Clock lockout (before preset)	CK-	PR –	12			ns			
Hold Time										
t _{IH}	Input	CK+	Input ±	5			ns			
Propagation	n Delay									
t _{CKO}	Clock	CK+	Output ±			8	ns			
toE	Output enable	OE -	Output -			8	ns			
t _{OD}	Output disable ²	OE +	Output +			8	ns			
t _{PR}	Preset	PR +	Output +			15	ns			
tppR	Power-on preset	V _{CC} +	Output +			10	ns			
Frequency	of Operation		- /							
f _{MAX}	Without Complement Array	Input ±	Output ±	55.0	1,4		MHz			
f _{MAX}	With Complement Array	Input ±	Output ±	35.7						
f _{CLK}	Clock period	CK+	CK+	62.5			MHz			

NOTES:

^{1.} All typical values are at $V_{CC}=5V$, $T_A=+25^{\circ}C$. 2. $C_L=5pF$; $V_T=V_{OL}+0.5V$. 3. Propagation delays measured with all outputs switching.

PLUS105-55

TIMING DIAGRAMS




324

November 1989

PLUS105-55

TIMING DIAGRAMS (Continued)



TIMING DEFINITIONS

SYMBOL	PARAMETER
t _{CKH}	Width of input clock pulse.
t _{CKL}	Interval between clock pulses.
t _{CKP2}	Operating period — when using Complement Array.
t _{IS1}	Required delay between beginning of valid input and positive transition of Clock.
t _{IS2}	Required delay between beginning of valid Input and positive transition of Clock, when using optional Comple- ment Array (two passes nec- essary through the AND Array).
t _{VS}	Required delay between V _{CC} (after power-on) and negative transition of Clock preceding first reliable clock pulse.
t _{PRS}	Required delay between negative transition of Asynchronous Preset and the first positive transition of Clock


SYMBOL	PARAMETER
t _{IH}	Required delay between posi- tive transition of Clock and end of valid Input data.
t _{CKO}	Delay between positive transition of Clock and when Outputs become valid (with PR/OE Low).
toE	Delay between beginning of Output Enable Low and when Outputs become valid.
t _{OD}	Delay between beginning of Output Enable High and when Outputs are in the OFF-state.
t _{SRE}	Delay between input I ₁₂ transition to Diagnostic Mode and when the Outputs reflect the contents of the State Register.
t _{SRD}	Delay between input I ₁₂ transition to Logic mode and when the Outputs reflect the contents of the Output Register.

325


SYMBOL	PARAMETER
t _{CKP1}	Operating period — without the Complement Array.
t _{PR}	Delay between positive transition of Preset and when Outputs become valid at "1".
t _{PPR}	Delay between V _{CC} (after) power-on) and when Outputs become preset at "1".
t _{PRH}	Width of preset input pulse.
f _{MAX}	Min. guaranteed operating frequency.
tnvck	Required delay between the negative transition of the clock and the negative transition of the Asynchronous PRESET to guarantee that the clock edge is not detected as a valid negative transition.

PLUS105-55

TIMING DIAGRAMS (Continued)



TEST LOAD CIRCUITS



LOGIC PROGRAMMING

PLUS105-55 logic designs can be generated using Signetics AMAZE PLD design software or one of several other commercially available, JEDEC standard PLD design software packages. Boolean and/or state equation entry is accepted.


PLUS105-55 logic designs can also be generated using the program table entry format detailed on the following pages. This program table entry format is supported by the Signetics AMAZE PLD design software (PTE module). AMAZE is available free of charge to qualified users.

To implement the desired logic functions, the state of each logic variable from logic equations (I, B, O, P, etc.) is assigned a symbol. The symbols for TRUE, COMPLEMENT, INACTIVE, PRESET, etc., are defined below.

PROGRAMMING THE PLUS 105-55


The PLUS105-55 has a power-up preset feature. This feature insures that the device will power-up in a known state with all register elements (state and output register) at a logic High (H). When programming the device it is important to realize this is the initial state of the device. You *must* provide a next state jump if you do not wish to use all Highs (H) as the present state.

VOLTAGE WAVEFORMS




PLUS105-55


PRESET/OE OPTION - (P/E)




"AND" ARRAY - (I), (P)



"OR" ARRAY - (N), (F)



"COMPLEMENT" ARRAY - (C)



NOTES:

- 1. This is the initial unprogrammed state of all link pairs. It is normally associated with all unused (inactive) AND gates T_{n_*}
- 2. Any gate Tn will be unconditionally inhibited if both the true and complement fuses of any input (I,P) are left intact.
- To prevent simultaneous Set and Reset flip-flop commands, this state is not allowed for N and F link pairs coupled to active gates T_n (see flip-flop truth tables).
- 4. To prevent oscillations, this state is not allowed for C link pairs coupled to active gates T_n.

PLUS105-55

FPLS PROGRAM TABLE

PROGRAM TABLE ENTRIES

	CI	181	-	#EI	A C	A 1.4	ıE															T	AND										OR					
								# .												_			IN	ACTIVE	0				: [INAC	TIV	Æ	ī	0				
İ	61	CN	CT	100	0	=\//	CE	# .				(DF.	(X)	(X)	()				_		1	G	ENERATE	A		Cn		1	SET			1	н				
								m. LIZ												-			P	ROPAGATE	•				:	RES	ET		-	L		Ns, I	rr	
																				_			TRANSPARENT - NO CHANGE -										1					
								PA												_		1	1	NACTIVE	0								PT	10	·			
			áR/	M	ΙA	BL	Ŀ_				-												Ι.		н	In	n, Pa			_		_	_	_				
	REV											-		L				I I	_		_	н	4		P/E													
	DATE											1	DON'T CARE	_				1	ŌE	_	_	L																
	AND															T				OP	TIOI	N (P	_			_	\perp	\Box										
T							_	INI	PUT	(Im)			_	_	_			PR	ESE	NT	STA	TE (Ps)	REMARK	S	1	NEXT	TST	ATE	(Ns)	T	01	R	OU	TPUT	(Fr)		\dashv
R	C	1	1	1	1	1 1	1								, — ,											1					1	_						
M		5	4	3	2	1	0	9	8	7	6	5	4	3	2	1	0	5	4	3	2	1	0			5	4	3	2	1 (+	7	6	5	4 3	2	1	0
1					-							\dashv	-										\Box			1				-	#	#	1	#	-	#		
3													_													上					1	\pm	1	#	i	\pm		
5		-	_	-	_		-				-	-	_			_	_	\vdash	-	-	-	-				+	\vdash			+	+	+	+	+	+	+	-	\vdash
6					=				_				_					F					\Box			F				-	Ŧ	7	7	7	-	\perp	-	\Box
8						\Box																				1					#	\pm	#	#	+	#		
9					_								-													\pm					\pm	\pm	\pm	\pm	-		-	
11							_						- 8			_	_	H		_		-				+				-	+	+	+	+	÷	+	-	\Box
13					-													F					\Box			1				1	#	\perp	#	#	8	_		\Box
15					_	-				II II																\pm					1	+	+	+	i	\pm		
16		-	-				-				-	-	_		_	_	_	\vdash	-	-	-	-	Н			+		-	-	+	+	+	+	+	_	+	+	\vdash
18									_	8-			_													1					1	7	7	1	1	_	1	\Box
20					7					8			7													1					#	\pm	#	#	+	_	Ι.	
20 21 22																										+					†	+		+	-	+		
23					-						_		-					F					\vdash			+				-	Ŧ	+	+	-	+	-	-	\Box
24 25 26									-				. 8							-						#				1	#	7	_	1	-	1		
27																										土					1	-		\pm				
28	-	-	-	_			_		_		-	-	-8		_	_		H	-	-	-	-				+	-			-	+	+	+	+	-	-	-	-
28 29 30 31 32					=								=					F		-						1					7	7	7	+	i	+		\Box
32																										1					#	_	\pm	1	_	\pm		
33 34 35 36					_								i													+					\pm	+	+			\pm		
35 36																		F								F					Ŧ	Ŧ	T	T	-	=		
37 38													-	1												1					1	#	7	7	-	T		口
39														$\overline{}$												+					1	+	\pm	\pm	ī	+		\Box
40	\vdash	-	_	_			-		_		-		-		-	_	_	\vdash	_	-	-	-				+	-			-	+	+	+	+	8	+	-	\vdash
42 43 44	H				_								_													1					1	#	1	#		1		口
44					7																					1					1	1	\perp	1	_			
45 46					i								_					\vdash		_						+					\pm		+	\pm	-			
47	Щ		_		-	-			_	\dashv	-		-					F								L					Ŧ	+	\mp	+	Ť	-		\Box
PH NC		0	1	2	3	2	5	6	7	2	3	4	5	6	7	8	9															0	1	2 3	1 1 5	6	7	8
VARIABLE	NAME																																					

NOTES:

- The FPLS is shipped with all links initially intact. Thus, a background of "0" for all Terms, and an "H" for the P/E option, exists in the table, shown BLANK instead for clarity.
 Unused C_n, I_m, and P_s bits are normally programmed Don't Care (-).
 Unused Transition Terms can be left blank for future code modification, or programmed as (-) for maximum speed.

- 4. Letters in variable fields are used as identifiers by logic type programmers.

November 1989 328

Signetics

Document No.	853–1280	
ECN No.	97039	
Date of Issue	July 7, 1989	
Status	Product Specification	
Programmable Logic Devices		

PLUS405–37/–45 Field-Programmable Logic Sequencers $(16 \times 64 \times 8)$

DESCRIPTION

The PLUS405 devices are bipolar, programmable state machines of the Mealy type. Both the AND and the OR array are user–programmable. All 64 AND gates are connected to the 16 external dedicated inputs (l_0-l_{15}) and to the feedback paths of the 8 on–chip State Registers $(Q_{P0}-Q_{P7})$. Two complement arrays support complex IF–THEN–ELSE state transitions with a single product term (input variables C_0 , C_{11} .

All state transition terms can include True, False and Don't Care states of the controlling state variables. All AND gates are merged into the programmable OR array to issue the next—state and next—output commands to their respective registers. Because the OR array is programmable, any one or all of the 64 transition terms can be connected to any or all of the State and Output Registers.

All state $(Q_{P0} - Q_{P7})$ and output $(Q_{F0} - Q_{F7})$ registers are edge-triggered, clocked J-K flipflops, with Asynchronous Preset and Reset options. The PLUS405 architecture provides the added flexibility of the J-K toggle function which is indeterminate on S-R flip-flops. Each register may be individually programmed such that a specific Preset-Reset pattern is initialized when the initialization pin is raised to a logic level "1". This feature allows the state machine to be asynchronously initialized to known internal state and output conditions prior to proceeding through a sequence of state transitions. Upon power-up, all registers are unconditionally preset to "1". If desired, the initialization input pin (INIT) can be converted to an Output Enable (OE) function as an additional user-programmable feature.

Availability of two user–programmable clocks allows the user to design two independently clocked state machine functions consisting of four state and four output bits each.

Order codes are listed in the Ordering Information Table.


FEATURES

- 50 and 58.8MHz minimum guaranteed clock rates
- 37 and 45MHz minimum guaranteed operating frequencies (1/(t_{IS1} + t_{CKO1})
- Functional superset of PLS105/105A
- Field-programmable (Ti-W fusible link)
- 16 input variables
- 8 output functions
- 64 transition terms
- 8-bit State Register
- 8-bit Output Register
- 2 transition Complement Arrays
- Multiple clocks*
- Programmable Asynchronous Initialization or Output Enable
- Power-on preset of all registers to "1"
- "On-chip" diagnostic test mode features for access to state and output registers
- 950mW power dissipation (typ.)
- TTL compatible
- J-K or S-R flip-flop functions
- Automatic "Hold" states
- 3-State outputs

APPLICATIONS

- Interface protocols
- Sequence detectors
- Peripheral controllers
- Timing generators
- Sequential circuits
- Elevator contollers
- Security locking systems
- Counters
- Shift registers

PIN CONFIGURATIONS



Philips Components





^{*}Refer to AC Specifications for clock and operating frequencies when using multiple clocks.

PLUS405-37/-45

PIN DESCRIPTION

PIN NO.	SYMBOL	NAME AND FUNCTION	POLARITY
1	CLK1	Clock: The Clock input to the State and Output Registers. A Low–to–High transition on this line is necessary to update the contents of both registers. Pin 1 only clocks P_{0-3} and F_{0-3} if Pin 4 is also being used as a clock.	Active-High (H)
2, 3, 5–9, 26–27 20–22	$ \begin{array}{c c} I_0 - I_4, I_7, I_6 \\ I_8 - I_9 \\ I_{13} - I_{15} \end{array} $	Logic Inputs: The 12 external inputs to the AND array used to program jump conditions between machine states, as determined by a given logic sequence. True and complement signals are generated via use of "H" and "L".	Active-High/Low (H/L)
4	CLK2	Logic Input/Clock: A user programmable function:	
		Logic Input: A 13th external logic input to the AND array, as above.	Active-High/Low (H/L)
		 Clock: A 2nd clock for the State Registers P₄₋₇ and Output Registers F₄₋₇, as above. Note that input buffer I₅ must be deleted from the AND array (i.e., all fuse locations "Don't Care") when using Pin 4 as a Clock. 	Active-High (H)
23	l ₁₂	Logic/Diagnostic Input: A 14th external logic input to the AND array, as above, when exercising standard TTL or CMOS levels. When I_{12} is held at +10V, device outputs $F_0 - F_7$ reflect the contents of State Register bits $P_0 - P_7$. The contents of each Output Register remains unaltered.	Active-High/Low (H/L)
24	I ₁₁	Logic/Diagnostic Input: A 15th external logic input to the AND array, as above, when exercising standard TTL levels. When I ₁₁ is held at +10V, device outputs $F_0 - F_7$ become direct inputs for State Register bits $P_0 - P_7$; a Low-to-High transition on the appropriate clock line loads the values on pins $F_0 - F_7$ into the State Register bits $P_0 - P_7$. The contents of each Output Register remains unaltered.	Active-High/Low (H/L)
25	I ₁₀	Logic/Diagnostic Input: A 16th external logic input to the AND array, as above, when exercising standard TTL levels. When I_{10} is held at +10V, device outputs $F_0 - F_7$ become direct inputs for Output Register bits $Q_0 - Q_7$; a Low-to-High transition on the appropriate clock line loads the values on pins $F_0 - F_7$ into the Output Register bits $Q_0 - Q_7$. The contents of each State Register remains unaltered.	Active-High/Low (H/L)
10–13 15–18	F ₀ – F ₇	Logic Outputs/Diagnostic Outputs/Diagnostic Inputs: Eight device outputs which normally reflect the contents of Output Register Bits Q_0-Q_7 , when enabled. When I_{12} is held at +10V, F_0-F_7 become inputs to State Register bits P_0-P_7 . When I_{10} is held at +10V, F_0-F_7 become inputs to Output Register bits Q_0-Q_7 .	Active-High (H)
19	INIT/OE	Initialization or Output Enable Input: A user programmable function:	
		 Initialization: Provides an asynchronous preset to logic "1" or reset to logic "0" of all State and Output Register bits, determined individually for each register bit through user programming. INIT overrides Clock, and when held High, clocking is inhibited and F₀ – F₇ and P₀ – P₇ are in their initialization state. Normal clocking resumes with the first full clock pulse following a High-to-Low clock transition, after INIT goes Low. See timing definition for t_{NVCK} and t_{VCK}. 	Active-High (H)
		 Output Enable: Provides an output enable function to buffers F₀ – F₇ from the Output Registers. 	Active-Low (L)

PLUS405-37/-45

TRUTH TABLE 1, 2, 3, 4, 5, 6, 7

	ОРТ	ION									
V _{cc}	INIT	ŌĒ	I ₁₀	I ₁₁	I ₁₂	CK	J	K	Qp	Q _F	F
	Н		*	*	*	Х	X	X	H/L	H/L	Q _F
	L		+10V	X	X	\uparrow	X	X	Q _P	L	L
	L		+10V	X	X	\uparrow	X	X	Qp	Н	н
	L		X	+10V	X	\uparrow	X	X	L	Q _F	L
	L		X	+10V	X	\uparrow	X	X	Н	Q _F	н
	L		X	X	+10V	X	X	X	Qp	Q _F	Qp
	L		Х	X	Х	X	X	X	Q _P	Q _F	Q _F
		Н	X	X	*	X	X	X	Q _P	Q _F	Hi–Z
+5V		X	+10V	X	X	\uparrow	X	X	Q _P	L	L
		X	+10V	X	X	\uparrow	X	X	Q _P	Н	н
		X	X	+10V	X	\uparrow	X	X	L	QF	L
		X	X	+10V	X	\uparrow	X	X	Н	Q _F	н
		L	X	X	+10V	X	X	X	Qp	QF	Q _P
		L	X	X	X	Χ	Χ	Χ	Q _P	Q _F	Q_F
		L	X	X	X	\uparrow	L	L	Q _P	Q _F	Q _F
		L	X	X	X	\uparrow	L	Н	L	L	L
		L	X	X	X	\uparrow	Н	L	Н	Н	н
		L	X	X	X	1	Н	Н	Q _P	Q _F	Q _F
1	Х	Х	X	X	Х	Х	Х	X	Н	Н	

NOTES:

1. Positive Logic:

S/R (or J/K) = $T_0 + T_1 + T_2 + ... T_{63}$ $T_n = (C_0, C_1)(I_0, I_1, I_2, ...) (P_0, P_1, ... P_7)$


- 2. Either Initialization (Active-High) or Output Enable (Active-Low) are available, but not both. The desired function is a user-programmable option.
- ↑ denotes transition from Low-to-High level.
- * = H or L or +10V
- 5. X = Don't Care (≤5.5V)
- H/L implies that either a High or a Low can occur, depending upon user-programmed selection (each State and Output Register individually programmable).
- 7. When using the Fn pins as inputs to the State and Output Registers in diagnostic mode, the F buffers are 3-Stated and the indicated levels on the output pins are forced by the user.

VIRGIN STATE

A factory-shipped virgin device contains all fusible links intact, such that:


- 1. INIT/OE is set to INIT. In order to use the INIT function, the user must select either the PRESET or the RESET option for each flip-flop. Note that regardless of the userprogrammed initialization, or even if the INIT function is not used, all registers are preset to "1" by the power-up procedure.
- 2. All transition terms are inactive (0).
- 3. All S/R (or J/K) flip-flop inputs are disabled
- 4. The device can be clocked via a Test Array preprogrammed with a standard test pattern
- 5. Clock 2 is inactive.

LOGIC FUNCTION



PLUS405-37/-45


FUNCTIONAL DIAGRAM



July 7, 1989 332


PLUS405-37/-45

LOGIC DIAGRAM



PLUS405-37/-45

DETAILS FOR REGISTERS FOR PLUS405



July 7, 1989

PLUS405-37/-45

ORDERING INFORMATION

DESCRIPTION	OPERATING FREQUENCY	ORDER CODE
28-Pin Plastic DIP (600mil-wide)	45MHz (t _{IS1} + t _{CKO1})	PLUS405-45N
28-Pin Plastic DIP (600mil-wide)	37MHz (t _{IS1} + t _{CKO1})	PLUS405-37N
28-Pin Plastic Leaded Chip Carrier	45MHz (t _{IS1} + t _{CKO1})	PLUS405-45A
28-Pin Plastic Leaded Chip Carrier	37MHz (t _{IS1} + t _{CKO1})	PLUS405-37A

ABSOLUTE MAXIMUM RATINGS¹

SYMBOL	PARAMETER	RATINGS	UNIT
V _{CC}	Supply voltage	+7	V _{DC}
V _{IN}	Input voltage	+5.5	V _{DC}
V _{OUT}	Output voltage	+5.5	V _{DC}
I _{IN}	Input currents	-30 to +30	mA
lout	Output currents	+100	mA
T _A	Operating temperature range	0 to +75	°C
T _{STG}	Storage temperature range	-65 to +150	°C

NOTES:

THERMAL RATINGS

TEMPERATURE				
Maximum junction	150°C			
Maximum ambient	75°C			
Allowable thermal rise ambient to junction	75°C			

The PLUS405 devices are also processed for operation over the military temperature range. For Specifications and ordering information, consult the Signetics Military Data Manual.

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

PLUS405-37/-45

DC ELECTRICAL CHARACTERISTICS $0^{\circ}\text{C} \le \text{T}_{\text{A}} \le +75^{\circ}\text{C}, 4.75\text{V} \le \text{V}_{\text{CC}} \le 5.25\text{V}$

				LIMITS			
SYMBOL PARAMETER		TEST CONDITIONS	Min	Min Typ ¹		UNIT	
Input volt	age ²						
V _{IH}	High	V _{CC} = MAX	2.0			V	
V _{IL}	Low	V _{CC} = MIN			0.8	V	
V _{IC}	Clamp ³	V _{CC} = MIN, I _{IN} = -12mA		-0.8	-1.2	V	
Output vo	oltage ²						
V _{OH}	High	V _{CC} = MIN, I _{OH} = -2mA	2.4			V	
V _{OL}	Low	V _{CC} = MIN, I _{OL} = 9.6mA		0.35	0.45	V	
Input curi	rent						
I _{IH}	High	V _{CC} = MAX, V _{IN} = V _{CC}		<1	25	μА	
I _{IL}	Low	V _{CC} = MAX, V _{IN} = 0.45V		-20	-250	μА	
Output cu	irrent			•		•	
I _{O(OFF)}	Hi–Z state	V _{CC} = MAX, V _{OUT} = 5.5V		1	40	μА	
		V _{CC} = MAX, V _{OUT} = 0.45V		-1	-40	μА	
Ios	Short circuit 3, 4	V _{OUT} = 0V	-15		-70	mA	
Icc	V _{CC} supply current ⁵	V _{CC} = MAX		190	225	mA	
Capacitar	nce	•		*	•		
C _{IN}	Input	V _{CC} = 5.0V, V _{IN} = 2.0V		8		pF	
C _{OUT}	Output	V _{CC} = 5.0V, V _{OUT} = 2.0V		10		pF	
				_	-		

- 1. All typical values are at V_{CC} = 5V. T_A = +25°C. 2. All voltage values are with respect to network ground terminal.
- Test one at a time.
 Duration of short–circuit should not exceed one second.
- 5. I_{CC} is measured with the INIT/OE input grounded, all other inputs at 4.5V and the outputs open.

July 7, 1989 336

PLUS405-37/-45

 $\textbf{AC ELECTRICAL CHARACTERISTICS} \; R_1 = 470 \Omega, \; R_2 = 1 \text{k}\Omega, \; C_L = 30 \text{pF}, \; 0^{\circ}\text{C} \leq T_\text{A} \leq +75^{\circ}\text{C}, \; 4.75 \text{V} \leq \text{V}_{\text{CC}} \leq 5.25 \text{V}$


				LIMITS						
SYMBOL	PARAMETER	FROM	то	PLUS405–37 PLUS405–45				45	UNIT	
				Min	Typ ¹	Max	Min	Typ1	Max	
Pulse wid	th		•							
t _{CKH1}	Clock High; CLK1 (Pin 1)	CK+	CK-	10	8		8.5	7		ns
t _{CKL1}	Clock Low; CLK1 (Pin 1)	CK-	CK+	10	8		8.5	7		ns
t _{CKP1}	CLK1 Period (without Complement Array)	Input +/-	Output +/-	27	22		22	18		ns
t _{CKH2}	Clock High; CLK2 (Pin 4)	CK+	CK-	10	8		10	8		ns
t _{CKL2}	Clock Low; CLK2 (Pin 4)	CK-	CK+	10	8		10	8		ns
t _{CKP2}	CLK2 Period (without Complement Array)	Input +/-	Output +/-	30	24		24	20		ns
t _{CKP3}	CLK1 Period (with Complement Array)	Input +/-	Output +/-	37	30		32	26		ns
t _{CKP4}	CLK2 Period (with Complement Array)	Input +/-	Output +/-	40	32		34	28		ns
t _{INITH}	Initialization pulse	INIT-	INIT+	15	10		15	8	7	ns
Setup time	e ²									
t _{IS1}	Input	Input ±	CK+	15	12		12	10		ns
t _{IS2}	Input (through Complement Array)	Input ±	CK+	25	20		22	18		ns
t _{VS}	Power-on preset	V _{CC} +	CK-	0	-10		0	-10		ns
t _{VCK}	Clock resume (after Initialization)	INIT-	CK-	0	-5		0	-5		ns
t _{NVCK}	Clock lockout (before Initialization)	CK-	INIT-	15	5		15	5		ns
Hold time										
t _{IH}	Input	CK+	Input ±	0	-5		0	- 5		ns
Propagati	on delay			1			l			
t _{CKO1}	Clock1 (Pin 1)	CK1+	Output ±		10	12		8	10	ns
t _{CKO2}	Clock2 (Pin 4)	CK2+	Output ±		12	15		10	12	ns
toE	Output Enable	OE-	Output -		12	15		12	15	ns
t _{OD}	Output Disable ²	OE+	Output +	-	12	15		12	15	ns
t _{INIT}	Initialization	INIT+	Output +		15	20		15	20	ns
t _{PPR}	Power–on Preset	V _{CC} +	Output +		0	10		0	10	ns
	y of operation					1	1			
f _{MAX1}	CLK1; (without Complement Array)			37.0	45.5		45.5	55.6		MHz
f _{MAX2}	CLK2; (without Complement Array)			33.0	41.7		41.7	50.0		MHz
f _{MAX3}	CLK1; (with Complement Array)			27.0	33.3		31.3	38.5		MHz
f _{MAX4}	CLK2; (with Complement Array)			25.0	31.3		29.4	35.7		MHz

NOTES:

^{1.} All typical values are at V_{CC} = 5V, T_A = +25°C. 2. C_L = 5pF; V_T = V_{OL} + 0.5V.


PLUS405-37/-45

TIMING DIAGRAMS



PLUS405-37/-45

TIMING DIAGRAMS (Continued)



PLUS405-37/-45

TIMING DEFINITIONS

SYMBOL	PARAMETER
t _{CKH1,2}	Width of input clock pulse.
t _{CKP1, 2}	Oerating period – when not using Complement Array.
t _{IS1}	Required delay between beginning of valid input and positive transition of Clock.
t _{CKO1, 2}	Delay between positive transition of Clock and when Outputs become valid (with INIT/OE Low).
t _{PPR}	Delay between V _{CC} (after power–on) and when Outputs become preset at "1".
t _{IS2}	Required delay between beginning of valid Input and positive transition of Clock, when using optional Complement Array (two passes necessary through the AND Array).
[‡] RJH	Required delay between positive transition of Clock and end of inputs I ₁₁ or I ₁₀ transition to State and Output Register Input Jam Diagnostic Modes, respectively.
f _{MAX1, 2,} 3, 4	Minimum guaranteed operating frequency.


SYMBOL	PARAMETER
^t CKL1, 2	Interval between clock pulses.
^t CKP3, 4	Operating period – when using Complement Array.
t _{iH}	Required delay between positive transition of Clock and end of valid Input data.
t _{OE}	Delay between beginning of Output Enable Low and when Outputs become valid.
t _{SRE}	Delay between input I ₁₂ transition to Diagnostic Mode and when the Outputs reflect the contents of the State Register.
trus	Required delay between inputs I ₁₁ or I ₁₀ transition to State and Output Register Input Jam Diagnostic Modes, respectively, and when the output pins become available as inputs.
tnvck	Required delay between the negative transition of the clock and the negative transition of the Asynchronous Initialization to guarantee that the clock edge is not detected as a valid negative transition.

SYMBOL	PARAMETER
t _{INITH}	Width of initialization input pulse.
t _{VS}	Required delay between V_{CC} (after power—on) and negative transition of Clock preceding first reliable clock pulse.
t _{OD}	Delay between beginning of Output Enable High and when Outputs are in the OFF–state.
t _{INIT}	Delay between positive transition of Initialization and when Outputs become valid.
t _{SRD}	Delay between input I ₁₂ transition to Logic mode and when the Outputs reflect the contents of the Output Register.
t _{RH}	Required delay between positive transition of Clock and end of valid Input data when jamming data into State or Output Registers in diagnostic mode.
t _{VCK}	Required delay between negative transition of Asynchronous Initialization and negative transition of Clock preceding first reliable clock pulse.


July 7, 1989 340

PLUS405-37/-45

TEST LOAD CIRCUIT



VOLTAGE WAVEFORMS




LOGIC PROGRAMMING

PLUS405 Logic designs can be generated using Signetics AMAZE design software or several other commercially available, JEDEC standard PLD design software packages. Boolean and/or state equation entry format is accepted.

PLUS405 logic designs can also be generated using the program table format detailed on the following page(s). This Program Table Entry format (PTE) is supported by the Signetics AMAZE PLD design software. AMAZE is available free of charge to qualified users.

To implement the desired logic functions, each logic variable (I, B, P, S, T, etc.) from the logic equations is assigned a symbol. TRUE, COMPLEMENT, PRESET, RESET, OUTPUT ENABLE, INACTIVE, etc., symbols are defined below


INITIALIZATION/OE OPTION - (INIT/OE)



PROGRAMMING THE PLUS405:

The PLUS405 has a power—up preset feature. This feature insures that the device will power—up in a known state with all register elements (State and Output Register) at logic High (H). When programming the device it is important to realize this is the initial state of the device. You must provide a next state jump if you do not wish to use all Highs (H) as the present state.


PRESET/RESET OPTION - (P/R)




July 7, 1989 341

PLUS405-37/-45


"AND" ARRAY - (I), (P)




"OR" ARRAY - J-K FUNCTION - (N), (F)



"COMPLEMENT" ARRAY - (C)



CLOCK OPTION - (CLK1/CLK2)



NOTES:

- 1. This is the initial unprogrammed state of all links.
- 2. Any gate T_n will be unconditionally inhibited if any one of its I or P link pairs is left intact.
- 3. To prevent oscillations, this state is not allowed for C link pairs coupled to active gates T_n.
- 4. These states are not allowed when using PRESET/RESET option.
- 5. Input buffer I₅ must be deleted from the AND array (i.e., all fuse locations "Don't Care") when using second clock option.

342

6. A single product term cannot drive more than 8 registers by itself when used in TOGGLE mode.

July 7, 1989

1 5

Field-Programmable Logic Sequencers ($16 \times 64 \times 8$)

PLUS405-37/-45

PLUS405 PROGRAM TABLE AND OR **OPTIONS** INACTIVE OR TOGGLE INACTIVE 0 INACTIVE 0 0 INIT/OE I, P Н GENERATE Α OE SET Н Ns. Fr L I, P PROPAGATE . RESET L CLK1 ONLY CLK1/ DON'T CARE TRANSPARENT NO CHANGE CLK2 CLK1 AND 2 Н INITIALIZATION/OUTPUT ENABLE CLOCK 1/2 INPUT (Im) PRESENT STATE (Ps) NEXT STATE (Ns) OUTPUT (Fr) 15 | 14 | 13 | 12 | 11 | 110 | 19 | 18 | 17 | 16 | 15 | 14 | 13 | 12 | 11 | 10 | P7 | P6 | P5 | P4 | P3 | P2 | P1 | P0 N7 N6 N5 N4 N3 N2 N1 N0 F7 F6 F5 F4 F3 F2 F1 F0 DATE. 9 11 12 13 14 15 16 PROGRAM TABLE 18 19 20 22 23 24 25 26 REV. 27 28 29 30 31 32 33 35 36 37 38 39 40 42 CF (XXXX) 43 44 45 46 47 **CUSTOMER SYMBOLIZED PART** 48 49 50 51 52 53 54 55 56 57 58 59 60 SIGNETICS DEVICE CUSTOMER NAME.

NOTES:

2 2 2 2 2 5 2 27

61 62

PIN NO. PIN LABELS

The FPLS is shipped with all links initially intact. Thus, a background of "0" for all Terms, and an "H" for the IN/E and H for the clock option, exists in the table, shown BLANK instead

for clarity.

Unused Cn Im, and Ps bits are normally programmed Don't Care (—).

Unused Transition Terms can be left blank for future code modification, or programmed as (—) for maximum speed.

Signetics

Document No.			
ECN No.			
Date of Issue	October 1989		
Status	Preliminary Specification		
Programmable Logic Devices			

DESCRIPTION

The PLUS405–55 device is a bipolar, programmable state machine of the Mealy type. Both the AND and the OR array are user–programmable. All 64 AND gates are connected to the 16 external dedicated inputs (I_0-I_{15}) and to the feedback paths of the 8 on–chip State Registers $(Q_{P0}-Q_{P7})$. Two complement arrays support complex IF–THEN–ELSE state transitions with a single product term (input variables C_0,C_1)

All state transition terms can include True, False and Don't Care states of the controlling state variables. All AND gates are merged into the programmable OR array to issue the next-state and next-output commands to their respective registers. Because the OR array is programmable, any one or all of the 64 transition terms can be connected to any or all of the State and Output Registers.

All state $(Q_{P0} - Q_{P7})$ and output $(Q_{F0} - Q_{F7})$ registers are edge-triggered, clocked J-K flipflops, with Asynchronous Preset and Reset options. The PLUS405 architecture provides the added flexibility of the J-K toggle function which is indeterminate on S-R flip-flops. Each register may be individually programmed such that a specific Preset-Reset pattern is initialized when the initialization pin is raised to a logic level "1". This feature allows the state machine to be asynchronously initialized to known internal state and output conditions prior to proceeding through a sequence of state transitions. Upon power-up, all registers are unconditionally preset to "1". If desired, the initialization input pin (INIT) can be converted to an Output Enable (OE) function as an additional user-programmable feature.

Availability of two user-programmable clocks allows the user to design two independently clocked state machine functions consisting of four state and four output bits each.

Order codes are listed in the Ordering Information Table.

PLUS405-55

Field-Programmable Logic Sequencer (16 \times 64 \times 8)


FEATURES

- 62.5MHz minimum guaranteed clock rate
- 55MHz minimum guaranteed operating frequency (1/(t_{IS1} + t_{CKO1})
- Functional superset of PLS105/105A
- Field-programmable (Ti-W fusible link)
- 16 input variables
- 8 output functions
- 64 transition terms
- 8-bit State Register
- 8-bit Output Register
- 2 transition Complement Arrays
- Multiple clocks
- Programmable Asynchronous Initialization or Output Enable
- Power-on preset of all registers to "1"
- "On-chip" diagnostic test mode features for access to state and output registers
- 950mW power dissipation (typ.)
- TTL compatible
- J-K or S-R flip-flop functions
- · Automatic "Hold" states
- 3-State outputs

APPLICATIONS

- Interface protocols
- Sequence detectors
- Peripheral controllers
- Timing generators
- Sequential circuits
- Elevator contollers
- Security locking systems
- Counters
- Shift registers

PIN CONFIGURATIONS



Philips Components





PLUS405-55

PIN DESCRIPTION

PIN NO.	SYMBOL	NAME AND FUNCTION	POLARITY
1	CLK1	Clock: The Clock input to the State and Output Registers. A Low–to–High transition on this line is necessary to update the contents of both registers. Pin 1 only clocks P_{0-3} and F_{0-3} if Pin 4 is also being used as a clock.	Active-High (H)
2, 3, 5–9, 26–27 20–22	$I_0 - I_4, I_7, I_6$ $I_8 - I_9$ $I_{13} - I_{15}$	Logic Inputs: The 12 external inputs to the AND array used to program jump conditions between machine states, as determined by a given logic sequence. True and complement signals are generated via use of "H" and "L".	Active-High/Low (H/L)
4	CLK2	Logic Input/Clock: A user programmable function:	
		Logic Input: A 13th external logic input to the AND array, as above.	Active-High/Low (H/L)
		 Clock: A 2nd clock for the State Registers P₄₋₇ and Output Registers F₄₋₇, as above. Note that input buffer I₅ must be deleted from the AND array (i.e., all fuse locations "Don't Care") when using Pin 4 as a Clock. 	Active-High (H)
23	l ₁₂	Logic/Diagnostic Input: A 14th external logic input to the AND array, as above, when exercising standard TTL or CMOS levels. When I ₁₂ is held at +10V, device outputs F ₀ - F ₇ reflect the contents of State Register bits P ₀ - P ₇ . The contents of each Output Register remains unaltered.	Active-High/Low (H/L)
24	I ₁₁	Logic/Diagnostic Input: A 15th external logic input to the AND array, as above, when exercising standard TTL levels. When I ₁₁ is held at +10V, device outputs $F_0 - F_7$ become direct inputs for State Register bits $P_0 - P_7$; a Low-to-High transition on the appropriate clock line loads the values on pins $F_0 - F_7$ into the State Register bits $P_0 - P_7$. The contents of each Output Register remains unaltered.	Active-High/Low (H/L)
25	I ₁₀	Logic/Diagnostic Input: A 16th external logic input to the AND array, as above, when exercising standard TTL levels. When I_{10} is held at +10V, device outputs $F_0 - F_7$ become direct inputs for Output Register bits $Q_0 - Q_7$; a Low-to-High transition on the appropriate clock line loads the values on pins $F_0 - F_7$ into the Output Register bits $Q_0 - Q_7$. The contents of each State Register remains unaltered.	Active-High/Low (H/L)
10–13 15–18	F ₀ – F ₇	Logic Outputs/Diagnostic Outputs/Diagnostic Inputs: Eight device outputs which normally reflect the contents of Output Register Bits Q_0-Q_7 , when enabled. When I_{12} is held at +10V, F_0-F_7 e(P_0-P_7). When I_{11} is held at +10V, F_0-F_7 become inputs to State Register bits P_0-P_7 . When I_{10} is held at +10V, F_0-F_7 become inputs to Output Register bits Q_0-Q_7 .	Active-High (H)
19	INIT/OE	Initialization or Output Enable Input: A user programmable function:	
		• Initialization: Provides an asynchronous preset to logic "1" or reset to logic "0" of all State and Output Register bits, determined individually for each register bit through user programming. INIT overrides Clock, and when held High, clocking is inhibited and F_0-F_7 and P_0-P_7 are in their initialization state. Normal clocking resumes with the first full clock pulse following a High–to–Low clock transition, after INIT goes Low. See timing definition for t_{NVCK} and t_{VCK} .	Active-High (H)
		• Output Enable: Provides an output enable function to buffers $F_0 - F_7$ from the Output Registers.	Active-Low (L)

PLUS405-55

TRUTH TABLE 1, 2, 3, 4, 5, 6, 7

	ОРТ	ION									
V _{CC}	INIT	ŌĒ	I ₁₀	I ₁₁	l ₁₂	CK	J	K	Q _P	Q _F	F
	Н		*	* "		X	X	X	H/L	H/L	Q _F
	L		+10V	X	X	\uparrow	X	X	Qp	L	L
	L		+10V	X	X	\uparrow	X	X	Qp	н	Н
	L		X	+10V	X	\uparrow	X	X	L	Q _F	L
	L		X	+10V	X	\uparrow	X	X	Н	Q _F	н
	L		X	X	+10V	X	X	X	Q _P	QF	Q _P
	L		X	X	X	X	X	Χ	Q _P	Q _F	Q _F
		Н	X	X	*	X	X	X	Q _P	Q _F	Hi–Z
+5V		X	+10V	X	X	1	X	X	Qp	L	L
		X	+10V	X	X	\uparrow	X	X	Q _P	Н	н
		X	X	+10V	X	\uparrow	X	X	L	Q _F	L
		X	X	+10V	X	1	X	X	Н	Q _F	н
		L	X	X	+10V	X	X	X	Qp	Q _F	Qp
		L	X	Χ	X	X	X	X	Q _P	Q _F	Q _F
		L	X	X	X	1	L	L	Qp	Q _F	QF
		L	X	X	X	\uparrow	L	Н	L	L	L
		L	X	X	X	\uparrow	Н	L	Н	Н	н
		L	X	X	X	1	Н	Н	Qp	Q _F	Q _F
1	X	X	X	X	X	Х	X	X	Н	Н	

NOTES:

1. Positive Logic:

- S/R (or J/K) = T₀ + T₁ + T₂ + . . . T₆₃

 T_n = (C₀, C₁)(I₀, I₁, I₂, . . .) (P₀, P₁, . . . P₇)


 Either Initialization (Active–High) or Output Enable (Active–Low) are available, but not both. The desired function is a user–programmable
- 3. The denotes transition from Low-to-High level.
- * = H or L or +10V
- 5. X = Don't Care (≤5.5V)
- 6. H/L implies that either a High or a Low can occur, depending upon user-programmed selection (each State and Output Register individually programmable)
- 7. When using the F_n pins as inputs to the State and Output Registers in diagnostic mode, the F buffers are 3–Stated and the indicated levels on the output pins are forced by the user.

VIRGIN STATE

A factory-shipped virgin device contains all fusible links intact, such that:

- 1. INIT/OE is set to INIT. In order to use the INIT function, the user must select either the PRESET or the RESET option for each flip-flop. Note that regardless of the userprogrammed initialization, or even if the INIT function is not used, all registers are preset to "1" by the power-up procedure.
- 2. All transition terms are inactive (0).
- 3. All S/R (or J/K) flip-flop inputs are disabled
- 4. The device can be clocked via a Test Array preprogrammed with a standard test pattern.
- 5. Clock 2 is inactive


LOGIC FUNCTION



October 1989 346

PLUS405-55


FUNCTIONAL DIAGRAM



October 1989 347

PLUS405-55


LOGIC DIAGRAM



October 1989

PLUS405-55

DETAILS FOR REGISTERS FOR PLUS405



October 1989 349

PLUS405-55

ORDERING INFORMATION

DESCRIPTION	OPERATING FREQUENCY	ORDER CODE
28-Pin Plastic DIP (600mil-wide)	55MHz (t _{IS1} + t _{CKO1})	PLUS405-55N
28-Pin Plastic Leaded Chip Carrier	55MHz (t _{IS1} + t _{CKO1})	PLUS405-55A

ABSOLUTE MAXIMUM RATINGS¹

SYMBOL	PARAMETER	RATINGS	UNIT
V _{CC}	Supply voltage	+7	V_{DC}
V _{IN}	Input voltage	+5.5	V _{DC}
V _{OUT}	Output voltage	+5.5	V _{DC}
I _{IN}	Input currents	-30 to +30	mA
I _{OUT}	Output currents	+100	mA
T _A	Operating temperature range	0 to +75	°C
T _{STG}	Storage temperature range	-65 to +150	°C

NOTES:

THERMAL RATINGS

TEMPERATURE							
Maximum junction	150°C						
Maximum ambient	75°C						
Allowable thermal rise ambient to junction	75°C						

The PLUS405 devices are also processed for operation over the military temperature range. For Specifications and ordering information, consult the Signetics Military Data Manual.

October 1989 350

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

PLUS405-55

DC ELECTRICAL CHARACTERISTICS 0°C ≤ T_A ≤ +75°C, 4.75V ≤ V_{CC} ≤ 5.25V

	,					
SYMBOL	PARAMETER	TEST CONDITIONS	Min	Typ1	Max	UNIT
Input volt	age ²					1
V _{IH}	High	V _{CC} = MAX	2.0			V
V _{IL}	Low	V _{CC} = MIN			0.8	V
V _{IC}	Clamp ³	V _{CC} = MIN, I _{IN} = -12mA		-0.8	-1.2	V
Output vo	ltage ²		-	•	•	•
V _{OH}	High	V _{CC} = MIN, I _{OH} = -2mA	2.4			V
V _{OL}	Low	V _{CC} = MIN, I _{OL} = 9.6mA		0.35	0.45	V
Input curr	ent		-	•		
I _{IH}	High	V _{CC} = MAX, V _{IN} = V _{CC}		<1	25	μА
I _{IL}	Low	V _{CC} = MAX, V _{IN} = 0.45V		-20	-250	μА
Output cu	rrent			•		
I _{O(OFF)}	Hi–Z state	V _{CC} = MAX, V _{OUT} = 5.5V		1	40	μА
		V _{CC} = MAX, V _{OUT} = 0.45V		-1	-40	μА
los	Short circuit 3, 4	V _{OUT} = 0V	-15		-70	mA
Icc	V _{CC} supply current ⁵	V _{CC} = MAX		190	225	mA
Capacitar	ce	*		***************************************	4	-
C _{IN}	Input	V _{CC} = 5.0V, V _{IN} = 2.0V		8		pF
C _{OUT}	Output	V _{CC} = 5.0V, V _{OUT} = 2.0V		10		pF

NOTES:

- 1. All typical values are at $V_{CC} = 5V$. $T_A = +25^{\circ}C$. 2. All voltage values are with respect to network ground terminal.
- 3. Test one at a time.
- 4. Duration of short-circuit should not exceed one second.
- 5. I_{CC} is measured with the INIT/OE input grounded, all other inputs at 4.5V and the outputs open.

PLUS405-55

AC ELECTRICAL CHARACTERISTICS $R_1 = 470\Omega$, $R_2 = 1k\Omega$, $C_L = 30pF$, $0^{\circ}C \le T_A \le +75^{\circ}C$, $4.75V \le V_{CC} \le 5.25V$

			то	LIMITS			
SYMBOL	PARAMETER	FROM		Min	Typ1	Max	UNIT
Pulse widt	th						
t _{CKH1}	Clock High; CLK1 (Pin 1)	CK+	CK-	7.5	6		ns
t _{CKL1}	Clock Low; CLK1 (Pin 1)	CK-	CK+	7.5	6		ns
t _{CKP1}	CLK1 Period (without Complement Array)	Input +/-	Output +/-	18	15.5		ns
t _{CKH2}	Clock High; CLK2 (Pin 4)	CK+	CK-	7.5	6		ns
t _{CKL2}	Clock Low; CLK2 (Pin 4)	CK-	CK+	7.5	6		ns
t _{CKP2}	CLK2 Period (without Complement Array)	Input +/-	Output +/-	18	15.5		ns
t _{CKP3}	CLK1 Period (with Complement Array)	Input +/-	Output +/-	26	21.5		ns
t _{CKP4}	CLK2 Period (with Complement Array)	Input +/-	Output +/-	26	21.5		ns
t _{INITH}	Initialization pulse	INIT-	INIT+	12	8		ns
Setup time	92	•	•				
t _{IS1}	Input	Input ±	CK+	10	9		ns
t _{IS2}	Input (through Complement Array)	Input ±	CK+	18	15		ns
t _{VS}	Power–on preset	V _{CC} +	CK-	0	-10		ns
t _{VCK}	Clock resume (after Initialization)	INIT-	CK-	0	-5		ns
t _{NVCK}	Clock lockout (before Initialization)	CK-	INIT-	12	5		ns
Hold time		•		-	•	•	
t _{IH}	Input	CK+	Input ±	0	-5		ns
Propagation	on delay		•	-	•	•	
t _{CKO1}	Clock1 (Pin 1)	CK1+	Output ±		6.5	8	ns
t _{CKO2}	Clock2 (Pin 4)	CK2+	Output ±		6.5	8	ns
t _{OE}	Output Enable	OE-	Output –		6.5	8	ns
t _{OD}	Output Disable ²	OE+	Output +		6.5	8	ns
t _{INIT}	Initialization	INIT+	Output +		12	18	ns
t _{PPR}	Power-on Preset	V _{CC} +	Output +		0	10	ns
Frequency	of operation		•	-	•		
f _{MAX1}	CLK1; (without Complement Array)			55.6	64.5		MHz
f _{MAX2}	CLK2; (without Complement Array)			55.6	64.5		MHz
f _{MAX3}	CLK1; (with Complement Array)			38.5	46.5		MHz
f _{MAX4}	CLK2; (with Complement Array)			38.5	46.5		MHz

NOTES:


October 1989 352

^{1.} All typical values are at V_{CC} = 5V, T_A = +25°C. 2. C_L = 5pF; V_T = V_{OL} + 0.5V.

Field–Programmable Logic Sequencer ($16 \times 64 \times 8$)

PLUS405-55


TIMING DIAGRAMS



Field-Programmable Logic Sequencer ($16 \times 64 \times 8$)

PLUS405-55





Field–Programmable Logic Sequencer (16 \times 64 \times 8)

PLUS405-55

TIMING DEFINITIONS

TIMINA DEI INTITOTO						
SYMBOL	PARAMETER					
t _{CKH1,2}	Width of input clock pulse.					
t _{CKP1, 2}	Oerating period – when not using Complement Array.					
t _{IS1}	Required delay between beginning of valid input and positive transition of Clock.					
t _{CKO1, 2}	Delay between positive transition of Clock and when Outputs become valid (with INIT/OE Low).					
t _{PPR}	Delay between V _{CC} (after power–on) and when Outputs become preset at "1".					
t _{IS2}	Required delay between beginning of valid Input and positive transition of Clock, when using optional Complement Array (two passes necessary through the AND Array).					
t _{RJH}	Required delay between positive transition of Clock and end of inputs I ₁₁ or I ₁₀ transition to State and Output Register Input Jam Diagnostic Modes, respectively.					
f _{MAX1, 2,} 3, 4	Minimum guaranteed operating frequency.					

SYMBOL	PARAMETER
t _{CKL1, 2}	Interval between clock pulses.
t _{CKP3, 4}	Operating period – when using Complement Array.
t _{IH}	Required delay between positive transition of Clock and end of valid Input data.
t _{OE}	Delay between beginning of Output Enable Low and when Outputs become valid.
t _{SRE}	Delay between input I ₁₂ transition to Diagnostic Mode and when the Outputs reflect the contents of the State Register.
t _{RJS}	Required delay between inputs I ₁₁ or I ₁₀ transition to State and Output Register Input Jam Diagnostic Modes, respectively, and when the output pins become available as inputs.
† _N VCK	Required delay between the negative transition of the clock and the negative transition of the Asynchronous Initialization to guarantee that the clock edge is not detected as a valid negative transition.


SYMBOL	PARAMETER
t _{INITH}	Width of initialization input pulse.
t _{VS}	Required delay between V _{CC} (after power–on) and negative transition of Clock preceding first reliable clock pulse.
t _{OD}	Delay between beginning of Output Enable High and when Outputs are in the OFF–state.
t _{INIT}	Delay between positive transition of Initialization and when Outputs become valid.
t _{SRD}	Delay between input I ₁₂ transition to Logic mode and when the Outputs reflect the contents of the Output Register.
t _{RH}	Required delay between positive transition of Clock and end of valid Input data when jamming data into State or Output Registers in diagnostic mode.
t _{VCK}	Required delay between negative transition of Asynchronous Initialization and negative transition of Clock preceding first reliable clock pulse.

October 1989 355


Field–Programmable Logic Sequencer ($16 \times 64 \times 8$)

PLUS405-55

TEST LOAD CIRCUIT



VOLTAGE WAVEFORMS




LOGIC PROGRAMMING

PLUS405 Logic designs can be generated using Signetics AMAZE design software or several other commercially available, JEDEC standard PLD design software packages. Boolean and/or state equation entry format is accepted.

PLUS405 logic designs can also be generated using the program table format detailed on the following page(s). This Program Table Entry format (PTE) is supported by the Signetics AMAZE PLD design software. AMAZE is available free of charge to qualified users.

To implement the desired logic functions, each logic variable (I, B, P, S, T, etc.) from the logic equations is assigned a symbol. TRUE, COMPLEMENT, PRESET, RESET, OUTPUT ENABLE, INACTIVE, etc., symbols are defined below.


INITIALIZATION/OE OPTION - (INIT/OE)



PROGRAMMING THE PLUS405:

The PLUS405 has a power—up preset feature. This feature insures that the device will power—up in a known state with all register elements (State and Output Register) at logic High (H). When programming the device it is important to realize this is the initial state of the device. You *must* provide a next state jump if you do not wish to use all Highs (H) as the present state.

PRESET/RESET OPTION - (P/R)




October 1989 356


Field-Programmable Logic Sequencer (16 \times 64 \times 8)

PLUS405-55







"OR" ARRAY - J-K FUNCTION - (N), (F)



"COMPLEMENT" ARRAY - (C)



CLOCK OPTION - (CLK1/CLK2)



NOTES:


- This is the initial unprogrammed state of all links.
- Any gate T_n will be unconditionally inhibited if any one of its I or P link pairs is left intact.
- To prevent oscillations, this state is not allowed for C link pairs coupled to active gates T_n. These states are not allowed when using PRESET/RESET option.
- 5. Input buffer I₅ must be deleted from the AND array (i.e., all fuse locations "Don't Care") when using second clock option.
- 6. A single product term cannot drive more than 8 registers by itself when used in TOGGLE mode.

October 1989 357

Field-Programmable Logic Sequencer (16 \times 64 \times 8)

PLUS405-55

PLUS405 PROGRAM TABLE



October 1989 358

The FPLS is shipped with all links initially intact. Thus, a background of "0" for all Terms, and an "H" for the IN/E and H for the clock option, exists in the table, shown BLANK instead To clarity.

Unused Cn Im, and Ps bits are normally programmed Don't Care (—).

Unused Transition Terms can be left blank for future code modification, or programmed as (—) for maximum speed.

Signetics

Programmable Logic Devices

Section 6 Programmable Macro Logic Data Sheets

INDEX

PLHS501	Programmable Macro Logic	361
PLHS502	Programmable Macro Logic	372
PLHS601	Programmable Macro Logic	384
PML2552	Programmable Macro Logic	395

Signetics

Document No.	853–1207				
ECN No.	98069				
Date of Issue	November 10, 1989				
Status	Product Specification				
Programmable Logic Devices					

FEATURES

- Programmable Macro Logic device
- Full connectivity
- TTL compatible
- SNAP development system
 - Supports third-party schematic entry formats
 - Macro library
 - Versatile netlist format for design portability
 - Logic, timing, and fault simulation
- AMAZE development system:
 - Supports third-party schematic entry formats
 - Boolean equation entry
 - Logic, timing, and fault simulation
- Delay per internal NAND function = 6.5ns (typ)
- · Testable in unprogrammed state
- Security fuse allows protection of proprietary designs

PLHS501

Programmable Macro Logic PMI™

STRUCTURE

- NAND gate based architecture
 72 foldback NAND terms
- 104 input-wide logic terms
- 44 additional logic terms
- 24 dedicated inputs (I₀ I₂₃)
- 8 bidirectional I/Os with individual 3-State enable:
 - -4 active-High ($B_4 B_7$)
- 4 active-Low $(\overline{B}_0 \overline{B}_3)$
- 16 dedicated outputs:
 - 4 active—High outputs
 O₀, O₁ with common 3-State enable
 - O₂, O₃ with common 3–State enable
 - 4 active-Low outputs:
 - $\overline{O}_4, \, \overline{O}_5$ with common 3–State enable
 - \overline{O}_6 , \overline{O}_7 with common 3–State enable
 - 8 Exclusive-OR outputs:
 - $X_0 X_3$ with common 3-State enable
 - X₄ X₇ with common 3–State enable

DESCRIPTION

The PLHS501 is a high-density Bipolar Programmable Macro Logic device. PML incorporates a programmable NAND structure. The NAND architecture is an efficient method for implementing any logic function. The SNAP software development system provides a user friendly environment for design entry. SNAP eliminates the need for a detailed understanding of the PLHS501 architecture and makes it transparent to the user. PLHS501 is also supported on the Signetics AMAZE software development system.

The PLHS501 is ideal for a wide range of microprocessor support functions, including bus interface and control applications.

PML is a trademark of Philips Components—Signetics


Philips Components





PLHS501

PIN CONFIGURATION



ARCHITECTURE

The core of the PLHS501 is a programmable fuse array of 72 NAND gates. The output of each gate folds back upon itself and all other NAND gates. In this manner, full connectivity of all logic functions is achieved in the PLHS501. Any logic function can be created within the core of the device without wasting valuable I/O pins. Furthermore, a speed advantage is acquired by implementing multi-level logic within a fast internal core without incurring any delays from the I/O buffers.

DESIGN DEVELOPMENT TOOLS

The SNAP Software Development System provides the necessary tools for designing with PML. SNAP provides the following:

- Schematicentry netlist generation from thirdparty schematic design packages such as OrCAD/SDT IIITM and FutureNetTM.
- Macro library for standard PLHS501 functions and user defined functions
- Boolean equation entry
- State equation entry
- Syntax and design entry checking
- Simulator includes logic simulation, fault simulation and timing simulation.

SNAP operates on an IBM® PC/XT, PC/AT, PS/2, or any compatible system with DOS 2.1 or higher. The minimum system configuration for SNAP is 640K bytes of RAM and a hard disk.

SNAP provides primitive PML function libraries for third-party schematic design packages. Custom macro function libraries can be defined in schematic or equation form.

After the completion of a design, the software compiles the design for syntax and completeness. Complete simulation can be carried out using the different simulation tools available.

The programming data is generated in JEDEC format. Using the Device Programmer Inter-face (DPI) module of SNAP, the JEDEC fusemap is sent from the host computer to the device programmer.

AMAZE

The AMAZE PLD Design Software development system also supports the PLHS501. AMAZE provides the following capabilities for the PLHS501:

- Schematic entry netlist conversion from third-party schematic software
- Boolean equation entry
- Logic and timing simulation
- Automatic test vector generation

AMAZE operates on an IBM PC/XT, PC/AT, PS/2, or any compatible system with DOS 2.0 or higher. The minimum system configuration for AMAZE is 640K bytes of RAM and a hard disk.

AMAZE compiles the design after completion for syntax and completeness. Programming data is generated in JEDEC format.


DESIGN SECURITY

The PLHS501 has a programmable security fuse that controls the access to the data programmed in the device. By using this programmable feature, proprietary designs implemented in the device cannot be copied or retrieved.

FutureNet is a trademark of FutureNet Corporation.
OrCAD/SDT is a trademark of OrCAD, Inc.
IBM is a registered trademark of International Business Machines Corporation.


PLHS501

PLHS501 FUNCTIONAL BLOCK DIAGRAM



PLHS501

FUNCTIONAL DIAGRAM



PLHS501

ORDERING INFORMATION

DESCRIPTION	ORDER CODE	
52-Pin Plastic Leaded Chip Carrier	PLHS501A	

ABSOLUTE MAXIMUM RATINGS1

		RATINGS		
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage		+7	V _{DC}
V _{IN}	Input voltage		+5.5	V _{DC}
V _{OUT}	Output voltage		+5.5	V _{DC}
I _{IN}	Input currents	-30	+30	mA
I _{OUT}	Output currents		+100	mA
T _A	Operating temperature range	0	+75	°C
T _{STG}	Storage temperature range	-65	+150	°C

NOTE:

THERMAL RATINGS

TEMPERATURE						
Maximum junction	150°C					
Maximum ambient	75°C					
Allowable thermal rise ambient to junction	75°C					

VIRGIN STATE

A factory shipped virgin device contains all fusible links open, such that:

- All product terms are enabled.
- 2. All bidirectional (B) pins are outputs.
- 3. All outputs are enabled.
- All outputs are active—High except B₀ − B₃ (fusible I/O) and O₄ − O₇ which are active—Low.

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

PLHS501


DC ELECTRICAL CHARACTERISTICS $0^{\circ}C \le T_{A} \le +75^{\circ}C$, $4.75V \le V_{CC} \le 5.25V$

				LIMITS		
SYMBOL	PARAMETER	TEST CONDITION	Min	Typ ¹	Max	UNIT
Input volt	age ²					
V _{IL}	Low	V _{CC} = Min			0.8	V
V _{IH}	High	V _{CC} = Max	2.0			V
V _{IC}	Clamp ^{2, 3}	V _{CC} = Min, I _{IN} = -12mA		-0.8	-1.2	V
Output vo	oltage					
		V _{CC} = Min				
V_{OL}	Low ^{2, 4}	I _{OL} = 10mA			0.45	V
V_{OH}	High ^{2, 5}	$I_{OH} = -2mA$	2.4			V
Input curi	rent					
		V _{CC} = Max				
IIL	Low	$V_{1N} = 0.45V$			-100	μА
I_{HH}	High	V _{IN} = 5.5V			40	μА
Output cu	urrent					
		V _{CC} = Max		-		
I _{O(OFF)}	Hi–Z state ⁹	V _{OUT} = 5.5V			80	μА
-(/		V _{OUT} = 0.45V			-140	
Ios	Short circuit ^{3, 5, 6}	V _{OUT} = 0V	-15		-70	mA
I _{CC}	V _{CC} supply current ⁸	V _{CC} = Max		225	295	mA
Capacitar	nce		•		•	
		V _{CC} = 5V				
CIN	Input	$V_{IN} = 2.0V$		8		pF
CB	1/0	V _{OUT} = 2.0V		15		pF


NOTES:

- All typical values are at V_{CC} = 5V, T_A = +25°C.
- 2. All voltage values are with respect to network ground terminal,
- 3. Test one at a time.
- 4. For Pins 15 19, 21 27 and 37 40, V_{OL} is measured with Pins 5 and 41 = 8,75V, Pin 43 = 0V and Pins 42 and 44 = 4.5V. For Pins 28 - 33 and 35 - 36, V_{OL} is measured under same conditions EXCEPT Pin 44 = 0V.
- V_{OH} is measured with Pins 5 and 41 = 8.75V, Pins 42 and 43 = 4.5V and Pin 44 = 0V.
- 6. Duration of short circuit should not exceed 1 second.
- 7. I_{CC} is measured with all dedicated inputs at 0V and bidirectional and output pins open.
- Measured at V_T = V_{OL} + 0.5V.
 Leakage values are a combination of input and output leakage.

TEST LOAD CIRCUITS




VOLTAGE WAVEFORMS



PLHS501

SNAP RESOURCE SUMMARY DESIGNATIONS



PLHS501

 $\textbf{MACRO CELL SPECIFICATIONS1 T_A = 0°C to +75°C, 4.75V \\ \leq V_{CC} \leq 5.25V, C_L = 30pF, R_2 = 1000\Omega, R_1 = 470\Omega \times 10^{-10} \text{ M} + 10^{-10$ (SNAP Resource Summary Designations in Parantheses)

Input Buffer (DIN501 [Non-inverting], NIN501 [Inverting])




		LIMITS		
SYMBOL	Min	Тур	Max	UNIT
Δt_{HL}	0.05	0.1	0.15	ns/p-term
Δt_{LH}	-0.02	-0.05	-0.08	ns/p-term

	PARAM	METER		LIMITS			NOTES	
SYMBOL	To (Output)	From (Input)	Min	Тур	Max	UNIT		
t _{PHL} t _{PLH}	X	1	4.5 5	5.5 6	6.5 7.5	ns ns	With 0 p-terms load	
t _{РНL} t _{РLН}	Y	1	2.5 4	3 4	3.5 4.5	ns ns	With 0 p-terms load	

Input Pins: 1 – 7, 9 – 14, 41 – 45, 48 – 52. Bidirectional Pins: 15 – 18, 37 – 40.

Maximum internal fan-out: 16 p-terms on X or Y.

NAND Output Buffer with 3-State Control (TOU501)



	PARAM	METER				
SYMBOL	To (Output)	From (Input)	Min	Тур	Мах	UNIT
t _{PHL}	Out	In	8.5	14.0	17.5	ns
t _{PLH}	Out	In	8.5	14.0	16	ns
t _{OE}	Out	Tri-Ctrl	8.5	15	18.5	ns
	Out	Tri-Ctrl	8.5	12.5	17.0	ns

Output Pins: 24 - 27.

Internal Foldback NAND (FBNAND)



		LIMITS		
SYMBOL	Min	Тур	Max	UNIT
Δt_{PHL}	0.05	0.1	0.15	ns/p-term
Δt_{PLH}	-0.0	-0.05	-0.1	ns/p-term


		PARAMETER		LIMITS				
SYM	IBOL	To (Output)	From (Input)	Min	Тур	Max	UNIT	NOTES
	PHL PLH	Out	Any	4.0 5.5	4.5 6.5	6.8 8	ns ns	With 0 p-terms load

Maximum internal loading of 16 terms.

^{1.} Limits are guaranteed with internal feedback buffers simultaneously switching cumulative maximum of eight outputs.

PLHS501

MACRO CELL SPECIFICATIONS (Continued) $T_A = 0^{\circ}C$ to +75°C, 4.75V $\leq V_{CC} \leq 5.25V$, $C_L = 30pF$, $R_2 = 1000\Omega$, $R_1 = 470\Omega$ (SNAP Resource Summary Designations in Parantheses)



	PARAM	METER				
SYMBOL	To (Output)	From (Input)	Min Typ		Max	UNIT
t _{PHL}	Output	In	8.0	11	13	ns
t _{PLH}	Output	In	8.0	11	13	ns
t _{OE}	Out	Tri-Ctrl	8.5	15	18.5	ns
	Out	Tri-Ctrl	8.5	12.5	17.0	ns

Bidirectional and Output Pins: 19, 21, 22, 23, 15 - 18.






	PARAM	METER	LIMITS			
SYMBOL	To (Output)	From (Input)	Min	Тур	Max	UNIT
t _{PHL} t _{PLH}	Out Out	In In	8.5 8.5	14 14	17.5 16.0	ns ns

Bidirectional Pins: 37 - 40.

Ex-OR Output Buffer (EXO501)



	PARAM	METER	LIMITS			
SYMBOL	To (Output)	From (Input)	Min	Тур	Max	UNIT
t _{PHL}	Out	A or B	8.5	14	17.5	ns
t _{PLH}	Out	A or B	8.5	14	16.0	ns
t _{OE}	Out	Tri-Ctrl	8.5	15	18.5	ns
	Out	Tri-Ctrl	8.5	12.5	17.0	ns

Ex-OR Output Pins: 28 - 33.


PLHS501

PLHS501 GATE AND SPEED ESTIMATE TABLE

FUNCTION	INTERNAL NAND EQUVALENT	TYPICAL t _{PD}	f _{MAX}	COMMENTS
Gates				
NANDs	1	6.5ns		For 1 to 32 input variables
ANDs	1	6.5ns		For 1 to 32 input variables
NORs	1	6.5ns		For 1 to 32 input variables
ORs	1	6.5ns		For 1 to 32 input variables
Decoders				
3-to-8	8	11ns		Inverted inputs available
4-to-16	16	11ns		Inverted inputs available
5-to-32	32	11ns		Inverted inputs available (24 chip outputs only)
Encoders				
8-to-3	15	11ns		Inverted inputs, 2 logic levels
16-to-4	32	11ns		Inverted inputs, 2 logic levels
32-to-5	41	11ns		Inverted inputs, 2 logic levels, factored solution.
Multiplexers	,			
4-to-1	5	11ns		Inverted inputs available
8-to-1	9	11ns		
16-to-1	17	11ns		
27-to-1	28	11ns		Can address only 27 external inputs – more if internal
Flip-Flops				
D-type Flip-Flop	6		30MHz	With asynchronous S–R
T-type Flip-Flop	6		30MHz	With asynchronous S-R
J-K-type Flip-Flop	10		30MHz	With asynchronous S-R
Adders				
8-bit	45	15.5ns		Full carry-lookahead (four levels of logic)
Barrel Shifters		•		
8-bit	72	11ns		2 levels of logic
Latches	^			
D-latch	3			2 levels of logic with one shared gate

PLHS501

APPLICATIONS



NuBus is a trademark of Texas Instruments, Inc.

Signetics

Document No.	853–1405		
ECN No.	98070		
Date of Issue	November 10, 1989		
Status	Product Specification		
Programmable Logic Devices			

PLHS502 Programmable Macro Logic

PMI TM

FEATURES

- Programmable Macro Logic
- Full connectivity
- Delay per internal NAND function = 6.5ns
- Clock frequency = 40MHz
 Operating frequency = 33MHz
- SNAP development system eases design
 - Supports third-party schematic entry formats
 - Macro library
 - Versatile netlist format for design portability
 - Logic, timing, and fault simulation
- TTL compatible
- Security fuse allows protection of proprietary designs
- Testable in unprogrammed state

STRUCTURE

- NAND gate based architecture
- 64 foldback NAND terms
- 80 additional logic terms
- 128 inputs per logic term
- 20 dedicated inputs
- 4 programmable input/clock inputs
- 8 independent clocks
 - 4 from input/clock pins
 - 4 from NAND array
- 8 bidirectional I/Os
- 16 dedicated outputs
- 8 active-High outputs
- 4 outputs with programmable polarity
- 4 3—State outputs with programmable polarity and independent 3—State control
- 16 buried flip-flops
 - 8 D type
 - 8 S-R type

DESCRIPTION

The Signetics PML family of PLDs provides the capability to create fast and cost effective solutions for a number of microprocessor interface and control applications. PML incorporates the unique feature of a programmable NAND structure as the basis of its architecture.

The PLHS502 is a high-density Bipolar Programmable Macro Logic Device. The folded NAND array combined with embedded I/O flip-flops allows for both timing control, wide decoders, multiplexers, and system input and output bus latches to be combined onto one device.

APPLICATIONS

- VRAM controllers
- DRAM/SRAM controllers
- Multiple state machines
- Timing control
- Error detection/correction

PML is a trademark of Philips Components-Signetics








PLHS502

Programmable Macro Logic

PIN CONFIGURATION



ARCHITECTURE

The core of the PLHS502 is a programmable fuse array of 64 NAND gates and 16 buried flipflops. The output of each gate and flip-flop folds back upon itself and all other NAND gates and lip-flops. In this manner, full connectivity of all logic functions is achieved in the PLHS502. Any logic function can be created within the core of the device without wasting valuable I/O pins. Furthermore, a speed advantage is acquired by implementing multi-level logic within a fast internal core without incurring any delays from the I/O buffers.

Buried Flip-Flops

The 16 buried flip-flops can be connected to the input or output structures through the NAND array. Intricate state machine designs can be implemented within the core without any unnecessary delays from the input or output buffers. Each flip-flop can be realized as an input or output register with no constraints.

The Clock Array

There are a combination of 26 possible inputs to the 'Clock Array':

 2 are directly from the input pins fed through an inverting buffer.

- 4 inputs with programmable polarity directly from the input pins.
- 4 inputs from 4 individual NAND terms.
- 16 inputs from the 'Q' outputs of the flipflops.

The wide selection of clocking options offers the user the capacity to create custom and independent clock functions for the flip-flops. This together with the full connectivity of the device, offers the capability to implement a variety of synchronous and asynchronous state machines. Another possible application is implementing multi-phase designs such as pipe-lined processing.

DESIGN DEVELOPMENT TOOLS

The SNAP Software Development System provides the necessary tools for designing with PML. SNAP provides the following:

- Schematic entry netlist generation from thirdparty schematic design packages such as OrCAD/SDTTM and FutureNetTM.
- Macro library for standard PLHS502 functions and user defined functions

- Boolean equation entry
- State equation entry
- · Syntax and design entry checking
- Simulator includes logic simulation, fault simulation, and timing simulation.

SNAP operates on an IBM® PC/XT, PC/AT, PS/2, or any compatible system with DOS 2.1 or higher. A minimum of 640K bytes of RAM is required together with a hard disk.

SNAP provides primitive PML function libraries for third party schematic design packages. Custom macro function libraries can be defined in schematic or equation form.

After the completion of a design, the software compiles the design for syntax and completeness. Complete simulation can be carried out using the different simulation tools available.

The programming data is generated in JEDEC format. Using the Device Programmer Interface (DPI) module of SNAP, the JEDEC fusemap is sent from the host computer to the device programmer.

FutureNet is a trademark of FutureNet Corporation.
OrCAD/SDT is a trademark of OrCAD, Inc.


IBM is a registered trademark of International Business Machines Corporation.

PLHS502

DESIGN SECURITY


The PLHS502 has a programmable security fuse that controls the access to the data programmed in the device. By using this programmable feature, proprietary designs implemented in the device cannot be copied or retrieved.

PLHS502 FUNCTIONAL BLOCK DIAGRAM




PLHS502


FUNCTIONAL DIAGRAM



TEST LOAD CIRCUITS



VOLTAGE WAVEFORMS



PLHS502

ORDERING INFORMATION

DESCRIPTION	ORDER CODE		
68-Pin Plastic Leaded Chip Carrier	PLHS502A		

ABSOLUTE MAXIMUM RATINGS1

		RATI		
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage		+7	V _{DC}
V _{IN}	Input voltage		+5.5	V _{DC}
V _{OUT}	Output voltage		+5.5	V _{DC}
I _{IN}	Input currents	-30	+30	mA
I _{OUT}	Output currents		+100	mA
T _A	Operating temperature range	0	+75	°C
T _{STG}	Storage temperature range	-65	+150	°C

NOTE:

THERMAL RATINGS

TEMPERATURE					
Maximum junction	150°C				
Maximum ambient	75°C				
Allowable thermal rise ambient to junction	75°C				

VIRGIN STATE

A factory shipped virgin device contains all fusible links open, such that:

- 1. All bidirectional (B) pins are outputs.
- 2. All outputs are enabled.
- 3. All outputs are active—Low except $O_0 O_7$, which are active—High.

DC ELECTRICAL CHARACTERISTICS $0^{\circ}C \le T_{A} \le +75^{\circ}C$, $4.75V \le V_{CC} \le 5.25V$

				LIMITS		
SYMBOL	PARAMETER	TEST CONDITION	Min	Typ1	Max	UNI
Input volt	age ²		•			
V _{IL}	Low	V _{CC} = Min			0.8	V
V _{IH}	High	V _{CC} = Max	2.0			V
V _{IC}	Clamp ²	$V_{CC} = Min, I_{IN} = -12mA$		-0.8	-1.2	V
Output vo	ltage					
		V _{CC} = Min				
V_{OL}	Low ²	I _{OL} = 10mA			0.45	V
V _{OH}	High ²	$I_{OH} = -2mA$	2.4			V
Input curr	rent					
		V _{CC} = Max				
l _{IL}	Low	$V_{IN} = 0.45V$			-100	μА
I_{IH}	High	V _{IN} = 5.5V			40	μА
Output cu	irrent			-		
		V _{CC} = Max				
I _{O(OFF)}	Hi–Z state	V _{OUT} = 5.5V			80	μА
		V _{OUT} = 0.45V			-140	
Ios	Short circuit	V _{OUT} = 0V	-15		-70	m.A
Icc	V _{CC} supply current	V _{CC} = Max			400	m.A
Capacitan	ice	•		•	•	
		V _{CC} = 5V				
CIN	Input	$V_{IN} = 2.0V$		8		pF
CB	1/0	V _{OUT} = 2.0V		15		pF

NOTES

- 1. All typical values are at $V_{CC} = 5V$, $T_A = +25^{\circ}C$.
- 2. All voltage values are with respect to network ground terminal.

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

PLHS502

MACRO CELL A.C. SPECIFICATIONS (SNAP Resource Summary Designations in Parentheses)

Input Buffer (DIN502, CDIN502, BDIN502 NIN502, CNIN502, BNIN502)




SYMBOL	Min	Тур	Max	UNIT
Δt_{HL}	0.05	0.1	0.15	ns/p-term
Δt_{LH}	-0.02	-0.05	-0.08	ns/p-term

	PARAM	METER		LIMITS			
SYMBOL	To (Output)	From (Input)	Min	Тур	Max	UNIT	NOTES
t _{HL} t _{LH}	X	1	4 4.5	5 5.5	6 6.5	ns ns	With 0 p-term load
t _{HL} t _{LH}	Y	1	2 3.5	3 3.5	3.5 4	ns ns	With 0 p-term load

Input Pins: 1, 2, 4–8, 10, 11, 13, 14, 17, 18, 53, 56–59, 61, 62, 64–66, 68. Bidirectional Pins: 19, 22–25, 27, 28, 30.

Limit of 16 NAND terms for Input Buffer (X and Y) and Internal Foldback NAND (Y).

NAND Output Buffer with 3-State Control (TOU502)



	PARAM	METER		LIMITS		
SYMBOL	To (Output)	From (Input)	Min	Тур	Max	UNIT
t _{PHL}	Out	In	8.5	9	13.5	ns
t _{PLH}	Out	In	9	10	14	ns
t _{OE}	Out	Tri-Ctrl	10	12	18.5	ns
	Out	Tri-Ctrl	8	10	16	ns

Bidirectional and Output Pins: 19, 22-25, 27, 28, 30.

Internal Foldback NAND (FBNAND)




SYMBOL	Min	Тур	Max	UNIT
Δt_{PHL}	0.05	0.1	0.15	ns/p-term
Δ t _{PLH}	-0.02	-0.05	-0.08	ns/p–term

	PARAM	METER	LIMITS				
SYMBOL	To (Output)	From (Input)	Min	Тур Мах		UNIT	NOTES
t _{PHL}	Υ	X	4.0	5.0	5.5	ns	With 0 p-term load
t ₽LH	Υ	Х	5.5	6.5	8	ns	With 0 p-term load

Limit of 16 NAND terms for Input Buffer (X and Y) and Internal Foldback NAND (Y).

PLHS502


MACRO CELL A.C. SPECIFICATIONS (Continued) (SNAP Resource Summary Designations in Parentheses)



	PARAM	METER		LIMITS			
SYMBOL	To (Output)	From (Input)	Min	Тур	Max	UNIT	
t _{PHL}	Out	In	9	10	19	ns	
t _{PLH}	Out	In	10	12	19	ns	
t _{OE}	Out	TriCtrl	10	12	18.5	ns	
	Out	TriCtrl	8	10	16	ns	

Output Pins: 47, 48, 51, 52.

Output with Programmable Polarity (EXO502)



	PARAM	METER		LIMITS		
SYMBOL	To (Output)	From (Input)	Min	Тур	Max	UNIT
ф _{НL} ф _{LH}	Out Out	In In	9 10	10 12	19 19	ns ns

Output Pins: 41, 42, 44, 45.

Output Buffer (NOU502)



	PARAM	METER		LIMITS		
SYMBOL	To (Output)	From (Input)	Min	Тур	Max	UNIT
фнь фин	Out Out	In In	8 9	9 10	14 13.5	ns ns

Output Pins: 31, 32, 34-36, 38-40.

PLHS502

D FLIP-FLOP (SNAP Resource Summary Designation = DFF502)


	INPUTS	OUTPUTS		
CLR	СК	ס	Q	ā
Н	Х	Х	L	Н
L	L	×	Q ₀	ರ₀
L	↑	Н	L	Н
L	1	L	н	L


NOTE:


 Q_0 , \overline{Q}_0 represent previous stable condition of Q, \overline{Q} .

		LIMITS					
SYMBOL	Min	Тур	Max	UNIT			
fcK1	33	37	40	MHz			
f _{CK2}	37	40	43.5	MHz			
fскзх	33	37	40	MHz			
fскзу	37	40	43.5	MHz			
tw ck1	15	10	8	ns			
t _{P CK1}	30	27	25	ns			
tw ck2, tw ck3Y	10	9	8	ns			
tp CK2, tp CK3Y	27	25	23	ns			
tw ck3x	10	9	8	ns			
t-р скзх	30	27	25	ns			
t _{SETUP} D	7	5.5	3	ns			
t _{HOLD} D	8.5	4.5	1	ns			
t _{W CLR} High	10	9	8	ns			

t _{SETUP} D			7 5.5		5	3		ns	
t _{HOLD} D		8	3.5	4.5	5	1		ns	
t _{W CLR} High			10	9			8	ns	
						LIMITS	;		
SYMBOL	FROM (INPU			TO (OUTPUT)		in	Тур	Max	UNIT
t _{PLH}	CK1		Q	Q, Q		.5	20	25	ns
t _{PHL}	CK1		Q,	Q, Q		.5	20.5	24.5	ns
t _{PLH}	CK2		Q	, a	1	2	14	16.5	ns
t _{PHL}	CK2		Q	, a	1	3	15	16	ns
t _{PLH}	CK3>	(Q	, a	1	4	16	19.5	ns
t _{PHL}	CK3>	(Q	, a	1	5	16	19	ns
t _{PLH}	CK3\	1	Q	Q, \(\overline{Q}\)		2	14	16.5	ns
tpil	CK3\	/	Q	Q, Q		3	15	16	ns
t PLH	CLR		Q	, Q	1	1	15	20	ns







		LIMITS		
SYMBOL	Min	Тур Мах		NOTES
Δt_{SETUP}	-0.02	-0.05	-0.1	ns/FO of CK1,2,3

NOTES:

- Setup and Hold times are with reference to rising edge of CK1, CK2, and CK3.
- 2. Limit of 16 Logic terms load on Q and Q.

		LIMITS		
SYMBOL	Min	Тур	Max	NOTES
Δt_{PHLK}	0.05	0.1	0.15	ns/FO of CK1,2,3
Δt_{PLHK}	0.05	0.1	0.15	ns/FO of CK1,2,3
Δt_{PLHQ}	-0.02	-0.5	-0.08	ns/p-term load on Q, Q
Δt_{PHLQ}	0.05	0.1	0.15	ns/p-term load on Q, Q

t_{PHL}

CLR

Q, Q

12

15

19.5

ns

PLHS502


S-R FLIP-FLOP (SNAP Resource Summary Designation = RSF502)

	INP	OUTF	PUTS		
CLR	СК	5	R	Q	Q
Н	X	X	Х	L	Н
L	L	X	X	Q ₀	\overline{Q}_0
L	1	Н	L	L	Н
L	1	L	н	н	L
L	1	Н	н	Q ₀	₲
L	1	L	ĮL	Not al	lowed

NOTE:

 Q_0, \overline{Q}_0 represent previous stable condition of Q, \overline{Q} .

		LIMITS		
SYMBOL	Min	Тур	Max	UNIT
f _{CK1}	33	37	40	MHz
f _{CK2}	37	40	43.5	MHz
fскзх	33	37	40	MHz
fскзу	37	40	43.5	MHz
tw ck1	15	10	8	ns
t _P CK1	30	27	25	ns
tw ck2	10	9	8	ns
t _{P CK2}	27	25	23	ns
tw ck3X	10	9	8	ns
^t P CK3X	30	27	25	ns
tw ck3Y	10	9	8	ns
[‡] P CK3Y	27	25	23	ns
t _{SETUP} S, R	7	5.5	3	ns
t _{HOLD} S, R	8.5	4.5	1	ns
t _{W CLR} High	10	9	8	ns



	LIMITS			
SYMBOL	Min	Тур	Max	NOTES
Δt_{SETUP}	-0.02	-0.05	-0.1	ns/FO of CK1,2,3

SYMBOL	FROM (INPUT)	TO (OUTPUT)	Min	Тур	Max	UNIT
t _{PLH}	CK1	Q, Q	16.5	20	25	ns
t _{PHL}	CK1	Q, Q	17.5	20.5	24.5	ns
t _{PLH}	CK2	Q, \(\overline{Q}	12	14	16.5	ns
t _{PHL}	CK2	Q, Q	13	15	16	ns
t _{PLH}	CK3X	Q, Q	14	16	19.5	ns
t _{PHL}	СКЗХ	Q, \(\overline{Q}	15	17	19	ns
t _{PLH}	CK3Y	Q, Q	12	14	16.5	ns
t _{PHL}	СКЗҮ	Q, Q	13	15	16	ns
t _{PLH}	CLR	Q	11	15	20	ns
t _{PHL}	CLR	Q	12	15	19.5	ns


NOTES:

- Setup and Hold times are with reference to rising edge of CK1, CK2, and CK3.
- 2. Limit of 16 Logic terms load on Q and Q.

		LIMITS			
-	SYMBOL	Min	Тур	Max	NOTES
	Δt_{PHLK}	0.05	0.1	0.15	ns/FO of CK1,2,3
	Δt_{PLHK}	0.05	0.1	0.15	ns/FO of CK1,2,3
	Δt_{PLHQ}	-0.02	-0.5	-0.08	ns/p-term load on Q, Q
	Δt_{PHLQ}	0.05	0.1	0.15	ns/p-term load on Q, Q

PLHS502

SNAP RESOURCE SUMMARY DESIGNATIONS




PLHS502

PLHS502 GATE AND SPEED ESTIMATE TABLE

FUNCTION	INTERNAL NAND EQUVALENT	TYPICAL t _{PD}	f _{MAX}	COMMENTS
Gates				
NANDs	1	6.5ns		For 1 to 32-pin input variables
ANDs	1	6.5ns		Additional internal inputs can be used as needed
NORs	1	6.5ns		Additional internal inputs can be used as needed
ORs	1	6.5ns		Additional internal inputs can be used as needed
Macro Flip-Flops				
D-Type Flip-Flop	N/A		40MHz	Total budget = 8
SR-Type Flip-Flop	N/A	-	40MHz	Total budget = 8
Gate Implemented Flip-Flo	ops			
D-Type Flip-Flop	6	1	35MHz	With asynchronous S-R
T-Type Flip-Flop	6	7	35MHz	With asynchronous S-R
J-K-Type Flip-Flop	10		35MHz	With asynchronous S-R
Transparent-D Latch	4		N/A	With asynchronous S-R
S-R Latch	2		N/A	With asynchronous S-R
Decoders				
3-to-8	8	11.5ns		Inverted inputs available
4-to-16	16	11.5ns		Inverted inputs available
5-to-32	32	11.5ns		Inverted inputs available (24 chip outputs only)
Encoders				
8-to-3	15	11.5ns		Inverted inputs, 2 logic levels
16-to-4	32	11.5ns		Inverted inputs, 2 logic levels
32-to-5	41	11.5ns		Inverted inputs, 2 logic levels
Multiplexers				•
4-to-1	5	11.5ns		Inverted inputs available
8-to-1	9	11.5ns		Inverted inputs available
16-to-1	17	11.5ns		Inverted inputs available
27-to-1	28	11.5ns		Can address only 27 external inputs – more if interna only. This disallows clock inputs to flip–flop.


PLHS502 Rough Resource Budget = 64 NANDs, 8 D, 8 SR, 24 inputs, 16 outputs, 8 bidirectionals.

APPLICATIONS



PLHS502

APPLICATIONS (Continued)



Signetics

Document No.			
ECN No.			
Date of Issue	November 1989		
Status	Preliminary Specification		
Programmable Logic Devices			

FEATURES

- Programmable Macro Logic
- TTL compatible
- SNAP development system
 - Supports third-party schematic entry formats
 - Macro library
 - Versatile netlist format for design portability
 - Logic, timing, and fault simulation
- Delay per internal NAND function = 4.5ns (typ)
- · Security fuse for copy protection

STRUCTURE

- 86 foldback terms
 - 78 foldback NAND terms
 - 8 foldback Exclusive-OR terms
- 64 additional logic terms
- 28 dedicated inputs
- 12 bidirectional pins with Active-High output and independent
 3-State control
- 12 dedicated Active-High outputs with independent 3-state control

PLHS601 Programmable Macro Logic PMI™

DESCRIPTION

The Signetics Programmable Macro Logic (PML) family of PLDs provides the capability to create fast and cost effective solutions for general purpose logic integration, microprocessor bus interface and control applications. PML incorporates folded NAND gates as the core of its architecture. With this architecture, multiple levels of logic can be realized within the device without wasting valuable I/O pins. Furthermore, full connectivity is established among the different macros within the device, which in turn eliminates the route and place restrictions associated with high density programmable gate arravs.

The PLHS601 is a high-density bipolar PML device. The high number of I/O pins and the folded NAND architecture makes this device ideal in a wide range of bus interface and control logic applications. The PLHS601 is a powerful solution to eliminate wait states and create cost-effective microprocessor support circuitry.

APPLICATIONS

- General purpose logic integration and microprocessor support logic
- PAL[®] and glue logic replacement
- High speed and wide address decoders
- Wide multiplexers and decoders
- Bus arbitration functions

ARCHITECTURE

The core of the PLHS601 is a programmable fuse array of 78 folded NAND gates and 8 folded Exclusive-OR gates. The output of each gate folds back upon itself and all other gates. In this manner, full connectivity of all logic functions is achieved. Any logic functions can be implemented within the core of the device without wasting valuable I/O pins. Furthermore, a speed advantage is achieved by creating multiple levels of logic within the folded core without incurring any delays from the I/O buffers.

Philips Components






PML is a trademark of Philips Components-Signetics.

[®]PAL is a registered trademark of Monolithic Memories, Inc., a wholly owned subsidiary of Advanced Micro Devices, Inc.

PLHS601

PIN CONFIGURATION



DESIGN DEVELOPMENT TOOLS

The SNAP Software Development System provides the necessary tools for designing with PML. SNAP provides the following:

- Schematicentry netlist generation from thirdparty schematic design packages such as OrCAD/SDT IIITM and FutureNetTM.
- Macro library for standard PLHS601 functions and user defined functions
- Boolean equation entry
- State equation entry

- Syntax and design entry checking
- Simulator includes logic simulation, fault simulation, automatic test vector generation, and timing simulation.

SNAP operates on an IBM® PC/XT, PC/AT, PS/2, or any compatible system with DOS 2.1 or higher. The minimum system configuration for SNAP is 640K bytes of RAM and a hard disk.

SNAP provides primitive PML function libraries for third-party schematic design packages.

Custom macro function libraries can be defined in schematic or equation form.

After the completion of a design, the software compiles the design for syntax and completeness. Complete simulation can be carried out using the different simulation tools available.

The programming data is generated in JEDEC format. Using the Device Programmer Interface (DPI) module of SNAP, the JEDEC fusemap is sent from the host computer to the device programmer.


FutureNet is a trademark of FutureNet Corporation.

OrCAD/SDT is a trademark of Or©AD, Inc.

IBM is a registered trademark of International Business Machines Corporation


PLHS601

FUNCTIONAL DIAGRAM



PLHS601

PLHS601 FUNCTIONAL BLOCK DIAGRAM



November 1989 387

PLHS601

ORDERING INFORMATION

DESCRIPTION	ORDER CODE
68-Pin Plastic Leaded Chip Carrier	PLHS601A

ABSOLUTE MAXIMUM RATINGS¹

		RATI		
SYMBOL	PARAMETER	Min	Max	UNIT
V _{CC}	Supply voltage		+7	V _{DC}
V _{IN}	Input voltage		+5.5	V _{DC}
V _{OUT}	Output voltage		+5.5	V _{DC}
I _{IN}	Input currents	-30	+30	mA
l _{out}	Output currents		+100	mA .
TA	Operating temperature range	0	+75	°C
T _{STG}	Storage temperature range	-65	+150	°C

NOTE:

THERMAL RATINGS

TEMPERATURE				
Maximum junction	150°C			
Maximum ambient	75°C			
Allowable thermal rise ambient to junction	75°C			

VIRGIN STATE

A factory shipped virgin device contains all fusible links open, such that:

- 1. All product terms are enabled.
- 2. All bidirectional (B) pins are outputs.
- 3. All outputs are enabled.
- 4. All outputs are Active-HIGH.

November 1989 388

Stresses above those listed may cause malfunction or permanent damage to the device. This
is a stress rating only. Functional operation at these or any other condition above those indicated in the operational and programming specification of the device is not implied.

PLHS601


DC ELECTRICAL CHARACTERISTICS $0^{\circ}C \le T_{A} \le +75^{\circ}C$, $4.75V \le V_{CC} \le 5.25V$

				LIMITS		
SYMBOL PARAMETER		TEST CONDITION	Min	Typ ¹	Max	UNIT
Input volt	age ²		•	•		
V _{IL}	Low	V _{CC} = Min			0.8	V
V _{IH}	High	V _{CC} = Max	2.0			V
V _{IC}	Clamp ^{2, 3}	V _{CC} = Min, I _{IN} = -12mA		-0.8	-1.2	V
Output vo	oltage					
		V _{CC} = Min				
V_{OL}	Low ²	$I_{OL} = 10mA$			0.45	V
V_{OH}	High ²	$I_{OH} = -2mA$	2.4			V
Input curi	rent					
		V _{CC} = Max				
IIL	Low	V _{IN} = 0.45V			-100	μΑ
I_{IH}	High	V _{IN} = 5.5V			40	μА
Output cu	ırrent					-
		V _{CC} = Max				
I _{O(OFF)}	Hi–Z state ⁶	V _{OUT} = 5.5V			80	μА
		V _{OUT} = 0.45V			-140	
Ios	Short circuit ^{3, 4}	V _{OUT} = 0V	-15		-70	mA
Icc	V _{CC} supply current ⁵	V _{CC} = Max			340	mA
Capacitar	nce	*	•	•		
		V _{CC} = 5V				
CIN	Input	$V_{IN} = 2.0V$		8		pF
CB	1/0	V _{OUT} = 2.0V		15		pF


NOTES

- 1. All typical values are at $V_{CC} = 5V$, $T_A = +25^{\circ}C$.
- 2. All voltage values are with respect to network ground terminal.
- 3. Test one at a time.
- 4. Duration of short circuit should not exceed 1 second.
- 5. I_{CC} is measured with all dedicated inputs at 0V and bidirectional and output pins open.
- 6. Leakage values are a combination of input and output leakages.

TEST LOAD CIRCUITS




VOLTAGE WAVEFORMS




PLHS601

SNAP RESOURCE SUMMARY DESIGNATIONS



PLHS601

MACRO CELL SPECIFICATIONS T_A = 0°C to +75°C, 4.75V \leq V_{CC} \leq 5.25V, C_L = 30pF, R₂ = 1000Ω, R₁ = 470Ω (SNAP Resource Summary Designations in Parentheses)



Input Buffer

	PARAM	METER	LIMITS				
SYMBOL	To (Output)	From (Input)	Min	Тур	Max	UNIT	NOTES
t _{PHL} t _{PLH}	X	!	4 4.5	5 5.5	6 6.5	ns ns	With 0 p-terms load
t _{PHL} t _{PLH}	Y	1	2 3.5	3 3.5	3.5 4	ns ns	With 0 p-terms load

Input Pins: 1 – 2, 4 – 8, 10 – 11, 13 – 15, 17 – 19, 52 – 53, 55 – 59, 61 – 62, 64 – 66, 68. Bidirectional Pins: 21 – 25, 27 – 28, 30 – 32, 34 – 35.

Maximum internal fan-out: 16 p-terms on X or Y.

Internal Foldback NAND (FBNAND)




		LIMITS	4.7	
SYMBOL	Min Typ		Max	UNIT
Δt_{PHL}	0.05	0.07	0.1	ns/p-term
Δt_{PLH}	-0.02	-0.05	-0.08	ns/p-term

	PARAM	METER	LIMITS				
SYMBOL	To (Output)			Max	UNIT	NOTES	
t _{PHL} t _{PLH}	Out	Any	2.0 3.7	2.7 4.5	4 6	ns ns	With 0 p-terms load

Maximum internal loading of 16 terms.

PLHS601

 $\begin{array}{c} \textbf{MACRO CELL SPECIFICATIONS} \text{ (Continued)} \ \ T_{A} = 0^{\circ}\text{C to } +75^{\circ}\text{C}, 4.75\text{V} \\ \underline{\qquad} \ \ \text{(SNAP Resource Summary Designations in Parentheses)} \end{array}$





	PARAM	METER				
SYMBOL	To (Output)			Мах	UNIT	
t _{PHL}	Output	In	8	9	11.5	ns
t _{PLH}	Output	In	9	10	13.5	ns
t _{OE}	Out	Tri-Ctrl	10	11.5	13.5	ns
	Out	Tri-Ctrl	8	9.5	11.5	ns

Bidirectional and Output Pins: 19, 21, 22, 23, 15 - 18.

Internal Ex-OR Feedback Terms (EXO601)



	LIMITS			
SYMBOL	Min Typ		Max	UNIT
Δt_{PHL}	0.05	0.07	0.1	ns/p-term
Δt_{PLH}	-0.02	-0.05	-0.08	ns/p-term

	PARAI	METER		LIMITS				
SYMBO	L To (Output)	From (Input)	Min	Тур Мах		UNIT		
t _{PHL} t _{PLH}	Out Out	A or B A or B	4 5.5	5 6.5	5.6 8	ns ns		


PLHS601

PLHS601 GATE AND SPEED ESTIMATE TABLE

FUNCTION	INTERNAL NAND EQUVALENT	TYPICAL t _{PD}	f _{MAX}	COMMENTS
Gates				
NANDs	1	4.5ns		For 1 to 32 input variables
ANDs	1	4.5ns		For 1 to 32 input variables
NORs	1	4.5ns		For 1 to 32 input variables
ORs	1	4.5ns		For 1 to 32 input variables
Decoders		3		
3to8	8	7.2ns		Inverted inputs available
4-to-16	16	7.2ns		Inverted inputs available
5-to-32	32	7.2ns		Inverted inputs available (24 chip outputs only)
Encoders				
8-to-3	15	7.2ns		Inverted inputs, 2 logic levels
16-to-4	32	7.2ns		Inverted inputs, 2 logic levels
32-to-5	41	7.2ns		Inverted inputs, 2 logic levels, factored solution.
Multiplexers				
4-to-1	5	7.2ns		Inverted inputs available
8-to-1	9	7.2ns		
16-to-1	17	7.2ns		
27-to-1	28	7.2ns		Can address only 27 external inputs – more if interna
Flip-Flops		-		
D-type Flip-Flop	6		45MHz	With asynchronous S–R
T-type Flip-Flop	6		45MHz	With asynchronous S-R
J-K-type Flip-Flop	10		45MHz	With asynchronous S-R
Adders	-	-		
8-bit	45	11.7ns		Full carry-lookahead (four levels of logic)
Barrel Shifters	•	A		
8-bit	72	7.2ns		2 levels of logic
Latches	•	•	•	
D-latch	3			2 levels of logic with one shared gate
		A		

PLHS601

APPLICATIONS



NuBus is a trademark of Texas Instruments, Inc.

Document No.	
ECN No.	
Date of Issue	November 1989
Status	Preliminary Specification
Programmable	Logic Devices

FEATURES

- Full connectivity
- Scan test
- Power down mode
- Power on reset
- 100% testable
- High-Speed and Standard versions
- SNAP development system
 - Supports third-party schematic entry formats
 - Macro library
 - Versatile netlist format for design portability
- Logic, timing, and fault simulation
- TTL compatible
- Power dissipation (TTL) = 630mW
- Power dissipation (CMOS) = 525mW
- Security fuse

PROPAGATION DELAYS

- Delay per internal NAND gate
 - = 12ns (typ) (High-Speed)
 - = 15ns (typ) (Standard)

STRUCTURE

- 112 possible foldback NAND gates:
 - 96 internal NAND
 - 16 from the I/O macros
- 114 additional logic terms
- 53 possible inputs (with programmable polarity)
- 29 dedicated inputs
- 24 bidirectional I/Os

PML2552

Programmable Macro Logic PML™

- 24 bidirectional pins
- 52 flip-flops
- 24 possible outputs with individual Output Enable control (8 with programmable polarity)
- Multiple independent clocks
- 20 Buried JK-type flip-flops with foldback (JKFFs):
 - 10 JKFFs with one shared preset signal and one shared clocked signal originating from the clock array.
- 10 JKFFs with 10 independent clock signals originating from the clock array and 10 independent clear signals
- 258 inputs per NAND gate
- Bypassable Input D-type flip-flop (DFFs)/Combinatorial Inputs:
 - 16 DFFs/combinatorial inputs
- DFFs clocked in two groups of eight
- DFFs not bypassed in unprogrammed state
- Independent bypass fuse on each DFF
- Inputs/bypassable D-type flip-flop outputs/foldback NAND gates:
 - 16 output DFFs/combinatorial inputs/ outputs with individual Output Enable control
 - DFFs clocked in two groups of eight
 - DFFs not bypassed in unprogrammed
 - Independent bypass fuse on each DFF
 - The DFF can be used as an internal DFF or an internal foldback NAND
 gate

- Combinatorial inputs:
 - 9 dedicated inputs to the NAND array
- 3 inputs optional to NAND array and/ or clock array
- 1 input optional to NAND array and/or clock array, and/or clock of Input D Flip-Flops (Group B)
- Separate clock array:
- Separate clock array for JKFFs clock inputs
- 4 inputs to clock array originate from NAND array
- 4 inputs (with programmable polarity) directly from input pins
- 10 inputs from Q outputs of JKFFs with clear
- Dedicated clocks:
 - One dedicated clock for input DFFs (Group A)
- Two dedicated clocks for output DFFs
- Scan test feature:
 - Scan chain is implemented through the 20 buried JKFFs and 16 output DFFs
 - Pins SCI, SCM, and CKE1 are used to operate the scan test
- Power down mode
- Dedicated pin (PD) freezes the circuit when brought to logic "1". The circuit remains in the same state prior to the logic "0" to logic "1" transition of the "PD" pin.
- When in the power down mode, the SCI pin acts as the 3-State pin for the 24 outputs.
- Power on reset:
- All flip-flops (16 input DFFs, 20 buried JKFFs, and 16 output DFFs) are reset to logic "0" after V_{CC} power on.

PML is a trademark of Philips Components-Signetics.


Philips Components





PML2552

PIN CONFIGURATION




396

ORDERING INFORMATION

DESCRIPTION	ORDER CODE
68-pin Plastic Leaded Chip Carrier High-Speed	PML2552AA
68-pin Ceramic Leaded Chip Carrier with quartz window High-Speed	PML2552ALA
68-pin Plastic Leaded Chip Carrier Standard	PML2552A
68-pin Ceramic Leaded Chip Carrier with quartz window Standard	PML2552LA


PML2552

FUNCTIONAL BLOCK DIAGRAM



PML2552

LOGIC DIAGRAM



PMI 2552

DESCRIPTION

The Signetics PML family of PLDs provides "instant gate array" capabilities for general purpose logic integration applications. The PML2552 is the first high density CMOS-PML product. Fabricated with the Signetics highperformance EPROM process, it is an ideal way to reduce NRE costs, inventory problems and quality concerns. The PML2552 incorporates the PML folded NAND array architecture which provides 100% connectivity to eliminate routing restrictions. What distinguishes the PML2552 from the "classic" PLD architectures is its flexibility and the potent flip-flop building blocks. The device utilizes a folded NAND architecture, which enables the designer to implement multiple levels of logic on a single chip. The PML2552 eliminates the NRE costs, risks, and hard to use design tools associated with semicustom and full custom approaches. It allows the system designer to manage reliable functionality, in less time and space plus a faster time to market. The PML2552 is ideal in todays instrumentation, industrial control, EISA. NuBusTM, bus interface and dense state machine applications in conjunction with the state-of-the-art CMOS processors. It is capable of replacing large amounts of TTL, SSI and MSI logic and literally allows the designer to build a system on the chip.

The SNAP development software gives easy access to the density and flexibility of the PML2552 through a variety of design entry formats, including schematic, logic equations, and state equations in any combination.

ARCHITECTURE

The core of the PML2552 is a programmable NAND array of 96 NAND gates and 20 buried JKFFs. The output of each NAND gate folds back upon itself and all other NAND gates and flip-flops. The 'Q' and 'Q' output of each flip-flop also folds back in the same manner. Thus, total connectivity of all logic functions is achieved in the PML2552. Any logic function can be created within the core without wasting valuable I/O pins. Furthermore, a speed advantage is acquired by implementing multi–level logic within a fast internal core without incurring any delays from the I/O buffers. Figure 1 shows the functional block diagram of the PML2552.

Macro Cells

There are 16 bypassable DFFs on the input to the NAND array. These flip—flops are split in two banks of 8 (Bank A and Bank B). Each bank of flip—flops has a common clock. In the unprogrammed state of the device the flip—flops are active. In order to bypass any DFF, its respective bypass fuse (BFA_X) must be programmed.

The 16 I/O pins ($IO_0 - IO_{15}$) and their respective D flip-flop macros can be used in any one of the following configurations:

- 1. As combinatorial input(s).
 - Each of the 16 3—State outputs can be individually disabled by the associated NAND term and the pin is used as an inverting or non—inverting input.
- 2. As registered DFF outputs.
 - These DFFs are split into two banks of 8, and each bank is clocked separately. The bypass fuse BFB_X (see PML2552 Logic Diagram) is used to bypass any one of these DFFs. The flip–flops are all active in an unprogrammed device.

- 3. As combinatorial outputs.
 - By programming the bypass (BFB_X) fuse of any one of the DFFs, the flip–flop(s) is bypassed. The I/O pin can then be used as a combinatorial output.
- As Internal foldback DFFs or foldback NAND gates
 - When the I/O pin is used as an input, the output macro can be used as an internal DFF or a foldback NAND term. If the bypass fuse is programmed, the macro will act as a foldback NAND term. Otherwise it will act as an internal DFF.

The 8 bidirectional pins (B0–B7) can be used as either combinatorial inputs or outputs with programmable polarity. The outputs are inverting in the unprogrammed state. In order to make the outputs non–inverting, fuse BFC_X (See Logic Diagram) must be programmed.

The NAND signal labeled 'OD' (Output Disable) shown on the PML2552 logic diagram is used for the Power Down mode operation. This signal disables the outputs when the device enters the Power Down mode and SCI is high.

Clock Array

The 20 buried JKFFs can be clocked through the 'Clock Array'. The Clock Array consists of 11 NAND terms. Ten of these terms are connected to the clock inputs of the Bank A flipflops that can be clocked individually. One NAND gate is connected to Bank B flip-flops that have a common clock. There are 18 inputs to the clock array. Four come directly from the input pins (with programmable polarity), 4 inputs are from 4 NAND gates connected circetly to the folded NAND array. 10 inputs are from the Q outputs of the JKFFs with clear.

PML2552

SCAN TEST FEATURE

With the rise in the ratio of devices on a chip to the number of I/O pins, Design For Testability is becoming an essential factor in logic design methodology. The PML2552 incorporates a variable length scan test feature which permits access to the internal flip—flop nodes without requiring a separate external I/O pin for each node accessed. Figure 2 (Scan Mode Operation) shows how a scan chain is implemented through the 20 buried JKFFs and 16 output DFFs. Two dedicated pins, SCI (Scan In) and SCM (Scan Mode), are used to operate the scan test. The SCM pin is used to put the circuit in scan mode. When this pin is brought to a logic "1", the circuit enters the scan mode. In this

mode it is possible to shift an arbitrary test pattern into the flip-flops. The SCI pin is used to input the pattern. The inverted outputs of flip-flops D0-D15 are observable on pins I/O0 – I/O15


The following are features and characteristics of the device when in Scan Mode:

- CKE1 is the common scan—clock for all the flip—flops when in scan mode. CKE1 overrides all clock resources of normal operational mode.
- 2. The Preset (PR) and Clear (CL) functions of the flip-flops are disabled.
- 3. Scan overrides the bypass fuse of the flip-flops. This means that all the bypassable

DFFs remain intact during scan operation even though they may have been bypassed during normal operation.

- To observe the SCAN data, the output buffers must be enabled by the Output Enable (tri-ctrl) terms.
- 5. The outputs of the flip–flops are complemented on pins I/O0 I/O15.
- All external inputs to flip—flops in the scan chain are disabled when the device enters the scan mode.
- 7. Blowing the security fuse does not disable the Scan Test feature.

SCAN MODE OPERATION



PML2552

Scan Test Strategy

The scan test pattern is design dependent and the user must make considerations for Design For Testability (DFT) during the initial stages of the design. A typical test sequence is to preload (i.e., enter a state); revert to normal operation (i.e., activate the next state transition); go back to scan mode to check the result. Note that the scan test feature available in the PML2552 is a variable length scan chain. The DATA entered at SCI (JKCL9) can be accessed anywhere between 21 clock cycles (at I/O0) to 36 clock cycles (at I/O15). For the strategy discussed here, DATA is read out after 36 clocks at I/O15 (i.e., D15). The following operation sequence suggests a possible scan test method


A conservative test policy demands proof that the test facility is working. Thus, to prove Scan Chain holds and maintains correct data:

- a. Fill chain with several patterns (for example, all ones and all zeros).
- b. Retrieve same patterns.

The user is responsible for managing an external test memory buffer for applied vectors and results, as part of the test equipment.

- Parallel readout of I/O0 I/O15 is possible, but assume only I/O15 is used for this strategy.
- The first DATA entered at SCI (or JKCL9) will be the content of D15 after 36 clocks.
 This DATA will be inverted at the output pin I/O15 (i.e., SCOUT). The last DATA entering the scan chain will be the content of JKCL9. Thus, the scan chain resembles a first-in-first-out shift register with inverted outputs (I/OO I/O15).
- 'Test Data' is read in at the SCI input and read out of the SCOUT output pin (I/O15). To enter 'Test Data':
 - a. Put device in Scan Mode by applying the scan control signals (SCM=1).
 - b. Clock device with scan clock (CKE1).
 - c. Apply consecutive serial test vectors.
 - d. Read back results as new 'Test Data' (States) are applied. The first 36 outputs read at SCOUT (I/O15) are random ('old') data (e.g., remnant of Step 1).
 - e. Apply 36 'Test Data' until the chain is full.
- To apply 'Test Data' (States), exit Scan Mode and apply on system clock together with any other possible test vectors.

- 5. To read result of the state transition, re-enter scan and apply the scan clock (CKE1). The result of the state transition in JKCL9 will be available at SCOUT (I/O15) after 36 clocks. The results can be stored in a user defined test memory buffer in inverted logic representation.
- As the results are being read and stored, new 'Test Data' can be entered via SCI.
- 7. Repeat for all test patterns of interest.
- 8. Figure 3 (FLOW_CHART) depicts a flow chart version of the test sequence.



PML2552


A Simple Example

Assume the last three cells of the scan chain (JKCL9, JKCL8, JKCL7 in Figure 4 contain a 3-bit up counter. Our test vector will be a single clock applied to the counter. Suppose we wish to first check the State 5 (i.e., 101) to State 6 (i.e., 110) transition, then the State 3 (i.e., 011) to State 4 (i.e., 100) transition. Assume the scan chain has been pre-verified and we may begin

Enter scan mode (set SCM=1)I apply 36 bits in sequence so that the value 101 (i.e., State 5) resides in the last three cells. Exit scan mode (set SCM=0) and apply a single clock to the counter. Now the value 110 (i.e., State 6) resides in the last three cells. Re-enter scan mode (set SCM=1) and read back 36 bits from position I/O15. Note that the outputs are complemented and are also read back in the reverse order. Therefore the value for STATE 6 read at I/O15 will be 100 which is the complement of STATE 6 (110) read in the reverse order.

As this is being read back, apply a new state. serially equal to the value 011 (i.e., State 3). This state should be loaded on the last three clock cycles during which STATE 6 is being read back at I/O15. After STATE 3 has been loaded (and STATE 6 read back), exit scan mode and apply a single clock which will invoke the STATE 3 (i.e., 011) to STATE 4 (i.e., 100) transition. Re-enter scan mode and read back 36 bits at I/O15. The last three bits should contain 110 which is the complement of State 4 read in the reverse order. Figure 4 (SCAN EXAMPLE) shows a flow diagram of this example. Note that the States will always be complemented and read back in the reverse at I/O15. Other sequences may be applied in the same manner.

A possible alternative to this example is to read back the output states at I/O0 (D0) instead of I/O15 (JKCL9). This will allow the outputs to be read back after 21 clock cycles rather than the 36 used in the above example.



PML2552

POWER DOWN

The PML2552 offers the user controlled capability of putting the device to "sleep" where power dissipation is reduced to very low levels. When brought to a logic "1", the PD pin freezes the circuit while reducing the power. All data is retained. This not only includes that of the registers, but also the state of each foldback gate. For those cases where it is desirable to 3—State the outputs, that can be accomplished by raising the SCI pin to a logic "1".

There is one point that should be noted while the circuit is in its power—down mode. The switching of any external clock pin will cause a disruption of the data. All clocks must be frozen before the circuit goes into power—down and stay that way until it powered back up. Clocks that are internally generated and feed the clock array are automatically stopped by the power—down circuitry. Any other input can toggle without any loss of data.

NOTE:

- During power down, external clocks (CKA, CKB/CKC, CKE1, CKE2) should not change
- SCM must be "0" as in normal operation mode.
- External clock recovery time (low-tohigh) is 60ns (high-speed) and 70ns (standard) after the device is powered up.
- Power Down Timing Diagrams on pages 17 and 18 are for combinatorial operation only.

DEVELOPMENT TOOLS

The PM2552 is supported by the Signetics SNAP software development package and a multitude of hardware and software development tools. These include industry standard PLD programmers and CAD software.

SNAP

Features

- Schematic entry using DASHTM 4.0 or above or OrCADTM SDT III
- State Equation Entry
- Boolean Equation Entry
- Allows design entry in any combination of above formats
- Simulator
 - Logic and fault simulation
 - Timing model generation for device timing simulation
- Synthetic logic analyzer format
- Macro library for standard PML2552 and user defined functions
- Device independent netlist generation
- JEDEC fuse map generated from netlist SNAP (Synthesis, Netlist, Analysis and Program) is a versatile development tool that speeds the design and testing of PML. SNAP combines a user—friendly environment and

powerful modules that make designing with PML simple. The SNAP environment gives the user the freedom to design independent of the device architecture.

The flexibility in the variations of design entry methodologies allows design entry in the most appropriate terms. SNAP merges the inputs, regardless of the type, into a high-level netlist for simulation or compilation into a JEDEC fuse map. The JEDEC fuse map can then be transferred from the host computer to the device programer.

SNAP's simulator uses a synthetic logic analyzer format to display and set the nodes of the design. The SNAP simulator provides complete timing information, setup and hold-time checking, plus toggle and fault grading analysis.

SNAP operates on an IBM® PC/XT, PC/AT, PS/2, or any compatible system with DOS 2.1 or higher. A minimum of 640K bytes of RAM is required together with a hard disk.

DESIGN SECURITY

The PML2552 has a programmable security fuse that controls the access to the data programmed in the device. By using this programmable feature, proprietary design implemented in the device cannot be copied or retrieved.


PML2552

DC ELECTRICAL CHARACTERISTICS 0° C \leq T_A \leq +75 $^{\circ}$ C, 4.75V \leq V_{CC} \leq 5.25V


					LIMITS		
SYMBOL	PARAMETER	TEST CONDITION	Min	Typ ¹	Max	UNIT	
Input volt	lage	v les					
V _{IL} V _{IH}	Low High	$V_{CC} = Min$ $V_{CC} = Max$	-0.3 2.0		0.8 V _{CC} + 0.3	V	
Output vo	oltage		*,				
V _{OL}	Low	V _{CC} = Min, I _{OL} =	5mA			0.45	V
V _{OH}	High	$V_{CC} = Min, I_{OH} = V_{CC} = Min, I_{OH} = -$	2.4 V _{CC} – 0.1V			V	
Input curi	rent						
I _{IL}	Low	V _{IN} = GND				-10	μА
I_{IH}	High	$V_{IN} = V_{CC}$				10	μА
Output cu	urrent						
I _{O(OFF)}	Hi–Z state	$V_{OUT} = V_{CC}$ $V_{OUT} = GND$,			10 -10	μA μA
I _{CC}	V _{CC} supply current	V _{CC} = Max, No load f = 1MHz	CMOS input ² TTL input ³		- 4	100 120	mA mA
I _{SB}	Standby V _{CC} supply current	$V_{CC} = Max$, No load $PD = V_{IH}$			10 20	mA mA	
Capacitar	nce						
C _{IN}	Input	V _{CC} = 5V, T _A = +25°C,		8		pF	
CB	1/0	$V_{CC} = 5V, T_A = +25^{\circ}C,$	$V_{10} = 2.0V$		16		pF

- 1. All typical values are at $V_{CC}=5V$, $T_A=+25^{\circ}C$. 2. CMOS inputs: $V_{IL}=GND$, $V_{IH}=V_{CC}$. 3. TTL inputs: $V_{IL}=0.45V$, $V_{IH}=2.4V$.

TEST LOAD CIRCUITS



VOLTAGE WAVEFORMS



PML2552

MACRO CELL AC SPECIFICATIONS Min: 0°C, 5.25V; Typ: 27°C, 5.0V; Max: 75°C, 4.75V (SNAP Resource Summary Designations in Parentheses)

> Input Buffer (DIN552, NIN552, BDIN55, BNIN552 CDIN552, CNIN552, CKDIN552, CKNIN552)



	PARAM	AMETER LIMITS							
SYMBOL	То	From	Н	HIGH-SPEED			TANDAR	D	UNIT
	(Output)	(Input)	Min	Тур	Max	Min	Тур	Max	
t _{PHL} t _{PLH}	X		3 3	6 6	10 10	3.5 3.5	6 6	10 10	ns ns
t _{PHL} t _{PLH}	Y		3 3	6 6	10 10	3.5 3.5	6 6	10 10	ns ns

Input Pins: 8–14, 16, 17, 20, 22–24. Bidirectional Pins: 1–3, 5–7, 46–48, 50–54, 57–64, 67, 68.

Internal NAND of Main Array (FBNAND, NAND)



	PARAM	METER			LIM	IITS			
SYMBOL	То	From	Н	GH-SPEE	D	S	UNIT		
	(Output)	(Input)	Min	Тур	Max	Min			
t _{PHL} t _{PLH}	Y	X	6 6	12 12	20 20	7.5 7.5	15 15	25 25	ns ns

Internal NAND of Clock Array (NAND)




	PARAM	METER			LIM	ITS			
SYMBOL	То	From	н	GH-SPE	D	S	UNIT		
	(Output)	(Input)	Min	Тур	Max	Min	Тур		
t _{PHL} t _{PLH}	Y	X	3 3	6 6	10 10	4.5 4.5	9	15 15	ns ns

November 1989 405

PML2552


MACRO CELL AC SPECIFICATIONS (Continued) Min: 0°C, 5.25V; Typ: 27°C, 5.0V; Max: 75°C, 4.75V (SNAP Resource Summary Designations in Parentheses)



	PARAM	METER		LIMITS					
SYMBOL	То	From	HIGH-SPEED STANDARD			UNIT			
	(Output)	(Input)	Min	Тур	Max	Min	Тур	Max	
t _{PHL} t _{PLH}	Out Out	In In	3 3	6 6	10 10	4.5 4.5	9	15 15	ns ns
t _{OE}	Out Out	Tri–Ctrl Tri–Ctrl	3 3	6 6	10 10	4.5 4.5	9	15 15	ns ns

Bidirectional Pins: 46-48, 50-54.

I/O Output Buffer with 3—State Control, DFF Bypassed (TOUT552 + NAND)




	PARA	METER			LIM	ITS			
SYMBOL	То	From	HIGH-SPEED STANDARD				UNIT		
	(Output)	(Input)	Min	Тур	Max	Min	Тур	Max	
t _{PHL} t _{PLH}	Out Out	In In	9	18 18	30 30	12 12	24 24	40 40	ns ns
t _{OE}	Out Out	Tri-Ctrl Tri-Ctrl	3 3	6 6	10 10	4.5 4.5	9	15 15	ns ns

I/O Pins: 1-3, 5-7, 57-64, 67, 68.

PML2552

MACRO CELL AC SPECIFICATIONS (Continued) (SNAP Resource Summary Designations in Parentheses) D FLIP-FLOP




				LIM	IITS			
SYMBOL	PARAMETER	Н	IGH-SPEE	D		STANDARI)	UNIT
		Min	Тур	Max	Min	Тур	Max	
f _{CKE}	Flip-flop toggle rate			50			33	MHz
tw CKE High	Clock HIGH	10			15			ns
tw cke Low	Clock LOW	10			15			ns
t _{SETUP} /D	/D setup time to CKE	30			40			ns
t _{HOLD} /D	/D holt time to CKE	4			7.5			ns

	PARAM								
SYMBOL	From	То	Н	HIGH-SPEED STANDARD			UNIT		
	(Input)	(Output)	Min	Тур	Max	Min	Тур	Max	
t _{PLH} t _{PHL}	CKE↑ CKE↑	a a	6	12 12	20 20	7.5 7.5	15 15	25 25	ns ns

PML2552

MACRO CELL AC SPECIFICATIONS (Continued) (SNAP Resource Summary Designations in Parentheses) D FLIP—FLOP (Continued)



			LIM	ITS				
SYMBOL	HI	GH-SPEE	D	S	TANDARI)	UNIT	
	Min	Тур	Max	Min	Тур	Max		
fcка, скв, скс		^	50			33	MHz	
tw cka, ckb, ckc High	- 10			15			ns	
tw cka, ckb, ckc Low	10			15			ns	
t _{SETUP} I/DA, I/DB	10			10			ns	
t _{HOLD} I/DA, I/DB	10			10			ns	
fcke			50			33	MHz	
t _{W CKE} High	10			15			ns	
t _{W CKE} Low	10			15			ns	
t _{SETUP} /D	30			40			ns	
t _{HOLD} /D	4			7.5			ns	


	PARAM	IETER	LIMITS						
SYMBOL	From	То	Н	GH-SPE	ED .	STANDARD		UNIT	
	(Input)	(Output)	Min	Тур	Max	Min	Тур	Max	
t _{РСН} t _{РНL}	CKA, CKB/CKC↑ CKA, CKB/CKC↑	a, ā a, ā	4.5 4.5	9	15 15	4.5 4.5	9	15 15	ns ns
t _{PLH} t _{PHL}	CKE↑ CKE↑	Out Out	9 9	18 18	30 30	12 12	24 24	40 40	ns ns


PML2552

MACRO CELL AC SPECIFICATIONS (Continued) (SNAP Resource Summary Designations in Parentheses) JK FLIP-FLOPS

		(JKP	R552)				
	INP	UTS		OUT	PUTS		
PR	СК	J	K	Q	Q		
L	X	Х	X	Н	L		
н	1	L	L	Q ₀	\overline{Q}_0		
Н	1	Н	L	Н	L		
Н	1	L	Н	L	Н		
н	1	Н	Н	TOGGLE			
Н	L	X	X	Q ₀	\overline{Q}_0		

		(JKC	L552)					
	INP	UTS		OUTF	PUTS			
CE	CK	Q	Q					
L	Х	X	Х	L	Н			
Н	1	L	L	Q ₀	₲₀			
Н	↑	Н	L	Н	L			
Н	1	L	Н	L	н			
Н	1	Н	Н	H TOGGLE				
Н	L	X	X	Q ₀	₲			





				LIM	IITS			
SYMBOL	PARAMETER	HI	GH-SPE	ΞD	5	TANDAR	D	UNIT
		Min	Тур	Max	Min	Тур	Max	
f _{CK1}	CK1 toggle frequency			50			33	MHz
f _{CK2}	CK2 toggle frequency			50			33	MHz
t _{W CK1} High	CK1 dock HIGH	10			15			ns
tw ck1 Low	CK1 clock LOW	10			15			ns
tw CK2 High	CK2 clock HIGH	10			15			ns
t _{W CK2} Low	CK2 clock LOW	10			15			ns
t _{SETUP} /J, /K	/J, /K setup time to CK1, CK2	25			30			ns
t _{HOLD} /J, /K	/J, /K hold time to CK1, CK2	0			0			ns
tw PR Low	Preset Low period	10			15			ns
t _W CL Low	Clear Low period	10			15			ns

	PARAM	METER							
SYMBOL	From	То	HIGH-SPEED STANDARD			UNIT			
	(Input)	(Output)	Min	Тур	Max	Min	Тур	Max	
t _{PLH}	CK1,2	a, a	1.5	3	5	1.5	3	5	ns
t _{PHL}	CK1,2	a, a	1.5	3	5	1.5	3	5	ns
t _{PLH}	PR	Q, Q	7.5	15	25	9	18	30	ns
t _{PHL}	PR	Q, Q	7.5	15	25		18	30	ns
t _{PLH}	CL	Q, Q	7.5	15	25	9	18	30	ns
t _{PHL}	CL	Q, Q	7.5	15	25		18	30	ns

PML2552

AC ELECTRICAL CHARACTERISTICS $0^{\circ}C \le T_A \le +75^{\circ}C$, $4.75V \le V_{CC} \le 5.25V$, $V_{PP} = V_{CC}$, $R_1 = 750\Omega$, $R_2 = 442\Omega$, $C_1 = 5pF$ for Output Disable) (See Test Load Circuit Diagram)

	PARAMETER	LIMITS				
SYMBOL		High-Speed		Standard		UNIT
			Max	Min	Max	
Scan mod	de operation ¹					
tscms	Scan Mode (SCM) Setup time	15		15		ns
tscmH	Scan Mode (SCM) Hold time	25		30		ns
t _{IS}	Data Input (SCI) Setup time	5		5		ns
t _{IH}	Data Input (SCI) Hold time	5		5		ns
t _{CKO}	Clock to Output (I/O) delay		30		40	ns
t _{CKH}	Clock High	10		15		ns
t _{CKL}	Clock Low	10		15		ns
Power do	wn, power up ²					
t ₁	Input (I, bypassed I/DA, I/DB, I/O, B) setup time before power down	40		50		ns
t ₂	Input hold time	30		35		ns
t ₃	Power Up recovery time		60		70	ns
t ₄	Output hold time	0		0		ns
t ₅	Input setup time before Power Up	20		25		ns
t _{OE}	SCI to Output Enable time ³		40		50	ns
t _{OD}	SCI to Output Disable time ³		40		50	ns
t ₆	Power Down setup time	10		15		ns
t ₇	Power Up to Output valid		70		80	ns
Power-or	n reset					
t _{PPR1}	Power-on reset output register (Q = 0) to output (I/O) delay		10		15	ns
t _{PPR2}	Power–on reset input register (Q = 0), buried JK Flip–Flop (Q = 0) to output (B, bypassed I/O) delay		40		50	ns


NOTE:

^{1.} SCM recovery time is 50ns after SCM operation. 50ns after SCM operation, normal operations can be resumed.

Timings are measured without foldbacks.
 Transistion is measured at steady state High level (–500mV) or steady state Low level (+500mV) on the output from 1.5V level on the input with specified test load ($R_1 = 750\Omega$, $R_2 = 442\Omega$, $C_L = 5pF$). This parameter is sampled and not 100% tested.


PML2552

TIMING DIAGRAMS




PML2552

TIMING DIAGRAMS (Continued)



PML2552

SNAP RESOURCE SUMMARY DESIGNATIONS



Section 7 Military Selection Guide

Programmable Logic Devices

	INDEX	
Military Selection Guide		417

Military Selection Guide

Programmable Logic Devices

Part Number	Device Description	Package Description	M38510/	JB**	JS**	Standard MIL-Drawing	MIL—Drawing Status**
PLHS18P8/BRA	PAL	20DIP3				5962-872801RA	A
PLHS18P8/BSA	PAL	20FLAT		NA	NA	5962-872801SA	Α
PLHS501/BXA	GATE ARRAY	64DIP9		NA	NA	PLANNED	
PLS159A	PLS	20DIP3		NA	NA	PLANNED	NA
PLUS16L8/BRA	PAL	20DIP3		NA	NA	5962-8515509RA	A
PLUS16L8/BSA	PAL	20FLAT		NA	NA	5962-8515509SA	A
PLUS16L8/B2A	PAL	20LLCC		NA	NA	5962-85155092A	Α
PLUS16R8/BRA	PAL	20DIP3		NA	NA	5962-8515510RA	Α
PLUS16R8/BSA	PAL	20FLAT		NA	NA	5962-8515510SA	Α
PLUS16R8/B2A	PAL	20LLCC		NA	NA	5962-85155102A	Α
PLUS20L8/BLA	PAL	24DIP3		NA	NA	5962-8767105LA	A
PLUS20L8//BKA	PAL	24FLAT		NA	NA	5962-8767105KA	Α
PLUS20L8/B3A	PAL	28LLCC		NA	NA	5962-87671053A	Α
PLUS20R8/BLA	PAL	24DIP3		NA	NA	5962-8767106LA	Α
PLUS20R8/BKA	PAL	24FLAT		NA	NA	5962-8767106KA	Α
PLUS20R8/B3A	PAL	28LLCC		NA	NA	5962-87671063A	Α
PLUS405/BXA	PLS	28DIP6		NA	NA	PLANNED	NA
PLUS405/BYA	PLS	28FLAT		NA	NA	PLANNED	NA
PLUS405/B3A	PLS	28LLCC		NA		PLANNED	NA
PLS167/BLA	PLS	24DIP3		NA		PLANNED	NA
PLS168/BLA	PLS	24DIP3		NA		PLANNED	NA
PLS173/BLA	PLA	24DIP3		NA		5962-8850402LA	A
PLS179/BLA	PLS	24DIP3		NA	NA	5962-8850701LA	Α
PLHS473	PLA	24DIP3		NA	NA	PLANNED	NA
32S100/BXA	PLA	28DIP6	50202	Α	NA		
32S100/BYA	PLA	28FLAT	50202	NA	NA		
32S100/B3A	PLA	28LLCC	50202	NA	NA		
32S101/BXA	PLA	28DIP6	50201	Α	NA		
32S101/BYA	PLA	28FLAT	50201	NA	NA		
32S101/B3A	PLA	28LLCC	50201	NA	NA		
32S105/BXA	PLS	28DIP6		NA	NA	5962-8670901XA	Α
32S105/BYA	PLS	28FLAT		NA	NA	5962-8670901YA	A
32S105/B3A	PLS	28LLCC		NA	NA	5962-86709013A	A
32S153A/BRA	PLA	20DIP3		NA	NA	5962-8768201RA	A
32S153A/BSA	PLA	20FLAT		NA	NA	5962-8768201SA	A
32S153A/B2A	PLA	20LLCC		NA	NA	5962-87682012A	A

Not available as a Class B standard product. See M38510 and/or Military Drawing columns for availability
 A = available, NA = not available, IP = in process, call for availability.

Section 8 Development Software

Programmable Logic Devices

INDEX

AMAZE – Automatic Map and Zap Equations Design Software	421
SNAP – Synthesis Netlist Analysis and Program Software	425
SNAP Data Sheet	427
Device Programmer Reference Guide	429

AMAZE Programmable Logic Development Software

Programmable Logic Devices

SOFTWARE SUPPORT FOR USER PROGRAMMABLE LOGIC

Computer Aided Design (CAD) support is becoming necessary to address the time-consuming details required by the more complex programmable logic devices available today. The design effort can include the manipulation of Boolean equation, truth tables, state diagrams, flowcharts etc., to create the binary fuse map required to program such devices.

For many years, design engineers have used programmable read-only memories (PROMs) to replace conventional logic. The architecture of the PROM can be described as a programmable logic device containing a **fixed** AND array followed by a **programmable** OR array. The fixed structure of the PROM requires a full assignment of output words to be programmed for every input combination. Therefore, little use can be made of programmable logic software programs for logic minimization or other compiling efforts when using PROMs.

Signetics Programmable Logic Devices are the most advanced approach to solving the inherent limitations of PROMs. Their architecture consists of a programmable AND array, followed by a programmable OR array – with the addition of a programmable invert function for flexible output control.

A Signetics PLD device can implement any set of Boolean expressions, provided that they are first put into the standard sum of the products form. The logical ANDs are implemented at the first gate level of the programmable logic device and the logical ORs are implemented by the second gate level within the PLD. The only limitations on the expressions are those imposed by the number of inputs, outputs, and internal product terms provided by the particular PLD circuit selected. The efficiency of implementing the set of equations can be increased significantly by applying De-Morgan's theorem, and utilizing the programmable invert function on each output.

If there seems to be too few product terms to handle a relatively large equation set, one of several minimization methods can be pursued.

The probability of reducing such equations to manageable size is enhanced through the flexibility of shared AND terms for each output function, the accessibility of all AND terms to each output, and having a programmable invert function on each output. All of these features can be utilized by applying the manual manipulation of Venn Diagrams or Karnaugh Maps. However, the time and effort to accomplish these tasks as well as document the effort for procurement specification purposes increase the need and desire to

have software programs to automatically perform such manipulations.

Many types of software programs are being developed to provide this assistance for operation on a wide range of computer hardware. This list of software is expanding rapidly, consisting of both Signetics generated software and some independent software houses' contributions.

This discussion is intended to outline the Signetics developed software program called AMAZE (Automatic Map And Zap Equation Entry). The AMAZE software program currently consists of five modules, BLAST ('Boolean Logic And State Transfer' entry program), PTP ('PAL To PLD' conversion program), DPI ('Device Programmer Interface' program), PLD SIM ('PLD Simulator' program) and the PTE ('Program Table Editor' program). Other modules will be added when product developments require additional software tools.

It must be noted that the AMAZE program is not by any means the total extent of software available for use in designing with PLD (Programmable Logic Devices). Several other commercially available PLD Design Software packages support Signetics' PLD product line. Please contact your local Signetics representative for the latest word on the most currently available software.

Programmable Logic Development Software

AMAZE

AMAZE Version 1.8

Description

The AMAZE software program Automatic Map And Zap Equation Entry software, consists of the following five modules:

- BLAST ('Boolean Logic And State Transfer' entry program)
- PTE ('Program Table Editor')
- PTP ('PAL To PLD' conversion program)
- DPI ('Device Programmer Interface' program)
- PLD SIM ('PLD Simulator' program)

Each module performs specific tasks as outlined in the following section.

Features

- Multiple modules allowing expansion for future requirements
- Each module designed to be user friendly
- Both HELP and ERROR messages
- Document printout: Header, Pin diagram, Boolean equation and Fuse map
- Interface with most commercial programmers
- SIMULATOR programs provide applications assistance and Automatic Test Vector Generation

Equipment Requirements (for Version 1.8)

- Platform 1: IBM-PC, XT, AT, PS-2 and compatibles
 - Memory: Minimum of 640K bytes
 - Operating system: PC-DOS version
 2.1 or higher
 - Disk Drive: One hard disk drive and one double sided floppy disk drive

Products Supported

AMAZE Version 1.8 supports the following products:

products:
20-Pin PLDs
PHD16N8 PLC18V8Z/I PLHS16L8A/B PLHS18P8A/B PLS1533 PLS153A PLUS153B PLUS163D PLUS16L8 PLUS16R6 PLUS16R6 PLUS16R6 PLUS16R6 PLUS16R8 PLS155 PLS1557 PLS159A
24–Pin PLDs
PLC42VA12 PLHS473 PLS167 PLS167A PLS168 PLS168A PLS173 PLS179 PLUS20L8 PLUS20R4 PLUS20R6 PLUS20R6 PLUS173B PLUS173B PLUS173D 10H20EV8/10020EV8
28-Pin PLDs
PLC415 PLS100 PLS101 PLS105/A PLUS105-40 PLUS405
52–Pin PLDs
PLHS501

AMA7F

Programmable Logic Development Software

BLAST

Boolean Logic And State Transfer program is a menu driven software package that supports the engineer in implementing logic designs into Signetics Programmable Logic Devices. It checks design data and automatically compiles a program table from Boolean and State Machine equations. Data from the program table is then used to produce a Standard File which contains the fusing codes in a form acceptable to all the AMAZE modules (i.e., PLD-SIM and DPI).

BLAST reports the logic and syntax errors, and lists the equations in a Sum of Products form, which can help the user to minimize the entered logic equations. It will automatically partition State machine designs into specified devices, and then delete redundant terms during compilation.

BLAST also provides the capability of modifying a current logic set programmed into a device by overlaying new data onto unused fuses.

BOOLEAN LOGIC AND STATE TRANSFER FEATURES

- User friendly interactive pinlist editor
- Boolean equation or state vector entry
- Schematic entry (with external schematic capture package)**
- On-line error checking, minimization, and design overlay
- Capable of partitioning single designs into multiple PLDs
- Supports all Signetics PLDs and PLEs
- User definable device files for support of PALs and other PLD devices

PTF

Program Table Entry is an interactive editor which allows the logic designer to enter data into AMAZE in the form of SIGNETICS APPROVED PROGRAM TABLES. Each Signetics PLD data sheet has the program table format which applies to that device. In addition, PTE can be used to document completed designs and to make changes in logic functions which have been previously defined in the BLAST module.

PROGRAM TABLE EDITOR FEATURES

- Allows easy creation and editing of new and existing PLD designs
- Truth-table representation of PLD fusemap in High./Low format
- On-line editor provides automatic cursor control and prevents syntax errors
- On-line help screen and print facility
- Operates on standard PLD fusemap files

PTP

PAL To PLD is a conversion program to allow easy transfer of the various PAL 20— and 24—pin circuits to the Signetics PLD 20— and 24—pin series devices.

PTP can automatically upload the PAL pattern from a Commerical programmer, convert the pattern into a PLD pattern, and then download the PLD pattern into the programmer. The PAL pattern and it's corresponding PLD pattern are documented, and the PLD pattern can be directed to other AMAZE modules.

PTP can also convert the PAL fuse file in a HEXPLOT format.

PAL-TO-PLD CONVERSION FEATURES

- Menu-driven fusemap conversion of 20and 24-pin PAL devices to pin and functional equivalent Signetics PLDs and PAL-type devices
- Automatic assembler removes duplicated p-terms providing efficient PLD mapping (PLD conversions only)
- Accepts JEDEC, fuseplot files or direct PAL master input via commercial PLD programmer
- User selectable RS-232 programmable interface parameters
- Provides fusemap conversion documentation
- Generates standard PLD fusemap files compatible with other AMAZE modules

The PTP module supports the conversion of the following device types:

PLS153 PLHS18P8	10H8, 10L8, 12H6, 12L6, 14H4, 14L4, 16H2, 16L2, 16C1, 16H8, 16L8, 16P8		
PLS155	16R4		
PLS157	16R6		
PLS159	16R8		
PLS173	14L8, 16L6, 18L4, 20C1, 20L2, 20L8		
PLS173	12L10, 20L10		
PLS179	20R8		

Signetics also provides a stand-alone version of the PTP module, SimPal, which supports the conversion of PAL device fuse maps into equivalent Signetics PAL-type PLDs.

Programmable Logic Development Software

AMAZE

DPI

Device Programmer Interface is the software module that provides the interface between the Standard File created by the AMAZE modules and a commercial programmer. This module allows both download (sending from host to programmer) and upload (sending from programmer into the host) operations.

DPI supports both JEDEC and Signetics High/ Low formats to convey fusing information to and from several commercial programmers.

DEVICE PROGRAMMER INTERFACE FEATURES

- Supports standard JEDEC and Signetics High/Low fusemap file formats
- RS-232 interface to commercial PLD programmers

- Screen menus for easy upload and download of fusemaps
- User selectable RS-232 parameters for programmer flexibility
- Test vectors automatically transferred to programmer along with fusemap file
- Operates with standard PLD fusemap files

PLD SIMULATOR

The PLD Simulator program is a software package that simulates the operation of the logic that has been defined for Signetics PLD products. The input to the program is the Standard File generated by other AMAZE modules. The simulator has the capability of running manually or automatically. In the automatic mode the simulator creates a file of test vectors

that can be used to test the programmed devices. In the manual mode the program will allow the operator to assign an input vector and observe the resultant output.

PLD FUNCTIONAL SIMULATOR FEATURES

- Functional simulation of designs created form equations, program tables or existing programmed devices
- Automatic test vector generation from standard or JEDEC PLD fusemap files
- Interactive keyboard entry or batch file input of test vectors
- Detects illegal State Machine transitions and flags affected p-terms
- On-line help screen

SNAP Programmable Logic Development Software


Programmable Logic Devices

INTRODUCTION

Philips Components-Signetics SNAP software is designed to provide the precise tools needed to complete a PLD de-

sign. The initial offering is depicted in Figure 1.1. This chart depicts the recommended sequence of operations for completing a Programmable Macro Logic

(PML) design. While other sequences may be used, the first-time user will most likely obtain the best results by following steps 1–9.



425

Programmable Logic Development Software

SNAP

Step 1

Step [1], ScCAPTURE, is the design entry. This may be accomplished in a number of ways, but the most popular today is schematic capture. SNAP supports OrCAD/SDT III™ and SNAP-DASH™ from FutureNet. Current methods of entry include Boolean equations, state equations, timing waveforms and manual netlist editing. The goal of Step 1 is to create a netlist description of a logic design which can be understood by the rest of SNAP.

Step 2

Step [2], NETGEN, is essentially automatic in that all netlist generation or conversion must be in a consistent format. The converted netlist is EDIF1.0 compatible.

Step 3

Step [3], MERGER, allows design pieces from different inputs to merge into a single netlist description. In theory, one section could be input by schematic capture, another by Boolean equation and another by state equation, etc. A composite netlist for all of these would be the output of MERGER.

Step 4

Step [4], SIMNET, is the preferred next step-

to verify the design by simulation. The bold designer could proceed to Step 8 and a final device, but if any problem occurs, Step 4 must be used to debug. In SIMNET, a binary format of the design will be generated for the logic and fault simulators. During this step the original netlist is translated into simulator primitives.

Step 5

Step [5], SIMSCL, reads the input vector (stimuli description), loads the network into memory and executes the logic/timing simulation. SIMFLT is an alternate simulation that gives a fault coverage assessment of the simulation. This tells the designer (in numbers) just how rigorous the simulation testing of the circuit is. A complete fault reprot is generated.

Step 6

Step[6], PLOT, allows a waveform display of selected nodes within the design so that its creator may observe the circuits modeled behavior.

Step 7

Step[7], SIMPRT, produces hardcopy of the various simulation reports for documentation.

The designer should iterate through Steps 4 – 7 until satisfied that correct operation is occur-

ring. Only if it is should the designer proceed to Step 8

Up to this point, the design is not bound to a specific Signetics part. In fact, the design could span multiple parts, or be migrated from one PLD to another, with only small effort.

Step 8

Step [8], COMPILER, is where the target part is chosen and a fuse table produced. The fuse table can then be manually edited or programmed into a part, as the designer chooses. However, one last action can help guarantee a successful final design: Post–compiled model generation.

Step 9

Step [9], MODGEN, takes the fusemap from the selected part and outputs a simulation model that reflects the precise models of the internal logic for the target PLD. Once this is done, Steps 5 – 7 may be repeated to verify conclusively that the design will work. If a problem is found, the designer may edit to debug the design. The final compilation will yield a programmed part that meets the designer's simulated specifications.

SNAP Version 1.2

Specifications

Programmable Logic Devices

FEATURES

- Schematic entry available using Data I/O SNAP-DASH™ or OrCAD SDT III™
- State equation entry
- Boolean equation entry
- Netlist entry
- Capability to design in one or any combination of formats
- Device independent, netlist based design platform
- Full support for the PML product line
- Philips LESIM 5—State gate array simulator:
 - Logic and fault simulation
- Model extraction and timing simulation
- Synthetic logic analyzer format
- Stimuli entry in waveform format
- Freezing of selected Critical paths
- Cell library for PML functions
- Capability to create user defined macros
- Full documentation of design and simulation results in waveform format
- JEDEC fusemap compiler and device programmer interface

GENERAL DESCRIPTION

Signetics SNAP (Synthesis Netlist Analysis & Program) software has been developed to support the Signetics PLD product line. This release of SNAP (Version 1.2) supports the PML family of programmable logic devices. Future versions of SNAP will support additional PLD devices until the full product line is covered.

The software gives freedom to design independently of the device architecture. This allows for shifting the design among a family of PLD devices. SNAP can handle a variety of design entry formats: schematics, Boolean equations, state equations, waveforms*, and netlists in any combination. The SNAP environment is familiar to logic designers who have worked with any type of PLD or gate array development software. Since the software is netlist based, it overcomes the limitations facing conventional PLD development software.

Figure 1 shows the SNAP Shell. The top part of the shell indicates the paths available for entering the design. The user can enter a design using any single method or any combination of methods. Thus, functions can be described in the most appropriate terms. For instance, schematics may be the best way of describing a shift register, and logic equations may be the optimum way for describing a decoder. Additionally, these designs can be united with a multiplexer, which is described by a netlist. Then SNAP merges the inputs into a high-level netlist for simulation and compilation into a JEDEC standard fuse map. For future universal workstation compatibility, the software supports the standard EDIF interface.

Simulator

SNAP incorporates Philips' 5–State gate array simulator, and provides the capabilities of full timing simulation, setup and hold-time checking, as well as toggle and fault grade analysis. The simulator is capable of displaying any set of nodes within a design in a wide range of formats. Using a synthetic logic analyzer the user can

zero in on a specific area. Simulations can occur with unit delays, estimations, or exact delays. The test vectors can be entered in waveform or 'H' and 'L' format.

In order to provide accurate timing analysis, SNAP calculates the final timing values as determined from the additive delay of each gate and I/O macro in a path. To assure the reliability of a design, the fault simulator determines the fault grade level and undetectable faults. This results in simulation data that conforms exactly to the characteristics of the actual device.

Compiler/Optimizer

SNAP also contains a fusemap compiler and model generator. The model generator extracts and creates the timing models of the specified device. These models are generated for timing and fault simulation. The compiler is also capable of optimizing the device to the architecture of the PLD selected for the design. For example, if a flip-flop macro is selected, the optimizer will design the macro from NAND gates for the PLHS501 (which lacks die-based flipflops). Alternatively, an internal die-based flip-flop is used for a device with flip-flops such as the PLHS502. The software contains extensive syntax and logic error checking, and allows for documentation of the design and simulation results.

HARDWARE SPECIFICATIONS

- IBM® Personal System/2[™], IBM PC/ XT/AT, or compatibles
- DOS 2.1 or higher
- Minimum of 640K bytes of RAM
- 5.25" or 3.5" double-sided, double-density disk drive, and a hard drive.


SNAP-DASH is a trademark of Data I/O Corporation OrCAD STD III is a trademark of Or/CAD, Inc. IBM is a registered trademark of International Business Machines Corporation.

November 1989 427

^{*} Under development for future releases.

SNAP Software Version 1.0

SNAP



428

ORDERING INFORMATION¹

DESCRIPTION	ORDER C	ODE
SNAP	SNAP12	MSC
SNAP + OrCAD SDT III	SNAPOR12	MSC
SNAP + SNAP-DASH	SNAPDSH12	MSC

PLD Programmer Reference Guide

Programmable Logic Devices

Data I/O Corporation 10524 Willows Road, N.E. Redmond, Washington 98073–9746 Telephone Number: (800) 247–5700

			IOM	DEL 29B	UI	NISITE		MODEL 60	MODEL 60		
TYPE	SIGNETICS PART NUMBER	DEVICE	ADAPTE	RREVISION	SYSTEM REVISION	ADAPTER REVISION	SYSTEM REVISION	ADAPTER	REVISION		
			DIP	PLCC	DIP	PLCC		DIP	PLCC		
PHD	PHD16N8	TBD	303A-011A;V11	TBD	V2.8	TBD	V15	TBD	TBD		
ECL	10H/10020EV8	14013B			V2.7	CPSITE;V2.7					
PAL	PLC16V8	863B	303A-011A;V05	303A-011B;V03	V2.1	CPSITE;V2.4	TBD	TBD	TBD		
PAL	PLC18V8Z	864F	303A-011A;V09	303A-011B;V04	V2.5	TBD	V15	TBD	TBD		
PAL	PLC20V8	864E	303A-011A;V06	303A-011B;V03	V2.1	CPSITE;V2.4	TBD	TBD	TBD		
PAL	PLHS16L8	1A17	303A-012;V02		V2.1	CPSITE;V2.1					
PAL	PLHS16L8	3D17	303A-011A;V09	303A-011B;V04			V14	360A001	360A006		
PAL	PLHS18P8	1A33	303A-012;V01		V2.1	CPSITE;V2.1					
PAL	PLHS18P8	3D33	303A-011A;V09	303A-011B;V04			V14	360A001	360 A006		
PAL	PLUS16L8	1B17	303A-011A;V08	303A-011B;V04	V2.3	CPSITE;V2.5	V14	360A001	360A006		
PAL	PLUS16R8/R6/R4	1B24	303A-011A;V08	303A-011B;V04	V2.3	CPSITE;V2.5	V14	360A001	360A006		
PAL	PLUS20L8	1B26	303A-011A;V08	303A-011B;V04	V2.3	CPSITE;V2.5	V14	360A001	360A000		
PAL	PLUS20R8/R6/R4	1B27	303A-011A:V08	303A-011B:V04	V2.3	CPSITE:V2.5	V14	360A001	360A00		
PLA	PLC153	8665	303A-011A;V05	303A-011B;V03	V2.1	CPSITE;V2.4	TBD	TBD	TBD		
PLA	PLC473	8678	303A-011A;V02	303A-011B;V03	V2.1	CPSITE;V2.4	TBD	TBD	TBD		
PLA	PLHS153	1A65	303A-012;V02		V2.1	CPSITE;V2.5					
PLA	PLHS473	1A78	303A-012:V02		V2.2	CPSITE:V2.4					
PLA	PLS100/1	9601	303A-001;V01						l		
PLA	PLS100/1	9661	303A-001:V05		V2.2	CPSITE;V2.2	V01	360A003			
PLA	PLS153/A	9665	303A-011A;V02	303A-011B;V02	V1.5		V01	360A002	A ONLY		
PLA	PLS153/A	9665	303A-001;V05	303A-011B:V02	V1.5	CPSITE:V1.5	V12	360A009	A ONLY		
PLA	PLS173	9676	303A-011A:V02	303A-011B;V02	V1.7		V08	360A002			
PLA	PLS173	9676	303A-001:V06	303A-011B;V02	V1.7	CPSITE:V1.7	V12		360 A00		
PLA	PLUS153B	1B65	303A-011A;V07	303A-011B;V03	V2.3	CPSITE;V2.3	V14	360A002	360 A009		
PLA	PLUS173B	1B76	303A-011A;V07	303A-011B;V03	V2.3	CPSITE;V2.3	V14	360A002	360A009		
PLS	PLC415	86AA	303A-011A;V10	303A-011B;V04	V2.6	TBD	TBD	TBD	TBD		
PLS	PLS105/A	9603	303A-011A;V02	303A-011B;V02	V1.5		V01	360A003	A ONLY		
PLS	PLS105/A	9603	303A-001;V01	303A-011B;V02					A ONE		
PLS	PLS105/A	9663	303A-001;V05	303A-011B;V02	V1.5		V01	360A003			
PLS	PLS105/A	9663	303A-011A;V02	303A-011B;V02	V1.5	CPSITE;V1.5	V12		360A00		
PLS	PLUS105-40	1B63	303A-011A;V09	303A-011B;V04	V2.5	TBD	V 12		360A000		
PLS	PLS155	9667	303A-011A;V02	303A-011B;V02	V2.5 V1.5		V01	360A002			
PLS	PLS155	9667	303A-011A;V02	303A-011B;V02	V1.5 V1.5	CPSITE:V1.5	V12	360A002	360A009		
PLS	PLS155	9668	303A-001;V05	303A-011B;V02	V1.5 V1.5	CPSITE;V1.5	V12 V13	360A002	360A003		
PLS	PLS157	9668	303A-001;V05	303A-011B;V02	V1.5 V1.5	CPSITE;V1.5	V13	360A002	360A009		
PLS	PLC42VA12	9668 868A	78D	303A-011B;V02	V1.5 V2.7	TBD	V13 V15	TBD	TBD		
PLS	PLC42VA12 PLS159A	6466			V2.7 V2.4	CPSITE:V2.4	V15 V12	360A002	360A00		
PLS	PLS159A PLS159A		303A-011A;V02	303A-011B;V02	1	OPSITE, V2.4		360A002			
PLS	PLS159A PLS167/A	6466 9660	1		V2.4 V1.5	CPSITE:V1.5	V05				
PL5	PLOID//A	9660	303A-011A;V02	303A-011B;V02	V1.5	GP511E;V1.5	V05	360A002			

November 1989 429

PLD Programmer Reference Guide

(CONTINUED)

Data I/O Corporation 10524 Willows Road, N.E.

Redmond, Washington 98073-9746 Telephone Number: (800) 247-5700

			MODE	EL 29B	UN	IISITE		MODEL 60	
TYPE	SIGNETICS PART NUMBER	DEVICE	ADAPTER	REVISION	SYSTEM REVISION	ADAPTER REVISION	SYSTEM REVISION	ADAPTER	REVISION
			DIP	PLCC	DIP	PLCC		DIP	PLCC
PLS	PLS167/A	9660					V12		360A009
PLS	PLS168/A	9674	303A-011A;V02	303A-011B;V02	V1.5	CPSITE;V1.5	V05	360A002	
PLS	PLS168/A	9674	303A-001;V06				V12		360A009
PLS	PLS179	9677	303A-011A;V02	303A-011B;V02	V2.4	CPSITE;V2.4	TBD	TBD	TBD
PLS	PLUS405	1B79	303A-011A;V07	303A-011B;V04	V2.6	CPSITE;V2.6	TBD	TBD	TBD
PML	PLHS501	1002				CPSITE;V1.7			
PML	PLHS502	01C05E			V2.4	***			
PML	PML2552	TBD			V2.8	****			

- 1. The software and hardware revisions listed are the first revisions released. All following revisions maintain support.
- 2. FOR UNISITE USERS ONLY: Family codes listed above (the first two digits) must be preceded with a "0" for PLCC packages. Pin codes listed above (the last two digits) must be preceded with a "7" for PLCC packages.
- 3. ***Needs a 40-Pin DIP to 68-Pin PLCC adaptor available from

Emulation Technology

Part Number: AS-68-40-O1P-6

****Needs a 40-Pin DIP to 68-Pin PLCC adaptor that is available from

Emulation Technology.
Part Number: AS-68-40-04P-6

EMULATION TECHNOLOGY, INC. 2368B Walsh Avenue, Blvd. D Santa Clara, California 95051 Telephone No. (408) 982-0660 Fax. No. (408) 982–0664

4. DEVICE CODE: XXYY

XX = FAMILY CODE YY = PIN CODE

PLD Programmer Reference Guide

Stag Micro Systems, Inc.

Western Area: 1600 Waytt Drive, Suite 3 Santa Clara, CA 95054 (408) 988–1118 Eastern Area: 3 Northern Blvd., Suite B4 Amherst, NH 03031 (603) 673–4380

	DEVICE	CODES	MODEL ZL30	MODE	L ZL30A	MODEL PE	PZ: ZM2200
SIGNETICS PART NUMBER	FAMILY CODES	PIN CODES	(DIP ONLY)	DIP	PLCC	DIP	PLCC
PHD-TYPE DEVICES							
PHD16N8			30A36	30A36	30A	TBA	
ECL-TYPE DEVICES							
10H/10020EV8			30A36	TBA	TBA	TBA	
PAL-TYPE DEVICES							
PLC16V8	12	154	30A27	30A27	30A001	30	
PLC18V8Z	12	205	30A34	30A34	30A001	TBA	
PLC20V8	12	155	30A29	30A29	30A001	TBA	
PLHS16L8 A/B	10	029	N/A	30A29*	30A101	TBA	
PLHS18P8 A/B	10	10	N/A	30A23*	30A101	29	
PLUS20L8 D/7	11	56	30A31	30A31	30A001	TBA	
PLUS20R8 D/7	11	57	30A31	30A31	30A001	TBA	
PLUS20R6 D/7	11	58	30A31	30A31	30A001	TBA	
PLUS20R4 D/7	11	59	30A31	30A31	30A001	TBA	
PLUS16L8 D/7	11	29	30A31	30A31	30A001	TBA	
PLUS16R8 D/7	11	30	30A31	30A31	30A001	TBA	
PLUS16R6 D/7	11	31	30A31	30A31	30A001	TBA	
PLUS16R4 D/7	11	32	30A31	30A31	30A001	TBA	SOCKET
PLA DEVICES	''	32	30A31	30A31	304001	IDA	SOURE
PLS100/101	13	00	30A01	30A01	30A001	17	
PLC153	12	05	30A27	30A27	30A001	34	ADAPTORS
PLS153/153A	14	05	30A01	30A27	30A001	17	ADAPTORS
PLHS153	10	05	N/A	30A01 30A27*	30A001	34	
PLUS153 B/D	11	05	30A27	30A27 30A27	30A001	34	ARE
PLS173	15	96					ARE
PLS173 PLUS173 B/D			30A01	30A01	TBA	23	
	11	96	30A31	30A31	TBA	TBA	DECLUBED
PLC473	12	132	30A24	30A24	30A001	32	REQUIRED
PLHS473	10	132	N/A	30A27*	30A101	30	l
PLS DEVICES							
PLS105/105A	13	02	30A01	30A01	30A001	17	
PLUS105-40	11	02	30A34	30A34	30A001	TBA	
PLC415	12	177	30A34	30A34	30A001	TBA	
PLC42VA12	12	197	30A34	30A34	30A001	TBA	
PLS155	14	06	30A01	30A01	30A001	17	
PLS157	14	07	30A01	30A01	30A001	17	
PLS159A	13	08	30A25	30A25	30A001	27	
PLS167/167A	15	91	30A01	30A01	30A001	TBA	
PLS168/168A	15	97	30A01	30A01	30A001	23	
PLS179	15	130	30A27	30A27	30A001	24	
PLUS405	11	138	30A31	30A31	30A001	TBA	
PML DEVICES							
PLHS501	10	133	N/A	30A22*	30A101		
PLHS502	10	189	N/A		30A102		

NOTES:

The software and hardware revisions listed are the earliest revisions that support these products. Later revisions can also be assumed to support these products.

^{*}Requires 30A101 adaptor; includes PLCC support.

Section 9 Application Notes

Programmable Logic Devices

INDEX

PLD Application	
AN7 AN8 AN11 AN14 AN15 AN18 AN21 AN23 AN24 AN26 AN27 AN28	Single Chip Multiprocessor Arbiter 435 Introduction to Signetics Programmable Logic 447 PLD Programmable Retriggerable One—Shot 459 Latches and Flip—Flops with PLS153 463 PLS159 Primer 476 Schmitt Trigger Using PLS153 and PLS159 487 9—Bit Parity Generator/Checker with PLS153/153A 495 PLS168/168A Primer 501 PLS173 as a 10—Bit Comparator, 74LS460 514 PLHS18P8A Primer 520 PLHS473 Primer 529 High—Speed 12—Bit Tracking A/D Converter Using PLS179 537
PML Application	n Notes
AN29	PLHS501 Programmable Macro Logic Primer 547
PLHS501 Applie	cation Notes, Vol. 1
	Designing with Programmable Macro Logic
Chapter 1	Introduction to PML Design Concepts 562 Performance 562 NAND Gate Flip—Flops 569
Chapter 2	Functional Fit
Chapter 3	Design Examples
Chapter 4	Successor Architectures
Chapter 5	Support Issues
Chapter 6	PLHS501 Examples Using AMAZE Revision 1.6 582
	Simple Gate Implementations 582 8-Bit Barrel Shifter 585 12-Bit Comparator with Dual 1-of-8 Decoders 591 8-Bit Carry Look-Ahead Adder 594 32-to-5-Bit Priority Encoder 597 8-Bit Shift Register with Sequence Detector 602 4-Bit Synchronous Counter 608
PLHS501 Applie	cation Notes, Vol. 2
	Designing with Programmable Macro Logic
Chapter 1	Introduction
Chapter 2	PLHS501 Review 613
Chapter 3	Flip–Flop Basics 615
Chapter 4	Notation 615 Flip—Flop Merging 615 VME Bus Examples 621
	Omnibyte VSBC20 Mailbox Interrupt Structure
Chapter 5	Micro Channel Interface
Chapter 6	NuBus Interface
Chapter 7	Nuggets 644 Data Bus Parity 644 Data Bus Operations 651
PLHS502 Applie	cation Notes, Vol. 1
. Elloose Appli	Designing with Programmable Macro Logic
Chapter 1	Introduction
Chapter 2	Development Support
Chapter 3	Capacity and Partitioning Considerations

Chapter 4	State Machine Design
Chapter 5	Additional Design Guidelines
Chapter 6	Additional PLHS502 Applications
Chapter 7	Advanced Flip–Flop Merging
riogialililable	Introduction
	Acknowledgements
	AMAZE Software
Product Section	Introduction
Chapter 1	PLA Devices
	Signetics PLUS153D
	Signetics PLUS173D 692 The PLHS473 692
Chapter 2	PAL-Type Devices 696
Onapior L	Signetics PLHS18P8B
	The PLUS16L8D and –7
	The PLUS16R8D and –7
	The PLUS20L8D and -7
	The PLUS20R8D and –7
Chapter 3	The PLC18V8Z 701 Sequencer Devices 703
Onapter 5	Introduction
	State Equation Tutorial
	The PLUS105
	The PLS155
	The PLS157
	The PLS159A
	The PLS167A
	The PLS179
	The PLUS405
Application Section	on Introduction
Chapter 4	Microprocessor Interfacing with Signetics PLDs
	Introduction
	System Partitioning
	Bus Size Decoding for the 68020 — PLUS18P8B
	The 80386 Pipeline Decoder — PLUS153D
	68030 Address Decoding — PLUS173D
	The 29000, SRAM and the PLUS20L8D
	Interrupt Handler — PLS179
	SCSI Target Interface — PLUS105 and PLUS153B
	Introduction
	Functional Description
	Port Operation
	Arbitration Software Sequence
	RESELECT Software Sequence
	TRANSFER Software Sequence
	DISCONNECT Software Sequence
Chapter 5	Hardware Description
Chapter 5	The CCITT V.27 Scrambler — PLC18V8Z
	A Novel Speech Synthesizer — PLS159A
	CCITT Forward CRC Polynomial — PLUS405
Chapter 6	Instrumentation
	Heart Beat Monitor — PLS159A, PLS168A and PLS153 757
	The Pulse Width Monitor — PLS168
Chapter 7	General Applications
Chapter /	Motor Stepper Controller with the PLS155
Chapter 8	Security Systems
	A Programmable Alarm System — PLS168

AN7 Single Chip Multiprocessor Arbiter

Application Note

Application Specific Products

INTRODUCTION

In multiprocessor environments there is considerable savings to be made through sharing system resources. If each processor must support its own bus structure, I/O devices, and bulk storage medium, system cost could be very high. In the configuration shown in Figure 1, all processors share a common communication bus, and a number of system resources.

Since every processor must use the common system bus to communicate with its peripherals, a priority structure that resolves simultaneous processor bus requests into a single bus grant must be integrated into the system. In addition to making request-grant transactions, transient bus contention due to grant switching must be removed by inserting precise guard band times between bus grants.


Signetics' Field Programmable Logic Sequencer provides a convenient and cost-effective means for implementing a synchronous arbiter to perform these tasks within a single chip.

ARBITER STRUCTURE


Within a multiprocessor system, two general classes of processors can be recognized: Priority A and Priority b. Priority A processors have the highest request priority and must only compete with other Priority A processors for bus control. The arbiter must issue "A" grants in manner that prevents any high priority "A" processor from locking out another Priority A processor. To enable this, the Priority A rules implemented here use a Last Granted Lowest Priority (LGLP) ring structure. After an "A" processor has completed a busrelated task, its next arbitrated request priority will be lowest in the "A" request group. The previously second highest priority "A" processor will then become highest priority requester. The net effect of the "round robin" exchange is that every Priority A processor will have a turn at being highest priority processor. Priority A processors are typically ones that perform real-time operations or vital system tasks.

Priority b processors are lower in priority than the "A's" and may only be granted system control when no "A" requests are pending. "b" processors usually perform background tasks. Within the Priority b group, further priority ordering exists such that each "b" processor has a fixed priority position.


Plumber¹, Pearce², and Hojberg³ present asynchronous techniques of arbiter implementation. These methods all have hardwired priority rules and imprecise guard band times during grant switching. As pointed out by Hoiberg, a synchronous state machine can be configured as a Mealy-type controller to provide not only precise guard band times and programmable priority rules, but also programmable input/output polarity. The state machine in Figure 2 is made from a control PROM array and an edge-triggered latch. The "A" and "b" requests and the machine's present state are used by the control PROM to determine the next "A" and "b" grants and the next state.



AN7



a. A and b service requests $(R_N,\,r_N)$ plus the present state determine, through the control PROM, the next state and the next grant outputs $(G_N,\,g_N)$.




b. Requests R_0 , R_1 , r_0 , and r_1 are asserted low in the same clock sample period. The priority rules that determine the order in which the grants are issued and the shaded guard-band areas are programmed into the control PROM. Note that the A and b request lines and the present state input to the PROM must have a set-up time equal or greater than the latch set-up time plus the PROM access time.

Figure 2. Arbiter Constructed from a Mealy-Type State Machine

SYSTEM OPERATION

Two machine states can be identified by inspection: a wait state and a grant state. The state machine enters a grant state as a response to a system request on either R_N or r_N. The machine will remain in this state with a single grant line asserted as long as the request remains asserted. Upon releasing the request line, the machine will pass through a single wait state before considering other pending requests. This provides a single state guard band time. The requests received must meet the set-up requirement of the edgetriggered latch after propagating through the control PROM. If these time considerations do not fit within a given multiprocessor structure, an input latch may be added such that the R_N and r_N lines are clocked through the latch by the system clock, thereby removing asynchronous set-up time considerations. On the basis of a state machine approach, two techniques of implementation are feasible: 1) using an architecturally advanced single IC controller, the FPLS, and, 2) a traditional PROM/LATCH configuration.

AN7



FPLS ARBITER IMPLEMENTATION

A five Priority "A" and three Priority "b" arbiter will be constructed such that all grant outputs will be asserted low for grants and all request inputs will be asserted low for system requests.

Brief FPLS Description

The FPLS block diagram shown in Figure 3(a) consists of a control PLA and 14 clocked S/R flip-flops. The control PLA is actually an AND-OR logic array that functions as a Content Addressable PROM. The PLA is organized as 48 words of 28 bits with 16 external input

lines, and six internal inputs fed back from the State Register. The 28 PLA outputs drive the S/R inputs of the six-bit State Register and eight-bit Output Register. Note that the state feedback path is made inside the FPLS.

 $I_{\rm N}$ and present state inputs, $P_{\rm S}$, represent 2^{22} possible input codes; 48 of these codes may be mapped in the PLA to provide a 14 bit register control word. As shown in Figure 3(b) each input code may be specified by assigning to the variables either Low "L", High "H", or Don't Care "." logic states. If any input code falls logically outside the programmed codes, the PLA asserts a Low on all its 28

internal outputs, thereby issuing a ''no change' command to the R/S flip-flops.

This is an important architectural feature because it requires that only state or output transition terms be programmed. Looping terms that change neither state nor output need not be programmed in the FPLS, owing to the functional characteristics of S/R flipflops tabulated in Figure 3(c). An example of this is shown in Figure 4.

The S/R inputs of both state and output registers are specified by using PLA outputs ("AND" functions of request inputs and present state) in the program table of Figure 3(c).

AN7

The corresponding next state of each bit will be set to 0 for "L", 1 for "H", and No Change for "-". The FPLS's PR/OE line may be assigned either Asynchronous Preset or Output Enable functions, via a user programmable option.

The entire function is integrated into a single 28-pin package designated as PLS105.

State Algorithm

Figure 5(a) displays the circular state form and all possible state transitions of the LGLP priority structure. Hex states 3F, 3E, 3D, 3C, and 3B are arbiter wait states Wo.4. In these states, processor "A" and "b" requests are monitored. Figure 5(b) illustrates a typical grant to processor A1 in hex state 07. As long as A1 asserts its request line low, the next state will be 0716 and the next output will remain with G1 asserted low and all the other grant outputs asserted high. Since no change in state or grant output results from this transition, no PLA resources are required.

As soon as processor A₁ returns its request line, R₁, to 1, a state transition is made to 3D. and an output transition is made to set all grant outputs to 1. Since processor A1 was the last to be granted system resources, it will now have the lowest A level request priority (LGLP). In wait state W2, the highest priority processor will be A2, second A3, third A4, and fourth Ao. To maintain the LGLP rule, grant transitions must follow the state rule $G_N \rightarrow W_{(N+1)}$, and wait states, W_M , must set their "A" priorities so that processor AM is highest priority. Priority decreases as one proceeds clockwise around the state ring to the lowest priority processor, A(m-1).

When no "A" requests are pending, "b" requests may be granted. To avoid upsetting the LGLP priority rule, a "b" grant must leave and return to the same wait state. Since the "b" priority structure is the same regardless of the wait state, only a single set of "b" transition terms are required.




Figure 4. FPLS State and Output Transitions

For example, a grant transition to g₂ (Hex 20 - 25) can be issued only if there are no "A", "b0", or "b1" requests pending. Given the binary wait state code 111XXX, where "X's" represent Don't Cares, a request code of 01111111 will transfer the arbiter to the grant state go from any of the wait states,

It is important to realize that in making this transition, the lower three-state bits will not be changed - they provide the wait state return address. When r2 returns high, 1XXXXXXX, a transition back to the previously exited wait state is made by forcing a "1" in the three most significant state bits and leaving the lower three-state bits unchanged.

All output and state bits are initially preset to "1" through the use of the optional preset function. Grant output lines are only forced low when transitions are made to grant states and are returned to "1" when jumping back to a wait state.

Table 1 provides the complete arbiter program. The complete arbiter circuit diagram is shown in Figure 6. The AMAZE equations are shown in Figure 7.

PROM/LATCH **IMPLEMENTATION**


The same five "A" processor and three "b" processor arbiter can be implemented with discrete PROM's and Latches using the same state diagrams for the FPLS, except that now looping transition terms must be programmed. Coding of all state and output transitions requires programming of two memory fields: the "A" request PROM's (2KX6) and the "b" request PROM (64 \times 3). The complete circuit diagram is shown in Figure 6(b).

The "A" request PROM's determine the next machine state (No-5) at all times, except when there are no "A" requests pending and there is a "b" request, or if the machine is presently in a "b" grant state. In these cases, the "b" request PROM controls the machine's next state.


The grant control lines are decoded from the next state lines and latched in two quad output latches. This PROM/LATCH organization is conceptually the same as that shown in Figure 2.

June 1988 438

AN7



AN7



AN7

Table 1. FPLS Program Table for Priority Arbiter

				TRANSITION TERM INPUT VARIABLE (Im) PRESENT STATE													OUTPUT TERM																				
No.	1	Τī	T =	T1	11	1	IN	PU	T VA	RIA	BLE	(In	1)				PRI	ESE	NT :	STA	TE	Ps)		N	EXT	ST	ATE	(Na	1)	C	UT	PUT	FU	NC	TION	l (Fi	1)
	5	4	3	2	1	0	9	8	7	6	5	4	3	2	1	0	5	4	3	2	1	0		5	4	3	2	1	0	7	6	5	4	3	2	1	0
0	-	-	-	-	-	-	-	-	-	-	-	_	-	-	_	L	Н	н	Н	н	Н	н		L	L	L	н	н	L	н	н	н	н	н	н	н	L
1	-	-	-	-	_	-	_	-	-	-	-	-	_	_	L	Н	Н	Н	Н	Н	Н	Н		L	L	L	Н	н	Н	Н	Н	Н	Н	Н	Н	L	Н
2	-	_	_	E	-	-	_	_	_	_	-	_	_	L	Н	Н	Н	Н	Н	Н	Н	Н		L	L	Н	Н	н	L	Н	н	н	Н	Н	L	Н	Н
3	-	-	_	-	-	-	-	_	-	_	-	_	L	Н	Н	Н	Н	Н	Н	Н	Н	Н		L	L	н	Н	Н	н	Н	Н	Н	Н	L	Н	Н	Н
4	=	=	=	-	-	-	=	-	-	=	-	L	Н	Н	Н	Н	Н	Н	Н		Н	н		L	Н	L	Н	Н	L	Н	Н	Н	L	Н	Н	Н	Н
5	=	=	=	-	-	-	-	-	-	-	-	=	-	-	L	-	н	H	H		н	L		L	L	L	Н	Н	Н	Н	Н	н	Н	Н	Н	L	Н
7	=	=	E	+	-	-	+=	-	-	-	-	-	E	H	H	-	H	H	H	H	H	L		L	L	н	Н	Н	<u>L</u>	Н	Н	Н	н	Н	L	Н	Н
8	=	=	Ε	=	=	=	=	=	=	=	+=	L	Н	Н	н	=	н	Н	Н		н	L		L	H	H	H	H	H	H	H	H	H	H	H	H	H
9	=	=	=	=	-	=	=	=	=		+=	Н	Н	н	н	L	н	н	н	н	н	L		L	-	L	н	Н	L	н	Н	Н	Н	Н	Н	н	L
10	-	=	=	=	-	-	-	-	-	-	-	=	-	L	=	Ė	н	н	Н	н	L	Н		L	L	н	н	н	ì	н	н	Н	н	н		н	H
11	-	-	-	-	-	-	-	-	-	-	-	-	L	н	_	-	Н	Н	Н	Н	L	н			L	н	н	н	Н	н	н	н	н	L	Н	н	н
12	-	=	-	-	T-	-	_		<u> </u>	<u> </u>		L	Н	Н	_	-	Н	Н	Н	Н	L	Н		L	Н	L	н	Н	L	Н	Н	н	L	Н	Н	Н	Н
13		-	-		-	-	-	-	-	-	-	Н	Н	Н	-	L	Н	Н	Н	н	L	н		Ļ	L	L	н	Н	L	Н	Н	н	Н	Н	Н	H-	L
14	-	-	=	-	-	-	-	-	-	-	-	Н	Н	н	L	Н	Н	Н	Н	н	L	н		L	L	L	Н	Н	н	н	н	н	н	н		L	н
15	=	-	-	-	-	=	-	1=	-	-	-	=	L	-	=	-	Н	н		Н	L	L		L	L	Н	н	Н	Н	Н	Н	н	н	L	Н	Н	Н
16	-	-	-	-	-	-	-	=	1=	=	=	L	H	=	-	-	Н	H	Н	H	L	L		L	н	L	н	Н	L	Н	Н	Н	L	Н	Н	Н	Н
18	=	=	=	=	=	=	=	=	=	-	=	Н	H	_	-	H	н	н	Н	н	L	L		L	L	L	H	H	H	Н	Н	H	Н	H	H	Н	H
19	=	=	=	=	-	Ε	Ε	=	=	=	=	н	н	L	Н	н	н	н	Н	н	L	L		L	L	Н	Н	Н	L	Н	Н	Н	Н	Н	L	H	Н
20	_	=	=	=	=	_	-	-	-	-	-	ï	-	_	-	=	н	Н	Н	ï	H	H		L	н	L	н	н	L	н	н	н	L	н		Н	H
21	_	-	-	=	-	-	-	_	-	=	=	Н	-	_	-	L	н	н	н	L	Н	н		L	L	L	н	Н	ī	н	н	н	н	н		н	L
22	-	-	-	1-	-	-	-	-	-	-	-	Н	-	-	L	Н	Н	Н	Н	L	Н	Н		L	L	L	Н	Н	L	н	н	Н	Н	н	Н	L	Н
23	-	-	-	-	-	-	-	-	-	-	-	Н	-	L	Н	Н	н	Н	Н	L	Н	Н		L	L	Н	н	н	Н	Н	н	Н	Н	Н	L	н	Н
24		-	-	-	-	-	-	-	-	-	-	Н	L	Н	Н	Н	Н	Н	Н	L	Н	Н		L	L	Н	Н	Н	Н	Н	н	H	H	L	Н	Н	Н
25	-	-	-	-	-	-	-	-	-	-	L	Н	H	Н	Н	Н	н	Н	Н	_	_	-		Н	L	н	-	-	-	н	Н	L	Н	н	Н	Н	Н
26	-	-	-	=	-	-	-	-	-	L	Н	Н	Н	Н	н	Н	Н	н	Н		_	-		н	н	L	-	-	-	н	L	Н	Н	н	Н	Н	н
27	=	=	=	=	-	-	-	-	L	H	Н	Н	Н	Н	Н	H	н	Н	H	Н	Н	=		H	L	L	-	-	-	L	Н	Н	H	H	H	Н	H
28	=	E	=	-	+-	-	-	=	-	=	-	=	=	-	Н	п	L	L	L	Н	Н	H		H	H	H	H	H	H	Н	Н	H	Н	Н	Н	H	H
30	Ξ	=	Ξ	E	=	Ε	E	E	Ε	E	E	Ξ	Ε	Н	_	+=	t	t	Н	н	H	L		н	н	н	н	L	-	н	Н	Н	Н	Н		Н	H
31	_	=	=	=	-	=	=	=	=	=	=	=	Н	-	_	-	L	ī	н	н	н	н		н	н	н	L	н	н	н	н	н	н	н	н	н	н
32	-	=	=	-	-	-	-	-	-	-	-	н	-	-	-	-	L	Н	L	Н	Н	L		н	н	н	н	н	н	н	н	н	н	н	Н	н	Н
33	-	-	_	-	-	-	_	-	-	-	Н		_	-	_	-	Н	L	Н	_	-			н	н	н	-	-	_	н	н	н	н	н	Н	Н	Н
34		-	-	_	_	-	-	-	-	Н	-	_	_	-	-	-	Н	Н	L	_	-	-		Н	Н	н	-	-	-	н	Н	Н	Н	Н	Н	Н	Н
35	-	-	=	-	-	-	-	-	Н	-	-	_	-	_	-	-	Н	L	L	_	_			Н	н	н	-	-	-	Н	н	Н	Н	н	Н	Н	н
36					_				-	-	-	-	-		-	-	Ш															_	_	_			_
									2	15	10	œ	æ	ď	Œ	œ														ô	Ó	ď	ાહ	၂၆	ပ်	O	ાઉ

AN7

```
************ ARBITERS ************
@DEVICE SELECTION
ARBITERB/82S105
 @STATE VECTORS
 [ FF5, FF4, FF3, FF2, FF1, FF0 ]
W0 = 03Fh; W1 = 03Eh;
W2 = 03Dh
W3 = 03Ch ;
W4 = 03Bh;
W04 = 111---b;
GAO = 06h;
GA1 = 07h;
GA2 = OEh ;
GA3 = OFh;
GA4 = 16h;
GBO = 101---b ;
GB1 = 110---b;
GB2 = 100---b;
 @INPUT VECTORS
@OUTPUT VECTORS
[OB2, OB1, OB0, OA4, OA3, OA2, OA1, OA0]
QAO' = FEh ;
QA1' = FDh ;
QA2' = FBh;
QA3' = F7h;
QA4' = EFh
QBO' = DFh ;
QB1' = BFh;
QB2' = 7Fh;
NOGRANT' = FFh;
@TRANSITIONS
WHILE [WO]
        CASE
                 [/RAO] :: [GAO] WITH [QAO']
                  [/RA1 * RA0] :: [GA1] WITH [QA1']
                 L/RA2 * RA1 * RA0] :: [GA2] WITH [QA2']

L/RA3 * RA2 * RA1 * RA0] :: [GA3] WITH [QA3']

L/RA4 * RA3 * RA2 * RA1 * RA0] :: [GA4] WITH [QA4']
         ENDCASE
WHILE [W1]
         CASE
                TOTAL TRANSPORT TO THE TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL TOTAL T
         ENDCASE
                                                                        a. Arbiter State Equations
                                                                                                      Figure 7
```

AN7

```
WHILE [W2]
   CASE
      [/RA2] :: [GA2] WITH [QA2']
      [/RA3 * RA2] :: [GA3] WITH [QA3']
[/RA4 * RA3 * RA2] :: [GA4] WITH [QA4']
      [/RA0 * RA4 * RA3 * RA2] :: [GA0] WITH [QA0']
[/RA1 * RA0 * RA4 * RA3 * RA2] :: [GA1] WITH [QA1']
   ENDOASE
WHILE [W3]
   CASE
      [/RA3] :: [GA3] WITH [QA3']
      [/RA4 * RA3] :: [GA4] WITH [QA4']
      L/RA0 * RA4 * RA3] :: [GA0] WITH [GA0']
[/RA1 * RA0 * RA4 * RA3] :: [GA1] WITH [GA1']
[/RA2 * RA1 * RA0 * RA4 * RA3] :: [GA2] WITH [GA2']
   ENDCASE
WHILE [W4]
      [/RA4] :: [GA4] WITH [QA4']
      E/RAO * RA4] :: EGA0] WITH [QA0']
      [/RA1 * RA0 * RA4] :: [GA1] WITH [QA1']
[/RA2 * RA1 * RA0 * RA4] :: [GA2] WITH [QA2']
      [/RA3 * RA2 * RA1 *RA1 * RA4] :: [GA3] WITH [QA3']
   ENDCASE
WHILE [W04]
   CASE
     L/RB0 * RA4 * RA3 * RA2 * RA1 * RA0] :: [GB0] WITH [@B0]
L/RB1 * RB0 * RA4 * RA3 * RA2 * RA1 * RA0] :: [GB1] WITH [@B1]
L/RB2 * RB1 * RB0 * RA4 * RA3 * RA2 * RA1 * RA0] :: [GB2] WITH [@B2]
   ENDCASE
WHILE [GA0]
   IF [RAO] THEN [W1] WITH [NOGRANT']
  IF [RA1] THEN [W2] WITH [NOGRANT']
  IF [RA2] THEN [W3] WITH [NOGRANT']
WHILE [GA3]
  IF [RA3] THEN [W4] WITH [NOGRANT']
WHILE [GA4]
  TE FRA41 THEN FWOT WITH ENORGANT 1
WHILE [GB0]
  IF [RB0] THEN [GB1] WITH [NOGRANT']
  IF [RB1] THEN [GB2] WITH [NOGRANT']
WHILE [GB2]
  IF [RB2] THEN [GB0] WITH [NOGRANT']
                            a. Arbiter State Equations (Continued)
                                      Figure 7 (Continued)
```

AN7

```
************** ARBITERB ***********
** CK ** 1-:


** I ** 2-:

** I ** 3-:

** I ** 4-:
                                            -- P1N** FNC **
|-28 ** +5V **VCC
|-27 ** I **N/C
CLOCK
RB2
                                            |-27 ** I
|-26 ** I
|-25 ** I
|-24 ** I
|-23 ** I
|-22 ** I
|-21 ** I
                                                            **N/C
                                    8
2
S
1
RRO
                                                            **N/C
RA4
RA3
                                                           **N/C
**N/C
                ** I
RA2
                        ** 9-1
** 10-1
                                            1-20 ** I
1-19 ** PR
                ** I
** 0
RAO
                                                            **N/C
                                                           **PRESET
OB2
                        ** 11=1
** 12=1
** 13=1
                                            :-17 ** 0
:-18 ** 0
:-17 ** 0
:-16 ** 0
                                                            **0A0
                ** 0
                                                            **DA1
OBO
                                                            **0A2
                                                            **0A3
                            b. Arbiter Pin List
             @DEVICE TYPE
            @DRAWING
            ********** MULTI-PROCESSOR BUS ARBITOR
            ******* ARBITERB REV. 0
            @DATE
             ******** JULY 26, 1985
            @SYMBOL
            @COMPANY
********** SIGNETICS
            @NAME
            ******* DAVID K. WONG
            @DESCRIPTION
@INTERNAL SR FLIP FLOP LABELS
FF0 FF1 FF2 FF3 FF4 FF5
            @COMMON PRODUCT TERM
            @COMPLEMENT ARRAY @LOGIC EQUATION
                                                             TB00770S
                     c. Arbiter Boolean Equations
                          Figure 7 (Continued)
```

AN7

Table 2. Arbiter Program Table



AN7

SUMMARY

As can be seen from the circuit diagrams, the FPLS can offer significant advantages over discrete MSI arrays in the design of state machines. The tradeoff in both design alternatives for the Priority Arbiter is shown in Table 2. Clearly, the FPLS approach uses fewer parts, with savings in PC board space and power requirements.

REFERENCES

 W.W. Plumber: "Asynchronous Arbiters"; IEEE Transactions on Computers, January 1972, pp. 37 – 42.

Table 3. Design Alternatives for the Priority Arbiter

PARAMETER	F.P.L.S.	PROM/LATCH
Parts count	1 IC	≈19IC's
PCB space	.84 in ²	7.92 in ²
Power	.65W	2.85W
Voltage	+ 5V	+ 5V

- R.C. Pearce, J.A. Field, and W.D. Little: "Asynchronous Arbiter Module"; *IEEE Transactions on Computers*, September 1975, pp. 931 – 933.
- 3. K. Soe Hojberg: "An Asynchronous Arbiter Resolves Resource Allocation Con-
- flicts on a Random Priority Basis''; *Computer Design*, August 1977, pp. 120-123.
- K. Soe Hojberg: "One-Step Programmable Arbiter for Multiprocessors"; Computer Design, April 1978, pp. 154 – 158.

AN8 Introduction To Signetics Programmable Logic

Application Note

Application Specific Products

Author: K. A. H. Noach

INTRODUCTION

Custom logic is expensive - too expensive if your production run is short, 'Random logic' is cheaper but occupies more sockets and board space. Signetics Programmable Logic bridges the gap. Using PLD, you can configure an off-the-shelf chip to perform just the logic functions you need. Design and development times are much shorter, and risk much lower than for custom logic. Connections are fewer than for random logic, and, for all but the simplest functions, propagation delay is usually shorter. Yet another advantage that PLD has over custom logic is that it allows you to redesign the functions without redesigning the chip - giving you an invaluable margin not only for cut-and-try during system development, but also for later revision of system design. You're not tied down by the need to recover capital invested in a custom chip.

A PLD chip is an array of logic elements – gates, inverters, and flip-flops, for instance. In the virgin state, everything is connected to everything else by nichrome fuses, and although the chip has the capacity to perform an extensive variety of logic functions, it doesn't have the ability to. What gives it that is programming: selectively blowing undesired fuses so that those that remain provide the interconnections necessary for the required functions.

Signetics Series 20 PLD, named for the number of pins, supplements the well-known Series 28. The package is smaller – little more than a third the size, in fact – but the improved architecture, with user-programmable shared I/O. compensates for the fewer pins. The series comprises the following members, in order of increasing complexity:

- PLS151 field-programmable gate
 array
- PLS153 field-programmable logic array

- PLS155 field-programmable logic sequencer
- PLS157 field-programmable logic sequencer
- PLS159 field-programmable logic sequencer

Entry to all the devices is via a product matrix, an array of input and shared I/O lines fuse-connected to the multiple inputs of an array of AND gates (see Figures 1, 2 and 5). To exploit the capacity of any device, it is important to make the most economical use of the AND gates it has available. Application of de Morgan's theorem can help in this. For example, inputs for the function

$$F = A + B + C + D$$

would occupy four of the AND gates of the product matrix. However, the same function rewritten as

$$\overline{F} = \overline{A} \ \overline{B} \ \overline{C} \ \overline{D}$$

would occupy only one. Moreover, the second function could be done on the simplest of the Series 20 devices (and leave eleven gates over for other functions), whereas the first could not. The fact that all inputs of the Series 20 devices, including the shared ones, incorporate double buffers that make the true and complement forms of all input variables equally accessible, greatly facilitates the use of de Morgan's theorem for logic minimization.

To convert the minimized logic equations to the pattern of fuses to be blown, you can use either a programming sheet (see e.g. Table 1) or Boolean equation program-entry software that lets you enter the equations via the keyboard of a terminal. The direct program-ability of logic equations makes system design with PLD simple and sure. Functional changes can be made by replacing one PLD chip by another differently programmed. In many cases you can even remove the original one, reprogram it on the spot, and re-insert it. Programming machines qualified for the Se-

ries 20 are at present available from DATA I/O, KONTRON, and STAG.

FPGA PLS151


The field-programmable gate array is the simplest of the Series 20 PLD devices; Figure 1 shows the functional diagram. The array can accept up to 18 inputs. There are six dedicated input pins (A) and twelve (A') that can be programmed as inputs, outputs, or bidirectional I/O. All input variables, whether on dedicated or programmed input pins, are available in both true and complement form in the product matrix (B), and both forms are buffered: either form can drive all 12 product lines if required. In the virgin state, all the input variables and their complements are connected to all the product lines via a diode and a fuse (C), and the product matrix is effectively inoperative. To enable it to generate the required functions, unrequired connections between individual input lines and product lines are severed by blowing the connecting fuses.

At the output of the product matrix are 12 NAND gates, each with 36 inputs to accommodate the 18 possible input variables and their complements. Each of the product terms is normally active-Low, but a unique feature of Signetics PLD is that any or all of them can be independently programmed active-High. This is done by means of an array of exclusive-OR gates (D) at the NAND-gate outputs; when the fuse that grounds the second input of each OR gate is blown, the output of that gate is inverted.

The product matrix and exclusive OR-gate connections shown in Figure 1 illustrate the flexibility conferred by having buffered complements of all input variables internally available, together with independently programmable output polarities. Output B₁₁, shown with its exclusive OR-gate fuse intact, is programmed

$$\overline{B_{11}} = I_0I_1\overline{I_5}$$

AN8




NOTE:

A dedicated inputs, A', programmable I/O B, product (NAND) matrix with fused connections C, each of the vertical lines in the matrix represents 36 inputs to the terminating NAND gated. D, exclusive-OR array with inputs grounded via fuses for polarity control. E, programmable Tri-state output buffers. F, fuse-programmable control matrix. Square dots (\blacksquare) represent permanent connections; round dots (\blacksquare) infact fuse connections. Connected as shown, the array is programmed for the functions $\blacksquare_{11} = I_0 =$

Figure 1. Field-Programmable Gate Array PLS151A

June 1988

AN8



At the same time, and without using any additional inputs, output B_{10} (fuse blown) is programmed

$$\mathsf{B}_{10} = \overline{\mathsf{I}_0} \; \overline{\mathsf{I}_1} \; \overline{\mathsf{I}_5}$$

Each of the exclusive-OR gates drives a three-state output buffer. In the virgin state all the buffers (E) are disabled and therefore in the high-impedance state. The function of the programmable I/O pins (A') is then determined by the I/O control matrix (F). The three AND gates at the control-matrix output are

Active-High, and when one of them is in the High state, the four output buffers it controls are enabled; the corresponding I/O pins then act as outputs. conversely, when a control-matrix AND-gate output is Low and the control fuse for the corresponding Tri-state buffer is intact, the pins controlled by that gate act as inputs. Thus, these pins can be programmed in groups of up to four to act as inputs or outputs according to the state of selected input variables. If required, any of the programmable I/O pins can be made a

dedicated output by blowing the control fuse of the output buffer associated with it.

The speed of the FPGA compares favorably with TTL, although its propagation delay is longer than the individual gate delay of TTL. When the number of inputs required is large, however, the FPGA more than makes up for this. When more than eight inputs are required, for example, the FPGA has a distinct advantage. Then, the overall propagation de-

AN8

lay of TTL often amounts to two or three gate delays, but that of the FPGA to only one.

FPLA PLS153

Architecture

With two levels of logic embodied in a product matrix terminating in 32 AND gates coupled to a ten-output OR matrix (Figure 2), the FPLA is a step up in complexity from the FPGA. Again, there is provision for 18 input variables, internally complemented and buffered, but here divided between eight dedicated input pins and ten individually programmable I/O pins. As before, exclusive-OR gates grounded by fuses provide output polarity control, and any of the programmable I/O pins can be made a dedicated output by blowing the control fuse of the output buffer associated with it.

Programming


When the required functions have been defined, corresponding programming instructions are entered in a programming table, the layout of which reflects the FPLA architecture. (A Signetics computer program named AMAZE, which accepts Boolean equations as input and generates an FPLA programming table as output, is also available.) The programming machine blows the FPLA fuses in the pattern prescribed by the table.

As an illustration of FPLA programming, consider a full adder. Figure 3 shows a TTL version (74LS80) and the corresponding logic equations. Note that the feedback of \overline{C}_{n+1} introduces a second propagation delay. In the FPLA this is eliminated by redefining Σ in terms of A, B, and Cn, as shown in Figure 4, and using the right side of the equation for \overline{C}_{n+1} instead of the term itself. At first glance this would appear to require a minimum of three product terms for \overline{C}_{n+1} plus four for Σ , or a total of seven. The Karnaugh maps, however, show considerable overlap between the two functions: the map for \overline{C}_{n+1} differs from that for Σ only by having A B C_n instead of $\overline{A} \ \overline{B} \ \overline{C_n}$. Rewriting the equation for $\overline{C_{n+1}}$ to introduce \overline{A} \overline{B} $\overline{C_n}$ and eliminate A B C_n ,

$$\overline{C}_{n+1} = A \overline{B} \overline{C_n} + \overline{A} B \overline{C_n} + \overline{A} \overline{B} C_n + \overline{A} \overline{B} \overline{C_n}$$

increases the number of product terms by one, but now $\overline{\mathbb{O}}_{n+1}$ and Σ have three terms in common. Therefore, since the FPLA allows multiple use of product terms, it is sufficient to program each of the common terms only once; thus, the original seven product terms are effectively reduced to five.

To fill in the programming table (Table 1), first allocate inputs and outputs.






Figure 4. Karnaugh Maps and Logic Equations for the Full Adder of Figure 3, Illustrating how the Equations are Reduced for the FPLA Implementation Shown in Figure 2 and Table 1

Inputs:
$$A = I_0$$
 Outputs: $\overline{C}_{n+1} = B_7$
 $B = I_1$ $\overline{\Sigma} = B_8$
 $C_n = I_2$ $\Sigma = B_9$

Next, enter the product terms of Σ in the product-matrix (AND) part of the table, using H to indicate a true input and L a false one.

- Term 0 is A B C_n: mark H, L, L in columns I₀, I₁, I₂ of row 0
- Term 1 is A B C_n: mark L, H, L in columns I₀, I₁, I₂ of row 1
- Term 2 is Ā B C_n: mark L, L, H in columns I₀, I₁, I₂ of row 2
- Term 3 is A B C_n: mark H, H, H in columns I₀, I₁, I₂ of row 3.

Fill the rest of rows 0, 1, 2, and 3 with dashes to indicate that all other inputs are to be disconnected from Terms 0, 1, 2, and 3 (fuses blown).

The product terms of $\boldsymbol{\Sigma}$ must be added to form the sum-of-products required at output

 $B_9.$ Indicate the required addition by putting an A (for Attached, i.e. fuse unblown) in the Term 0, 1, 2, and 3 spaces of column B(O) $_9$; Term 4 is not required for Σ , so put a dot in the Term 4 space to indicate that it is to be disconnected (fuse blown). To indicate that the output is to be Active-High, put an H in the polarity square above the B(O) $_9$ column. Finally, fill row D_9 with dashes to indicate that all fuses on line D_9 of the control matrix are to be blown and B_9 is to be a dedicated output. This completes the programming of Σ .

The Σ output on B_8 is programmed in just the same way, except that the polarity square above the $\mathsf{B}(\mathsf{O})_8$ column is marked L to indicate Active-Low. (Note that in the FPLA, the Σ and Σ outputs change simultaneously, because all output signals traverse the exclusive-OR array (D), whether they are Active-High or Active-Low. In the TTL full adder shown in Figure 3, the output inverter delays the change of Σ with respect to Σ .)

AN8

Table 1. FPLA Programming Table Filled in for the Full Adder of Figure 2

										alpho congress											Н		L	P)L/	RIT	Υ		_	_
	TT	Г		in the second	-	-		mile spec	Al	ND		olum (San	No.	garane.			escore.				۳	_	_	_	-	R			100	_
	E R M	Г				I								В	(I)										B((0)				_
	lin	7	6	5	4	3.	2	1	0	9	8	7	6	5	4	3	2	1	0		9	8	7	6	5	4	3	2	1	T
エー	0	F	-	-	-	-	L	L	Н	-	_	-	-	_	-	-	-	-	-		Α	Α	Α						DOM: NO	Г
B(O)	1	F	-	-	-	-	L	Н	L	-	-	-	-	-	_	-	-	_	-		Α	Α	Α							Γ
B(O) HIGH LOW (POL.)	2	_	-	_	_	-	н	L	L	_	_	-	_	-	_	-	_	_	-		Α	Α	Α							I
宝	3	E	_	_	_	_	Н	Н	Н	_	_	_	_	_	_	_	_	_	-		Α	A	•							L
	4	Ŀ	-	_	_	_	L	L	L	_	_	<u> -</u>	_	-	_	_	_	_			•	•	Α				Ш			ļ
B(O) ACTIVE A INACTIVE •	5	L			Щ			_	\vdash	\vdash		\vdash				Щ			Ш		Н		_	\vdash			Ш			ļ
B(O)	6	┡	_	-	Ш	\vdash	_	_	\vdash	\vdash	_	_	<u> </u>	_		L	L	_	Н		Н	_	_	_	_		Н			ļ
A E S	7	_	\vdash		Н	\vdash	L	_	\vdash	\vdash	_	_	_	Щ	_	H	\vdash		Н		Н		<u> </u>	_	_		Н			Ļ
N N N	8	⊢	\vdash		Н	_	_	_	\vdash	\vdash	_	⊢	L	Н	Н	Н	\vdash	_	Н		Н	\vdash	_	\vdash	_		Н	\vdash		ł
	9	\vdash	-		Н		H	\vdash	\vdash	H	-	\vdash	\vdash	H	Н	Н	H	-	Н		Н	\vdash	\vdash	\vdash	-		Н	\vdash		╀
01-1	10	\vdash	\vdash	-	\vdash	\vdash	\vdash	-	\vdash	\vdash	-	-	-	\vdash	\vdash	\vdash	\vdash	-	\vdash		Н	\vdash	\vdash	\vdash	-	\vdash	\vdash	\vdash		+
	-	\vdash	-		\vdash	-	-	-	\vdash	\vdash	-	-	-	\vdash	\vdash	\vdash	\vdash	-	\vdash		Н	\vdash	-	-	_	-	Н	\vdash	_	ł
L, B(I) CTIVE NT CA	12	\vdash	-		\vdash	-		-	-	\vdash	-	\vdash	-	\vdash	\vdash	\vdash	\vdash	\vdash	\vdash		Н	-	-	\vdash	-		H	$\vdash\vdash$	_	ł
I, B(I) INACTIVE I, B DONT CARE (AND)	13	\vdash			\vdash	-	-	-	-	\vdash	\vdash	\vdash	-	\vdash	\vdash	\vdash	\vdash	\vdash	\dashv		Н		-	-	_		\vdash	\vdash	_	H
₹ @@0	15	\vdash			\vdash			\vdash	\vdash	\vdash	\vdash	\vdash	\vdash	\vdash	\vdash	\vdash	-	-	\dashv		Н	\vdash	-	\vdash	_		\vdash			ł
	16	\vdash	\vdash	\vdash	Н	-	\vdash	-	H	\vdash	\vdash	\vdash	\vdash	Н	Н	Н	Н	\vdash	\dashv		Н	\vdash	\vdash	\vdash	_	\vdash	Н	\vdash	_	ł
	17	\vdash	\vdash	-	Н	\vdash	\vdash	\vdash	Н	\vdash	\vdash		\vdash	Н	Н	Н	Н	Н	\dashv		Н	\vdash	\vdash	\vdash	_	\vdash	Н	\vdash		ł
	18	\vdash		\vdash	Н	-	\vdash	\vdash	Н	\vdash	\vdash	\vdash	\vdash	Н	Н	Н	H	\vdash	\dashv		Н	\vdash		\vdash	-	\vdash	Н	\vdash		t
	19	\vdash	\vdash	\vdash	Н	Н	\vdash	\vdash	Н	Н	\vdash			Н	Н	-	Н	\vdash	\dashv		Н	-		\vdash			Н	\vdash	-	t
	20	\vdash			Н	\vdash	\vdash	\vdash	\vdash	\vdash	\vdash	\vdash	\vdash	\vdash	Н		\vdash		\dashv		Н	\vdash		\vdash	_		Н	\vdash	_	t
	21	Г			Н									\Box					\neg		Н						Н	\vdash	-	t
	22	Н		\vdash	Н	Н		\vdash	Н	Н				П	\neg	Н			\dashv		Н			\vdash			Н		_	t
	23								П					П		П	П				П						П			t
	24										\Box																П	\Box		t
	25																				П						П	\Box		t
	26																				П									T
	27																													T
	28																													Γ
	29	Г																			П									Γ
	30																													I
	31																													ſ
	D9	E	Ξ	=	-	-	-	=	Ξ	=	=	=	-	-	=	-	Ξ	Ξ	-		-	4	-	Y	Y	4	Y	Y	4	1
	D8	-	_	_		-	-	_	-	_	_	-	-		-	_	-	_	-)		_			1	1				
	D7	E	-	-	-	Н	-	-	-	_	_	_	_	-	_	_	_	_	-	-			_							
	D6	L	Ш	\Box				-	Ш				-				Ш							_						
	D5	L	Ш	Ш	\Box		Щ	Щ	Ц	2		_		Щ				Щ		!					_					
	D4	\vdash	Н	\Box			\Box	\square		Щ		-	_	Щ	_	\Box		\vdash	-							_				
	D3	\vdash	\vdash	\vdash	\Box			\vdash	\sqcup	\vdash		\vdash		\sqcup		\square	Ш		_								_			
	D2	\vdash	\vdash	\vdash	\vdash	_	-	\square	Н	\vdash	\vdash	-		\vdash	-	\vdash	\vdash		\dashv									_		
	D1 D0	\vdash	\vdash	\vdash	\vdash	\dashv	\dashv	\vdash	\vdash	Н	_	-	-	\vdash	-2"	\vdash	Н	\vdash	-										_	
	PIN NO.	Ω	7	6	5	4	3	2	1	19	10	17	16	15	1/1	12	12	11	0											_
	1 1	Ť	H				$\overline{}$	-		$\overline{}$	Σ		,,,	10	17	10	14		\dashv											
	VARIABLE					ENABLE	C _n	В	Α	Σ	2	C _{n+1}																		

TB01480S

AN8

The output C_{n+1} on B_7 contains three of the same terms as Σ , plus the term \overline{A} \overline{B} $\overline{C_n}$. Only this last term needs to be additionally programmed in the product matrix: mark L, L, L in columns I_0 , I_1 , I_2 of the Term 4 row. Indicate the addition

$$\overline{A} \overline{B} \overline{C_n} + \overline{A} \overline{B} \overline{C_n} + \overline{A} \overline{B} \overline{C_n} + \overline{A} \overline{B} \overline{C_n}$$

by putting an A in rows 0, 1, 2, and 4 of column B(O)₇, and show that Term 3 (A B C_n) is not required by putting a dot in the Term 3 row to indicate disconnection (fuse blown). Put an L in the B(O)₇ polarity square to indicate Active-I ow

Identifying B7 as a dedicated output by indicating that all the fuses to control term D7 are to be blown, would now complete the programming of the full adder. However, a useful supplementary feature would be a Carry Enable function to keep the B7 output buffer in the high-impedance state except when the enable input I3 is true. The output buffer is enabled when both the fuses of a control term are blown, or when one is blown and the term that controls the output buffer is true. Thus, a Carry Enable can be provided via the l₃ input by leaving intact the fuse for Active-High operation of the enable signal to control term D7. To indicate this, put an H in the I2 column of row D7 and fill the rest of the row with dashes

The full adder with output Carry Enable uses only four of the eight dedicated inputs, three of the ten programmable I/O pins, and five of the 32 AND gates. The remaining capacity can be used for programming other functions which may, if required, also make use of AND-gate outputs already programmed for the full adder.

All fuses not indicated as blown in the programming table are normally left intact to preserve capacity for later program revisions or the addition of supplementary functions. If it is essential to minimize propagation delay, however, the finalized program should include instructions for blowing all unused fuses to minimize load capacitance.

FPLS PLS155 - PLS157 - PLS159 Architecture

The FPLS (Figure 5) is the most complex of the Series 20 PLD devices. Like the FPLA, it has a 32-term product matrix followed by an OR matrix. In the FPLS, however, the OR matrix is larger and comprises three distinct parts, with architecture differing in detail from type to type. In the PLS155, for instance, the first part consists of eight 32-input gates coupled, like those of the FPLA, to an output-polarity-controlling exclusive-OR array. The

second consists of twelve additional gates which control four flip-flops. These are what give the FPLS its sequential character, enabling it to dictate its next state as a function of its present state. The third part is the deceptively simple Complement Array (I in Figure 5): a single OR gate with its output inverted and fed back into the product matrix. This enables a chosen sum-of-products to become a common factor of any or all the product terms and makes it possible to work factored sum-of-products equations, it is also useful for handshaking control when interfacing with a processor and for altering the sequence of a state machine without resorting to a large number of product terms.

PLS155 has four dedicated inputs and eight programmable I/O pins that can be allocated in the same way as in the FPLA. It also has four shared I/O pins (L) whereby the flip-flops can be interfaced with a bidirectional data bus. Two product terms, L_A and L_B in the control matrix F, control the loading of the flip-flops, in pairs, synchronized with the clock.

Figure 6 shows the architecture of the flip-flop circuitry in the PLS155. The flip-flops are positive-edge-triggered and can be dynamically changed to J-K, T, or D types according to the requirements of the function being performed; this considerably lessens the demands on the logic. The Tri-state inverter between the J and K inputs governs the mode of operation, under the control of the product term F:

- When the inverter is in the highimpedance state, the flip-flop is a J-K type, or a T type when J = K.
- When the inverter is active, K = J and the flip-flop is a D type; the K input must then be disconnected from the OR matrix

All the product terms from the product matrix (T_0 to T_{31} in Figure 5) are fuse-connected to the J and K input OR gates. if both fuses of any one product term are left intact, J = K and the flip-flop is a T type.

The flip-flops of the PLS155 have asynchronous Preset and Reset controlled by terms in the OR matrix that take priority over the clock. Their three-state output buffers can be controlled from the enable pin OE or permanently enabled or disabled by blowing fuses or leaving them intact in the enable array (K in Figure 5).

The PLS157 and PLS159 sequencers have, gespectively, six and eight flip-flops. The architecture differs in detail but is similar in principle to that of PLS155.

Programming

The FPLS is programmed in much the same way as the FPLA, using a table to instruct the machine that blows the undesired fuses. It is not necessary to work with a circuit diagram; in fact, it is even undesirable to do so, since applying the necessary logic reduction techniques would in most cases make the diagram difficult to read and more a hindrance than a help. An example of how to program the FPLS as a universal counter/shift-register is given in the Appendix.

DEVELOPMENT AND PRODUCTION ECONOMY WITH PLD

Underlying the design philosophy of the Signetics Series 20 PLD is the concept of programmable arrays whose architecture emulates logic equation formats rather than mere aggregations of gates. The unique combination of features which support this philosophy includes:

- double-buffered true and complement inputs
- programmable-polarity outputs
- programmable I/O for internal feedback and maximum freedom in allocating inputs and outputs
- truth-table programming format

These features are common to all the PLD devices. In the field-programmable logic sequencers they are further supported by:


- flip-flops with dynamically alterable operating modes
- a complement array for simplified handshaking control

From the development engineer's point of view an important advantage of PLD is that it eliminates breadboarding. Once the functions required in terms of minimized logic equations are worked out, a PLD can be programmed accordingly. Once programmed, it will perform those functions.


Loading the instructions into the programming machine usually takes no more than a couple of hours; after that, the machine can program the devices at a rate of 100 an hour. Moreover, since any PLD can be programmed in many different ways, PLD has considerable potential for simplifying purchasing and stock control. One type of device can be programmed to perform a diversity of tasks for which it would otherwise be necesary to purchase and stock many different devices.

Series 20 PLD is second-sourced by Harris Semiconductor.

AN8



AN8



APPENDIX

Programming an FPLS as a Counter/Shift-Register

Objective: to program a PLS155 FPLS as a count-up, count-down, shift-right, shift-left machine governed by three control terms - COUNT/SHIFT, RIGHT/UP, LEFT/DOWN. Direct implementation would result in a machine with 64 state transitions (see Table A-1), which is beyond the scope of the PLS155 or even the 28-pin PLS105. Logic reduction is therefore necessary.

As there are only four feedback variables (D, C, B, A), you can do the reduction by hand, one mode at a time; the control terms need not be included till the summary equations are written. Using the transition mapping method suggested here, you can examine the excitation equations for all types of flip-flops

(R-S, J-K, D, T) and choose those types that will perform the required functions using the fewest product terms. Table A-2 summarizes the rules for flip-flop implementation using transition maps; the transition symbols used in the table mean:

PRESE	 NEXT STATE	TRANSITION SYMBOL
0	0	0
0	1	а
1	0	β
1	1	1

Using these symbols, construct Table A-3 from Table A-1 to enable you to examine the excitation equations for all types of flip-flops. Proceeding one mode at a time, transfer the state conditions from Table A-3 to Karnaugh maps, as in Figure A-1. Following the rules in

Table A-2, derive the excitation equations for the different types of flip-flops (the examples shown in Figure A-1 omit the T type because it is the same as the J-K type when J = K). In deciding which types of flip-flop to use, remember that logic minimization with PLD is different from logic minimization with 'random logic': with random logic you seek to reduce the number of standard packages required; with PLD you seek to reduce the number of product terms.

From Figure A-1 it is evident that you should choose J-K or T flip-flops for the counter mode and D flip-flops for the shift mode, for you then require only one product term per flip-flop per mode. Table A-4 summarizes the number of product terms per mode the various types of flip-flops would require.

Table A-5 shows the completed programming table for the counter/shift-register. The programming of Terms 0 to 15 reflects the flipflop excitation equations and illustrates the value of being able to switch the flip-flops dynamically from one type of operation to another. Terms 16, 17 and 18, respectively, provide for INITIALIZE, asynchronous RESET, and STOP functions.

The programming of the two additional inputs HALT and BUSY illustrates the value of the complementary, which is made active when HALT and BUSY are Low (A in the Complement square of Term 18) and propagated into all the other terms (dot in the Complement squares of TEMS of TEMS in the Complement squares of TEMS of TEMS in the Complement of the product terms will be true and the state of the machine will not change. If the Complement Array were not used, twice the number of product terms would be required, even if one of the additional inputs were omitted

As it is, the design uses only 19 of the 32 product terms available, so there is ample capacity for extending its capabilities. For example, the shift-left function can be augmented by a binary multiplication capability, using a D type flip-flop to make it shift one, two, or three places according to the state of two extra inputs, X and Y. Table A-6 shows the revised programming table. The binary multiplication function occupies nine additional product terms.

ACKNOWLEDGEMENT

Electronic Components and Applications; Vol. 4, No. 2, February 1982. Reprinted with the permission of PHILIPS.

AN8

Table A-1. Present-State/Next-State Table for Counter/Shift-Register

STATE		PRE	SENT									NEXT	STATI	Ē						
NO.		ST	ATE		C	ount	Dov	/n		Cour	nt Up)		Shift	Left	:		Shift	Righ	t
	D	С	В	Α	D	С	В	Α	D	С	В	Α	D	С	В	А	D	С	В	Α
0	0	0	0	0	1	1	1	1	0	0	0	1	0	0	0	0	0	0	0	0
1	0	0	0	1	0	0	0	0	0	0	1	0	0	0	1	0	1	0	0	0
2	0	0	1	0	0	0	0	1	0	0	1	1	0	1	0	0	0	0	0	1
3	0	0	1	1	0	0	1	0	0	1	0	0	0	1	1	0	1	0	0	1
4	0	1	0	0	0	0	1	1	0	1	0	1	1	0	0	0	0	0	1	0
5	0	1	0	1	0	1	0	0	0	1	1	0	1	0	1	0	1	0	1	0
6	0	1	1	0	0	1	0	1	0	1	1	1	1	1	0	0	0	0	1	1
7	0	1	1	1	0	1	1	0	1	0	0	0	1	1	1	0	1	0	1	1
8	1	0	0	0	0	1	1	1	1	0	0	1	0	0	0	1	0	1	0	0
9	1	0	0	1	1	0	0	0	1	0	1	0	0	0	1	1	1	1	0	0
10	1	0	1	0	1	0	0	1	1	0	1	1	0	1	0	1	0	1	0	1
11	1	0	1	1	1	0	1	0	1	1	0	0	0	1	1	1	1	1	0	1
12	1	-1	0	0	1	0	1	1	1	1	0	1	1	0	0	1	0	1	1	0
13	1	1	0	1	1	1	0	0	1	1	1	0	1	0	1	1	1	1	1	0
14	1	1	1	0	1	1	0	1	1	1	1	1	1	1	0	1	0	1	1	1
15	1	1	1	1	1	1	1	0	0	0	0	0	1	1	1	1	1	1	1	1
CONTROL TE	RMS																			
COUNT/SHIFT					1				1				0				0			
RIGHT/UP					0				1				0				1			
LEFT/DOWN					1				0				1				0			

Table A-2. Rules for Flip-Flop Implementation Using Transition Maps

FLIP-FLOP TYPE	INPUT	MUST INCLUDE	MUST EXCLUDE	REDUNDANT
R-S	S	а	β,0	1,x
	R	β	a,1	0,x
D	D	a,1	β,0	×
T	Т	a,β	0,1	×
J-K	J	а	0	1,β,×
	K	β	1	0,a,x


AN8

Table A-3. Transition Table for Counter/Shift-Register

STATE		PRE:	SENT									TRAN	SITION	l						
NO.		ST	ATE		С	ount	Dow	/n		Cour	nt Up			Shift	Left			Shift	Righ	t
	D	С	В	Α	D	С	В	Α	D	С	В	Α	D	С	В	Α	D	С	В	Α
0	0	0	0	0	a	а	а	а	0	0	0	а	0	0	0	0	0	0	0	0
1	0	0	0	1	0	0	0	β	0	0	а	β	0	0	а	β	а	0	0	β
2	0	0	1	0	0	0	β	a	0	0	1	а	0	а	β	0	0	0	β	а
3	0	0	1	1	0	0	1	β	0	а	β	β	0	а	1	β	а	0	β	1
4	0	1	0	0	0	β	а	а	0	1	0	а	a	β	0	0	0	β	a	0
5	0	1	0	1	0	1	0	β	0	1	a	β	а	β	а	β	а	β	а	β
6	0	1	1	0	0	1	β	а	0	1	1	а	a	1	β	0	0	β	1	a
7	0	1	1	1	0	1	1	β	а	β	β	β	а	1	1	β	а	β	1	1
8	1	0	0	0	β	а	а	а	1	0	0	а	β	0	0	а	β	а	0	0
9	1	0	0	1	1	0	0	β	1	0	а	β	β	0	а	1	1	а	0	β
10	1	0	1	0	1	0	β	а	1	0	1	а	β	а	β	а	β	а	β	a
11	1	0	1	1	1	0	1	β	1	а	β	β	β	а	1	1	1	а	β	1
12	1	1	0	0	1	β	а	а	1	1	0	а	1	β	0	а	β	1	а	0
13	1	1	0	1	1	1	0	β	1	1	а	β	1	β	а	1	1	1	а	β
14	1	1	1	0	1	1	β	а	1	1	1	а	1	1	β	а	β	1	1	a
15	1	1	1	1	1	1	1	β	β	β	β	β	1	1	1	1	1	1	1	1

Table A-4. Number of Product Terms Required for Counter/Shift-Register Flip-Flop Excitation

FLIP-FLOP TYPE	COUNT	COUNT	SHIFT RIGHT	SHIFT LEFT	TOTAL
SR only	8	8	8	8	32
JK only	4	4	8	8	24
D only	10	10	4	4	28
FPLS	4(J-K)	4(J-K)	4(D)	4(D)	16



AN8

Table A-5. PLS155 FPLS Programming Table for the Counter/Shift-Register

	7 6	Ľ	POL	I	Ϊ	I	TH
O<		_		THE REAL PROPERTY.	-		
O<**I B(I) Q(P) Q(N) P Q(N) P 3 2 1 0 8 A B A 7							-
M 3 2 1 0 7 6 5 4 3 2 1 0 3 2 1 0 3 2 1 0 B A B A	7 6		Е	B(O))		
		5		3		1	0
	-1-	-		-	-	-	- A
	_ _		-1-		-	1-	- A
S	- -	-	-1-	-1-	-	-	·A
3 - L H L H L J L L L O	_ _		-1-	-	-	-	· A
I		-	- -		-	-	
5 • L L H H L > C dunt H 0		-		-	-	-	· A
			- -		-	-	A
7 · L L H H L / H H H O	- -	-				-	A
	- -	-	- -	- -	- -	-	A
FMEE	- -	-			-	- [-	- A
10 • L H L L L I - LEFT H H	- -	-	-[-	- [-	-	T-	· A
0<-1	- -	- [-	- [-	- [-	- [-	- -	A
	- -	-		-]-	-	-	- A
13 OLLHLLSSHIFT HH	- -	-	- -	- [-	-	-	A
11 0 0 0 0 0 0 0 0 0	-1-	-	- -		-	-	A
		-	- -	- -	- -]-	A
	- -	-	-[-	-[-	-	-	
17	- -	- [-	- -	- -	-	-	
0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	- -	-				-	
0 8 4 4 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1		T				Τ	T
* ^{- 트} 크로 20	\top	I	T	I	I		\Box
21		\perp	\perp	I	I	\perp	I
22		L	\perp				I
23			\perp			\perp	\perp
1 1 24		_	4	\perp	\perp	\perp	\perp
25		\perp	+	_	\perp	\perp	\perp
26	\perp	\perp	+	+	+	+	\perp
27	\perp	+	+	+	+	+	\perp
28	+	+	+	+	+	+	+
29 29	+	+	+	+	+	+	+
30	+	+	+	+	+	+	+
31 Fo	+	+	+	+	+	+	+
	100	-	N 400		-	1	
L _B	TT	1			1	1	T
D ₇ • 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0							
D ₁ • 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0							
P ₅ • 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0							
D ₄							
$ \begin{array}{c ccccccccccccccccccccccccccccccccccc$							
D ₂							
D ₁							
5 4 3 2 19 18 13 12 9 8 7 6 17 16 15 14							
WARIABLE NAME 1- × 1- × 2004T SHIP 1- NAME							
VARIABLE NAME 1- × LEFT DO RIGHT UP THAP THAP TAPA							
			- CONT CONT.	nach parts			

TB01470

AN8

Table A-6. Modified PLS155 FPLS Programming Table for the Counter/Shift-Register With the Addition of a Binary Multiplier

			ted entire	01-10-10	1000	Contraction of the Contraction o			graden.	and the same of th	de Corre				E	/F T	VP	F		ΙĒο	= A	E.	= A	and the same						P	OL A	RIT	ν	4,8 30	
																A				A	A	E _A	A							Ė			Ė		Н
	T							-	-	ND				and the same of						H	wheten						0	R					marcue)	NEW YORK	
অৰ ণ।	E R			-	ī		-			B(1)					Q(P)				Q(N)		F	•						B(0)			
া বি	M	C	3	2	1	0	7	6	5	4	3	2	1	0	3	2	1	0		3	2	1	0	В	A	В	Α	7	6	5	4	3	2	1	0
FB (1)	0	•	L	Н	4	H	L	-	-	-	-	-	-	-	-	-	-	-		-	-	-	0	-	-	-	-	-	-	-	-	-	-	-	A
EA. EB TROL ILE BLE F/F TYPE (OR)	1	•	L	Н	4	Н	4	-	-	-	_	-	-	-	-	-	-	4		-	-	0	-	-	-	-	-	-	-	-	-	-	-	_	A
NA J. PARILLE SA SA SA SA SA SA SA SA SA SA SA SA SA	2	•	L	Н	L	Н	L	-	_	-	_	-	-	-	-	-	L	L		-	0	-	-	-	-	-	-	-	-	-	-	-	-	-	A
EA. ED IDLE CONTROL CONTROL ENABLE DISABLE J/K D OR J/K (OR)	3	•	4	Н	L	Н	L	-	-	-	-	-	-	-	-	L	L	L		0	-	-	-	-	-	-	-	-	-	-	-	-	-	-	A
	4	•	L	L	H	Н	L	-	_	-	-	-	-	-	-	-	-	-		-	-	-	0	-	-	-	-	-	-	-	-	-	-	-	A
I	5	•	L	L	Н	Н	L	-	-	-	-	-	-	-	-	-	-	Н		-	-	0	_	-	-	-	-	-	-	-	-	-	-	-	A
(OR) (OR) (OR) (POL)	6	•	L	L	Н	Н	L	-	-	-	-	-	-	-	-	-	H	H		-	0	-	-	-	-	-	-	-	-	-	-	-	-	-	A
(0 = J/K) TOGGLE SET RESET HOLD (OR) LOW (POL.)	7	•	L	L	Н	Н	L	-	-	-	-	-	_	_	-	Н	Н	H		0	-	_	-	-	-	-	-	-	-	_	-	-	-	-	A
	8	·	L	Н	L	L	L	-	-	L	н	-	_	-	Н	-	-	-		-	-	-	H	-	-	_	-	-	-	_	-	-	-	_	A
FIGIRIT	9	•	L	Н	L	L	L	-	-	Н	L	-	-	-	_	Н	_	-		-	-	-	H	-	-	-	-	<u>-</u>	-	-	-	-	-	-	A
ত্ৰণা ১ৰেন	10	·	-	Н	L	L	L	-	-	н	Н	-	-	-	-	-	Н			-	-	-	H	-	-	_	-	_	-	-	-	-	_	-	A
1 11 11	11	·	L	Н	L	L	L	-	-	L	Н	-	-	-	-	-	-	Н		-	-	Н	-	-	-	-	-	-	-	-	-	-	_	-	A
CCTIVE O WEARTE A ANSPARENT — ANSPARENT — AND P. R. B(O), (Q = D) (ACTIVE A (ACTIVE A (ACTIVE A)	12	·	L	Н	L	L	L	-	-	Н	L	-	-	-	Н	-,	-	-		-	-	Н	-	-	-	-	-	-	-	-	-	-	-	-	A
C C CTIVE NERATE OPAGATE ANSPARENT AND AND AND AND AND AND AND AND AND AND	13	•	L	Н	L	L	L	-	-	Н	Н	-	-	-	-	Н	-	-		-	-	·H	-	-	-	-	-	-	-	-	-	-	-	-	A
C IMACTIVE GENERATE FROMGATE TRANSPARENT AND PROPERTIES AND P. R. B(O). (Q * ACTIVE IMACTIVE (OR)	14	•	L	н	L	L	L	-	-	L	H	-	-	-	-	-	Н	-		-	Н	_	-	-	-	_	<u> </u>	-	-	-	_	-	-	-	A
Z S E E	15	•		Н	L	L	L	-	-	Н	۲	-	-	-	-	-	-	H		-	Н	-		-	-	_	-	-	-	-	-	-	_	-	A
이프기	16	·	L	Н	L	L	L	-	-	Н	Н	-	-	-	Н	-	-	-		-	H	_	_	-	-	-	-	Ŀ	-	-	-	_	_	-	A
PROGRAM TABLE ENTRIES I, B(I), Q(P) INACTIVE I, B, Q I	17	Ŀ	L	Н	L	L	L	-	-	L	Н	-	-	-	-	Н	-	-		Н	-	-	-	-	-	-	-	Ŀ	-	-	-	-	_	_	A
PROGRAM TABLE ENTRIES I, B(I), Q I, B, Q I, B, Q DON'T CAR	18	Ŀ	L	Н	L	L	L	-	-	Н	4	-	-	_	-	-	H	-		Н	_	-	-	-	-	_	-	Ŀ	-	-	-	-	-	-	A
ROG TAB B, O ON T	19	·	L	Н	L	L	L	-	-	Н	Н	-	-	-	-	-	-	H		н	-	-	-	-	-	_	-	-	-	-	-	-	-	-	Α
- E-1-10	20	·	L	L	Н	L	L	-	-	_	-	-	_	=	-	-	Н	-		÷	-	_	Н	-	-	_	-	Ŀ	-	-	-	_	_	_	A
	21	Ŀ	L	L	Н	L	L	-	-		-	_	_		_	Н	-	-		上	-	Н		-	-	_	-	느	-	-	-	-	_	_	A
	22	Ŀ	L	L	H	L	L	-	-	_	_	-	-		Н	-	-	-		-	н	-	-	_	-	_	-	<u> -</u>	-	-	-	-	_	_	A
	23	·		L	Н	L	L	-	_	_	-	_	_		_	-	-	Н		Н	_	-	-	-	-	_	-	-	-	-	-	_	-	_	A
	24		Н	-	-	=	L	-	-	-	-	_	-	_	_	-	-	-		-	-	-		-	-	-	-	-	-	-	-	-	_	-	•
	25	·	-	-	-	-	Н	-	-	_	-	-	-	-	-	-	-	-		느	-	-	-	-	-	-	-	-	-	-	-	-	-	-	•
	26	A	-	-	-	-	_	-	L	-	-	-	-	-	-	-	-	-		-	-	-	-	_	-	-	-	-	-	-	-	-	_	_	•
	28	\vdash		-	-	Н	_	\vdash	_	\vdash	_	_	-	Н	\vdash		\vdash	Н		\vdash	-		Н	_	\vdash	_	\vdash	\vdash	-	-	-	-	_	_	-
	_	\vdash	\vdash	-	-	Н	_	\vdash	_	\vdash	_	_	-	Н	\vdash	-	-	Н		\vdash	-	\vdash	Н			-	\vdash	\vdash	-	-	-	_	-	_	-
	29 30	\vdash	\vdash	-	-	Н		\vdash	_	\vdash	_	_	\vdash	Н	\vdash	-	\vdash	Н		\vdash	-	-	Н	-	\vdash	-	\vdash	\vdash	-	-	-	-	-	_	-
	31	\vdash	\vdash		-	Н	_	\vdash	_	Н		-	\vdash	Н	\vdash	-	-	Н		\vdash	-		Н	-	\vdash	-	\vdash	\vdash	-	\vdash	\vdash	-	\vdash	_	-
	F _C		-	-	-	L	_		_	_	_	_	_	-	-	-	-	-		\vdash	\vdash	Н	Н	Н		-	\vdash	\vdash	1	-		-	\vdash	_	-
	L _B	1			-	-	-		_	Ĥ	-	_		Н		-	-	H	-	1				-		-	_	-		-	-	-			-
	LA		\vdash			Н		\vdash		Н	\vdash	\vdash		Н	\vdash		-	Н	6									T	T	T	T	T	T	T	I
	D ₇		0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	5							-									
	D ₆	•	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0		5																
	D ₅		0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	5		-														
	$\overline{D_4}$	•	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	5	6																
	D_3	•	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	6			1										_			
	$\overline{D_2}$															Ĺ	Ť	H	5								_			_			_		-
	D_1																	П	5-							-							-	┙	1
	D ₀	-	-	-	-	-	-	-	L	-	-	-	-	-	-	-	-	-	6				_			_				_					┙
			5	4	3	2	19	18	13	12	9	8	7	6	17	16	15	14	Γ																
			1	-	H					-			H		D	c	В	A																	
	۳			LEFT DOWN	a	COUNT SHIFT	RHOW	ーサルムト	BUSY					本のトーシル				"																	
	WAB I		N +	2	2	15	星	4	5					i																					
	VARIABLE NAME		'	I	RIGHT! UP	N	'							Ē																					
	>			YE.	2	8																													
	_			-		_				-	-		-	-		_	-		-	2017	-	Let cont		ALC: UNKNOWN	40.00		10000000		The second		of the party	nophics in		-	

TB01460S

AN11 PLD Programmable Retriggerable One-Shot

Application Note

Application Specific Products

Author: David Wong

FEATURES

- Programmable pulse-width/delay
- Maximum 256 clock cycles
- Asynchronous TRIGGER input
- Active-High and Active-Low outputs
- Asynchronous RESET
- 20-pin package

THEORY OF OPERATION


The one-shot consists of an FPLS PLS159 and an external clock which may be part of the system in which this one-shot is to work. As shown in Figure 1 and Table 1 the FPLS is configured to have a latch and an eight-bit binary up counter which is presettable by input data to any number less than 256. Since the input data is inverted before it is loaded into the registers, counting from the comple-

ments of the input to FF will give the correct number of counts as counting from the input down to 00.

Pulse-width/delay inputs may be the outputs of another device or switches. When /RESET goes Low, flip-flops are set to all 1's (terms PB and PA). At the rising edge of the next clock, data is latched into the registers (terms LB and LA). When /TRIG goes Low, it is latched into the input latch formed by term # 0, 1, 2 and 13. The output O1 of the latch goes High and O2 goes Low which enables the 8-bit counting cycle. The O1 and /O1 will maintain their output levels until the end of the counting cycle at which time the counter reaches the count FF, resets the latch by term # 13, and sets O2 High. At the rising edge of the next clock, terms LA and LB cause data to be loaded again into the registers, and the device is ready for another /TRIG input. The output wave-forms are illustrated in Figure 2.

If the /TRIG pulse-width is longer than the desired pulse-width of the one-shot, the device will react as mentioned above, and at the end of the count cycle new data will be loaded, another count cycle begins while the outputs remain set by the /TRIG input without changing throughout the change-over of one count cycle to another. O1a, on the other hand, will go Low for one clock period at the change-over. As long as the /TRIG is Low, O₁₂ will continue to pulse Low for one clock period at the change-over of one count cycle to another. The output O2 will pulse High for one clock cycle at the change-over. Figure 2 illustrates output wave-forms for both cases. The output wave-forms are as illustrated in Figure 2.

The one-shot is implemented by programming the PLS159 as shown in Table 1. The logic representation of the program is shown in Figure 3.



November 1986 459

PLD Programmable Retriggerable One-Shot

AN11

Table 1, PLS159 FPLS Program Table


													FF N	IOD			110	GRAMMABLE RETRIGO	T		8						Т	POL	ARI	TY	1
										A	A	-	_			Α	A			-	_	_	:		_			L			1
E				AND									REMARK						((OR)			_	_	REMARK						
E R			- 1				Е	3(I)		Q(P)										Q(N)									(0)		1
M	С	3	2	1	0	3	2	1	0	7	6	5	4	3	2	1	0		7	6	5	4	3	2	1	0	3	2	1	0	2.1
0	-	L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	LATCH	-	-	-	-	-	-	-	-	A	•	+	A	
1	-	-	-	_	_	-	н	-	-	-	-	-	-	-	-	-	_	(t	-	-	-	-	-	-	-	-	Α	•	+	+	
2	_	-	-	-	-	Н	-	-	-	-	-	-	-	-	-	-	_	it .	-	-	_	-	-	-	-	-	•	A		\perp	
3		L	_		_	_		-	-	-	-	_	-	-	_		-		+	-	-	\vdash	_	-	-	-	⊢	-	+	1	1
4	-	_	-	Н	-	_	Н	-	-	-	-	-	-	-	-	-	-	COUNT CYCLE	-	-	-	_	_	_	-	0	•	•	+	+	0.75
6	_	-	-	Н	_	-	Н	-	-	-	-	_	-	-	_	- Н	H		1-	-	-	_	_	0	0	_	•	•	-	-	-
7	-	-	_	H	-	-	Н	_	-	-	-	-	-	-	_	н	H		1-	_	-	_	0	0	-	-	•	•	+	+	-
8	_	-	_	H	_	_	7	_	-	=	=	E	-		H				+	-	=	0	-	-	-	=			-	+	-
9	_	-	_	Н	-	-	7	_	-	-	-	-	Н		H	Н	-		E	-	0	_	_	-	-	-			+	+	<u> </u>
0	_	_	_	H	_	-	H	_	-	-	-	Н	H	Н		Н	H		=	0	-	-	-	_	-	-				+	
11	-	-	-	H	-	-	Н	-	-	-	-	н	Н		Н		_	V	0	-	_	-	_	-	-	-			+	+	
12				-							1								Ť											1	
13	-	-	-	-	-	-	-	-	-	Н	H	H	H	Н	Н	Н	H	LATCH	-	-	-	-	-	-	-	-	•	A	A		
14																															
15																														-	
16		_	_	_	_	_		_	_	_	-	_	_	_					1	_	_			_		_	┡	_	1	1	
17	_	L	-	_	-		-	<u> </u>	-	-	-	_	_	_	_		_		1	-	_		_	_	_	_	1	-	-	1	
18	_	-	-	-	-	_	-	_	-	-	-	_	-	-			-		+	-	-	H		-	_	-	-	-	-	\vdash	-
20	-	\vdash	-	-	-	\vdash			-	-	-	-	-	-	-	-	-		+	-	-		-	-	-	-	\vdash	-	+	+	-
21		-	-	-	-	-		-	-	-	-	-	-	-	-				+	-	-	\vdash	-	-	\vdash	-	\vdash	\vdash	\vdash	+	-
22	_	\vdash	-			-		-	-	-	-	-	\vdash	\vdash	-				+	-	-		-	\vdash	\vdash		\vdash	-	\vdash	+	-
23		-								\vdash		-	\vdash						+	H	\vdash		-	\vdash	-	-	\vdash	\vdash	\vdash	+	
24													\vdash						+	-					\vdash		\vdash	+	+	+	
25																			+									\vdash	t	+	
26																												Т	T	T	
27																															
28																															
29		L																	\perp									_			
30		_		_	_				_	_	L	_	_						1	-	_						1	_		1	
31		_	_		_	_	-		_	-	-	_							\vdash												
F _c		_	-	-	-	-			-	-	-	-			_			657 O. T. P. 141611	-												
P _B	_	Ē	-	L	-	_	_	-	-	-	-	-	-	_	_	-	-	SET Q4 TO Q7 HIGH	1												
L _B	_	_	-	_	-	_	_	-	-	ш	4	Н	ч	H	H	+	H	LOAD DATA AT NEXT UK	+												
P _A	_	-	_	L	_	_	_	_	_	-	-	-	-	-	-	-		SET Q. TO QS HIGH	1												
R _A	Ť			_							-						-	5-1 QF 10 Q5 1110H	1												
LA	_	_	-	-	-	-	-	-	-	н	Н	Н	H	Н	Н	н	H	LOAD DATA AT NEXT UK	1												
D3	_	_	-	-	-	-	~	-	-	-	-	-	-	-	_	-	-		1												
D2	-	_	-	-	-	-	-	_	-	-	_	-	-	-	-	-	-		1												
D1	-	-	-	-	-	-	-	-	_	-	-	-	-	-	-	-	-														
D0	-	-	-	-	-	-	-	-	_	-	-	-	-	-	_	-	-														
PII	1	5	4	3	2	9	8	7	6	19	18	17	16	15	14	13	12														
N A M E S		TRIG		RESET		ota	101	02	01																						

COMMENTS:
This one-shot will load data at the end of the count cycle. If TRIG pulse-width is longer than the count cycle, output B3 will go Low for one clock period and go High again for another count cycle. Outputs B2 and B0 stay Low and High respectively until TRIG goes High and count cycle is completed without interruption.

November 1986 460

PLD Programmable Retriggerable One-Shot


AN11



November 1986 461

PLD Programmable Retriggerable One-Shot

AN11



Signetics

AN14 Latches and Flip-Flops With PLS153

Application Note

Application Specific Products

DESCRIPTION

Using the simple AND, OR and INVERT logic functions of the PLS153, memory functions such as latches and edge-triggered flip-flops may be implemented with a relatively small part of the chip and without external wiring. In this application note, we will discuss the implementation of two R-S latches, a D-latch, an edge-triggered R-S flip-flop, and an edge-triggered D flip-flop.

INTRODUCTION TO PLS153

To implement this function, let's first take a look at the PLS153 logic diagram and its programming table as shown in Appendices A and B. On the left side of the logic diagram (Appendix A) are eight dedicated inputs, Io to I7, each of which has a true and a complement output. Each output is connected to the inputs of 32 AND functions (we will call them AND-terms from now on), the outputs of which are, in turn, connected to the inputs of ten OR functions. The output of each OR function is connected to one input of an Exclusive-OR function, which is in turn connected to a non-inverting output buffer. The function of the XOR is to control the output polarity. The output, in its virgin state, is noninverting, since one side of the XOR is connected to ground by the fuse X_n , where $n=0,\ 1,\ 3...9$. To have the output inverted, one needs only to blow fuse X_n open so that the X_n input is unconditionally High. The output buffers are all three-state buffers which may be enabled or disabled by their corresponding AND gates. The output buffers are disabled in their virgin state. All pins labeled "B" are bidirectional. Input buffers of the "B" pins are identical to those of the "I" pins.

The programming table shown in Appendix B emulates a truth table. All the inputs to the device are positioned on the left side, and all the outputs are on the right side. Each row in the table corresponds to an 18-input ANDterm with up to ten outputs. On the left side, or the input side of the table, each column represents an input. The 18 columns represent input buffers I₀ to I₇, B₀ to B₉. To distinguish between inputs and outputs of the bidirectional pin, B(I) is used for input and B(O) is used for outputs as shown in the programming table. On the right side of the table, each column represents an output circuit (B(O)0-9) which consists of an OR gate, an XOR, and a non-inverting three-state buffer. The output buffers are controlled by AND-terms Do to Do, the inputs of which may be connected to any number of the 18 inputs.

The polarity of the outputs is defined by the POLARITY entries which are on the upper right corner of the programming table.

To program the inputs to the AND-terms, an "H" will cause the fuse of the inverting input buffer to be blown, leaving the non-inverting buffer connected to the AND-term; an "L" will do the opposite. A "-" will cause both fuses to be blown, and therefore the programmed input is a "Don't care". A "O", the virgin state of the device, has both fuses intact, which causes the output of the AND-term to be unconditionally Low.

To program the outputs, a "." causes the fuse that connects the output of AND-term to the input of an OR to be blown and thus renders the output inactive. An "A" causes the fuse to remain intact and thus the output is active.

The output polarity of each output buffer may be programmed by entering an "H" or an "L" in the POLARITY section. An "L" causes the XOR to blow its grounding fuse and become inverted, whereas an "H" leaves the fuse intact and the output is non-inverted.


To AND several inputs, we put them in a row; to OR several inputs, we put them in different rows, as shown in illustrations in Appendix B.


AN14

SIMPLE R-S LATCH

A simple R-S latch may be formed by cross-coupling two NAND functions together as shown in Figure 1.

As an illustration, let's assign the input R to I_0 of the PLS153, input S to I_1 , output Q to B_0 , and output \overline{Q} to B_1 . As shown in Table 1, to form the NAND gates we need to program the POLARITY Low on B(O)0 and B(O)1. To unconditionally enable the output buffers, we "dash" out all inputs to D_0 and D_1 . As for the inputs, we put an ''H'' on I_0 , term-0 for the input R, non-inverted; another "H" on B(I)1, term-0 for the feedback from Q. In the same manner, we program I_1 , term-1 and $B(O)_0$ "H". The POLARITY, rows 0, 1, Do and D1, forms a "truth table" with which one can analyze his own or someone else's design. The program in Table 1 may be illustrated as shown in Figure 2.





AN14

Table 1. PLS153/153A Programming Table

СО	DE	N	0.				_		-														PC	LA	R	TY				
T			AUTO.	- TO - 10	-4.5	(91.63	0.000	AN	Jh		set out	TO A CO								H	L			0	L R	L		L	L	
TERM	-	150.00	1.00		despitation.				۲		35000	SUZ	B(1)		W. C.	20.00	-		H	ALTERNATION OF THE PARTY OF THE	-	_	B(0)		-	-		
M	7	6	5	4	3	2	1	0	9	8	7	6	5	4	3	2	1	0	REMARKS	9	8	7	6	5	4	3	2	1	0	REMARKS
0	-	-	-	-	-	-	-	Н	-	-	-	-	-	-	Ξ	-	Н	-		•			0	0	•				A	Q=/(R.Q)
1	-	-	-	-	-	-	Н	-	-	-	=	-	=	-	F	-	H	Н		•	•	•	•		•			A	•	Q=/(5.Q)
2													Г		_															
3										Г																				
4																														
5																										-	L	L	Ц	
6								L			_	L			_		L				L				L	L	L	L	Ц	
7									L	L	L	L	L	L	L	L	L				L				L	-	L	L	Ц	
8	L				L	L	L	L	L	L	<u> </u>	L	L		L		L				L	L			L	-	L	L	Ц	
9	L	L			L	L	L	L	L	L	<u> </u>		L		L	_	L			_	_	\vdash	_		_	i	1	L	Н	
10	_	_	_	-	i H	-	_	-	-	-	-	-	-	-	<u> </u>	-	-	H	ļ	-	-	H	_	_	-	i	-	-	Н	-
11	L	-	_	-	i H	-	_	-		-	H	_	-		<u> </u>	-	-			-	-	H	_	-	H	-	1	\vdash	Н	-
12	L	-	-	-	H	-	-	-	_		H	-	-		H	-	-	H		\vdash	-	-		-	-	-	-	-	Н	
13	L	L	L	1	<u> </u>	L	L	L	L	_	i	_	_		i	_	L	L		L	-	\vdash		L	_	i-	<u> </u>	-	Н	
14	\vdash	H	_	\vdash	H	H	-	-	H	L	H	H	\vdash	H	i	-	H	H		-	-	-	_	H	-	H	\vdash	-	Н	
15	\vdash	\vdash	-	\vdash	-	\vdash	-	\vdash	\vdash	\vdash	-	-	-	-	\vdash	-	\vdash	H	ļ	⊢	-	\vdash	-	_	H	\vdash	⊢	\vdash	Н	
16	⊢	\vdash	H	-	-	\vdash	-	-	\vdash	-	-	H	\vdash	-	-	-	-	H		-	H	-	_	_	-	+	-	-	Н	
17 18	\vdash		-	\vdash	-	\vdash	-	H	\vdash	\vdash	-	-	\vdash	-	\vdash	-	\vdash	Н	-	_	-	\vdash	_	H	-	+	-	\vdash	Н	
19	\vdash	-	\vdash	\vdash	-	\vdash	-	-	\vdash	-	\vdash	\vdash	\vdash	H	-	-	-	Н		\vdash	\vdash	\vdash	_	Н	-	+	-	\vdash	Н	-
20	\vdash	-	\vdash	-	-	\vdash	-	\vdash	\vdash	\vdash	\vdash	-	\vdash		\vdash	-	-	\vdash		Н	\vdash	\vdash	_	\vdash	-	\vdash	\vdash	\vdash	Н	
21	\vdash	-	H	\vdash	\vdash	\vdash	-	\vdash	H		-	-	\vdash		\vdash	-	\vdash	Н		\vdash	\vdash	\vdash		\vdash	-	-	-	-	Н	
22	H		\vdash	\vdash	H		\vdash		\vdash		H	-	\vdash	\vdash	-	-	-	Н				\vdash				-	\vdash		Н	
23	H	\vdash	\vdash	\vdash	-				H		H				-	-	-					Н			\vdash	!-	\vdash		Н	
24	Н		\vdash	\vdash	-				\vdash		Н				H					Н		\vdash				!-			Н	
25	Н	\vdash			H				Н						-		\vdash				\vdash	Н		П	\vdash	!-	\vdash		Н	
26	П			\vdash	-				Г						\vdash											!-			Н	
27									Г						-							-				-			П	
28															-											1		Г	П	
29																												Г	П	
30																														
31																							-		200000	_	-	-		
D9			L		_	L	L					_	L		_						I	T	T	T	ĭĬ	IT	īT	T	ī	
D8		L			_		L					L			<u> </u>	_											il	il	il	
D7	L	L			_		L		L		Ŀ	L	_		_	_		Ц					- 1				: 1		il	i
D6	\vdash	L	L		<u> </u>	_	_				<u> </u>	_	_		_	_	L			PERMIT	_	1	_		- 1	- 1	. 1			
D5	H	H	\vdash		-	-	-		H		\vdash	-	-	H	<u> </u>	-	-	H		_	-	1		_		- 1	- 1			
D4	H	H	\vdash	-	-	-	-		-		\vdash	-	-	H	-	_	-	H		Ι	I				_	- 1				
D3	H	H	-	\vdash	-	-	-	-	-	H	\vdash	-	-	-	-	-	-	H		Ī	l	1 1			Ī	-	- 1			
D2 D1	-	-	-	-	-	-	-	-	-	-	H	-	-	-	-	-	-	H		Ī	I				1	1	_			
DO	-	=	-	-	=	-	-	-	-	-	-	-	-	-	Ē	-	-	-		I	I					1	1	1		~
	8						2	1			17		15	14	12		11			10	10	17	16	15	14	12	12	111	0	
	°	-	0	3	4	3	-	+	13	10	1/	10	13	14	13	12		9		13	10	17	10	13	14	13	12	111	3	PLS153
KS																			,									_		in
AB																												10	8	
REMARKS																												B(0) (QA)	B(0)0 (Q0)	0
R							8	Q									6	o										90	90	
			\Box	L			L_											Ĺ								L	_	1		

TB00860S

AN14


ANOTHER SIMPLE R-S LATCH


Another way to implement a simple latch is shown in Figure 3, in which two NOR functions are cross-coupled to form a latch.


As with the previous example, we first define the input and output pins. For this example, we use l_2 for the R input, l_3 for the S input, B_2 for the Q output, and B_3 for the $\overline{\mathsf{Q}}$ output. We program B_2 and B_3 to have inverted outputs by programming POLARITY of B_2 and B_3 Low, as shown in Table 2. Terms 6 and 7 are ORed together by $\mathsf{B}(\mathsf{O})_2$, rows 6 and 7. In the same manner $\mathsf{B}(\mathsf{O})_3$ ORs Terms 8 and 9. The programmed table of this design may be represented as shown in Figure 4.

Since each AND-term of the PLS153 can accommodate up to 18 inputs (true or inverting inputs of eight from I_0 to I_7 and ten from B_0 to B_9), and each OR circuit can be connected to up to thirty-two AND-terms, we can add additional features such as those shown in Figure 5.

The programming of this design is left to the reader as an exercise.







AN14

Table 2. PLS153/153A Programming Table

СО	DE	N	0.																	F	_		PC)L/	RI		L		T.	
T			e committee	A SERVICE				A	ND			The same	Zaren (a	e u to	and the last			A 100	1	H	_			6	R	L	L	L	L	
ERM		CONTRACT OF THE PARTY OF THE PA	2.00				er a company	- Control of					B(1)	-		-0.00		1	Г				B(0)					
M	7	6	5	4	3	2	1	0	9	8	7	6	5	4	3	2	1	0	REMARKS	9	8	7	6		4	3	2	1	0	REMARKS
0	-	-		-	-	-	-	Н	-	-	Ξ	-	-				Н	-	R.Q	•	•	•	•	٠	•	•	•	•	A	Q=/(R·Q) Q=/(S·Q)
1	-	-	-	-	-	-	Н	-	-	-	-	-	-	-	_	-	-	Н	5-Q	•	•	•	•	•	•	•	•	Α	٠	Q=/(s.Q)
2		L	L		_		L	L	L	_	-	L	L	L	-	L	L	L		┖	L	-			L	L	L	L	L	
3	L			_	<u> </u>	_	_	L	L	\vdash	-	L	_	L	Ŀ	_		L		┡		Ŀ		_	H	H		_	H	
4	H	<u> </u>	_	-	i	-	-	-	┡	\vdash	H	-	-	-	<u>.</u>	_	L	_		⊢	-	H		-	H	<u> </u>		-	\vdash	
5	Н	-	-	-	-	1,1	-	-	\vdash	\vdash	-	\vdash	-	\vdash	\vdash	-	-	-	70		•	ŀ	•	•	•	-		-	•	Q=/(R+Q)
7	-	-	-	-	-	H -	-	-	-	-	=	-	-	-	H	-	-	-	R	:	•	÷	•	•	•	÷	A	•	-	Q=/(R+Q)
8	-	-	-	-	F	-	-	-	-	+	-	-	-	-	۳	-	-	-	Q	•	•	-	•	•	\vdash	A	•	•	•	Q=/(R+Q)
9	-	-	-	-	Н	-	-	-	-	-	Ε.	-	-	-	Ē	-	-	-	5		•	<u>.</u>	•	•	•	A	•	•	•	Q=/(Q+5)
10	\vdash	\vdash			-			\vdash	H		-	-	\vdash						-	1	-	H	-	Ė	H	٣				4-7(41-7
11					-		\vdash	\vdash	T	\vdash					-							-			Н				П	
12					-															Г					П				П	
13																														
14																														
15					-				L		-				_															
16	Ш				⊢	L		L	L		L				<u>_</u>		L	L		L					L				Ц	
17	\vdash			_	i	_	_	Ľ	L	\vdash	Ŀ		_		-	_	L			L		-	L		H		Щ	_	Ц	
18	H	_	_	-	\vdash	-	_	-	L	-	H		_		H	_	-	L				H			H	H	Н	_	H	
19 20	H	-	-	H	-	\vdash	-	-	┞	\vdash	-	H	_	H	\vdash	-	\vdash	-		\vdash		-	H		H	H	Н	_	Н	
21	Н	-			\vdash	-	-		\vdash	-	-		_		\vdash	-	-	-		\vdash	H	\vdash	Н	_	H	\vdash	Н	_	Н	
22	Н	\vdash	-	Н	-		\vdash		\vdash		\vdash		-	\vdash	\vdash	-	\vdash	\vdash		\vdash	H	\vdash	Н		Н	\vdash	\vdash	_	Н	
23	Н				-				H		-		-		-							Н	Н		Н	H	Н	_	Н	
24	Н				-						-														Н				Н	
25					_				Г		-									Г									П	
26									Г																				П	
27																														
28									L		_																			
29	Ц	L			<u> </u>				L		L																			
30	H	_			-	L	_		L		H	H	_		-							Н			_				Ц	
31	Н	_	H	H	-	-	_		H	H	-	H	_	H	-	_	H	_		L,		Ų	Ų	_	Ų	J		_	Ų	
D9 D8	\vdash		\vdash	\vdash	-		-	\vdash	\vdash	H	\vdash	\vdash	_	H	\vdash	_	-	H		ĭ		ıŢı	H			1	1		ıŢ	1
D6	H	Н	H	\vdash	_		-	\vdash	\vdash	H	-	\vdash		H	H	_	\vdash	H									1			
D6			Н	Н					H	H		H				-	Н						_	- 1	- 1	- 1 '		- 1		
D5	Н		Н					Н		Н		Н								1 ,				_		. 1 .	- 1	- 1		
D4																							_		Ц!					
D3																								_		!	!			
D2																					-	1 1					┙,	- 1		
D1	-	_		-	Ξ	-	-	-	-	-	=	-	-	-		-	-											_		
D0	-		-	-		-	-	-	-	-		-	-			-		-		_	_	_	_				-		_	က
PN	8	7	6	5	4	3	2	1	19	18	17	16	15	14	13	12	11	9		19	18	17	16	15	14	13	12	11	9	PLS153
S																														(0
AR																														07
REMARKS																										(Q1)	(Q)			1
R					es.	⋖	S	QL.							10	œ	le	G								B3 (8	82	80	nata.
																										w				

TB008705


AN14

D-LATCH

A simple D-latch can be constructed with an PLS153 as shown in Figure 6.


This circuit may be easily programmed into the PLS153 as shown in Table 3. The program may, in turn, be represented as shown in Figure 7.


This circuit may be expanded to have multiple D-latches using the same latch enable (LE).




R-S FLIP-FLOP

Two R-S latches may be combined to form a master-save flip-flop that is triggered at the rising-edge of the clock (or the falling-edge of the clock, if the designer so desires). Figure 8 shows a combination of two sets of cross-coupled NOR gates concatenated to form the flip-flop. The implementation of this circuit using PLS153 is as illustrated in Table 4 and Figure 9.







AN14

Table 3. PLS153/153A Programming Table

T	7 6				1000	1000	4.4		-																						
0 -			NEW YOR					III				-				10.00	CHILD				⊢	_	L				L	L	L	L	
0 -		_		1			AN	טע			0.000	B(1/			o Dist	_				\vdash	_			O B(-	
0 -		15			2	1	ī	6	Ω	7	6	5	') A	2	2	1	ΙΛ	DE.	84 /	RKS	6	R	7	6	5	$\frac{3}{4}$	3	2	1		REMARKS
1 -				-	-	-	1	-		-	-	-		-	-	Н		2.		inko	•	0	•	•	•	ö	•	•		A	/(R.Q)
	+-		-	F	=	н	<u>н</u> -	E		H	-		H		-	-	Н	5.			•	•	H	-		ď	•	•	A	•	/(s·Q)
4	+	Ŧ	╀	F	F	M	H	F	F	Ë			H			-	-	2.	W		H		Ě			H	Ĭ	×	A	Ě	/(2.M)
3	+	+	+	\vdash		\vdash	\vdash	\vdash		\vdash		Н	Н	Н	_	-		\vdash			\vdash	\vdash	\vdash	Н	Н	\vdash	\vdash	Н		Н	
4	+	+	+	-	\vdash	-	Н	\vdash		\vdash		\vdash	Н	Н	_	\vdash		\vdash			\vdash	\vdash	\vdash	Н	_	Н	-	Н		Н	
5	+	+	+	-	-	\vdash	Н	\vdash	\vdash	\vdash		Н	Н	Н	_	H		\vdash		-	\vdash	H	\vdash	Н	_	\dashv	H	\vdash		Н	
6 -		-	-	-	Н	-	-	-			-	-			-		-	R				•	•	•	•		•	Α	٠	•	}/(R+Q)
7 -	-	-	-	-	-	-	-	-	-	-	-	-		Н	_	-	-	Q				•		•	•		•	Α	٠	•)
8 -	-	_			-	-	-	-	-	-	-	-		-	Н	-	-	Q				•	•	•	•	6	A	•		•	}/(Q+5)
9 -				H	-	-	-	-	-	-	-				-		-	S				•	•	•	•	•	A	•	•	•	1/(4+3)
10	+		+	+	F	⊢	H	F	F	H								3			H		H			\dashv	^				<u> </u>
11 -	- 1	Н	+	+	-	-		-	-	Ŀ	-	-	H	-	_	-	-	LE	• T			•	-	•	•			•	•	•	}(LE . D+
12 -	- L		\rightarrow	-	-	-	-	-	-		-	-	н	-	_	-	-	LE			ŀ	•	-	•	•	슀	•	•	•	•	(LE.Q)
13	+	+	+	-	-	-	Ť	-		H	H	Н	4	Ĥ	_	Ē	-		- 4		Ė	-	Ĥ	Ť	_	Α	ŕ		_	Ĥ	,
14	+	+	+	-	-	\vdash	\vdash	\vdash		H		Н	H	H	_		\vdash	\vdash			\vdash	H	H	\vdash	-	\dashv	H	\dashv	-	Н	
15	+	+	+	-		\vdash	\vdash	\vdash		\vdash		Н	Н	H		\vdash	Н	\vdash			\vdash		Н	Н	_	\dashv	-	\dashv	-	Н	
16	+	+	+	-	+			\vdash		\vdash		Н	Н			\vdash	Н						Н	Н		-	-	\vdash		Н	
17	+	+	+	-			-	\vdash		Н	\vdash	Н	Н	Н			Н	\vdash			\vdash	Н	Н			-			-	Н	
18	+	t	+	-	-	\vdash		\vdash				Н	Н					\vdash		1						_				Н	
19	+	$^{+}$	+	-	+			Н		-		Н	Н		_	\vdash										-		\dashv	\neg	Н	
20	+	+	+	-	+			\vdash		\vdash		\vdash	Н			\vdash					\vdash	\vdash				-			\neg	Н	<u> </u>
21	+	†	+	 		1		\vdash					Н	Н		Н					\vdash	Н	Н								
22	+	†	+	-				\vdash				Н	Н													-				Н	
23	+	+	+	-	\vdash			Н		Н			Н			\vdash					\vdash		Н			-				Н	
24	\top	†	+	_								П	Н			Т										_				Н	
25	\top	†	+	_			Н						Н	П												_				Н	
26	+	1	+	<u> </u>	\vdash		Н						Н								Н					_				Н	
27	+	†	+	-	\vdash	\vdash		Н		Н	Н		Н													_	П			Н	
28	\top	1	†	!									۲													_				Н	
29																															
30		T																								_					
31		T																													
D9		Ι																				Y	Υ.	Y	4	1	4	4	4	Y	1
D8		I		1														-		-	_	_		- 1					- 1		
D7	I	I																-							- 1		- 1		- 1		
D6																		-		-				_	- (1.	- 1				
D5																					<u> </u>	_			_		li				
D4 -	: -	_	-	-	-	-	-	-	-		-			-	-	-	-				-	-			-	۱'	- 1	li			
D3 -				-	-	-	-	-	-			-		-	-		Ξ	-				_		-	- 1	-	۱,	1.			
D2 -				-	-	-	-	-			-	-	-	-	-	-	-	-				_	<u> </u>		-	<u> </u>		┛.	- 1 '		
D1 -	- -	-	-	-	-	-	-	-	-		-	-		-	-	-	Ξ				<u> </u>	-				<u>'</u>		_	۱ '		
D0 -	-	1-	-	-	-		-		_			-		-	-	-	-							_	_	_	_		-		က
	3 7	6	5	4	3	2	1	19	18	17	16	15	14	13	12	11	9				19	18	17	16	15	14	13	12	11	9	PLS153
S																															(0
R																															07
REMARKS																															7
R	U	2	1	8	œ	S	o.						0	10	C	, Car	74									B4	B 3	Bz	Š	98	
													9		J	. `	_									80	GC3	a.	2	A.	

AN14

Table 4. PLS153/153A Programming Table


СО	DE	N	0.			_	-								-	-	_						РО	LA	RI			_		
-			N.S.		19.0	20000	V	A	TE	an un	WE WA	OF THE				72.192	Special Control			L	L			Ĺ		L	L	L	L	
T ERM	┝		under State		Marian I		e constant	Al	ΝD		000		B(1\				e mineral		⊢	-			O B(_	-	_		
R	7	6	5	4	3	2	1	In	9	B	7	6	5	4	3	2	1	n	REMARKS	9	8	7	6	5	4	3	2	1	0	REMARKS
0	÷	-	-	-	-	Ĺ	-	Н	-	-	÷	-	-	-	-	-	-	-	CK.R	·	•		•	•	Ö	٠	•	•	A	}/(R.CK+BI)
1	F	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	Н	-	B ₁	•	•		•	•	•	-	•	•	A)
2	-	-	-	-	-	-	-	-	-	-	-	-	-	-	Ε	-	-	Н	Во	•	•		•	•	•	•	•	A	•	1/(5. CK + Bo)
3	-	-	-	-	-	L	Н	-	-	-	-	-	-	-	Ξ	-	-	-	CK.S	•	•	•	•	•	•	•	•	A	•)
4	Г								Г	Г																				
5	-	-	-	-	-	Н	-	-	-	-	-	-	-	-	Ξ	-	-	Н	CK. Bo	•	•	•	•	•	•	•	A	•	•	}/(Bo . CK+B3)
6	-	-	-	-	-	-	-	-	-	-	Ξ	-	-	-	Н	-	-	-	B ₃	•	•	•	•	•	•	•	Α	•	•	
7	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	Н	-	-	Bz	•	•	•	•	•	•	A	•	•	•	}/(B1 · CK+B2)
8	-	-	-	-	-	Н	-	-	-	-	-	-	-	-	-	-	Н	-	CK · B1	•	•	•	•	•	•	Α	•	•	•)
9																									1					
10									L								L												L	
11									L					L			L			L		L				_		L	L	
12																	L			L	L	_				_	L	L	L	
.13	L	L	L	L		L	L		L	L	L			Ц		L	L			L		-				Ŀ	L	L	L	
14	Ш		\vdash		_	L	_		L	L	L		_	L	Ŀ	_	L			L		i	L			<u> </u>	L	L	L	
15	Н	H	H	H	_	-	L		L		H	L	_	H	i	-	L			⊢	L	i	H		H	i–	_	_		
16	\vdash	H	L	H	_	-	L		L		H		-	H	H	-	L			L	L	H	L		H	<u> </u>	-	-	_	
17	\vdash	\vdash	\vdash	Н	-	-	\vdash	H	⊢	\vdash	\vdash	\vdash	-	Н	-	-	-	H		\vdash	H	-	\vdash	_	Н	\vdash	-	H	-	
18	Н	H	H	Н	-	-	H	H	H	-	\vdash	\vdash	-	H	-	-	H	H		\vdash	H	-	H	_	Н	\vdash	-	H	-	
19 20	Н	H	H	H	\vdash	H	-	H	\vdash	-	\vdash		-	Н	\vdash	-	-	H		\vdash	-	\vdash	H	_	Н	\vdash	-	\vdash	\vdash	<u> </u>
21	Н	Н	\vdash	Н	\vdash	H	\vdash	\vdash	\vdash		\vdash	-	-	Н	\vdash	-	\vdash			\vdash		\vdash	Н	_	Н	\vdash	\vdash	-	\vdash	
22	Н	Н	\vdash	Н	-	\vdash			\vdash		\vdash		\vdash	Н	\vdash	-	\vdash			\vdash	-	\vdash	Н	_	Н	\vdash	-	\vdash		
23	Н	H	Н	Н	-	H	-		\vdash	\vdash	-		\vdash	Н	-	-				\vdash		-	Н	_	H	-	-	\vdash	\vdash	
24	Н	Н	Н	Н	-	\vdash			H		-		-		-	-			-	\vdash		-	Н		Н	-				
25	Н	Н	Н			-			H		-		\vdash		H	\vdash				Н					H	\vdash	\vdash		-	<u> </u>
26	Н	Н	Н	Н		\vdash			H		H			Н	-		\vdash			Н		-				-				
27	Н								H		H				H					Н		-	Н			\vdash			\vdash	
28	П		П			-			Г		\vdash				-						\vdash					H				
29	Г		П			Г			Г														П			\vdash				
30		П							Г																			\vdash		
31									Г																					
D9																								T		1				
D8																						1					1			
D7																				_		귀			- 1		П			
D6									L											_	-					- 1	il		il	i
D5	Ц		Ц			L			L		_									-	_	1		_		.	il	1	il	
D4	Ц		Ц						L		_		_		_	L	L			i	_	<u> </u>			7		il	il	il	i
D3	-	-	-	-	-	-	-	-	Ŀ	-	Ŀ	-	-	-	Ŀ	-	-	-		i	i	i			_	_	1	il	il	i
D2	H	_	-	-	-	_	-	-	Ŀ	-	-	-	-	-	F	-	-	-		i	1			<u> </u>	_	_			il	
D1	-	-	-	-	-	_	-	-	Ŀ	-	-	-	-	-	-	-	-	-		i	1	i			_	_	_	_		
D0	$\overline{}$	-	-	_	-	-		1	10	40	17	16	- 15	1/	-	-		-		10	10	47	46	45	_	_	-	-	_	PLS153
PN	8	7	6	5	4	3	2	1	19	Ig	17	10	15	14	13	12	111	a		19	Ig	17	10	15	14	13	12	111	9	5
XS																														in
AB																														71
REMARKS															20	20										G	10			7
R						S S	w	a							=	Q = B2	60	89								Bang	B2 =	5	80	-
						Ľ	L.,	匚		L					G	10	(ar	427			L					QC7	W.	1401		


AN14

D FLIP-FLOP

An edge-triggered master-slave D flip-flop may be constructed with two D-latches in the manner shown in Figure 10.

An PLS153 may be programmed as shown in Figure 11 to implement the D flip-flop which is equivalent to the circuit shown in Table 5 in the PLS153 logic representation.





471

AN14

Table 5. PLS153/153A Programming Table

СО	DE	N	0.															_					РО							
T	parameter 1	er en	7/4000	45075			100	AB	TD	- A		un die		Naria	10000	13.00000		57200		L						L	L	L	L	
TERM	-	ar an		0.0000	i i	10.00/5		AI	AD.		1	No years	B(1\	Y-100	Services	025h	10 V		H				O B(-	
R	7	6	5	Δ	3	2	1	0	9	8	7	6	5	1	13	2	1	0	REMARKS	9	8	7	6			3	2	1	In	REMARKS
0	-	-	-	-	-	L	-	Н	-	-	Ė	-	-		-	-	-	CHEST	RICK	•			•		•	÷	•	•	A	
1	Ξ	-	-	-	-	-	-	-	-	-	-		-	-	<u> </u>	-	Н	A	Bi		•	•	•	٠	•		•	•	A	7(2 5/2 5/2)
2	-	-	-	-	-	-	-	-	-	-	-	-	-	-	+	-	-	Н	Bo	H		-				-		A	i i	
3	-	-	-	-	-	L	Н	-	-	-	-	-	-	-	<u> -</u>	-	-	-	S.EK	T		!				-		A	П	
4									r		-							Г		T						-			П	
5	-	-	-	-	-	Н	-	-	-	-	-	-	-	-	-	-	-	Н	CK . Bo		Г						Α			}/(Bo·CK+Q)
6	-	-	-	-	F	-	-	-	-	-	F	-	-	-	Н	-	-	-	Q	Г							A)
7	-	-	-	-	F	-	-	-	-	-	-	-	-	-	-	Н	-	-	B ₂							A				}/(B1 · CK+B2)
8	-	-	-	-	-	Н	-	-	F	-	-	-	-	-	-	-	Н	-	B1 · CK	П						Α)
9																						_				1				
10																														
11	-	-	-	L	H	-	-	-	-	-	-	-	-	-	<u> </u> -	-	-	-	CK . D						Α					(CK . D+CK.
12	-	-	-	H	-	-	-	-	-	-	-	-	-	Н	Ŀ	-	-	-	CK . B4						Α					(B4)
13	-	-	-	-	<u> </u> -	-	-	-	-	-	-	-	-	-	-	-	-	-								L				
14	Ŀ	-	-	H	-	-	-	-	Ŀ	-	Ŀ	-	-	H	-	-	-	-	CK.B4					Α						(CK. B4+CK.
15	Ŀ	-	-	L	-	-	-	-	-	-	-	-	Н	-	Ŀ	-	-	-	CK · Q	L	L	<u>. </u>	Ш	A		_			Ц	()
16	L	L	L	L	-	L	L	L	L	L	-				<u> </u>			L			L	_	Ш			<u>. </u>			Ш	
17	<u> </u>	L	_	_	Ŀ	-	L	1	L	\vdash	i	_	_		-	_	L	L		L		_	Ш			<u>. </u>	Ш	L	Н	
18	L	_	_	_	-	-	_	-	L	-	Ŀ	_	_		-	_	L			_			Ш			-		L	Н	
19	L	_	L	_	i	L	L	-	L	\vdash	i	_	_		i	_	_	_		\vdash	L	-	Ш			<u> </u>		L	Ш	
20	H	_	L	_	i -	-	-	-	L	\vdash	i	_	-		i	_	-	_		<u> </u>			\sqcup		Н	Ŀ	Щ	L	Н	
21	H	_	H	H	<u> </u>	-	-	\vdash	┡	\vdash	<u> </u>	-	-		-	-	\vdash	H		_			\vdash			<u> </u>	\vdash	_	Н	
22 23	Н	-	H	H	-	-	-	\vdash	⊢	\vdash	-	-	\vdash		-	\vdash	-	-	ļ	\vdash	-	-	H		H	<u> </u>	H	-	Н	
24	Н	-	H	H	-	\vdash	-	\vdash	H	\vdash	\vdash	\vdash	\vdash	H	-	-	\vdash	-		\vdash	-	-	\vdash		H	-	H	H	Н	
25	H	-		-	\vdash	\vdash	-	\vdash	H	\vdash	\vdash	-	-	H	\vdash	-	\vdash	\vdash	-	\vdash	\vdash	-	H	_	H	-	Н	H	Н	
26	H	-	\vdash	\vdash	-	-	-	\vdash	\vdash	\vdash	-		-	H	-	-	\vdash	-		\vdash	\vdash	\vdash	\vdash		\vdash	-	\vdash	-	Н	
27	Н		-	-	\vdash	\vdash	-	\vdash	H	\vdash	-			H	-		\vdash	\vdash	-	\vdash		\vdash	H	_	H	\vdash	Н	-	Н	
28	H			\vdash	\vdash	-	\vdash	\vdash	\vdash	\vdash	-		\vdash	H	-	-	\vdash	-		\vdash		-	H		H	-	\vdash	-	Н	-
29	Н				-			\vdash	H	\vdash	-			H	-	-				\vdash	\vdash	-	H	_	Н	\vdash	Н	_	Н	
30					-	-			H	+	-				-					\vdash		H	H	_	Н	H	Н	_	Н	
31					-				Г		-				-								H		Н	H	Н		Н	
D9																				7	Y	Y	Y	4	T	Y	4	4	Y	
D8																				-		- 1								l
D7											L											Цļ	. 1.		- 1			- 1	11	l I
D6																					-				- 1	- 1		- 1	1	ı I
D5	-	-	-	-	Ξ	-	-	-	E	-	-	-	-	-	-	-	-	-		1		1		ا لـ				- 1		1
D4	-	-	-	-	_	-	-	-	-	-	Ξ	-	-	-	-	-	-	-			<u> </u>	1		-					1	
D3		-	-	-		-	-	-	-	-	Ξ	_	-		Ξ	-	=	-			<u>' </u>		1 1	-	_					1
D2	-	-	_	-	-	-	-	-	-	-	_	Ξ	-	-			-			<u> </u>	<u>.</u> I	-		-	_	_				1
D1	-	_	-	-	-	-	-	-	Ŀ	-		-	-	-	Ξ	-	-	-			_			-		_		_		
D0	-			-		_	-	-	-	-			-	-		-	-				_			_	_			-		က
PN	8	7	6	5	4	3	2	1	19	18	17	16	15	14	13	12	11	9		19	18	17	16	15	14	13	12	11	9	2
S																														PLS153
REMARKS																														ינט
MA													(a)		83	Bz								Ø						
RE				CK	۵	CK CK	10	QL.					35	84	=	10	×	30						Bs	4	Вз	22	34	30	
				_		Ľ	41	-					60-7	(ALL	9	10	a)	ш						QC7	VO.	BD	G)	(27	B	


472

TB00830S

June 1988

AN14

APPENDIX A



AN14


Appendix B. PLS153/153A Programming Table

СО	DE	: N	0		-		-		-			-	-			-		-	-		-			Gilbert.	PC	1 4	RI	TY	gallens			
		. 14	Ο.																			Н	н							Н	Н	
T					-			A	ND				Hav'				100000	(B) CS (H	1		•••	0	R	_				
ERM								en en en en en en en en en en en en en e			Philippin .	di territoria	B	1)	200,700,000											B(0)					
M	7	6	5	4	3	2	1	0	9					4	3	2	1	0	RE	M	ARKS	9	8	7	6	5	4	3	2	1	0	REMARKS
0	H	H	Н	Н	Ξ	-	-	-	Ŀ	E	Ξ	E	E	-	Ξ	E	-	-	A.	8.	C.D	A	•	•	•	A	•	•	•	•	•	{ X = A . B . C . D
1		L	L	L	L	L	L	L	L	L	L	L	L	L	-	L	L	L	L			L	\vdash	L	L		L	L	L	L	Ц	(T =/(A.B.C.D)
2	L	L	L	L	-	L	-	L	L	L	Ŀ	1	L	L	Ŀ	\vdash	L	L	<u> </u>			L	\vdash	i	H	_	H	Ŀ	_	-	Н	
3	H	-	Ļ	Ļ	H	-	-	\vdash	-	-	i	+	-	-	i	\vdash	-	-	Ļ	_		L	-		H	_	H	\vdash	-	-	Н	(u = = = =
5	۴	L	L	L	F	F	-	-	F	-	F	-	F	-	F	-	-	-	A.	8.	<u>c.D</u>	ŀ	A	ŀ	•	•	A	·	•	•	ŀ	$\begin{cases} Y = \overline{A} \cdot \overline{B} \cdot \overline{C} \cdot \overline{D} \\ U = /(\overline{A} \cdot \overline{B} \cdot \overline{C} \cdot \overline{D}) \end{cases}$
6	H	\vdash	\vdash	\vdash	\vdash	\vdash		\vdash	┝	+	+	\vdash	\vdash	+	-	\vdash	┝	\vdash	\vdash			⊢	\vdash	\vdash	\vdash	_	Н	\vdash	-	\vdash	Н	(U=/(A+B+C+D)
7	H		H	-	-	+	-	\vdash	H	\vdash	+	\vdash	\vdash	\vdash	-	\vdash	\vdash	\vdash	H			H	-	-	H	_	H	H	-	\vdash	Н	
8	H	H	\vdash	\vdash	-	+	\vdash	\vdash	H	+	۲	+	\vdash	\vdash	<u> </u>	\vdash	\vdash		H		-	H	\vdash	H	Н	\vdash	Н	H		H	Н	
9	-	Н	L	-	Ŀ	-	-	-	1=	-	-	-	-	-	Ŀ	-	-	\vdash	8.	3			•	A	•	•	•	A			•	\ Z=(B.C+B.D1
10	-	Н	-	L	-	-	-	-	F	-	E	-	-	-	-	-	-	-	B			•	•	A	•	•	•	Α	•	•	•	(ē.D)
11	-	-	L	L	Ξ	-	-	-	F	-	-	-	-	-	-	-	-	-	ē.			•	•	A	•	•	•	A	•	•	•	V=/(B.C+8.D
12																																+ E.D)
13									L								L															
14	L			L	_	L	L	L	L	L	-	L	L	L	L	L	L		_			L						_	L		Ц	
15	H	L	-	L	H	\vdash	-	-	┡	┞	i	L	L	L	L	-	\vdash	L	<u> </u>			L	-	H		_		H	H		Н	
16	H	H	H	-	H	-	\vdash	\vdash	H	\vdash	i	\vdash	-	H	H	-	-	H	<u> </u>			H	-	-	Н	_	H	-	H	_	Н	
18	H	-	\vdash	\vdash	\vdash	\vdash	\vdash	-	H	\vdash	-	-	\vdash	H	-	┝	\vdash	H	┝			H	H	\vdash	Н	_	Н	\vdash	H	\vdash	Н	
19	Н		\vdash	\vdash	-	\vdash	\vdash	\vdash	┝	\vdash	-	-		H	-	\vdash	+		\vdash	-		H	\vdash	\vdash	Н		Н	\vdash	-	-	Н	
20	H	\vdash	\vdash	\vdash	H	\vdash	\vdash	\vdash	H	\vdash	-	-	\vdash		-	-	+	\vdash	\vdash			H	\vdash	\vdash	Н		Н	\vdash	H	-	Н	
21	Н			\vdash	-	\vdash	\vdash	H	H	\vdash	<u> </u>	1			H		\vdash		\vdash	-		H	\vdash	Н	Н		Н	Н	Н		Н	
22					-	\vdash	Т		Г	\vdash	 					T						T		Н							Н	
23																						Г									П	
24																																
25																							17.7									
26	L	L	L	L	_	L			L	L	-		L		_	L	L															
27	L	L	_	L	-	L	L	L	L	L	-	L	L		-	L	L	L	_			L			Ц			_			Ц	
28	L	-	-	H	-	-	L	L	L	-	i	-	_		H	L	-	H	_			L		\vdash			H	\vdash	L		Н	
29 30	H	H	H	H	H	\vdash	-	-	H	\vdash	i-	-	-	-	i-	-	-	H	<u> </u>	-		H	H	H	Н		H	H	_	L	Н	
31	\vdash	H	\vdash	\vdash	-	\vdash	\vdash	\vdash	H	┝	-	\vdash	-	H	\vdash	-	-	H	\vdash			\vdash		\vdash	Н	-	Н	\vdash		H	Н	
D9	-	-	-	-	Ŀ	+	-	-	1	-	-	-	-	-	-	-	-	-				7	-	Y	Y	Y	Y	Y	Y	4	V	
D8	-	-	-	-	-	-	-	-	E	-	Ē	-	-	-	E	-	-	-				_									1	
D7	-	-	-	-	-	-	-	-	-	-	Ē	-	-	-	Ē	-	-	-	_			_	_		1	- 1						
D6											-							П	_			_	-		_	- 1	1.					
D 5		-	-	-	-	-	-	-	E	-	-	-	Ξ	-	Ξ	-	-	Ξ	—		-		<u>. </u>			┙.	Т,					1
D4			=	-	=	-	-	-	E	-	Ξ	-	-	Ξ	Ξ	-	-	-	-		-	-	1			_	-					-
D3	Ξ	-	-		=	-	-	-	E	-	Ξ	-	-	Ξ	Ξ	-	Ξ	Ξ	—			-	<u>-</u>		-	-	-		- 1		Ш	
D2	Н				_	-			L		<u> </u>		L	L		_		Ц	2	-		-	<u>'</u>		-	-	-	_	_		П	
D1 D0	Н	-	-		-	-	-	H	H	-	-	-	-	H	-	-	-	Н				_	_			i		_	_	_		
PN	0	7	6	E	4	2	2	4	10	10	17	10	15	14	12	10	44	0				10	10	17	16	15	14	_	_	_	_	(2)
	0	-	0	5	4	3	4	+	19	10	11/	10	15	14	13	12	111	a			-	19	18	17	10	10	14	13	12	Ш	9	43
REMARKS																																PLS153
AR																																
M																																<u>a</u>
CC	Y	60	O	a					×	>	N		٢	2	>							×	>	2		-	2	>				
	\Box			_				_	_	_						_	_															

TB00820S

AN14

APPENDIX C



Signetics

AN15 PLS159 Primer

Application Note

Application Specific Products

INTRODUCTION

The PLS159 is a field programmable logic sequencer which consists of four dedicated inputs, four bidirectional I/O's, eight flip-flops, thirty two 16-input AND gates, twenty 32-input OR gates, and a complement array. Each flip-flop has a bidirectional I/O and may be individually programmed as J-K or D flip-flop, or switch between the two types dynamically. The flip-flops will accept data from the internal logic array or from the bidirectional I/O, or they may be set or reset asynchronously from the AND array. The output polarity of the four bidirection is controlled by the AND array. Figure 1 is the logic diagram of PLS159.

PROGRAMMING THE PLS159

The programming table is shown in Table 1 where there is a place for everything that is

shown in Figure 1. The program table is basically divided into two main sections. The left hand side of the table, section A, represents the input side of the AND gates, while the right hand side, section B, represents the OR gates sections which includes the flipflops and the combinatorial outputs B(0) to B(3). The flip-flops modes are defined in section C and the output polarities of the combinatorial outputs are defined in section E. The programming symbols are detailed in Figure 2.

As shown in Table 1, the programming table is very similar to a truth table. Each column in section A represents an input to the 32 AND gates, and each row represents an AND gate connecting to 17 inputs. Columns I_0 to I_3 represent the 4 dedicated inputs, I_0 to I_3 . Columns B(I) $_0$ to B(I) $_3$ represent the inputs of the 4 bidirectional I/O, I_3 to I_3 . Columns

 $Q(P)_0$ to $Q(P)_7$ represent the feedback, F_0 to F_7 , from the flip-flops (the present state). Column "C" represents the complement array.

As shown in Figure 1, the outputs of the AND gates are connected to an array of OR gates which, in turn, are connected to either flipflops or output circuits. Columns $Q(N)_0$ to $Q(N)_7$ represent the next state which the flipflops will be in. Columns $B(O)_0$ to $B(O)_3$ represent the combinatorial outputs B_0 to B_3 .

Each row represents an AND gate with 17 inputs each of which may be true and/or complement and is, therefore, a perfect decoder. Referring to the programming symbols in Figure 2, to implement the equation

all one has to do is to enter one line as shown in Table 2, term-0.






Table 1. FPLS Program Table




The FPLS can be programmed by means of Logic Programming equipment.

With Logic programming, the AND/OR-EX-OR input connections necessary to implement the desired logic function are coded directly from the State Diagram using the Program Tables on the following pages.


In these Tables, the logic state or action of all I/O, control, and state variables is assigned a symbol which results in the proper fusing pattern of corresponding links defined as follows:




"AND" ARRAY - (I), (B), (Qp)



"COMPLEMENT" ARRAY - (C)




"COMPLEMENT" ARRAY (cont.)



"OR" ARRAY - (QN = D-Type)

Figure 2

479 June 1988



"OE" ARRAY - (E)

NOTES:

- 1. This is the initial unprogrammed state of all link pairs. It is normally associated with all unused (inactive) AND gates.
- 2. Any gate (T, F_C, L, P, R, D)_n will be unconditionally inhibited if any one of the I, B, or Q link pairs is left intact.
- 3. To prevent oscillations, this state is not allowed for C link pairs coupled to active gates T_{n} , F_{C} .
- 4. $E_n = 0$ and $E_n = \bullet$ are logically equivalent states, since both cause F_n outputs to be unconditionally enabled.
- 5. These states are not allowed for control gates (L, P, R, D)_n due to their lack of "OR" array links.

Figure 2 (continued)

Table 2. FPLS Program Table

CC	DE	NC).							H		F	FN	OE	E					-	E	В	_	-	E	Α	-	H	H			
T			-	-	-	Managana		-	NE)	_				-		_			-	man order	-	_		(C	R)		rr	64	11	+	
T E R M	С		-	1		L		(1)			-			P)	persona			REN	ARKS					(N)					B(REMARKS
	_					3	2			7	6		4				0	_		7		5	4	3		1						
0	-	H	H	H	H	1-	-	-	-	-	_	-	-	-	_	_	_	A*B	*C*D	-	-	-	_	上	-	_	-		•	•	A	2=A*B*C*D
2	-	1	Н	1	-	+	-	-	-	H		-	-				_	/A*	B#/C	-	-		H	+	-					Δ		Y= /A* B*/C
3	-	-	1	-	-	F	-	-	-	F	F			F			Ē	1112	DEIC	F				F			F	Н	1		Ť	12/11/0 2/0
4	_	=	=	-	-	-	-	_	-	-	-	-	_	-	_	-	_	410	,	-	-	-	-	-	-	-	-	•	A			¥= [
5																																
6	0						0	0	-	-	_	$\overline{}$			0	0	0			0	0	0	0	0			0	A	A	A		CONDITION
7	-	-	-	0	-	-		-	-	-	-	-	-	-	=	_	_	.0		F	=	-	=	=	-	-	_	А	•		•	W=0
9	-	Н	-	-	-	-	-	-	-	-	-	-	-	-	-	-	_	A *	/R	-	-	-		+	-	-		A	-			W=A*/B
10	-	-	-	H	_	-	-	-	-	-	-	-	_	-		_	-	C*		-	_	_		-	-	-		A				W=C*/D
11				1																												
12																																
13																				-				L					_			
14 15	-	-	-	-	-	-	-	-	-	-	-	-	-	-	_	_	_	-		-	-			-		\vdash	\vdash	H	-	-	\dashv	
16	-	-	-	+	-	\vdash	-	-	-	-	-	-	-	\vdash	-		-	-		+	-	-		-	-	\vdash	\vdash	H	-	-	\dashv	
17	-	1		+		\vdash			-					\vdash						+				\vdash	\vdash		H	Н	1	-	\dashv	
18						\vdash								Г																		
19																																
20	_	L	_			L	-		1	L					_		L			L	_			L				Ц	_		_	
21 22	-	\vdash	-	-	-	\vdash	-	-	-	-	-		-	H	-	-	-	-		\vdash	-		Н	\vdash	-	Н	Н	Н	-	-	\dashv	
22		\vdash		-	-	\vdash	\vdash	\vdash	-	\vdash				\vdash	-			-		\vdash	-		Н	\vdash		Н	Н	Н	-		\dashv	
24		\vdash		\vdash		\vdash														\vdash				\vdash				Н	1			
25																																
26																																
27	-	-	_	-	-	-	-	_	-	L	-	-	-	-	_		-	-	-	\vdash	-	-		┞	-		Н	H	-	-	-	
28 29	-	\vdash	-	-	\vdash	\vdash	-		-	\vdash	-		-	\vdash	\vdash	-	H	-		\vdash	-	-	-	\vdash	-		Н	Н	-	\dashv	\dashv	
30	-			\vdash											-					1				1			Н	\vdash	-		\dashv	
31		Г																														
FC																												Y	T	Y	Y	
PB	-	-		-	-		-	_	-	_			-	-	-	-	-			l	ļ		1		ı			H	1	1	1	
RB LB	-	-	-	-		-	\vdash	-	-	-	-	-		\vdash	-	-					I	1	1		1				- 1		- (
PA		1	-	+			\vdash		-	-												1	I	1	1			. 1 .	- 1		1	
RA																							1		1				- 1	- 1		
LA																		Į							1				1		-1	
D3	_	-		-		_			_	_				_				}					1	1	I	1		7				
D2 D1	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-						ı	Ī	1							
D0	-	-	-	-	+	-	-	-	-	-	-	-		-			-			I	1	1	1	1	1				-	_	ַו [တ
P	N	5	4	3	2	9	8	7	6	19	18	17	16	15	14	13	12		************	19	18	17	16	15	14	13	12	9	8	7	6	N
200	_			C																								w		Υ		PLS159

Notice that only I_0 to I_3 on the left hand side and $B(O)_4$ on the right hand side have entries to implement the equation. All unused columns are dashed out or dotted out.

To implement the equation

$$Y = /A * B * /C,$$

enter one line as shown in Table 2, term-2 where the entry "H" represents the noninverting input buffer while the entry "L" represents the inverting buffer. To have the AND gate to be unconditionally "High", dash out all the inputs of that particular AND gate as shown in Table 2, term-4. The virgin condition of the device, as shipped from the factory, has all connections intact, which means that the inverting and the non-inverting buffers of the same inputs are connected together. Such connection will cause the AND gate to be unconditionally "Low" as shown in Table 2, terms 6 and 7. The unconditional High and Low states are normally useful only internally and seldom brought out to the output pins.

To implement the equation

$$W = A * /B + C * /D,$$

enter one line for A * /B and another line for C * /D as shown in Table 2, terms 9 and 10. Use one line to AND something together; use different lines to OR something together — one line per item to be OR'ed.

All the pins which are labelled B's are bidirectional I/O pins. Their input buffers are represented by the B(I) columns on the left hand side of the programming table. An "H" entry represents the non-inverting buffer and an "L" entry represents the inverting buffer. Their output buffers are represented by the B(O) columns on the right hand side of the table. An "A" entry means that the output is active (connected to the AND gates); a "."

entry means that the output is inactive (not connected). The outputs may be programmed to be inverting or noninverting. The polarity of each output is determined by its exclusive OR gate (Figure 1 and Figure 2). To have a non-inverting output, enter an "H" in the section labelled "POLARITY" (Table 1, Section E). To have an inverting output, enter an "L". For example, Table 3, terms—0 and—2 implement the equation

$$Z = /(A * B)$$
 and $Y = A * B$

respectively. The above two equations may also be implement by term-4 which uses the same AND gate to drive two OR gates.

Besides being able to have programmable Active-High or Active-Low output, the programmable output polarity feature also low output, the programmable output polarity feature also allows the user to minimize his AND term utilization by converting his logic equation into other forms such as conversion by De Morgan Theorem.

For example, the equation

$$X = A + B + C + D$$

takes four AND terms to implement as shown in Table 3, terms 6 to 9. By using De Morgan Theorem, the same equation is changed to

$$/W = /A * /B * /C * /D$$

The result is as shown in term 11-a saving of three AND terms. The output buffers are disabled in their virgin states so that they all behave as inputs. The buffers are enabled or disabled by their corresponding Control AND terms D_0 to D_3 (see Figure 1). The Control AND terms are represented in the programming table on the last four rows on the left hand side. Dashing out all the inputs will

cause the output buffer to be unconditionally enabled, whereas a "O" (zero) will cause the buffer to be unconditionally disabled. The buffers may also be controlled by a logical condition, e.g. A * /B * /C, etc.


There are eight flip-flops on the chip each of which may be programmed as a J/K or a D flip-flop, or they may be programmed to switch dynamically. As shown in Figure 1, each flip-flop is a J/K to begin with. A tri-state inverter is connected in between the J and K inputs of each flip-flop, which when enabled by the AND gate F_C, will cause the flip-flop to function as a D flip-flop. The inverters are enabled by FC through fuses Mo to M7. A "." in the F/F Mode entry of the programming table means that particular fuse is to be disconnected and that particular flip-flop is to be J/K. An "A" entry will leave the M fuses intact, which allow the flip-flop to be D or J/K as controlled by the output of FC (see Figure 2, "OR" ARRAY - (MODE)). The inputs to the flip-flops are represented by the programming table as the next state, Q(N)0 to 7 since their inputs are from the OR array. The outputs of these registers are connected to their respective tri-state inverting output buffers, four of which are controlled by EA and the other four by EB. A "." in EA will enable outputs F₀ to F₃, whereas a "-" will disable them. An "A" will allow the output buffers to be controlled by /OE, pin 11. Table 4, terms 0, 1 and 3 represent the following equations

$$Q_0: J = A * C + /B * /E$$
 eq. 1

$$Q_0: K = A * /C$$
 eq. 2

Notice that the J input in equation 1 is represented by the "H" entry in terms-0 and 1, column $Q(N)_0$ while the K input in equation 2 is represented by the "L" entry in term-3, column $Q(N)_0$. An undefined input, J or K, is considered "Low".

Table 3. FPLS Program Table



PLS159 Primer

AN15

Table 4. FPLS Program Table

CC	DE	NO).									F	F N	10[ÞΕ					Е	В			E	Α		P	OL/	ARI	TY	
										_						A	0			-	-		L								
Ţ	L	_				_			ANI)									L	_		_			OR)	_				
T E R	С	1		1	To	1		(1)	ΤΛ	7	6	E		P)	2	14	Ιo	REMARKS	1	T e	T E	Q	(N)	12	1	0	1-	B	(0)	10	REMARKS
0	-			H		13	-		-	ť	-	-	-	-	-			A*C	Ľ	-	_	-		-	Ė		۲	-	i.	۲	\J=A*C
1	-	1:	1	-	L	-	-	-	-	+	-	-	-	-	-	-	-	/8*/E	-	-	+	-		-	-			+		\vdash	1 + /8 * /E
2		\vdash	F	1	-	1	\vdash	1	+	†		\vdash		\vdash			\vdash	70272	\vdash	+	\vdash	\vdash	t	+	\vdash	1	t	†		\vdash	
3	-	Н	-	L	-	1=	-	-	-	-	-	-	-	-	-	-	-	A*/C	-	-	-	-	1-	-	-	· L	T				K=A*/C
4		\vdash							T			1							Г				T		T		T				
5	-	L	L	L	-	-	-	-	-	-	-	-	-	-	-	-	F	/A*/B*/C		0			0		Α						D=/A*/B*/C
6	_	Ŀ	_	-	H	Ŀ	-	-	I-	I-	-	_	-	-	-	-	-	E	0	0		0			A		L			L	+E
7		L	L	L		L			1	L									L		L		L	L	L		L	L		L	,
8	-	1	L	+	-	1-	-	-	-	1-	-	-	-	-	-	-	+	/A*/B*/C	-	=	1=	=	1-	1	H		1	+	-	1	D=/A*/B*/C
9	-	-	-	-	H	1-	1-	-	-	1-	-	-	-	-	-	-	-	E	1-	-	1-	=	1-	-	+	1-	1	-	-	-	(+E
10	-	+	-	+	+	1	-	+	+	\vdash	-	-	-	-	-	-	+	-	\vdash	1	0	-	+	+	+	+	+	+	-	-	-
11 12	-	1	=	+	+	1	=	-	=	+	-	- H	-	-	E	1	-	-	1	0	_	1-	+	+	+	+	+	+	-	+	T=1
13	=	E	-	-	-	1	E	1	-	E	_	H	-	-	=	-	+	-	0		-	+	1	+	E	+	+	+	+	+	$T=Q_5$
14	-	F	F	+	+	F	-	F	F	F	11	1.1	-	F	F	F	1	 	۲	-	-	+	F	+	+	+	+	+	+	+	T=Q5*Q6
15		T		-		1	1		1	1	-					1			1	+	1	+	+	+	1	+	\dagger	+		\vdash	
16		Τ		T		T	T	T		T				Г		T	\vdash			T		T	T	\top			T	T			
17																										T					
18										L													L	L		L	L				
19		L							L	L						L			L	L			L			1	L				1
20	-	L	_	1	1	\vdash	-	\vdash	4	\perp	-	-	_	L	_	\vdash	-		\vdash	1	-	1	1	+	+	\perp	╀	\perp	-	-	1
21	-	\vdash	-	\vdash	\vdash	\vdash	+	+	\vdash	╀	-	-	-	\vdash	-	-	+	-	\vdash	+	-	+	╀	+	\vdash	+	╀	\vdash	\vdash	\vdash	-
22 23	-	⊢	-	╁	\vdash	\vdash	\vdash	+	+	╁	-	\vdash	-	\vdash	-	╁	+		\vdash	+	+	+	+	+	+	+	╁	+	\vdash	+	-
24	-	╁	\vdash	+	+	╁	+	+	+	+	\vdash	\vdash		\vdash	-	+	\vdash	-	\vdash	+	+	+	+	+	+	+	+	+	+	+	+
25	-	1	-	+	+	\vdash	+	+	+	+	+	\vdash		\vdash	\vdash	+	+	<u> </u>		+	+	+	†	+	+	+	$^{+}$	+	+	+	
26		T		1	\vdash	\vdash	T		T	T	\vdash					\vdash			\vdash	T	T	t	t	†	t	†	t	T	T	†	
27										T											T		T	T	T		T	T	T		
28										L											I		L				I				
29		L			L	L				L		L		L	L	L			L	L		L	L	1	L	\perp	L	1		L	
30	-	-	-	-	-	-	1	+	-	1	-	-	_	-	-	-		-	1	1	-	+	\perp	+	1	+	+	+	-	-	
31	-	1	-	-	-	-	-		-	1	-	-	_	_	-	-	-	-	L				L				L	L			
FC PB	-	F	-	+	-	F	-	+	+	+	-	-	-	-	-	-	-	N		-	T			-	T	1			- 1	- 1	1
RB	\vdash	+	-	+	+	-	-	+	+	+	-	-			-	+				1		1	1			1	1	- 1	- 1	- 1	1
LB		1		+	+		1	+	†	+						\vdash	†	W .		1	1	1	1	1		1		.	.	1	
PA				İ	İ			I	I	I								1					1			1					;
RA																								<u>'</u>	1	i			. 1		,
LA																		Į.						i	ŀ	i	1	. 1	1	i	1.
D3	_	1	-	-	-	1	1	-	-	1	-	_		_	_	1	-		L	ı	1	1	1	ī	1	Т	\neg	- 1			1
D2	-	-	-	+	-	-	-	-	+	+	-	-	-	\vdash		-	+	{	ı	ŀ	1	1	T	T	T	T	T	Т	1	1	1
D1 D0		-		+	+	\vdash	+	+	\vdash	+	-	-			\vdash	-	+	1 1	I	1	1	1 .	1	ı	1	Τ	1	1	T		၈
P	_	5	4	3	2	0	8	7	6	19	18	17	16	15	14	13	12		10	115	17	16	115	114	11	3 12	0	8	7	6	2
		Ť	Ť	1	-	Ť	Ť	1	-	1.3	1.3	-				1	1.2		1	1.0	1	1	1	+	Ť	1.4	+	+	ŕ	Ť	15
DEMANDE	HEMARK	A	В	C	D																										PLS159

A D flip-flop may be implemented by first entering an "A" in F/F MODE. Then enter "0" in the row F_C , which will unconditionally enable the tri-state inverter between the J and K inputs. The following logic equation may be implemented as shown in Table 4, term 5

$$Q_1: D = /A * /B * /C + E.$$

Notice that the entries in term 5, columns Q(N)_{0 to 7} are "A" and "." instead of "H" and "L" as in the case of J/K flip-flops. The entry "A" will cause the fuse connecting to the "K" input to be disconnected and the "J" fuse to be intact. Whereas the entry "." will cause both fuses to be disconnected. This feature enables the user to quickly recognize the mode in which the flip-flops are operating without having to go through the control terms. Some commercially available device programmers in the market may not have the software capability to implement this feature, in which case an "H" and a "-" may be used in place of "A" and "." respectively as shown in Table 4, terms 8 and 9.


Of course, the term $F_{\mathbb{C}}$ may have inputs instead of zeros and dashes, in which case the flip-flop modes are controlled dynamically.

When both the J and K inputs are ''1's'', the flip-flop will toggle. A simple 3-bit counter may be implemented using only AND terms as shown in Table 4 terms 11, 12 and 13. The logic equations for the three flip-flops are as the following:

$$\begin{array}{lll} Q_5\colon T=1; & (Q_5 \text{ toggles unconditionally}) \\ Q_6\colon T=Q_5; & (Q_6 \text{ toggles when } Q_5=1) \\ Q_7\colon T=Q_5\,^*Q_6; & (Q_7 \text{ toggles when } Q_5\ ^* \\ & Q_6=1) \end{array}$$

The above equations represent an octal upcounter. However, since the outputs of the flip-flops are inverted, the counting sequence of the outputs is that of a down-counter.

The flip-flops may be asynchronously set and reset by the Control AND terms PA/PB and



RA/RB respectively. As shown in Figure 1, PA and RA controls flip-flops F_0 to F_3 , while PB and RB control F_4 to F_7 .

In order to save the number of input pins, the eight flip-flops may be synchronously loaded directly from their own output pins. To use this feature, EA and/or EB must be programmed "A" or "-" so that the output buffers may be disabled before loading. As shown in Figure 1, every flip-flop has an OR/ NOR gate the input of which is directly connected to the output pin and the outputs of the OR/NOR are connected to the K and J inputs respectively. This OR/NOR gate inverts the input and feeds it to the flip-flop in a "wire-OR" fashion. Therefore, when loading data directly into the flip-flops from the output pins, caution must be exercised to insure that the inputs from the OR array does not interfere with the data being loaded. For example, if the data being loaded is a "1" on the output

pin, the J input will be a "0" and the K input will be a "1". If, at the same time, a "1" is present at the J-input from the OR array, the flip-flop will see "1's" in both J and K inputs. It will toggle as a result. The OR/NOR gates are enabled by the Control AND terms LA and LB. LA controls flip-flops F_0 to F_3 and LB controls F_4 to F_7 .

All Control AND terms function and are programmed in the same manner as the other AND terms. The only difference is that the Control AND terms are not connected to the OR array.

The outputs of the flip-flops may be fed back into the AND array as the present state, Q(P). The output of the AND array into the OR array and the inputs to the flip-flops is the next state, Q(N). As an example, Figure 3 is a state machine implemented in a PLS159 as shown in Table 5, terms 0 to 6.

Table 5. FPLS Program Table

CC	DE	NC).										F N							E	В				EΑ			PC	LA	RI	TY	A
										0						•					0							H	Η]	Н	Н	
Ţ								-	NE)															(OF	٦)			•			
T E R	С	L		1	_	L	В	(1)	_		_	_	Q	(P)	_		_	REMARKS	L	_	_	Q	(N)	_		4	_	B(0)	_	REMARKS
	-				0	3	_	1									0			6												
0	-	H			-	F	-	-	-			L		L					<u>_</u>	L	1	- -	- 4	- 6	- 1	-	H	•	•	•		
2	-	-	-	H	L	F	-	-	-	L			Ĺ					-	1	L	11	- H	1.	- 1	-	4	+	•	A			
3	-	F	-	+	-	F	-	-	F	14	<u></u>	L	H	L	1	L	H	-	1	-	H	+	+	+	+	+	-	4	-	-	•	-
4		+	1	+		\vdash	+	+	-	L	L	L	L	L	L	L	L	 	1	L	1	1	1	+,	_	H	_			A		
5	=	-	=	Hi	=	E	=	=	=	L	-	-	L	-	-	-	-		_	L	-	-	-	-	-		-	\rightarrow	\rightarrow			-
6	-	-		H		-	+	+	-	E	L	L	L		L			-	L		L								A			
7		\vdash		П	-	+	+	+	+	۲	-	-	-	-	-	П	-		F	-	۲	+	+	+	+	+	Ҡ	-	1	_	Ť	
8			-	+	+	1	\vdash	+	+	+	\vdash			\vdash	\vdash	\vdash	\vdash		\vdash	-	+	+	$^{+}$	+	+	+	1	\forall	\forall			
9				†	+	\vdash	t	\vdash	+	\vdash				\vdash	\vdash				\vdash		T	+	+	†	†	\forall	1		7			
10				1	\vdash	1															T	\dagger	†	+	+	+	1		7			
11				\dagger		1															T	1	T	+	+	1	7					
12				T													T						T	\dagger	1	1						
13				Γ						Γ												T	T	T			7					1
14																						I	I	I								
15																						I	I	I	I	I	I					
16						L																	I									
17		L		L						L	L			L		L			L			L	\perp	1	1	_	_					
18		L		1	L	L	1	-	-	1	L	_		L	_	1	_		L	L	L	\perp	\perp	\perp	4	4	4		-		<u> </u>	
19	-	L	_	1	-	┡	1	-	-	\vdash	_	-	_	L	L	-	-		L	1	1	\perp	+	+	+	4	4	_	-		_	
20	-	_	-	+	-	\vdash	-	-	-	1	-	-	_	\vdash	H	-	-	-	L	-	+	+	+	+	+	+	4	-	-		-	
21 22	-	H	-	+	-	\vdash	+	+	-	\vdash	-	-	-	1	-	-	+		\vdash	-	\vdash	+	+	+	+	+	+	-	-		-	-
23	-	-	-	+	\vdash	\vdash	+	+	\vdash	\vdash	-	-	-	\vdash	+	-	+	-	\vdash	\vdash	\vdash	+	+	+	+	+	+	-	-	_	-	
24	-	-	\vdash	+	+	+	+	+	\vdash	\vdash	-	-	-	\vdash	-	+	+-	-	\vdash	+	+	+	+	+	+	+	+	\dashv	\dashv	_	-	-
25	-	\vdash		+	+	+	+	+	+	\vdash	\vdash		-	\vdash	+	+	+	-	\vdash	\vdash	+	+	+	+	+	+	\dashv	-	-	_	-	-
26	-		-	+	+	+	+	+	+	\vdash	\vdash	\vdash	\vdash	+	+	+	+		\vdash	\vdash	+	$^{+}$	$^{+}$	+	+	+	\dashv	+	+	_	\vdash	-
27		\vdash		†	\vdash	+	t	+	\vdash	+				\vdash	\vdash	+	T		\vdash	\vdash	+	†	†	†	+	+	1			_		
28				T	T	†	T		\vdash							T				T		†	†	+	1	1	7	-				
29				T				T						\vdash		Т	T			\vdash	T	T	+	T	1		\neg					
30				T															-			T	T									
31																						T										
FC																								-				Ti	T	7	1	1
PB			L	L			1	1		1						L		A	1	t				ī		1	1	1	1		1	I
RB		_	L	1	-	1	-	1	1	1	-			1	-	-	-		ı	1		1	1	1		1	ļ	1	1		1	l .
LB	-	-		1	-	\vdash	+	-	-	-	-	-	-	\vdash	-	-	-	{	l	1	1	1	1	1		1	1	1	1		1	I
PA RA	-	-		+	\vdash	\vdash	+	+	+	-	-	-	-	+	+	-	+	A	ı	Ţ	I	Ţ	1	1		1	Ţ	1	1			1
LA	-			-	\vdash	+	+	+	+	+	-	-	-	+	-	-	+		1	1	I	1	-	I	ī	1	1	1	1		1	ŀ
D3	_	-	-	-		-	+	-	-	-		-	_	+	-	-	-			1	1	1		1	ì	1	1] !	1		1	l
D2		-	E	E	-	E	+	-	=	-	-	-	=	-	-	-	E		1	1	1	T	1	1	- 1	T	1	1	_		1	
D1	-	-	-	=	=	1	-	-	-	-	Ē	=	-	1-	-	Ē	E			1	1	1	1	1	- 1	- 1	-	- 1	- 1			
D0	_	-	-	-	-	-	-	-	-	-	-	-	_	-	_	-	-		1	1	1	1	-	1	-	- 1	- !	- !	- 1	_		0
P	_	5	4	3	2	9	8	7	6	19	18	17	16	15	14	13	12		19	18	1	7 16	6 1	5 1	4	13	12	9	8	7	6	25
0,00	MARKS																															LS159
č	Ĭ	A	B	C	D																							W	X	Υ	Z	۵
														-	_		-	-	-		_	_	-	_	-	_	_	-				TBO

Signetics

AN18 Schmitt Trigger Using PLS153 and PLS159

Application Note

Application Specific Products

INTRODUCTION

One of the many features of the PLS153 to 159 series is the availability of individually controlled Tri-state I/O pins. Taking advantage of this feature, a Schmitt trigger may be constructed using one input pin, two bidirectional I/O pins and additional components of three resistors. The two threshold voltages, as well as the hysterisis, are determined by the values of the three resistors and the parameters of the PLS153/159 device, which are 1) input threshold voltage, VTH, 2) High output voltage, VOH, and 3) Low output voltage, VOL. The circuit may be simplified if Schmitt function is needed only on Low going High or High going Low, and if the hysterisis and threshold voltages are not important.

DESCRIPTION

A simplified block diagram of a non-inverting Schmitt trigger is shown in Figure 1 where $R_1,\ R_2,\$ and $R_1,\ R_3,\$ form two pairs of voltage dividers one of which get into action at input voltage direction of High going Low and the other Low going High. Assuming that input voltage starts at zero volt, the output voltage is therefore at V_OL which causes Q_2 to pull R_3 towards ground. As the input voltage increases, only a fraction of the voltage is

impressed upon the input buffer due to the dividing network R_1 and R_3 . As soon as the input voltage reaches a point where $V_1=V_{\rm TH}$ ($V_{\rm TH}=1.38V$ typical), the output switches to $V_{\rm OH}$ which, in turn, turns off Q_2 and turns on Q_1 . V_1 will jump to a value greater than $V_{\rm TH}$ and Q_1 then pulls the input pin, through R_2 , towards $V_{\rm OH}$, which in turn locks the output to a High state even if the input voltage fluctuates, as long as it does not fluctuate outside of the designed hysterisis. When the input voltage goes from a High to a Low, the Schmitt function repeats itself except that Q_1 and Q_2 reverse their roles.


The triggering voltages, V_H (Low going High) and V_L (High going Low) are: $V_H = V_{TH}$ [($R_1 + R_3$)/ R_3] - V_{OL} (R_1/R_3); $V_L = V_{TH}$ [($R_1 + R_2$)/ R_2] - V_{OH} (R_1/R_2); where, at room temperature, $V_{CC} = 5.0V$, $I_{OH}/I_{OL} < 1$ mA. V_{TH} is the threshold voltage of the device, typically 1.38V; V_{OL} is the output Low voltage of the device, typically 0.36V at $I_{OL} | < 1$ mA; V_{OH} is the output High voltage of the device, typically 3.8V at $I_{OH} | < 1$ mA.

The implementation of Figure 1 using PLS153/153A is as shown in Table 1, and Figure 2a. A scope photo of the operation of the circuit is shown in the Appendix. The

implementation using PLS159 is shown in Table 2 and Figure 2b. In Tables 1 & 2, V_1 is the input pin, V_0 is the output pin, V_2 is the output which pulls down V_1 and V_3 is the output pin that pulls up V_1 . The Schmitt output is available at pin B_0 for external use, and is available internally at the input buffers of I_0 and $B(I)_0$. However, there is a propagation delay between the two signals from the I_0 buffer and the I_0 0 buffer and the I_0 10 buffer.

An inverting Schmitt triggered buffer may be constructed using the same principle. A simple block diagram of such inverter is shown in Figure 3a. The circuit is implemented using H/L programming table as shown in Table 3 for PLS153 and Table 4 for PLS159. Table 3 is also represented in logic symbols in Figure 3b. If the voltage levels (VL and VH) and the hysterisis are not critical, one I/O pin may be used to pull the input pin High and Low. Therefore one I/O pin and a resistor may be saved. The drawback is that the range of VH and VL is quite limited. The circuit is as shown in Figure 4.

If Schmitt function is needed only in one direction, one of the resistor/output circuit may be eliminated. The circuit is as shown in Figure 5.



487

June 1988

AN18

Table I. PLS153/153A Programming Table

CO	DE	N	0.	PRODUCTION OF THE PARTY OF THE		Neptric O		-		(Construction of the Const		NAME OF TAXABLE PARTY.		**************************************	Martine Com		Hopaman				7	F			RI					
T			MAC	0.965.0	NAME OF THE OWNER, OF THE OWNER, OF THE OWNER, OF THE OWNER, OF THE OWNER, OWNER, OWNER, OWNER, OWNER, OWNER,	101200	AUGUS	A	ND	720 ES	e/A/28			asonas	2512730	Mary III		37.000	1	\vdash			_	님	Н		H	H	H	
Ė	-	10000	10000	or formation	eneman I	Ulvillo		MI	H	MANAGER	011551	Orpide	B(1)	estes		1000			-	_		-	B()) H	-		-	_	
ERM	7	6	15	4	3	2	1	0	9	8	7	6	5	4	3	2	1	0	REMARKS	911	R	71	6	5	41	3	2	1	0	REMARKS
0	Ė	-	-	-	-	-	-	H	Ė	-	_	-	-			_					۲	Ť	1						A	
1	0	0	0	0	0	0	0		0	0	0	0	0	0	0	0	0	0			٦	\dashv	7							
2	-	-	-	-	0	-	-	Ė	Ė	Ė	Ė	_	_	-		_	-	-			٦		7				A			OUTPUT VOH
3	Г	Г	Г			Г			Г	Г										П	7	-								
4																					_									
5																					4				_					
6	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0		\vdash	4	1	4	A	A			L	\sqcup	SAME AS
7	L	L	L	L	<u> </u>	L	L	L	L	L	-	L	_		<u> </u>	L	L	L		\vdash	j	_	4		_		L	L	Ш	TERMS 1 4 2
8	L	L	L	L	<u> </u>	L		L	L	L	-		_	L	<u> </u>	_	L	L		\vdash	ij	_	4		4		L	_	Ц	WITH
9	L	_	L	L	<u>. </u>	L	L	L	L	-	-	_	<u> </u>	L	<u> </u>	_	_	_	ļ	\vdash	-i	-	4	_	_i	_	H	_	\sqcup	8(0)4 = V2
10	L	-	-	-	H	H	-	-	L	┝	i	-	-	-	H	-	H	H		\vdash	i	+	+	-	i	_	H	_	H	B (0) 5 = V2
11 12	-	\vdash	-	-	-	-	-	\vdash	-	-	-	-	-	-	-	-	\vdash	-		+	4	+	+	-	-	_	\vdash	-	Н	
13	H	-	-	-	\vdash	-	-	-	-	\vdash	-	-	-	-	-	-	-	-		+	-	\dashv	\dashv		-	-	-	-	Н	
14	H	-	H	-	-	\vdash	\vdash	\vdash	Ͱ	\vdash	-	\vdash	-	\vdash	-	-	-	-		\vdash	4	+	+	\dashv	-	_	-	-	H	
15	H		H		<u> </u>		-	-	H	\vdash	-		-		-	-	H	\vdash		\vdash	+	+	+	\dashv	-		H	-	\vdash	
16	H				<u> </u>			\vdash	H	\vdash	H		-		-	\vdash		\vdash		\vdash	1	\dashv	+		1		Н		Н	
17	T	Т			-				Г	\vdash	-				-			\vdash		\vdash	1	7	7		1			Т	Н	
18	Г				-				Г	Г					_					\Box	1		\neg					Г	П	
19									Г				,								7				1					
20																					_									
21																					_				_					
22	L	L			_				L	L	L		L	L	<u> </u>		L	_		\sqcup	4	_	4		_				\perp	
23	L	L	L		-	Ш	_	L	L	L		L	_	L	_	_	L	L		\vdash	4	-	4	_	_			L	₽	
24	L		L		-	L	_		L	_	H		_	H	<u> </u>	_	L	_		\vdash	ij	-	4	_	-			L	\vdash	
25	<u> </u>	_	L	H	-	<u> </u>	_	H	L		-		_	H	<u> </u>	_	-	-		\vdash	4	+	4	_	—i	_	_	L	\vdash	
26 27	H	_	H	H	-	H	H	H	L	-	\vdash	H	_	H	-	_	H	-		\vdash	4	\dashv	+	\dashv	-i	_	H	-	\vdash	
28	Н	-	H	Н	-	Н	-	\vdash	\vdash	H	\vdash	Н		H	-	_	H	H		\vdash	+	\dashv	+	\dashv	-	_	-	H	\vdash	
29	Н	-	Н	Н	\vdash	Н	-	Н	\vdash	H	\vdash	Н	_	H	\vdash	_	H	\vdash	-	\vdash	+	\dashv	\dashv	-	\dashv	_	H	H	\vdash	
30	Н	Н	Н	Н	-	Н		Н	H		Н	Н	-	H	-	_	H	\vdash		\vdash	+	+	+	-	-		-	-	H	
31	\vdash		Н	Н		Н		H	H		Н	Н		H				H		\vdash	1	\dashv	+		_		\vdash	-	\vdash	
D9	Н		Н					П	r		Н	П		Н		_		Т		4	7	4	Ψ.	Ψ.	٣.	4	Ψ	4	7	
D8																			D				1				. 1		!	1
D7																					-	_	1			- 1.1				I I
D6																				 	-	and the last of th	۱,۲	li	1.			- 1	П	i
D 5																			The same of the sa	 	-		÷	٦;		H		- 1	il	i
D4	Ц										Ш								B	ii	i	i	i	- i	۱,	1			il	i
D3	Ш		Ц	_	Ш	Ц		Ц		Ц	Ц	Ц	- 1	L	_				<u> </u>	i	-	i	i	i	i	۱ ا			il	i
D2	-	_	-	=	-	_	-	=	_	=		-	_	-	=	-	-	Н		1 1	i	i	i	1		_	_		il	İ
D1	_	_	_	=	=	-	_	-	-	-	H		_	-	=	_	_	L		1 1	ī	i	i	-	_	-	_	_		I
D0	0	7	6	-	-	2	-	-	10	10	17	-	45	10	12	10	44	-		10 4	٦١	47	ie!	45	14	12	12	44	10	1 ~
PN	Ö	1	0	2	4	3	2	-	19	18	1/	16	15	14	13	12	"	9		19 1	9	1/	10	10	14	ıs	12	ш	3	2
X																														7
AB								>													-		-				6	72	2	ဟ
REMARKS			-	1																										PLS153
2																														-
						_								_							1		_					_	L	


NOTE:

Schmitt trigger output may be obtained from both 1_0 and $B(1)_0$ to drive the AND-ARRAY.

June 1988 488

TB01730S

AN18




AN18

Table 2. PLS159 FPLS Programming Table

СО	DE	NC).			No.						F	FN	OE	ÞΕ		-			E	В			E	A		P)L/	AR	ΤY	
		feet control			nombro.		Consenten	nerowal .			L								L									H	H	Н	
Ţ									AND)					_									(0	R)			-			
T E R	С	L	-	_	,	L		(1)	-	L	_	posenie		(P)	process,	,	,	REMARKS	L	-		Q	(N)	,	-		_	В	(0)	_	REMARKS
Daretton remove	L	3	2	1	_	3	2	1	0	7	6	5	4	3	2	1			7	6	5	4	3	2	1	0	3		_	0	
0	_	=	=	_	Н	느	-	-	-	느	-	=	=	=	=	-	-		E	-	-	=	_	-	-		0	0		A	NON-INV. BUFR
1	٥	0	0	0	0	0	0	0	0	0	0	٥	0	0	0	0	0		E	-	-	-	=	-	_	_	•	•	A		OUTPUT VOL
2	=	1	-	-	-	F	-	-	=	1=	-	-	-	=	=	=	_		=	=	-	_	_		_	_	•	A	0		OUTPUT VOH
3	_	-	\vdash	-		H	-	H	-	\vdash	-	-	-	H	H	-	-		H	-	-	\vdash	H	Н	_	Н	H	L	L	\vdash	
4	-	\vdash	-	-	\vdash	H	-	┝	\vdash	⊢	\vdash	H	-	H	H	-	\vdash		H	\vdash	\vdash	H	\vdash	Н	_	Н	H	H	H	╀	-
5	_	H	-	-	\vdash	H	-	-	\vdash	\vdash	-	H	-	H	-	-	-		L	-		H	H	Н	_	Н	H	H	_	\vdash	
7		-	-	H		H	\vdash	-	-	⊢	-	H	-	\vdash	-	-	-		-	-	\vdash	Н	\vdash	H	_	Н	H	\vdash	H	+	
_	_	⊢	-	-		H	\vdash	⊢	-	╀		-	-	\vdash	-	-	\vdash		\vdash	-	_	-	Н	\vdash	_	Н	⊢	-	H	\vdash	
8	\vdash	\vdash	-	H	_	H	-	-	-	⊢		-	-	\vdash	-	-	-		\vdash	-		Н	\vdash	\vdash	_	Н	H	-	H	+-	
9	-	⊢	\vdash	H		\vdash	\vdash	-	⊢	⊢	\vdash	\vdash	\vdash	\vdash	-	-	-		\vdash	\vdash		-	-	H		H	<u> </u>	-	H	\vdash	
10	L	-	-	-		-	-	-	-	-	-	-	-	-	-	-	-		-	-	-	H	-	H	_	Н	-	-	-	+	
11	-	\vdash	-	-	-	-	-	-	-	-	-	-	-	\vdash	-	-	-		-	-	-	H	-	H	_	H	-	-	-	+	<u> </u>
13	_	-	-	-	-	-	-	-	-	\vdash	-	\vdash	-	-	-	\vdash	-		\vdash	-	-	H	-	H	_	\vdash	\vdash	-	-	\vdash	
14	-	\vdash	-	-	-	-	\vdash	-	\vdash	⊢	-	\vdash	-	\vdash	\vdash	-	-		\vdash	-	\vdash	H	\vdash	\vdash	_	Н	H	-	-	-	-
15	_	\vdash	\vdash	-	H	\vdash	\vdash	\vdash	-	⊢	\vdash	-	\vdash	\vdash	-	\vdash	\vdash		\vdash	\vdash	\vdash	\vdash	\vdash	\vdash	_	Н	H	H	-	\vdash	
16	-	\vdash	-	-	\vdash	\vdash	-	\vdash	\vdash	\vdash	\vdash	-	-	\vdash	\vdash	\vdash	-		\vdash	-	-	\vdash	\vdash	Н	_	Н	\vdash	Н	-	╁	
17	-	\vdash		\vdash	-	\vdash	\vdash	\vdash	╁	⊢	\vdash	\vdash	\vdash	\vdash	-	\vdash	-		\vdash	-		\vdash	\vdash	\vdash	_	Н	\vdash	\vdash	-	\vdash	
18	-	\vdash	\vdash	-		H	-	-	\vdash	╁	\vdash	-	-	\vdash	\vdash	\vdash	-		\vdash	\vdash		\vdash	Н	\vdash	_	Н	\vdash	\vdash	-	\vdash	
19	_	\vdash		-		\vdash	-	\vdash	\vdash	\vdash	\vdash	\vdash	-	\vdash	\vdash	\vdash			\vdash	\vdash	\vdash	\vdash	Н	\vdash	_	Н	\vdash	-	\vdash	\vdash	
20		\vdash	-	\vdash		\vdash	\vdash	-	+	\vdash	-	-	\vdash	\vdash	-	\vdash	\vdash	-	\vdash		\vdash	\vdash	\vdash	Н	-	Н	H	H	-	+	
21	\vdash	\vdash		-	\vdash	\vdash	-	+	\vdash	\vdash	\vdash	-	\vdash	\vdash	-	\vdash	-		\vdash		\vdash	Н	\vdash	Н	_	Н	H	Н	\vdash	+	
22	-	\vdash		H		\vdash	\vdash	\vdash	\vdash	\vdash		-	\vdash	\vdash	-	\vdash	\vdash		\vdash	-		Н	\vdash	\vdash	_	Н	H	\vdash	\vdash	\vdash	
23	\vdash	\vdash	-	-	\vdash	H	-	-	\vdash	\vdash	\vdash	\vdash	-	\vdash	\vdash	-	\vdash		\vdash		\vdash	Н	\vdash	Н	_	Н	\vdash		\vdash	+	
24		\vdash		\vdash		\vdash	\vdash	\vdash	+	\vdash	\vdash	\vdash	\vdash	\vdash	-	\vdash	-		\vdash				\vdash	Н		Н	\vdash	\vdash	\vdash	\vdash	
25				-		\vdash	\vdash	\vdash	\vdash	\vdash			-	-		\vdash	-		\vdash			\vdash	\vdash			Н	H		\vdash	+	
26		\vdash		Н		\vdash	\vdash	\vdash	\vdash	\vdash		\vdash	_	\vdash	-	\vdash	\vdash								_	Н	H			+	
27				\vdash		H		\vdash	\vdash	\vdash			\vdash	\vdash	\vdash		\vdash		\vdash				\vdash	\vdash		Н	\vdash		\vdash	+	
28			-	\vdash		\vdash		\vdash		\vdash			-	\vdash		\vdash	-		\vdash					\vdash	_	Н	H			+	
29		\vdash		\vdash	Н	\vdash	\vdash	\vdash	+	\vdash		-							\vdash						_		H		\vdash	+	
30		\vdash			Н	H	-			\vdash				H					\vdash						_		H		\vdash	+	
31					Н		\vdash	\vdash		\vdash				\vdash		\vdash	\vdash		\vdash							Н	H			\vdash	
FC	_	\vdash			Н	\vdash	-	\vdash	\vdash	\vdash			\vdash	\vdash			\vdash										¥	-	-		
PB									\vdash	\vdash						\vdash		la .				i					- 1	- 1		- 1	
RB		П			H															_							- 1	- 1			;
LB					Н					\vdash								W .	ı	1		1		1			- 1	- 1	- 1		
PA																		A.	1		1	1		1							
RA									Г	Г								<u> </u>						'			- 1	- 1	- 1		;
LA					П					Г								7	1	1	' I	1		1							
D3								Г		Г							Г		· -								H	- 1	- 1		.
D2	_	-	_	_	-	_	_	-	н	-	_	_	-	-	_	-	_		<u>'</u>	<u>'</u>								7	. 1		
D1	_	-	-	_	-	_	-	-	L	-	_	-	-	-	-	-	-		_	_	_	1	_	-				_		il	
D0	_	_	_	_	_	_	-	-	-	-	_	_	_	-	-	_	_		· T	· 					_					H	
PI	N	5	4	3	2	9	8	7	6	19	18	17	16	15	14	13	12		19	18	17	16	15	14	13	12	9	8	7	6	2
REMARKS					٧،		٧a	۲۶																							PLS159

TB01740S

AN18



AN18

Table 3. PLS153/153A Programming Table

CO	DE	EN	0.	-	_	-									-	-		_				of the last	PO	LA	RI	ΤY				
_	-	W and	NAME OF TAXABLE PARTY.	portion .	Marin Da	Section 1	1 7/5					5 (4)		da ta		duis.		1500									L	L	L	
TERM	L	e less		-				Al	ND			AL 4-	D	781	2.00	A 50 D	10000		1	L				O B(R			_	_	
R	ļ-,	6	TE.	T A	12	12	14	ĪΛ	1	Τø	17	6	B(1/4	2	2	14	TΛ	REMARKS		Ω	7	6	5		3	2	1	n	REMARKS
0	۲	10	13	14	13	14	۲	Н	٦	P	+	0	3	-	۲	-	۲	-	REMARKS	1	4	H	0	-	۲	ř	0	•	A	INV. BUFFER
1	0	6	0	0	-	0	0		6	1	10	0	0	5	6	0	0	0	 	H	-	Н	Н		Н	H		A	•	OUTPUT VOH
2	Ľ	Ľ	Ľ	Ľ	۲	Ľ	1	Ë	Ľ	1	۲	Ľ	Ľ	Ĕ	Ľ	Ľ	Ľ	Ľ		Н	٦	Н		Н	Н	H	A	0		OUTPUT VOL
3	Н	t	\vdash	\vdash	!	†	T	\vdash	t	t	!-	\vdash			-	\vdash	1	\vdash		П					П	H	Ė			
4	Г	\vdash	\vdash		!	T	\vdash	Т	Г	T	-		Г	Г	_															
5						T										1														
6														L	L		L			Ц								L		
7	L	L			-	L		L	L	L		L		L	L	L	L	L		Ш	_							L	L	
8	L	L	L	L	_	L	L	L	L	L	L		L	L	L	L	L	L		Ц	_	L	L	L	L	_	L	L	L	
9	Ŀ	\vdash	L	\vdash	Ŀ	┡	L	L	L	╀	i	L	L	L	Ŀ	L	L	L		Н	_	\vdash	L	L	H	i	L	L	L	
10	H	⊢	-	-	i	╀	┡	┞	┞	╀	i	⊢	-	\vdash	H	┡	\vdash	┝		Н	-	\vdash	H	H	H	H	H	H	Н	
11 12	\vdash	+	-	-	-	+	+	-	\vdash	+	-	\vdash	-	\vdash	-	\vdash	\vdash	+		H	-i	\vdash	\vdash	\vdash	H	\vdash	H	-	H	
13	\vdash	+	\vdash	+	-	+	-	\vdash	-	+	-	\vdash	-	\vdash	-	-	\vdash	+	-	H	\dashv	\vdash	-	\vdash	H	\vdash	\vdash	\vdash	\vdash	
14	H	\vdash	⊢	┝	\vdash	\vdash	\vdash	\vdash	Ͱ	┝	\vdash	\vdash	\vdash	\vdash	\vdash	\vdash	┝	\vdash		Н	\dashv	\vdash	Н	Н	Н	\vdash	H	\vdash	Н	
15	H	\vdash	\vdash	\vdash	-	+	\vdash	\vdash	┢	+	+	\vdash	\vdash	\vdash	-	\vdash	\vdash	\vdash	 	Н	-	Н	H	Н	Н	H	H	\vdash	Н	7.0
16	Г	\vdash		\vdash	<u> </u>	\vdash	\vdash	\vdash	t	†	۲			\vdash	H	\vdash	\vdash	\vdash		Н	٦	Н	Н	Н	Н	H	Н		Н	
17	H	\vdash	\vdash	\vdash	H	\vdash	\vdash	\vdash	H	†	۲	\vdash			-	\vdash	\vdash	\vdash	†	Н	٦	Н	Н	Н	Н	H	Н	\vdash	\vdash	
18	Г				!		Т	Г	Г	T	<u></u>				_															
19									Г																					
20										L																				
21	L				_				L	L	L				L		L	L		Ш	_					_				
22	L	L	L	L	-	L	L	L	L	L	L	L	L	L	L	L	L	L		Ш	_	Ц				L		L		
23	L	L	L	L	Ŀ	L	L		L	L	i	L	L	L	Ŀ	L	L	L		Н	_	Н	Щ		L	Ŀ		_		
24	H	L	L	L	H	\vdash	_		L	┡	i	L	L		i H	-	L	\vdash		Н	_	Н	H		H	<u> </u>	\vdash	L	L	
25 26	H	H	H	H	H	-	H	H	L	\vdash	H	H	H	H	H	-	-	⊢	-	Н	-i	Н	Н		H	H	H		H	
27	H	H	H	\vdash	\vdash	\vdash	\vdash	H	H	\vdash	-	H	H	H	-	\vdash	\vdash	\vdash		Н	\dashv	Н	H	H	H	-	H	H	H	
28	H	Н	\vdash		\vdash	\vdash	H	Н	H	\vdash	\vdash	H	\vdash	H	\vdash	\vdash	\vdash	\vdash	-	H	\dashv	Н	H	Н	Н	-	\vdash	\vdash	H	
29	Н		\vdash		\vdash	\vdash	\vdash	\vdash	H	\vdash	\vdash	Н	H	Н	\vdash	\vdash	\vdash	\vdash	-	Н	\dashv	Н	Н	Н	Н	\vdash	H	\vdash	\vdash	
30	H		\vdash		H	\vdash	\vdash		Н	\vdash	-	Н			H	\vdash	Н			Н	\dashv	Н	Н	Н	Н	H	H	-	\vdash	
31	Г		Т		H	\vdash	\vdash		Н	\vdash		Н			-	\vdash	\vdash			Н		Н	Н	Н	Н	-	Н			
D9									Г									Г		-	Y	Y	Y	Y	Y	Y	Y	Y	7	
D8																					_	- 1							Н	
D7																					_		- 1	- 1					11	
D6																				<u> </u>			-		- 1				1	
D5	L	Щ			-		L		L											 		_	_	۲,				: 1	il	
D4	L	Ш	L	L	<u> </u>		L	H	_	L					_	L	L	L		: i									il	
D3	\vdash	H	H	H	<u> </u>	-	-	H	L	H	H	H		H	H	-	L	-		1 1		_			_	_			il	
D2 D1	=	-	_	\vdash	-	-	_	-	F	-	F	_	_	H	=	=	=	H		1 1		1				-	_		il	
D0		H	=		E		=		E	E	E		_	H	F	=	=	L		1 1					-	-	1	_	1	
PN	8	7	6	5	4	3	2	1	10	18	17	16	15	14	12	12	11	0		19	18	17	16	15	14	12	12	11	0	
	Ť	H	_	-	7	۲	-	+	13	10	"	10	13	14	13	14	11	3		13	10	17	10	13	14	13	12	11	3	
18																														75
AH								ゞ																			2	٧,	°,	က
REMARKS																														PLS153
<u>«</u>																														
	_	_	_	_	_	_	_	_	_	_	_	\Box	_	_	_		_	_		\sqcup			\Box		\Box				_	

TB01580S

AN18

Table 4. PLS159 FPLS Program Table


co	CODE NO. FF MODE						EB			EA				P	OL/	ARI	TY														
				olesses and									L			L		-							Н	Н	L				
TERM	<u>_</u>	_		AND			L			_	(OR)				D/O)																
Ř	С	Ļ	B(I) 3 2 1 0 3 2 1 0 7 6						Q(P) 7 6 5 4 3 2 1 0				REMARKS	Q(N							B(O)				REMARKS						
_	-	3	2	1	0	3	2	1	0	7	6	5	-	3	2	1	0		17	6	5	4	3	2	1	0	3	2	-	-	
0	=	=	=	=	H	F	=	-	=	F	-	-	-	=	_	-	=		=	-	-	=	=	=	=	-	0	•	•	A	INV. BUFFER
1 2	٥	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0		F	-	=	-	=	-	=	=	•	0	A	+	OUTPUT VOL
3	_	F	-	-	=	F	-	-	-	-	-	=	=	F	_	-	-		F	=	=	F	F	F	=	F	·	A	\vdash		OUTPUT VOH
4	\vdash	\vdash	\vdash	\vdash	\vdash	\vdash	⊢	\vdash	\vdash	\vdash		\vdash	-	\vdash	-	-	\vdash		\vdash		\vdash	Н	Н	Н	Н	\vdash	H	\vdash	\vdash	\vdash	-
5	\vdash	\vdash	\vdash	H	\vdash	\vdash	\vdash	\vdash	\vdash	\vdash	\vdash	\vdash			-	-	\vdash		\vdash		\vdash		Н	Н	\vdash	Н	H		\vdash	\vdash	-
6	\vdash	\vdash	\vdash	H	\vdash	\vdash	\vdash	\vdash		\vdash		\vdash	\vdash	H	\vdash	H	-		\vdash	\vdash	-	Н	Н	H	H	\vdash	\vdash	\vdash	\vdash	\vdash	
7	\vdash	\vdash	\vdash	\vdash	\vdash	H	\vdash	\vdash		\vdash		\vdash	\vdash	\vdash	\vdash	H	-		\vdash	\vdash	-	Н	Н	Н	\vdash	\vdash	H	\vdash	\vdash	\vdash	-
8	_	\vdash	\vdash	-		H	-	-	-	\vdash	\vdash	\vdash	-	\vdash	_	H	\vdash		\vdash	-	\vdash	Н	Н	Н	\vdash	H	H		-	\vdash	
9	\vdash	\vdash	\vdash	-		\vdash	\vdash	\vdash	\vdash	\vdash		\vdash	\vdash	\vdash	H	H	-		\vdash	\vdash	\vdash	Н	Н	Н	\vdash	H	H	-	\vdash	\vdash	
	<u> </u>	\vdash	-	H		H	\vdash	\vdash	-	H		\vdash	\vdash	\vdash	_	H	-		\vdash	\vdash	\vdash	Н	Н	Н	Н	\vdash	H	\vdash	\vdash	1	-
10	\vdash	\vdash	-	-	H	-	-	\vdash		\vdash	H	H	-	\vdash	\vdash	-	-		\vdash	-	-	H	H	H	H	H	-	\vdash	\vdash	\vdash	-
11	-	\vdash	-	-	H	\vdash	-	\vdash	-	-	-	-	H	\vdash	\vdash	-	-		-	-	-	H	Н	H	\vdash	H	\vdash		-	-	-
12	-	\vdash	-	\vdash	\vdash	\vdash	\vdash	\vdash	\vdash	\vdash	H	-	H	H	\vdash	-	\vdash		\vdash	\vdash	\vdash	H	\vdash	Н	H	H	\vdash	\vdash	-	-	
	_	\vdash	-	<u> </u>	\vdash	H	-	H	\vdash	\vdash				\vdash	-	-	-		H	-	\vdash	H	H	Н	Н	Н	H		-	\vdash	
14	_	H	-	H	H	\vdash	-	-		-	-	-	-	\vdash	-	-	-		-	H	\vdash	H	H	H	H	H	H	H	\vdash	\vdash	
15	\vdash	\vdash		H		H	\vdash	-		\vdash				\vdash	H	-	-	-	⊢		-	\vdash	Н	Н	Н	H	H		\vdash	\vdash	
16	\vdash	\vdash	-	H		\vdash	\vdash	-	\vdash	\vdash		\vdash	-	\vdash	_	H	-		\vdash		H	Н	Н	Н	Н	Н	-		\vdash	\vdash	
17	\vdash	\vdash		H		\vdash	-	H	\vdash	\vdash			-	\vdash	H	_			⊢		-	Н	Н	\vdash	\vdash	Н	H		-	\vdash	
18	\vdash	\vdash	-	L	\vdash	H	\vdash	H	-	\vdash		\vdash	-	\vdash	_	H	\vdash		\vdash	-	-	H	Н	Н	Н	Н	H	\vdash	-	\vdash	
19	_	\vdash	-	L		H	-	\vdash	-	\vdash		H	-	\vdash	L	-	-		\vdash		\vdash	\vdash	Н	Н	\vdash	H	_		-	\vdash	
20	_	\vdash	_	_	\vdash	H	-	-	\vdash	\vdash	\vdash	\vdash	\vdash	\vdash	_	H	-		\vdash		\vdash	Н	H	Н	\vdash	Н	-		\vdash	\vdash	
21	Щ	L		L	\vdash	H	-	H	H	\vdash	\vdash				_	-	-		\vdash		H	H	H	H	\vdash	\vdash	H	\vdash	-	-	
22	Н	H	\vdash	_		\vdash	\vdash	-	\vdash	\vdash		-		\vdash	_	-	-		⊢		-	\vdash	H	\vdash	Н	H	L	-	H	\vdash	-
23	_	\vdash	_	_	\vdash	H	-			\vdash		\vdash		\vdash	_	-	-		\vdash		-	Н	Н	\vdash	\vdash	H	L	-	\vdash	⊢	
24	_	\vdash	\vdash	_		L	_	<u>_</u>	\vdash	\vdash		-	_	H	_	-	-		-		-	Н	H	\vdash	\vdash	Н	L	-	-	\vdash	-
25	Щ	H	Н	L	\vdash	H	-	-	-	\vdash			\vdash	\vdash	_	-	-		\vdash	-	-	Н	Н	H	\vdash	H	H	-	-	⊢	
26	Щ	H	\vdash	_	Н	H	_	-	\vdash	\vdash		\vdash	-	\vdash	_	-	-		\vdash	-	\vdash	H	H	H	Н	\vdash	H	-	-	\vdash	
27	_	H	\vdash	_	Н	H	_	\vdash	_	\vdash		\vdash	-	\vdash	H	H	-		⊢	\vdash	-	\vdash	H	\vdash	\vdash	\vdash	\vdash	-	-	\vdash	-
28	_	\vdash	\vdash	_	Н	L	_			\vdash	H	\vdash		\vdash	L	-	-		\vdash		-	-	H	\vdash	\vdash	H	L	-	-	1	
29	_	\vdash	\vdash	_	Н	H	-			\vdash	H	\vdash	-	\vdash	_	-	-		\vdash	-	-	H	Н	\vdash	\vdash	\vdash	L	-	-	⊢	
30	\square	\vdash	_	_	Н	-			-	H	H	_	-	H	_	-	-		-	-	-	H	\vdash	H	-	H	\vdash	-	-	-	
31		L			Ц	L	L				L			L		L	_		Ļ												L
FC	\vdash	\vdash	_	_	Н	-	-	H	-	H	H	H	H	H	_	-	-						1		5 .		- 1	- 1	- 1	- 1	I
РВ	_	\vdash	_	_	Н	\vdash	\vdash	-	-	H	H	H	\vdash	H	_	-	-			1		1		1				- 1	.	1	I
RB	_	\vdash	_	_	Н	-	-	-		H	H	H	-	\vdash	-	-	-		•	1 0	i	1		٠		1		- 1		1	I
LB	-	\vdash		_	Н	-	-	H	-	H	H	_	-	-	_	-	-		1	1	1	1		1					ı	1	L
PA	-	-	_		Н	-	-	-	-	H	H	-	H	H	-	-	-		1	I	1	l .	I	1		1	1	1	1	1	I
RA	\Box	H	Щ		\vdash	H	-		-	H	-	H	H	H	<u> </u>	-	-		1	1	1	1		1	1	1	1	1	1	1	I
LA		\vdash			Н	-	_			-	H	H	-	-	_	-	-		ı	I	I	I	ı	1	1	1	- 1		- 1	.	I
D3		\vdash			Н	-	_		-	H	H	H	H	H	_	-	-		1	1	1	1				lė,		1	1	1	I
D2	-	_	_	-	_	-	-	-	1	-	-	-	-	-	-	_	-		1	1	1	1		1,0				Γ	1	1	I
D1	_	-	_	_	_	=	-	-	Н	=	-	-	-	-	_	-	-		1	1 8	1	1	1	1		1			Γ	1	
D0	-	_	-	-		_	-		-	_	_	-	_	-	_	_	-		146	100	-	16	45	4.6	46	16			-	Ę	6
PI	N_	5	4	3	2	9	8	7	6	19	18	17	16	15	14	13	12		19	18	17	16	15	14	13	12	9	8	7	6	27
REMARKS					٧,		٧,	٧2	%																						PLS159


493

TB01590S


June 1988

AN18





APPENDIX A



Signetics

AN21 9-Bit Parity Generator/Checker With 82S153/153A

Application Note

Application Specific Products

INTRODUCTION

This application note presents the design of a parity generator using Signetics PLD, 82S153 or 82S153A, which enables the designers to customize their circuits in the form of "sum-of-products". The PLA architecture and the 10 bi-directional I/O's make it possible to implement the 9-bit parity generator/checker in one chip without any external wiring between pins. A logic diagram of the device is shown in Appendix A.

The parity of an 8-bit word is generated by counting the number of "1's" in the word. If the number is odd, the word has odd parity. If the number is even, the word has even parity. Thus, a parity generator designed for even parity, for example, will generate a "0" if the parity is even, or a "1" if parity is odd. Conversely, an odd parity generator will generate a "0" if the parity of the word is odd, or a "1" if the parity is even. This bit is then concatinated to the word making it 9-bits

long. When the word is used elsewhere, its parity may be checked for correctness.

FEATURES

- Generates even and odd parities (SUM_E and SUM_O)
- SUM_E = "1" for even parity, "0" for odd parity
- SUM_O = "1" for odd parity, "0" for even parity
- Generate parity or check for parity errors
- · Cascaded to expand word length

DESCRIPTION


The most straight forward way of implementing the parity generator/checker is to take the 9-input truth table (8 inputs for the 8-bit word, and 1 input for cascading the previous stage) and put it in a 256×4 PROM. Since there are 2^9 combinations and half of them is odd,

the other half is even, the circuit will take 256 terms. An alternative is to divide the 9-bits into 3 groups of 3-bits as shown in Figure 1. If the sum of the 3-bits is odd, then the intermediate output SU1, or SU2, or SU3 equals 1. Otherwise it equals 0. The intermediate results are grouped together and SUMO becomes "1" if the sum is odd, otherwise SUMO equals "0". The circuit is implemented using AMAZE as shown in Figure 3. SU1 is an intermediate output for inputs Io, I1 and I2. In the same manner, SU2 and SU3 are intermediate outputs for I3, I4, I5 and I6, I7, I8. The design uses up 16 product terms and 5 control terms leaving 16 product terms and 4 bi-directional I/O's to implement other logic designs.

The design is tested by using the logic simulator provided by AMAZE. The input test vector is chosen to exhaustively test for all 8 input combinations at all 4 sections of the circuit

9-Bit Parity Generator/Checker With 82S153/153A

AN21



I ₀	I ₁	I ₂	SU1
0	0	0	0
0	0	1	1
0	1	1	0
0	1	0	1
1	0	1	0
1	0	0	1
1	1	0	0
1	1	1	1

l ₃	14	I ₅	SU2
0	0	0	0
0	1	1	0
0	0	1	1
0	1	0	1
1	0	1	0
1	1	0	0
1	0	0	1
1	1	1	1

16	17	I ₈	SU3
0	0	0	0
0	1	- 1	0
1	0	1	0
1	1	0	0
0	0	1	1
0	1	0	1
1	0	0	1
1	1	1	1

SU1	SU2	SU3	SUMo	SUME
0	0	0	0	1
0	0	1	1	0
0	1	0	1	0
0	1	1	0	1
1	0	0	1	0
1	0	1	0	1
1	1	0	0	1
1	1	1	1	0

Figure 1. Block Diagram of 9-Bit Parity Generator/Checker

```
****************** PARGEN ***********
** FNC **FIN ----- PIN** FNC **
10
         I 1
                        1-19 ** /O **SUME
12
                                 **SUMO
13
         ** I
             ** 4-! 8 !-17 ** B **N/C
14
         ** I
             ** 5-1
                        1-16 ** B
                                 **N/C
             ** 6-| S |-15 ** B
15
         ** I
                                **N/C
         ** I
                7-1
                    1 |-14 ** B
5 |-13 ** 0
             **
16
                                 **N/C
17
        ** I
             ** 8-1
                                 **SU3
18
                9-1
                       i-12 ** 0
                                 **SU2
        ** OV
             ** 10-1
                        1-11 ** 0
                                **SU1
                 Figure 2. Pin List
```

9-Bit Parity Generator/Checker With 82\$153/153A

AN21

```
******** PARGEN **********
@DEVICE TYPE
828153
GDRAWING
****** PARITY GENERATOR/CHECKER
@REVISION
@SYMBOL
****** FILE ID: PARGEN
GCOMPANY
****** SIGNETICS
@DESCRIPTION
    This circuit is a 9-bit parity generator/checker commonly used *
    for error detection in high speed data transmission/retrieval. The odd parity output (SUMO) is high when the sum of the data
    bits is odd. Otherwise it is low.

The even parity output (SUME) is high when the sum of the data
    bits is even. It is low otherwise.
@COMMON PRODUCT TERM
@I/O DIRECTION
********************
* SU1, SU2 and SU3 are outputs which are defined in the PIN LIST *
    and therefore they don't need to be defined here again.
@OUTPUT POLARITY
********************
    The output polarities of different outputs are defined in the **
    PIN LIST. They don't have to be defined again here.
@LOGIC EQUATION
**********************
  SU1, SU2, and SU3 are intermediate terms
                 TRUTH TABLE
         INPUTS
                              OUTPUTS
                        SUMO
SU3
SU2
    SU3
          SU2 SU1
                                SUME = /SUMO
     18
          17
14
                 16
           I 1
      0
                 Ō
           O
      0
           1
            0
SU1 = /12 * /I1 * IO + /I2 * I1 * /IO + I2 * /I1 * /IO + I2 * I1 * /IO + I2 * I1 * IO ; SU2 = /I5 * /I4 * /I3 + /I5 * I4 * /I3 + I5 * /I4 * /I3 + I5 * I4 * I3 *
SU3 = /I8 * /I7 * I6 + /I8 * I7 * /I6 + I8 * /I7 * /I6 + I8 * I7 * I6 ;
SUMO = /SU1 * /SU2 * SU3 + /SU1 * SU2 * /SU3 +
        SU1 * /SU2 * /SU3 + SU1 * SU2 * SU3 ;
SUME = /(/SU1 * /SU2 * SU3 + /SU1 * SU2 * /SU3 + SU1 * /SU2 * /SU3 + SU1 * SU2 * SU3);
   Figure 3. AMAZE Implementation of the Parity Generator/Checker Circuit
```

9-Bit Parity Generator/Checker With 82\$153/153A

AN21

Table 1. Programming Table

```
Cust/Project -
          - ******* REV. -
Rev/I. D.
825153
                                   POLARITY
T
                               !L:H:H:H:H:H:H:H:H:H!
F (----
       I ! B(i)
                                     B(n)
  .!7_6_5_4_3_2_1_0!9_8_7_6_5_4_3_2_1_0!9_8_7_6_5_4_3_2_1_0!
 0!---,-LLH!--,---,---!..,AAAA,..AA!
 1!----,- L H L!--,----,- --!. ., A A A A, . . A A!
 2!- - - -,- H L L!- -,- - - -,- - - -!. .,A A A A,. . A A!
 3!- - - -,- H H H!- -,- - - -,- - -!. .,A A A A,. . A A!
 4!-- L L,H ---!--,----,- --!. .,A A A A,. A . A!
 5!- - L H,L - - -!- -,- - - -,- - - -!. .,A A A A,. A . A!
 6!--HL,L---!--,---,---!..,AAAA,.A.A!
 7!--H H,H ---!--,----,----!. .,A A A A,. A . A!
8!L H --,----!--,----,----L!. .,A A A A,A . . A!
 9!H L - -,- - - -!- -,- - - -,- - - L!. .,A A A A,A . .
10!L L - -,- - - -!- -,- - - -,- - - H!. .,A A A A,A . . A!
11!H H - -,- - - -!- -,- - - -,- - - H!. .,A A A A,A . . A!
15!----,----,----,H H H -!A A,A A A A,. . .
16!0 0 0 0,0 0 0 0!0 0,0 0 0 0,0 0 0 0!A A,A A A A,A A A A!
17!0 0 0 0,0 0 0 0!0 0,0 0 0 0,0 0 0 0!A A,A A A A,A A A A!
18!0 0 0 0,0 0 0 0!0 0,0 0 0 0,0 0 0 0!A A,A A A A,A A A A!
19!0 0 0 0,0 0 0 0!0 0,0 0 0 0,0 0 0 0!A A,A A A A,A A A A!
20!0 0 0 0,0 0 0 0!0 0,0 0 0 0,0 0 0 0!A A,A A A A,A A A A
21:0 0 0 0,0 0 0 0:0 0,0 0 0 0,0 0 0 0:4 A,A A A A,A A A A
22!0 0 0 0,0 0 0 0!0 0,0 0 0 0,0 0 0 0!A A,A A A A,A A A A!
23!0 0 0 0,0 0 0 0!0 0,0 0 0 0,0 0 0 0!A A,A A A A,A A A A!
24!0 0 0 0,0 0 0 0!0 0,0 0 0 0,0 0 0 0!A A,A A A A,A A A A!
25!0 0 0 0,0 0 0 0!0 0,0 0 0 0,0 0 0 0!A A,A A A A,A A A A!
26!0 0 0 0,0 0 0 0!0 0,0 0 0 0,0 0 0 0!A A,A A A A,A A A A!
27!0 0 0 0,0 0 0 0!0 0,0 0 0 0,0 0 0 0!A A,A A A A,A A A A!
28:0 0 0 0,0 0 0 0!0 0,0 0 0 0,0 0 0 0!A A,A A A A,A A A A
29!0 0 0 0,0 0 0 0!0 0,0 0 0 0,0 0 0 0!A A,A A A A,A A A A!
3010 0 0 0,0 0 0 010 0,0 0 0 0,0 0 0 014 4,4 4 4 4,4 4 4
31!0 0 0 0,0 0 0 0!0 0,0 0 0 0,0 0 0 0!A A,A A A A,A A A A
D9!---,---
D8!---,---,---
D7!0 0 0 0,0 0 0 0!0 0,0 0 0 0,0 0 0 0!
D6!0 0 0 0,0 0 0 0!0 0,0 0 0 0,0 0 0 0!
D5!0 0 0 0,0 0 0 0!0 0,0 0 0 0,0 0 0 0!
D4:0 0 0 0,0 0 0 0!0 0,0 0 0 0,0 0 0 0!
D2!----!---!--!--!
DO!O O O O,O O O O!O O,O O O O,O O O!
   IIIIIIIISSNNNNSSSISSNNNNSSSI
  7654321000////000800////0008
               M M C C C C 3 2 1
                               M M C C C C 3 2 1
               E O
                               E O
```

9-Bit Parity Generator/Checker With 82\$153/153A

AN21


```
This is a test pattern for the 9-bit parity generator/checker *
   circuit. The simulator will use this file as an input to
   simulate the logical function.
*************************
                     EXPECTED
        UU
             555
                    DUTPUTS
"IIIIIIII MMBBBBUUUI
                     BBBBB
"76543210 E076543218
                      98321
                     "HLLLL
LLLLLLL ///////L
HLHHLHLL ///////H
                     "LHLLH
LHHLLHHL ///////H
                     "LHLHL
HHLHLLHL ///////L
                     "HLLHH
LLHLHHLH ///////H
                     "LHHLL
HLLHHLLH ///////L
                     "HLHLH
LHLLHLHH ///////L
                     "HLHHL
HHHHHHHH //////H
                     "LHHHH
QUIT
                         a. Input Pattern PARGEN.TST
825153
      A:pargen.STD
 This file is the result of logic simulation of the parity generator/checker
" circuit. The inputs are read from input file PARGEN.TST
 INPUTS \langle =B(I/0)=\rangle
                     TRACE TERMS
" 76543210 9876543210
 000000000 HL...LLLO ;
 10110100 LH....LLH1 ;
 01100110 LH....LHL1 ;
 11010010 HL...LHH0 ;
 00101101 LH....HLL1 ;
 10011001 HL....HLHO ;
 01001011 HL...HHL0 ;
 11111111 LH....HHH1 ;
             ---- I/O CONTROL LINES
         OOIIIIOOOI DESIGNATED I/O USAGE
         1000111100
                   ACTUAL I/O USAGE
" PIN LIST...
" 08 07 06 05 04 03 02 01 19 18 17 16 15 14 13 12 11 09 ;
                        b. Output File From SIMULATOR
                           Figure 4. Test Vectors
```

499

9-Bit Parity Generator/Checker With 82S153/153A

AN21

APPENDIX A



Signetics

AN23 PLS168/168A Primer

Application Note

Application Specific Products

INTRODUCTION

THE PLS168/168A is a bipolar Field-Programmable Logic Sequencer as shown in Figure 1, which consists of 12 inputs, a 48 product term PLA and 14 R/S flip-flops. Out of the 14 flip-flops, six are buried State Registers (P₄ - P₉), four Output Registers (F₀ - F₃), and four Dual-purpose Registers (Po-Pa), which may be used as Output or State Registers. All flip-flops are positive edge-triggered. They are preset to "1" at power-up, or may be asynchronously set to "1" by an optional PR/OE pin, which may be programmed either as a preset pin or as an Output Enable pin. Additional features includes the Complement Array and diagnostics features.

ARCHITECTURE

As shown in Figure 2, the device is organized as a decoding AND-OR network which drives a set of registers some of which, in turn, feedbacks to the AND/OR decoder while the rest serve as outputs. Outputs P₀ to P₃ may be programmed to feedback to the AND/OR decoder as State Registers and, at the same time, used as outputs. The user now can design a 10-bit state machine without external wiring. The AND/OR array is the classical PLA structure in which the outputs of all the AND gates can be programmed to drive all

the OR gates. The schematic diagram of the AND-OR array is shown in Figure 3. This structure provides the user a very structured design methodology which can be automated by CAD tools, such as Signetics AMAZE software package. The output of the PLA is in the form of sum-of-products which, together with the RS flip-flops, is the ideal structure for implementation of state machines. (Refer to Appendix A for a brief description of synchronous finite state machines.)


Design Tools

A direct approach to implement a design using the PLS168/168A is the H/L table supplied in the data sheet as shown in Table 1. The table is organized according to input and output of the PLA decoding network. The lefthand side of the table represent the inputs to the AND-array, which includes input from input pins and present state information from the feedback buffers which feedback the contents of the State Register. The righthand side of the table represents the output of the OR-array, which drives the State and Output Registers as the next state and output. Each column in the lefthand side of the table represents an input buffer, which may be inverting, non-inverting, disconnected or unprogrammed. Each column in the righthand side of the table represents a pair of outputs to the flip-flops, which may be set, reset,

disconnected or unprogrammed. The programming symbols are H, L, -, and 0. (See Figure 4 for details.) For inputs buffers, "H" means that the non-inverting buffer is connected, "L" means that the inverting buffer is connected, "-" means that both inverting and non-inverting buffers are disconnected. and "0" means that both inverting and noninverting buffers are connected which causes that particular AND-term to be unconditionally Low. On the output side of the table, "H" means that the particular AND-term is connected to the OR-term on the "S" input of the particular flip-flop, "L" means that the ANDterm is connected to the "R" side, "-" means that the AND-term is not connected to the flip-flop at all, and "0" means that the AND-term is connected to both the "S" and "R" sides. More details of the symbols and their meanings are shown in Appendix B. Each row in the table represents an ANDterm. There are 48 AND-terms in the device. Therefore, there are 48 rows in the table. An example of implementing a transition from one state to another is shown in Figure 4a. The state diagram can be implemented by the PLS168 as shown in Figure 4b. The state diagram is translated into H/L format as shown in Figure 4c. The first column on the lefthand side of the table is for the Complement Array which will be discussed in detail in the next section.


501

AN23




AN23

Table 1. PLS168/168A Programming Table




TB020305


AN23



AN23



AN23




T												AN	D											F				0	PTI	ON O	(PI	R/C	E)				Ц
E R	Г						INF	TU								PF	RES	EN	IT S	STA	ΓE				NE	XT	STA	ATE						C	UT	PU	Т
М	С	1	1 0	9	8	7	6	5	4	3	2	1.	0	9	8	.7	6	5	4	3	2	1	0	9	8	7	6	5	4	3	2	1	0	3	2	1	0
00	-	Н	L	-	-	-	-	4	-	-	-	-	-	-	-	-	-	Н	L	-	_	-	-	-	-	-	-	L	Н		-	-	-	Н		-	-
01																																					
PI No		1 8	1 9	2	2	2	2	2	3	4	5	6	7																	1 6	1 5	1 4	1 3	1	1	9	8
N A E	Ā	/N1	NØ																															OUTØ			

TB02010S

c. PLS168 Programming Table

Figure 4. Implementing State Machine with PLS168

AN23




Complement Array

An additional feature is the Complement Array, which is often used to provide escape vectors in case the state machines get into undefined states during power-up or a timing violation due to asynchronous inputs. A logic diagram of the Complement Array is shown in Figure 5. The output of the Complement Array is normally Low when one or more AND-terms are High. If all of the AND-terms are Low, then the output of the Complement


Array will be High. In this example, if each AND-term is a decoder for a particular state and input combination, and if the circuit gets into an undefined state, none of the AND-terms will be High. Therefore, the output /C will be High, which will then enable the AND-term S which in turn may be used to reset all registers to Low or High as predefined. The state machine thus escapes from being in an undefined state by using the Complement Array and one AND-term. Without the Complement Array an alternate way of escaping

from being in an undefined state is by defining all possible states which are not being defined. This method may require quite a few AND-terms depending on the design. Another application for the Complement Array is illustrated by the following example. As shown in Figure 6, when the machine is in state 23, if input vector equals 1001, it will go to next state 24. If the input is 1101, then go to state 25. But if the input is neither 1001 nor 1101, then go to state 03. It takes only two terms to implement the first two transition vectors. To implement the third vector "go to state 03 if input is neither 1001 nor 1101", the Complement Array accepts the outputs of the first two AND-terms as inputs. If the input vector is neither 1001 nor 1101, then both terms will be Low, which causes the output of the Complement Array (/C) to be High. A third AND-term is used to AND state 24 and /C together to set the registers to state 03. The State Diagram is translated into AMAZE syntex as shown in Figure 6b, where all vectors are in square brackets and the Complement Array is represented by the ELSE statement. The State diagram Figure 6a can also be expressed in the format of a program table as shown in Figure 6c. The complement array may be used to exit from different present states to different next states. It can be used many times in one state machine design as shown in Figures 7a, b, and c where the state diagram is implemented using the AMAZE state equation syntex and the H/L format.

AN23



AN23



a. State Diagram

WHILE [00]
IF [0000] THEN [01] WITH [OUT0]
IF [0001] THEN [02] WITH [OUT1]
ELSE: [3F] WITH [OUT9]
WHILE [01]
IF [0010] THEN [03] WITH [OUT2]
IF [0011] THEN [04] WITH [OUT3]
ELSE: [2F] WITH [OUT6]
WHILE [02]
IF [0100] THEN [05] WITH [OUT4]
IF [0100] THEN [05] WITH [OUT4]
ELSE: [2F] WITH [OUT7]


b. AMAZE State Equation


Т	Г											AN	D															0	PTI	ON	_	R/C	E)				\Box
E R	H	Γ					INF	UT	-					Г		PI	RES	SEN	IT S	TA	TE			\vdash	NE	XT	ST/	TE		0	n	_		- 0	UT	PU	\forall
М	С	1	1 0	9	8	7	6	5	4	3	2	1	0	9	8	7	6	5	4	3	2	1	0	9	8	7	6	5	4	3	2	1	0	3	2	1	0
00	A	L	L	L	L	-	_	-	-	-	_	-	-	L	L	L	L	L	L	-	-	_	-	L	L	L	L	L	Н	-	_	-	-	L	L	L	L
01	Α	L	L	L	Н	-	-	-	-	_	-	-	-	L	L	L	L	L	L	-	-	-	-	L	L	L	L	Н	L	-	-	-	-	L	L	L	Н
02	•	-	-	_		-	-	-	_	-	-	-	_	L	L	L	L	L	L	-	-	-	-	Н	Н	Н	Н	Н	Н	-	-	_	-	Н	L	L	Н
03																																					
04	Α	L	L	Н	_	-	-	-	-	_	-	-	-	L	-	L	L	L	Н	-	-	-	-	L	L	L	L	Н	Н	-	-	-	-	L	L	H	L
05	Α															-	L	L	L	Н	L	L	-	-	-	-	L	L	Н	Н							
06	•														-	Н	L	Н	Н	Н	Н	-	-	-	-	L	Н	Н	L								
07														L																							
08	Α	L	Н	L	_	-	-	-	-	-	-	-	-	L	L	L	L	Н	L	-	-	-	-	L	L		Н	L	Н	-	-	-	_	L	Н	L	L
09	Α	L	Н	L	Н	-	-	_	-	-	-	_	-	L	L	L	L	Н	L	-	-	-	-	L	L	L	Н	Н	L	-	-	-	-	L	Н	L	Н
10	•	-	-	-	_	-	_	-	-	-	-	-	-	L	L	L	L	Н	L	-	_	-	-	Н	L	Н	Н	Н	Н	_	-	_	-	L	Н	Н	Н
11																								L													
PI No																			1	1 5	1 4	1 3	1	1	9	8											
N A N	À	IN3	INZ	INI	IND																													0P3	0P2	0P1	OPØ


c. PLS168 Programming Table

Figure 7. Applications of Complement Array

AN23







AN23

Optional Preset/Output Enable

The PR/OE pin provides the user with the option of either using that pin to control the Tri-state output buffers of the Output Registers, or have that pin to asynchronously preset all registers to High. The purpose of the preset function is to provide the system a way to set the PLS168 to a known state, all Highs. The output enable function are sometimes used where the state machine is connected to a bus which is shared by other output circuits. It is also used during power-up sequence to keep the PLS168 from sending power glitches to other circuits which it drives. By programming the PR/OE pin to control the Tri-state output buffers, the preset function is permanently disabled. By programming the PR/OE pin to control the asynchronous preset of the registers, the output buffers are permanently enabled. While using the preset function to asynchronously preset the register, if a rising edge of the clock occurs while the preset input is High, the registers will remain preset. Normal flip-flop operation will resume only after the preset input is Low and the rising edge of the next clock. Setting the registers to a predefined pattern other than all Highs may be accomplished by using a dedicated p-term, which is activated by an input pin which will also inhibit all other p-terms which are being used. The inhibiting of other p-terms eliminates the problem of undetermined state of an RS flip-flop caused by having Highs on both R and S inputs.

Diagnostic Features

In debugging a state machine, sometimes it is necessary to know what is the content of the state register. The buried State Register may be read by applying +10V on I_0 , which will cause the contents of register bits P_4 to P_5 , P_6 to P_9 to be displayed on output pins F_2 to F_3 and P_0 and P_3 respectively. While the device can handle the +10V on pin I_0 , prolonged and continuous use will cause the chip to heat up since more power is being dissipated at +10V. To facilitate more expedient functional tests, synchronous preset vectors as described above may be used to set the State Register to different states without having to go through the entire sequence.

Timing Requirements

Since the PLS168 is intended to be a synchronous finite state machine, the inputs are expected to be synchronous to the clock and set-up and hold time requirements are expected to be met. In general, the set-up time requirement is measured at its worst case as having the entire AND-array connected to the OR-term being measured and there is only one active AND-term to drive the entire line. The set-up time decreases from there as less p-terms are used. This is due to the capacitance of the unused AND-terms being removed from the line. Figure 8a shows the typical set-up time requirement of a PLS168A device. Figure 8b shows the normalized setup time as a percentage of the worst case, which is with 48 terms connected. In a typical state machine design, some flip-flops will change states more frequently than others. Those that change more frequently will have more p-term loading on its OR gates than those that change states less frequently. The different loadings on the OR-terms cause different delay on the inputs of the flip-flops as shown in Figure 9. If an input fails to meet the set-up time specification, it is possible that the resultant of the input change gets to one set of flip-flops before the rising edge of the clock while it gets to other flip-flops during or after the clock's rising edge. The result is that some flip-flops have changed states and some have not, or some get into metastable condition as shown in Figure 10. The state machine is now either out of sequence or is in an undefined state. This problem often occurs with asynchronous inputs which is generated totally independent of the clock on the system. A common remedy for the problem of asynchronous inputs is to use latches or flipflops to catch the input and then synchronously feed it to the state machine. This minimizes the problem with the different propagation delays due to different p-term loading. But there is still a finite probability that the external latches or flip-flops will get into metastable condition, which may be propagated into the state machine. Nevertheless, the window for the flip-flops in state machine to get into undefined states or metastable condition is narrowed by a great extent.

AN23


APPENDIX A


INTRODUCTION TO STATE MACHINE

A state machine is a synchronous sequential circuit which interprets inputs and generates outputs in accordance with a predetermined logic sequence. It is analogous to running a computer program with a computer. The state machine, with its sequence coded in hard-

ware, can run much faster than a computer running the sequence in software. Therefore, it is often used in controller applications where speed is important.

Generally, state machines may be classified as Mealy or Moore machines as shown in Figures 1a and 1b. The fundamental difference of the two types are: the output of a Moore machine is a dependent of only the state of the memory elements whereas the output of a Mealy machine is a dependent of both the state of the memory elements and the inputs to the state machine. The figures also show graphic representations of the logic sequence in the form of state diagram in which the bubbles represent state vectors, and the arrows represent transitions from present states to next states.





AN23

APPENDIX B


LOGIC PROGRAMMING

The FPLS can be programmed by means of Logic programming equipment.

With Logic programming, the AND/OR gate input connections necessary to implement the desired logic function are coded directly from the State Diagram using the Program Table on the following page.

In this table, the logic state or action of control variables C, I, P, N, and F, associated with each Transition Term T_n , is assigned a symbol which results in the proper fusing pattern of corresponding link pairs, defined as follows:


PRESET/OE OPTION - (P/E)




PROGRAMMING:

The PLS168A has a power-up preset feature. This feature insures that the device will power-up in a known state with all register elements (state and output register) at a logic high (H). When programming the device it is important to realize this is the initial state of the device. You *must* provide a next state jump if you do not wish to use all highs (H) as the present state.


"AND" ARRAY - (I), (P)



"OR" ARRAY - (N), (F)



"COMPLEMENT" ARRAY - (C)



NOTES:

June 1988

- 1. This is the initial unprogrammed state of all link pairs. It is normally associated with all unused (inactive) AND gates $T_{\rm n}$ -
- 2. Any gate T_n will be unconditionally inhibited if any one of its I or P link pairs is left intact.
- 3. To prevent simultaneous Set and Reset flip-flop commands, this state is not allowed for N and F link pairs coupled to active gates Tn (see flip-flop truth tables).

4. To prevent oscillations, this state is not allowed for C link pairs coupled to active gates T_n.

Signetics

AN24 PLS173 as a 10-Bit Comparator, 74LS460

Application Note

Application Specific Products

DESCRIPTION

The PLS173 is a 24-pin PLA device which has 10 bidirectional outputs and 12 dedicated inputs. The output of the device is the sum of products of the inputs. The polarity of each output may be individually programmed as Active-High or Active-Low. A logic diagram of the device is shown in Appendix A. A 10-bit comparator similar to the 74LS460 compares two 10-bit data inputs to establish if EQUIVALENCE or NOT EQUIVALENCE exists. The output has True and Complement comparison status outputs. The logic diagram of the comparator is shown in Figure 1.

The truth table is as shown in Table 1 where vectors a and b are 10-bit inputs to A9 to A0 and B9 to B0. If the input to A9-A0 is bit-to-bit equivalent to the input to B9-B0, the two input vectors are considered EQUIVALENT, and output EQ goes High and NE goes Low. If the two input vectors are not bit-to-bit equivalent, then EQ goes Low and NE goes High. The circuit is implemented with AMAZE as shown in Figures 2a, 2b and 2c. The result of logic simulation of the circuit is shown in Figure 2d.

Notice that on the OR side of the program table in Figure 5, all the fuses in the OR-term are intact, which means that all the AND-terms are still connected to all the OR-terms. This feature provides for future modification. But if all the unused AND-terms are deleted, the device will run faster. There are also many unused AND-terms which will provide for future modification. But if they are deleted (both on the AND and OR side), it will amount to about 450 µA per term power saving. Figure 3 is the program table with all unused terms deleted.

Table 1. Function Table

A ₉ - A ₀	B ₉ - B ₀	EQ	NE
а	а	Н	L
b	b	Н	L
a	b	L	Н
b	а	L	Н




Figure 1. Logical Equivalent Circuit of 10-Bit Comparator

***************** AN24_173 ************* ****** P I N PIN** FNC ** 1-24 ** +5V **VCC AO 1-1 I BO ** ** 2-1 1-23 ** **B9 A1 Ι ** 1-22 ** **40 1-21 ** B1 ** 4-! **BB A2 ** ** 5-1 1-20 ** **A8 B2 ** ** 6-1 S 1-19 ** O **NF 1-18 ** /0 **EQ A3 ** вз 1-17 ** **B7 ** ** 8-1 1-16 A4 **A7 **B6 1-14 **A6 GND ** OV 1-13 ** **B5 a. Pin List of 10-Bit Comparator Figure 2


AN24

```
****************** AN24_173 *************
@DEVICE TYPE
825173
eDRAWING
        ..... 10-BIT COMPARATOR USING PLS173
@REVISION
 ..... REV-0
@DATE
 ..... OCT-14-85
@SYMBOL
       ..... AN24_173
@COMPANY
     ..... SIGNETICS
@NAME
            ..... DAVID WONG
@DESCRIPTION
This circuit compares two 10-bit inputs. If they are bit-to-bit equivalent, outputs EQ goes HIGH and NE goes LOW. If the inputs are not bit-to-bit equiv-
alent to each other, outputs EQ goes LOW and NE goes HIGH. @COMMON PRODUCT TERM
TO = AO * /BO; T1 = /AO * BO;
T2 = A1 * /B1;
   = /A1 * B1
   = A2 * /B2
T5
   = /A2 * B2 ;
   = A3 * /B3
   = /A3 * B3
T8
   = A4 * /B4
T9
   = /A4 * B4
T10 = A5 * /B5
T11 = /A5 * B5

T12 = /A6 * B6
T13 = A6 * /B6

T14 = A7 * /B7
T15 = /A7 * B7
T16 = A8 * /B8
T17 = /A8 * B8 ;
T18 = A9 * /B9;
T19 = /A9 * B9;
@I/O DIRECTION
@OUTPUT POLARITY
@LOGIC EQUATION
b. Boolean Equations of 10-Bit Comparator
                            Figure 2 (Continued)
```


AN24



AN24

```
A: AN24_173.STD
 825173
   AMAZE FILE ID: AN24_173
LOGIC SIMULATION OF 10-BIT COMPARATOR
   <==INPUTS==> <=B(I/O)=> TRACE TERMS
   109876543210 9876543210
   00000000000 0000LH0000 :
   01000000000 0000HL0000 ;
   100000000000 0000HL0000 :
   11000000000 0000LH0000
   000100000000 0000HL0000
   00100000000 0000HL0000
   001100000000 0000LH0000
   000001000000 0000HL0000
   000010000000 0000HL0000
   000011000000 0000LH0000
   000000010000 0000HL0000
   000000100000 0000HL0000
   000000110000 0000LH0000
   00000000100 0000HL0000
   00000001000 0000HL0000
   000000001100 0000LH0000
   000000000001 0000HL0000
   000000000010 0000HL0000
   000000000011 0000LH0000
   000000000000 0100HL0000
   000000000000 1000HL0000 ;
   000000000000 1100LH0000
   00000000000 0001HL0000
   000000000000 0010HL0000 ;
   00000000000 0011LH0000 ;
   000000000000 0000HL0100
   00000000000 0000HL1000
   000000000000 0000LH1100 ;
   000000000000 0000HL0001 ;
   000000000000 0000HL0010 ;
   000000000000 0000LH0011 ;
                IIIIOOIIII DESIGNATED I/O USAGE
" PINLIST...
" 13 11 10 09 08 07 06 05 04 03 02 01
" 23 22 21 20 19 18 17 16 15 14;
d. Test Vectors Generated by AMAZE After Logic Simulation
                  Figure 2 (Continued)
```


AN24



AN24

APPENDIX A

FPLA LOGIC DIAGRAM FOR PLS173



Signetics

AN26 PLHS18P8A Primer

Application Note

Application Specific Products

FEATURES

- 100% functional replacement for all 20-pin PALs
- I/O propagation delay: 20ns (max)
- Security fuse lock
- 10 inputs
- 8 bidirectional I/O lines
- Tri-state outputs have programmable polarity
- Architecture: 8 groups of nine AND gates. Total of 72 product terms
- Software support on Signetics AMAZE
- Complete TTL compatibility
- Each bidirectional I/O has individually controllable output enable

ARCHITECTURE

The PLHS18P8A is an oxide-isolated, bipolar field-programmable logic array. This device is configured as a decoding two-level AND-OR (sum of products) structure. The PLHS18P8A block diagram is shown in Figure 1. All the AND gates are linked to ten inputs (I₀ - I₉) and eight bidirectional I/O lines (B(0) - B(7)). These links can be made via the on-chip true/complement buffers. The 72 AND gates are configured in 8 groups which contain 9 AND gates each. In every group, eight AND gates are used for user-defined logic functions and the ninth AND gate is used as a tristate output enable control. This gives the user capability to control the output enable by means of a product term. The outputs of the eight logical product terms are ORed together (see Figure 1). The output polarity of each OR gate is individually programmable via an Exclusive-OR gate. The user has a choice of Active-Low or Active-High on each of the eight outputs. Figure 2 shows the logic diagram of the PLHS18P8A.

HOW A DEVICE IS PROGRAMMED

There are three main programmable sections on the PLHS18P8A:

- A. The AND array.
- B. The output polarity.
- C. The security fuse.

A. The AND Array - The AND array fuses are back-to-back diode pairs which act as open connections in a virgin device. These open connections are configured as 'Don't Cares' (' - ') in an unprogrammed device. The open connections are pulled to a logic High ('1') (see Figure 3). Consequently, all unprogrammed AND locations are pulled to a logic High ('1') state. This means that in an unprogrammed device, all the product terms are active. During fusing, current is avalanched across individual diode pairs. This essentially short circuits the diode and provides a connection for the associated product term. Figure 3 shows how a typical connection is made to the AND array (see Appendix B for a description of the vertical fuses).

The inputs to the AND array consist of 10 dedicated inputs (I0 - I9) and 8 bidirectional I/Os (B(0) - B(7)). Initially, all these inputs are configured as 'Don't Cares' ('-'). These inputs can be connected to the AND array through an inverting or non-inverting buffer. The AND gate can be connected to the inverting buffer by programming the inverting fuse. Similarly, a connection can be made to the non-inverting buffer by programming the non-inverting fuse. Disabling an AND term is achieved by implementing a logical Low ('0') on the output of the specified AND gate. When both fuses of an input (e.g. 10 and $\overline{10}$) are programmed, both the inverting and noninverting buffers are connected to the inputs of the AND gate. To achieve this a '0' should be entered on the program table under the specified input. This will in turn create a logical Low ('0') on the output. To avoid any glitches on the output, it is a good practice to program all inputs to force a logical Low ('0').

In each block of nine AND gates, one gate is used as an output enable control for the tristate output (Terms 0, 9, 18, 27, 36, 45, 54, 63, designated as D on Table 2). The remaining eight gates are connected to a fixed OR gate. Since in the unprogrammed state the outputs of all the AND gates are at logic High ('1'), the output of the OR gate also acquires a logic High state. Therefore the user is responsible for deactivating any unwanted product terms. This is done by creating a logic

Low ('0') on the outputs of the unwanted product terms as previously explained. Moreover, the output buffer is always enabled since the product term controlling the tri-state output buffer also has a logic High state. If any of the bidirectional pins are to be defined as inputs, the product term controlling the specified bidirectional pin must be disabled. The bidirectional pin can also be configured as a dynamic I/O by defining the required logic for the output-enable-control product term.

The actual programming of the PLHS18P8A is carried out according to JEDEC¹ standards and the specific programming algorithm developed for the part.

According to JEDEC standards on data preparation for the PLD programmer, a "1" specifies a high impedance for the specified fuse and "0" a low impedance for the designated fuse

For the AND array, the programming algorithm leaves the fuse intact (open-circuited) when a JEDEC "1" is specified. Consequently, a JEDEC "0" programs and short circuits the specified fuse. The programming algorithm is different for the output polarity and will be explained in the next paragraph on Special Conditions for the Output Polarity.


B. Special Conditions For The Output Polarity — In an unprogrammed device, all the output polarities are configured as inverting buffers. In this state, the device will have logic Low on all its outputs. The outputs of the PLHS18P8A are configured as tri-state buffers. The two inputs of each Ex-OR gate are connected as follows: one input is connected to the output of the fixed OR gate. The second input is a connection to ground (logic Low) through a fusible link.

As mentioned earlier, an unprogrammed fuse acts as an open connection which is pulled to a logic High. Therefore the output of the ExOR gate acts as an inverting buffer. When the fuse is programmed, there is a connection between ground (logic Low) and the input of the Ex-OR gate. This will cause the Ex-OR gate to act as a non-inverting buffer.

For more information on standard data transfer format between the data preparation system and PLD programmer, refer to JEDEC — Solid State Engineering Council publications.


PLHS18P8A Primer

AN26




PLHS18P8A Primer

AN₂6



June 1988

PLHS18P8A Primer AN26






Table 1. Programming Algorithm

JEDEC SPECIFICATION	AND ARRAY FUSE PROGRAMMING ALGORITHM	OUTPUT POLARITY FUSE PROGRAMMING ALGORITHM
1 — High impedance	Fuse unprogrammed (open circuit)	Fuse programmed (short circuit)
0 — Low impedance	Fuse programmed (short circuit)	Fuse unprogrammed (open circuit)

Figure 4 shows the definition of the output polarity for the PLHS18P8A. As can be seen, the output configuration of the PLHS18P8A is equivalent to an Ex-OR gate.

The programming algorithm for the output polarity section of the PLHS18P8A is different from that of the AND array. For the output polarity a JEDEC "1" (high impedance) programs (short circuits) the Ex-OR gate fuse, whereas a "0" (low impedance) leaves the fuse intact (open circuit).

The programming specifications are transparent to the user and do not need to be taken

into consideration when designing with the PLHS18P8A. Table 1 shows the resulting programming algorithm from the JEDEC specification.

C. The Security Fuse — Programming equipment used to program the PLHS18P8A are capable of determining the logic pattern stored in this device (see Appendix A). The security fuse can be blown to disable the programmer from reading the pattern in a programmed device. This feature adds a measure of protection for proprietary designs.

The procedure for programming this fuse depends on the programmer manufacturer and is explained in the manufacturer's operations manual.

DESIGN TOOLS FOR THE PLHS18P8A

Many CAD tools such as Signetics' AMAZE software² are available to implement designs using the PLHS18P8A. The AMAZE software enables the user to enter the design in the form of Boolean equations or via the program table shown in Table 2. This program table is a one-to-one map of all the programmable links of Figure 2. The following explains the implementation of designs using the program table. Also, an example on using the Boolean Logic Entry program of the AMAZE software is given.

Using PTE (Program Table Entry) — Assume that Z is a typical logic function with the following equation:

$$Z = P0 + P1$$

Where P0 and P1 are product terms with the following equations:

The program table in Table 2 is used to implement this equation. Table 3 shows the implementation of the logic function using the PTE. The first group of AND terms is used to implement this function. B(7) is used for the output, 10, 11, and 12 as inputs.


- Term 0 is the direction control term. It is the tri-state output enable control term. Since Z is configured as an output, leaving Term 0 in its unprogrammed state causes the output to be unconditionally enabled.
- Term 1 is the P-term labeled P0, where A*/B*C is designated by HLH in columns I0, I1, and I2.
- Term 2 is the P-term labeled P1, where /A*B*/D is designated by LHL in columns I0, I1, and I2.
- Terms 3, 4, 5, 6, 7. At least one input (or all the inputs) must be set to zero to disconnect these terms from the OR gate.
- The output polarity for B(7) is H, and this is entered in the 'Polarity' section.

Using BLAST (Boolean Logic And State Transfer)—The BLAST module in AMAZE can be used to implement the above equation. Figures 5 and 6 show the pin list and logic equation format. Table 4 is the program table generated from these equations.

^{2.} Refer to Signetics Programmable Logic Data Manual for a complete description of the AMAZE programmable logic development software.

PLHS18P8A Primer


AN26



524 June 1988

PLHS18P8A Primer

AN₂₆



PLHS18P8A Primer AN26

```
File Name : 18PRIMER
Date : 5/22/1986
Time : 13:52:54
** FNC **PIN -----
                                     -- PIN** FNC **
                                   1-20 ** +5V **VCC
             ** I ** 1-! P
** I ** 2-! L
В
             ** I ** 3-!

** I ** 4-!


** I ** 5-!

** I ** 5-!
                                    1-18 ** /0 **INVERT
                                      1-17 ** I
n
                                8
                                                   ##INPUT
N/C
                                     1-16 ## B
                                                   **BIDIR
                     ** 6-1
** 7-1
                                8
                                    |-15 ** /B **/BD
|-14 ** /B **N/C
|-13 ** /B **N/C
                                 P
N/C
                                8
             ** I
                     ** 8-1
N/C
                     ** 9-1
             ## OV ## 10-1
                                      1-11 ** I
AND
                                                   ##N/C
                             Figure 5
```

```
File Name : 18PRIMER
Date : 5/22/1986
Time : 13:53:59
eDEVICE TYPE
PLH818PBA
ODRAWING
..... PLHS1BPBA PRIMER
ORFVIRION
ODATE
..... May 1986
ORYMBOL
..... PLHS18P8A
OCOMPANY
..... SIGNETICS
..... Ali Sheissari
@DESCRIPTION
****
     This is an example of implementing equations for
   @COMMON PRODUCT TERM PA = \Delta * /B * C_{3} " PO and P1 are used to declare common
@I/O DIRECTION
D7 = 1;
D6 = 1;
                      " Defines B7 to be an output
                     " Defines B6 to be an output "
" Defines B5 to be an input "
" Defines B5 to be an input "
" B4 an output when A is true otherwise an input "
" B3 an output when B is true otherwise an input "
D5 = 0;
D3 = B;
COUTPUT POLARITY
                     " Documents the output polarity as active high 
" Documents the output polarity as active high 
" Documents the output polarity as active high
X7 = O<sub>3</sub>
X6 = 1;
X4 = O<sub>3</sub>
X3 = 1;
                      " Documents the output polarity as active high
@LOGIC EQUATION
                      "Examples of some simple equations
Z = PO + P1:
INVERT = /( INPUT );
BIDIR = /BDIR * B ;
/BDIR = /( A * C * D * /Z * INVERT * INPUT * BIDIR );
                       Figure 6. Boolean Equation File
```

PLHS18P8A Primer

AN₂₆



PLHS18P8A Primer

AN₂₆

APPENDIX A

Programmers

The PLHS18P8A can be programmed by means of logic programming equipment. With Logic Programming, the AND/Ex-OR gate input connections necessary to implement the desired logic are coded directly from the logic equations using the program table shown in Table 2.

The symbols used in the program table correspond to the fusing pattern of the corresponding link pairs, defined in Figure 6.

To program the device, the address of every fuse to be programmed must be entered in the programmer. This is a tedious and errorprone method of implementing the required logic pattern. Using CAD software, such as Signetics' AMAZE software, enables users to go directly from program table or logic equations to a fuse plot. The fuse plot can be downloaded to a programmer through a serial port. The downloaded fuse plot is in JEDEC format

APPENDIX B

The vertical fuse is the latest in programmable logic technology. It combines reliability, low capacitance and testability in an incredibly small space.

The vertical fuse takes advantage of the properties of silicon and aluminum. The virgin fuse is a three-layer device: a shallow layer of N-type silicon on top, a layer of P-type silicon in the middle, and a layer of N-type silicon on the bottom. This forms a pair of PN diodes, back-to-back, which will not allow current to pass under normal circumstances.

There is a cap of aluminum on top of this structure. During programming, high current conditions (50 to 100 times what is seen during normal operation) is induced by avalanche breakdown of the reverse-biased diode. The aluminum will "spike" through the shallow N-type layer. Once the aluminum has spiked through, the top diode in the pair is shorted out. The whole vertical fuse will then look like a pure PN diode. Before programming, the fuse is an excellent blocking element, having current leakages in the order of nanoamps. After programming, the fuse is set as a small, well-defined diode.

QUALITY

Besides the AC and DC parametrics, each and every fuse goes through three tests for forward characteristics, reverse characteris-

tics, and programmability. Extensive on-chip test circuitry ensures full AC parametric testing before and after the part is programmed. This insures that the customer receives the highest possible fusing yield which is made possible by vertical fuses. Vertical fuses also offer the smallest and fastest array structure together with the highest reliability possible.

APPENDIX C

Test Array

The PLHS18P8A may be subjected to AC and DC parametric tests prior to programming via an on-chip test array. Table C1 shows the test columns in the part. The test sequence is as follows.

Test column 1 is connected to B(O)0, 2, 4, 6 while test column 2 is connected to B(O)1, 3, 5, 7. Applying 10V to Pin 11 will put all the outputs in the Active-High mode and tri-state its associated input buffer.

Applying 10V to Pin 8 will disable B(O) 0-3, enable B(O) 4-7, tri-state B(I) 4-7, tri-state its associated input buffer, disable the AND array and enable test columns 1 and 2. The test columns are defined during programming by the PLD programmer.

Table C1. Test Columns of PLHS18P8A

TEST										INP	UTS							
COLUMN					- 1	s								B(ls)			
	9	8	7	6	5	4	3	2	1	0	7	6	5	4	3	2	1	0
1	Н	Н	Н	Н	Н	Н	Н	Н	Н	Н	Н	Н	Н	Н	Н	Н	Н	Н
2	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L

Signetics

AN27 PLHS473 Primer

Application Note

Application Specific Products

INTRODUCTION

The PLHS473 is a 24-pin field- programmable logic array (FPLA) which has 11 dedicated inputs, 2 dedicated outputs and 9 bidirectional I/Os. The logic array consists of 24 programmable product terms which are connected to 22 programmable OR terms in the classical PLA architecture. A functional diagram is shown in Figure 1. The shaded areas represent programmable interconnects between vertical and horizontal lines. Eleven dedicated inputs, In to I10, are located on the upper lefthand corner of the diagram, and the 9 bidirectional I/Os, Bo to Ba are located on the lower righthand corner. All inputs to the AND array have true and inverting input buffers. The output portion of the 9 bidirectional I/Os and 2 outputs may be programmed to be Active-High or Active-Low by altering fuses X₀ to X₈, X_A and X_B which are connected to one leg of the Exclusive-OR gates. Each output is connected to two ORterms, one of which provides the logic function OR to the output while the other provides the ENABLE function for the tri-state output buffer. Alternatively, each output may be configured to emulate an open-collector output by programming the output to an unconditional LOW and apply the logic function on the tri-state controlling OR-term as shown in Figure 2. In addition, the PLHS473 has a security fuse which may be programmed to lock out unauthorized access to the fuse map of the design.

This device is fabricated with an oxide-isolation process for the best speed/power performance. The programmable element is a "vertical fuse" which is actually two PN diodes connected back-to-back (anode-to-anode

stacked on top of one another) as shown in the insets of Figure 1. The fuses are normally open-circuited. To program a fuse, a sufficiently high voltage is applied across the two diodes such that one diode breaks down which induces metal migration across the PN junction of the avalanched diode. This technology allows smaller chip size and faster speed performance. The guaranteed propagation delay may be tested by using the two factory-programmed test columns and a test row as a test vehicle for speed testing. These test columns are to be deleted automatically in the process of programming.

The vertical fuses of an unprogrammed device, being normally open-circuited, set all AND terms to a High state and disconnected to all OR terms. The OR terms are normally Low when they are not connected to the AND terms. Once an AND term is programmed to make connections with the OR array, it cannot be disconnected. However, AND terms may be disabled by having the true and inverting input buffers (e.g., A * /A, B * /B, etc.) of all inputs connected to the AND term which is to be disabled.


While even a single input, (A * /A), will hold the AND term to a Low, glitches may develop if the input voltage changes state. Therefore, it is recommended that the complementary buffers of all inputs in the disabled AND term be connected.

Programming the PLHS473


The programming table and symbols of the PLHS473 are shown in Table 1 where there is a place for every function that is shown in Figure 1. The table is divided into two main

sections. The left side of the table, sections A and B, represents the input side of the AND array (section A has all dedicated inputs In to I₁₀, section B has inputs from the bidirectional I/Os B₀ to B₈), whereas the right side, sections C, D, and E, represents the outputs of the OR array. Section C represents the OR array which controls the tri-state output buffers of the bidirectional I/Os Bo to Bo and outputs OA and OB, while section D represents the OR array which drives the outputs. Section E controls the output polarity of each output. As shown in Table 1, the program table is very similar to a truth table. Each row represents one of the 24 product terms, while each column in sections A and B represents an input to the 24 product terms and in sections C and D, each column represents an output. The intersection of a column and a row in sections A and B represents four possible fuse configurations, namely, 1) both inverting and non-inverting input buffers are connected to the AND term, 2) only the inverting buffer is connected, 3) only the noninverting input buffer is connected, and 4) both inverting and non-inverting buffers are disconnected. These four configurations are represented as "0", "L", "H", and "-", respectively. Each intersection of a row and a column in sections C and D involves only two fuse configurations, either connected or disconnected. Therefore, the entry there is either "A" or "-", respectively. In the polarity control section (section E), each square represents the configuration of the fuse connected to the Exclusive-OR, which is connected to a particular output pin. An "H" represents an Active-High or non-inverting output, an "L" represents an Active-Low or inverting output. See Table 1 for further details.

PLHS473 Primer AN27



PLHS473 Primer AN27



Notice that as shown in Figure 1, all fuses in their unprogrammed state are normally open-circuited. This means that all product terms are initially disconnected to the OR array, all

OR gates are initially at a logic LOW, and all output pins are initially in High-Z state. Therefore, if anys of the outputs are to be enabled, its controlling OR term must be set to a logic

HIGH. An example is shown in Table 2, term 0 where pins O_A , O_B B(O)₈ are programmed as dedicated outputs. The input section of term 0 is entirely "dashed out" (this is actually its unprogrammed state) which causes the AND term to be unconditionally HIGH. OR terms E_A , E_B , and D_B are connected to product term 0 by the "A" entries in their respective squares. The rest of the D section and the B(O) section are "dotted out" (left unconnected) since we are not concerned with them for the moment. If more outputs are needed later on, their corresponding squares may be changed to "As" from "dots" as the need arises.


Table 1. PLHS473 Programming Table

		STOMER NAME															AN	ID					0	R																			
																				_						- 1	- [7	ACTIV	'E	I A	1												
1				-			-													_	l li	VACT	TIVE	10		į	-	NACT	IVE		B(O)											
S	GN	ETI	CS	DE	VIC	E #	£					CF	(X	XXX	()_						1	В		+	Н	- 1	Ľ			1													
С	UST	OM	IER	SY	МВ	OL	IZE	D F	PAR	RT #	<i>+</i>													-	I,B	(I)			ONT	ROL													
																						B		į L	4	ŀ						-+	0.		-10								
1																					0	ON'I	CAF	RE I-	-	i	Н	IGH		н			Si	=C	TIO	N.	E \	×					
	101	ARA	A IVI	IAC	LE	# .				_	1EV				JAI	E _				_	_					-	L	ow		L	(POL	.) [PC	LARI	TY				
																										!																	
Т										A	ND										т											0	R										
E R						ı										B (I)				E R M		E					D					()					B (O)				
М	10	9	8	7	6	5	4	3	2	1	0	8	7	6	5	4	3	2	1	0	м	В	Α	8	7	6	5	4	3	2	1	0	В	Α	8	7	6	5	4	3	2	1	0
0																					0																						
1	-	-	_	_		_	-	-	-	+	\vdash	+	+-	-	-	-	-	-	-	-	1 2	_			-	-			-	-	-	-			_	-	-	-	_			_	_
3	3													+-	+-	-	3	-	-	-		-			-	-	-	\dashv	_	-	-	-	-	-	-	\vdash	_	-	_				
4						_						1									4																						
5																5																											
6 7	-	-	_				-	-	-	-	-	+	-	-	-	-	-	-	-	-	6	_	-		-				-	-	-	-			_	-	-	-	-				_
8	\vdash	-	-	-	-	_	-	-	-	-	+-	+	+-	-	-	-	-	\vdash	+	-	8	-	-	-	-	-	_	-	-	-	-	-		-	-	-	-	+	-		_	\vdash	_
9	-	-	-		-		-	+	-	+	+	+	-	-	-	-	+	+-	+	-	9	-	-	-	-	-	-	-	-		-			-	-	-	-	+				-	_
10	I										_	_									10																						
11	+			S	EC	TIC	NC	Α			-	+		S	EC	TI	NC	В		_	11	-			S	EC	TIC	N	С			-	_			S	EC	CTIC	NC	D			_
13	+										-	+								-	13	-										\dashv	-										_
14	+	ī					,				, -	+		,		î	,		1	_	14	-	7						1			\dashv	-			,	r		ſ				_
15																					15																						
16	-	-	_				_	-	-	-	-	-	-	_	-	_	-	-	-	-	16	_	-							_		_		_	_	-	-	-	-		_		_
17	+	-	-	\vdash	-		-		-	+	+-	+	+	-	-	-	-	-	+	-	17	-	-			-	-	-		-	-	-	-	-	-	+	+	+	-	-	-		-
19	+									+	1	+	+-	+-	-	-	-	+	+-	-	19	-	+-			_							-	-	-	+	+	+	-			-	-
20																					20																						
21																					21																						
22	-	-	-		_	_	-	-	-	-	-	+	-	-		-	-	-	-	-	22	-	-				_						_	-	-	-	-	-	-	-	_	-	-
PIN	11	10	9	8	7	6	-	+	-	2	+	-	-	0.0	200	-	16	1-	4.0	45	23	-	-			-	-		-	_		_	40	10	05	-	-	+	-	-	-	-	
VARIABLE Z	11	10	9	8	/	6	5	4	3	2	1	23	22	21	20	17	16	15	14	13	Notes 1. The FPLA is shipped with all links open. 2. Unused I and B bits in the AND array exist as Don't Care (-) in the virgin state. 3. All P-terms are inactive on all outputs (B, O) in virgin array. 4. Unused product terms can be left blank.											he	19	18	23	22	21	20	17	16	15	14	13


PLHS473 Primer

AN27

OUTPUT POLARITY - (0, B)



AND ARRAY - (I, B)




532

OR ARRAY - (O, B)



NOTES

- 1. This is the initial unprogrammed state of all link pairs.
- 2. Any gate P_n will be unconditionally inhibited if any one of its (I, B) link pairs is programmed for a connection.



VIRGIN STATE

A factor shipped virgin device contains all fusible links.

- 1. All output at "L" polarity.
- 2. All P_n terms are enable.
- 3. All Pn terms are active on all outputs.

June 1988

Once we have determined the outputs, we can proceed with defining the logic functions. As an example, the logic function

is shown in Table 2, term #2 where in the column labeled "INPUT-1", an "H" is entered to represent a connection of the non-inverting input buffer of INPUT-1 and the AND term 2. In the column labelled "INPUT-2", an "L" is entered to represent the connection of the inverting input buffer of INPUT-1 and the AND term 2. On the output side of the table, O_B in term 0 is programmed "A" to make a connection between term 2 and the OR term which is connected to the output pin O_B : The output polarity of O_B is arbitrarily set to Active-High by programming an "H" in the O_B column of the polarity section.

A sum of several product terms (AND-OR) is implemented by connecting multiple AND terms to the same OR term. An example is shown in Table 2, terms 4 and 5, which implement the logic function

OUT-1 = (INPUT-1 */INPUT-2) + (INPUT-3 * INPUT-4)

The logic function

OUT-2 = /((INPUT-1 * INPUT-2) + (INPUT-3 * INPUT-4))

is shown in terms 9 and 10. The output is Active-Low as programmed "L" in the polarity section of OUT-2. As a rule, the AND function is implemented in a row, whereas the OR function is implemented in a column. Since the AND portions of terms 2 and 4 are the same, they may be combined as shown in term 7, which saves a duplicated term.

Table 2 terms 12 and 13 together emulate an open-collector output as an example. The logic equation

is implemented by first programming O-C Active-High in the polarity section. Terms 12 and 13 implement the sum of product function. Notice that the B(O) of O-C is programmed as a "dot" in both terms 12 and 13, which, together with the polarity control, causes it to be unconditionally Low, since a disconnected OR term is unconditionally Low. The intersections of column D7 and terms 12 and 13 are programmed "A" so that the tristate output buffer of B(O)7 is enabled at input conditions (INPUT-1 * INPUT-2) = 1 or (INPUT-3 * INPUT-4) = 1. Terms 10 and 11 may be represented as shown in Figure 3.

Signetics produces a software package, AMAZE, as a design tool which assists implementation of logic design and documentation. For further information on AMAZE software, refer to the AMAZE User's Manual. Two simple circuits shown as examples are implemented using AMAZE. The first circuit is a simple cross-coupled RS latch. The second circuit is a multiplexer/demultiplexer which multiplexes four inputs to one output or demultiplexes one input into four outputs. Both circuits are put into the same PLHS473 device

Table 2. Examples of Programming PLHS473

	ICT	.01	ıer	. A14																			Al	ND		_			0	R		_											
1 -	CUSTOMER NAME														ACTIVE A																												
	PURCHASE ORDER # CF (XXXX)												INACTIVE 0 INACTIVE						ΠVE		B(C))																					
	CUSTOMER SYMBOLIZED PART #												1	(, B H							1																						
	TOTAL NUMBER OF PARTS												ī	Ē	B L CONTROL																												
																				-	1	DON'T CARE - HIGH H																					
Pf	300	3RA	M.	TAE	BLE	#.			_	_ F	REV			[DAT	E_				-	_	LOW L (POL)								POLARITY													
																N H L																											
т										Α	ND										т											C	R										
E	l B (I)													T E R	E				D						(B (O)							_										
М	10	9	8	7	6	5	4	3	2	1	0	8	7	6	5	4	3	2	1	0		В			7	6	5	4	3	2	1	0	В	Α	8	7	6	5	4	3	2	1	0
0	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	0	A	Α	Α	۰	•	•	٠	۰	•	۰	•	•	•	•	•	•	•	٠	•	•	•	
2	4	4	-	-	-	-	-	-	-	-	-	+=	-	-	-	-	-	-	-	-	2								•	•		•	A										
3												<u> </u>	_								3	Ė		Ť															Ě				Ť
4	H		-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	4	•	•	•	•	•	•	•	۰	•	•	•		A	•	•	•	•	•	•	0	•	•
5	-	_	Н	H	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	6		•	·	•	•	•	•	•	•	•	•	•	A	•	•	•		•	•	•		
7	Н	L	-	-	-	-	-	-	-	-		-	-	-	-	-	-	-	-	-	7		•	•	•	•	•	٠	•	•	•	•	A	A	•		•	•	•	•	۰	•	
8																					8														ļ.								
9	Н.	H	-	- H	-	-	-	-	-	-	-	-	=	=	=	=	-	=	=	-	9			•	•	•			•	•	•	0	0	0	A				•		•		
11	-	F	-	"	-	-	-	-	-	-	+	-	-	F	-	-	-	-	F	Ē	11	-	Ť	Ť	Ť	Ť	Ť	Ť	Ť	Ť	Ť	_	Ť	Ť	-	Ť	Ť	Ť	-	٠	Ť	-	Ť
12		Н	_	-	-	-		-	-	-	-	-		-	-	-	-	-	-	-	12	0	•		A	•	•		•		•	•	•				•	•			•		•
13	-	-	н	H	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	13	•	•	•	A	•	•	۰	•	•	۰	•	•	۰	•	•	•	•	•	•	۰	•	
15	\vdash	\vdash				-		-	\vdash	\vdash	-	\vdash	\vdash	-	-		\vdash		_	Н	15	\vdash	-	-						_	Н		_	\vdash	\vdash	\vdash	\vdash	\vdash	-		\vdash		\vdash
16																					16																						
17								_		_			-			_	_				17	_	-																				
19		\vdash	-	-	-	\vdash	\vdash	-	-	-	-	\vdash	-	-	-	-	\vdash			Н	18	\vdash	-	\vdash	-	-	-	-	\vdash		Н	Н	_	-	\vdash	-	\vdash	\vdash	-	-	\vdash	-	\vdash
20																					20																						
21																					21																						
22		-	-	-	-	-	-	-	-	-	+	\vdash	-	-	-	-	-		-	-	22	-	-	-	-		-	-	-	_	\vdash	-	-	-	-	-	\vdash	-	-	-	\vdash	\vdash	\vdash
PIN	11	10	9	8	7	6	5	4	3	2	1	23	22	21	20	17	16	15	14	12	23	\vdash	-	\vdash		-				_	Н	\vdash	10	10	22	22	21	20	17	16	15	14	1
VARIABLE	INPUT-1.	INPUT-2 5		INPUT-4 .	,				3	_		23	22	21	20	17	16	13	14	13	1. 2. 3.	Notes 19 16 23 22 21 20 17 16 18 14 1							13														

TB03100S

```
File Name : 473PRIME
Date : 9/4/1986
Time: 15:53:28
** FNC **PIN ----- PIN** FNC **
            ** I ** 1-: (-24 ** +5V **VCC
** I ** 2-: :-23 ** /0 **Q
15
/R
            N/C
N/C
            ** 1 ** 4-1 L (-21 ** /8 *****/C

** 1 ** 5-1 H (-20 ** 8 ****)

** 1 ** 5-1 H (-19 ** 0 ****/C

** 1 ** 7-1 4 (-18 ** 0 ****/C

** 1 ** 7-1 4 (-18 ** 0 ****/C

** 1 ** 7-1 4 (-18 ** 0 ****/C

** 1 ** 8-1 7 (-17 ** /8 ****/C
N/C
N/C
N/C
N/C
Sú
91
             ** I ** 10-:
                                     1-15 ** 8 **C
                                    1-14 ee B eeB
DIR
             44 1 44 11-1
                                   ;-13 ** B **A
            ** OV ** 12-1
GND
                                                            TB03170S
                   Figure 4. Pin List
```

```
File Name : 473PRIME
Date : 9/4/1986
Time : 15:54:14
@DEVICE TYPE
PLHS473
eDRAWING
erevision
EDATE
       File name = 473PRIME
ecompany
ename
EDESCRIPTION
econnon PRODUCT TERM
eI/O DIRECTION
  "The I/O DIRECTION definition is optional, and may be defaulted
  to the PIN LIST unless it is bidirectional and is controlled by
   a logic equation. "
  * Each output must be defined seperately by its own
                logic equation. "
   07 = 1 :
  ************** I/O DEFINITION FOR MUX/DEMUX CIRCUIT ************ *
    D3 = DIR ; " When DIR = 1, B3, B2, B1, B0 become outputs. Data flows
                from F to A, B, C, D. *
    D2 = DIR ;
   D1 = DIR;
D0 = DIR;
    D5 = /DIR; * When DIR = 0, B5 becomes an output, output buffers
                of BO to B3 are disabled. Data flows from A, B, C,
               Figure 5. Boolean Equations
```

```
COUTPUT POLARITY
 " The definition of output polarity is optional and may be defaulted
   the PIN LIST. "
 " ******* POLARITY DEFINITION FOR R/S LATCH ********** "
                  * Outputs with the same polarity may be defined
                     in the same equation. Since the outputs Q and
                     QNOT are defined as active LOW, this equation
                     causes the XOR to function as an inverter. "
 * ****** POLARITY DEFINITION FOR MUX/DEMUX CIRCUIT ******** *
    X5, X3, X2, X1, X0 = 0; " Outputs B0, B1, B2, B3, B5 are active
                             HIGH. "
@LOGIC EQUATION
 * ********* EQUATIONS FOR R/S LATCH ************************* *
       = /( /S * QNOT ) ; " The equation must used the format
                              output = /( ..... ); since output
                              Q is defined as active LOW. "
    QNOT = /( /R + Q );
 * ******* EQUATIONS FOR MUX/DEMUX CIRCUIT ************* "
    F = (A * /S0 * /S1) +
       ( B * S0 * /S1 ) +
       ( C * /SO * S1 ) +
       (D * SO * S1);
    A = (F * /S0 * /SI);
    B = ( F * SO * /S1 ) ;
    C = (F * /S0 * Si);
    D = (F * S0 * S1);
           Figure 5. Boolean Equations (Continued)
```

```
File Name : 473FRIME
Date : 9/4/1986
Time: 15:56:24
Cust/Project -
Date
Rev/I. D.
PLHS473
                       ! POLARITY !
                       !LLLLLHLHHHH!
R ! _ I _ ! _ B(i) _ !E _ D _ !O _ B(o) _ !
M !!9876543210!876543210!BA876543210!BA876543210!
---!0------!
 0!-----H!-H------!AA..A.A....!AAA.A.A....!
 1'-----H-!H------!AA..A.A....!AA.AA.A....!
 2'-L1-------H'AA..A.A....'AA..AAA....
 3!-LH------!-----H-!AA..A.A....!AA..AAA....!
 4!-HL------!-----H--!AA..A.A....!AA..AAA....!
 51-HH-------!----H---!AA..A.A....!AA..AAA....!
 6!-LL-----!---H----!AA..A.A...!AA..A.A....!
 71-LH------!---H-----!AA..A.A....!AA..A.A.A.A.
 8:-HL-----:-:--H----::AA..A.A....:AA..A.A.A.
 9!-HH-----!--H----!AA..A.A...!AA..A.AA...!
 11'H-----'----'AA..A.AAAAA'AA..A.A....'
 13!----!---!
 141-----
 15!-----!-----!
 181------
 171-----!-----!
 18!-----
 19!----!---!---!
 201------
 21!----!---!
 22!-----!----!
 23!----!---!.....!
   DSSNNNNN// QQNFNDCBA
                        NNQQNFNDCBA
   110/////RS N/ /
                        // N/ /
   R CCCCCC OC C
                        CC 0C C
       Figure 6. Program Table
```

Signetics

AN28 High-Speed 12-Bit Tracking A/D Converter Using PLS179

Application Note

Application Specific Products

INTRODUCTION

The general technique underlying the operation of this A/D converter is illustrated by the fuctional block diagram in Figure 1. The system consists of a D/A converter, a comparator circuit, and digital logic circuitry. The digital logic circuitry outputs a digital vaue which is converted to analog by the D/A converter.

The comparator senses when the output is greater or less than the input and causes the digital circuit to decrement or increment its digital output respectively. The initial conversion is completed in 13 clock cycles. If tracking mode is used, the A/D converter then tracks the input voltage as it changes by incrementing or decrementing 1-LSB per clock. The tracking function makes it possible to make an A/D conversion in one clock cycle if the input changes less than the value of 1-LSB per clock period. The conversion may be halted and the digital output, as well as the converted analog output from DAC, will hold their output constant indefinitely. This feature works well as sample-and-hold since its output voltage will not decay over time whereas the output of an analog sample/hold will decay due to charge leakages.

In order to avoid the violation of setup time by the output of the comparator, its output is latched. There is a built-in 2-phase clock in U2 which may be used to drive the logic circuitry and the latch of the comparator (see Signetics NE5105 data sheet for details on output latches of voltage comparators).

The analog input voltage may be sampled and held by an analog sample/hold circuit to

keep the input to the ADC from changing. The DONE output may be used to control the sample-and-hold if needed.

This paper discusses only the digital circuit which contains the SAR and the Up/Down Counter. The analog circuits are not within the scope of this paper.


SAR

Two PLS179s are connected together to form a 12-bit shift register and up/down counter. The schematic diagram of the A/D converter is shown in Figure 2. U2 contains bits 0 to 4 and U1 contains Bits 5 to 11. Interconnects are made as shown in the diagram. The digital output to the DAC is in natural binary format (e.g. 0000 0000 0000 egual zero, and 1111 1111 1111 is full scale or 4095). After the/ST input becomes 0, at the rising edge of the next clock, the SAR is initialized to halfscale (1000 0000 0000) and the DONE flipflop is reset to output 0 which causes the open-collector output /DONE_OC to become high impedance. The digital output is converted by the DAC and is compared to the analog input voltage by the comparator. If the digital output is greater than the analog input, the SAR shifts the 1 to next MSB on the right. The content of the SAR becomes (0100 0000 0000). If the digital output is still greater than the input, the SAR shifts right one bit again. The content of the SAR then becomes (0010 0000 0000). The shifting of 1 to the next MSB in equivalent to reducing by half the value of the bit under consideration. If the output is still too large, the SAR reduces it by half again by shifting to the right one more time.


The SAR keeps shifting to the right until the digital output is less than the input. When the output is less than the input, the SAR adds one bit to the next MSB while keeping all the higher order bits unchanged. For example, if the current output is 0001 0000 0000 and the output is less than the input, the SAR adds one bit to the right at the next clock. The output becomes 0001 1000 0000. The output is again compared to the input. If the addition of that one bit is too much, it will be shifted to the right until the output becomes less than the input. When that happens, that SAR will again add one bit to the right. The algorithm of the SAR may be summarized as the following: If the output is greater than the input, shift to the right; otherwise add one bit to the right. This process continues until all 12 bits have been operated on. The last bit (Bit 0) is always changed from 0 to 1, which is used as the condition to set DONE to 1 which, in turn, sets open-collector output, /DONE OC, to 0.

UP/DOWN COUNTER

After DONE becomes 1, if /ST and /HOLD are 1 and /TRACK is 0, the SAR turns into a 12-bit up/down counter. If the analog input voltage increases, the counter will increment by 1 at every clock until it matches the input. If the input decreases, the counter will decrement by 1. When /HOLD becomes 0, the counter is inhibited and the output is held indefinitely. The counters consist of 12 toggle flip-flops and 2 p-terms per flip-flop for directional control. The counter will operate only



AN28



AN28

after the approximation cycle is completed and DONE is 1.

Since the /ST and /HOLD inputs may be asynchronous with the clock, in order to minimize the possibilities of having a metastable condition from happening, these inputs close-up are latched by flip-flops /START of U1 and /HLD of U2 respectively. Once they are latched, subsequent operation begins at the rising-edge of the next clock. The output of the comparator may be latched to prevent setup time violation. (Signetics NE5105 is a high-speed comparator with an output latch. External latch may be used with other comparators.)

CLOCKS

U2 generates an optional 2-phase clock which may be used to control the latch of the comparator. The two clocks are basically 180° out of phase and CLOCK2 has an additional 25ns propagation delay behind CLOCK1. CLOCK2 is used to drive the clockinputs of the PLS179 devices.

The clock frequency is controlled by R and C. Those who want to use the built-in clock

should experiment with RC time constants for the best value. It is recommended that the capacitance should be less than 1000pF for best results (see Ap Note AN13 for more detail).

DONE AND /DONE_OC

The output DONE is reset to 0 when /ST is 0. It remains 0 until the approximation cycle is completed. After the least significant bit becomes 1, the DONE bit becomes 1 at the next clock. It remains 1 until it is reset again by input /ST.

The /DONE_OC output is configured to emulate an open-collector output. The output is programmed to have a logic 0. When DONE is 0, the Tri-state output buffer is set to Hi-Z condition. As soon as DONE equals 1, the Tristate buffer is enabled and /DONE_OC becomes 0.

In the initial phase of A/D conversion, 13 clock cycles are required. It is essential that the input voltage to the comparator remains unchanged while the SAR is converting. It may be necessary to have a sample/hold at


the front end. The DONE output may be used to control the analog sample/hold circuit.

INPUT LATCHES

Flip-flop /START and 2 p-terms in U1 are configured as a non-inverting D flip-flop. The input, /ST, and the output /START have the same polarities. Flip-flop /HLD and 2 p-terms in U2 also form a non-inverting D flip-flop. The output /HLD and the input /HOLD have the same polarities.

AMAZE INPLEMENTATION

The implementation of the logic circuit using AMAZE is as shown in the appendices. The SAR circuit is first designed as a state machine (file name: ADCS.SEE). It is then partitioned into two PLS179s after proper pin assignments are made. Then the up/down counter, input latches, 2-phase clocks and the open-collector output, are implemented by using Boolean equations in their respective .BEE files (file names: ADCB1.BEE and ADCB2.BEE) in AMAZE. The files are then assembled to produce the fuse-maps of PLS179 (ADCB1.STD and ADCB2.STD).



AN₂₈

APPENDIX A: STATE EQUATIONS OF SAR

```
File Name : ADCS
Date : 10/21/1986
Time : 11:2:14
@DEVICE SELECTION
ADCB1/PLS179
ADCB2/PLS179
<u>@STATE VECTORS</u>
C /START, BIT11, BIT10, BIT9, BIT8, BIT7, BIT6, BIT5, BIT4, BIT3, BIT2, BIT1, BIT0, DONE ]
                                                  "START CONVERSION PROCESS"
HALFSCALE, = - 1000 0000 0000 0 b;
ST204B = 1 1000 0000 0000 0 b;
                                                  "SET SAR TO HALF SCALE"

"PRESENT STATE = 2048 (HALF SCALE)"
             = 1 -100 0000 0000 0 b;
             = 1 --10 0000 0000 0 b;
= 1 ---1 0000 0000 0 b;
ST512
ST256
             = 1 ---- 1000 0000 0 b;
= 1 ---- -100 0000 0 b;
= 1 ---- -10 0000 0 b;
ST128
ST64
ST32
             = 1 ---- 10000 0 b;
= 1 ---- 1000 0 b;
= 1 ---- 1000 0 b;
STB
ST4
              = 1 ---- --- --10 0 b;
= 1 ---- --- 10 b;
ST1
             = - -1-- --- - b ;
= - -1- --- - b ;
= - --1 --- - b ;
AD1024
                                                  "ADD 1 BIT TO THE RIGHT"
AD512
              = ---- -b;
= ----- -b;
= ----- -b;
AD128
AD64
AD32
              = - ---- - b
AD16
              = - ---- 1--- b ;
AD8
              = - ---- --- b
An2
              = - ---- ---1 - b ;
AD1
SH1024
              = - 01-- --- - b :
                                                  "SHIFT ONE BIT TO THE RIGHT"
SH512
              = - -01- ---- - b ;
= - --01 ---- - b ;
SH256
              = - ---0 1--- - b ;
SH128
SH64
              = - ---- 01-- --- b
              = ---- 01- --- b;
= ---- -01 --- b;
= ---- b;
SH32
SH16
SHB
              = - ---- 01-- - b :
SH4
              = - ---- -01- - b ;
              = - ---- --- 1 b
SHO
@INPUT VECTORS
[ COMPARE ]
GREATER = 1 b ; "IF DIGITAL OUTPUT IS GREATER THAN ANALOG INPUT, ...." LESS = 0 b ; "IF DIGITAL OUTPUT IS LESS THAN ANALOG INPUT, ...."
@OUTPUT VECTORS
```

AN28

APPENDIX A: STATE EQUATIONS OF SAR (Continued)

```
@TRANSITIONS
WHILE [ INIT ]
            IF [] THEN [ HALFSCALE ] "INITIALIZE REGISTER TO HALF SCALE"
WHILE [ ST2048 ]
            IF [ GREATER ] THEN [ SH1024 ] "IF GREATER THAN, SHIFT 1 BIT"
IF [ LESS ] THEN [ AD1024 ] "IF LESS THAN, ADD 1 BIT"
WHILE [ ST1024 ]
            IF [ GREATER ] THEN [ SH512 ]
IF [ LESS ] THEN [ AD512 ]
WHILE [ ST512 ]
            IF [ GREATER ] THEN [ SH256 ]
IF [ LESS ] THEN [ AD256 ]
WHILE [ ST256 ]
            IF [ GREATER ] THEN [ SH128 ]
IF [ LESS ] THEN [ AD128 ]
WHILE [ ST128 ]
            IF [ GREATER ] THEN [ SH64 ]
IF [ LESS ] THEN [ AD64 ]
WHILE [ ST64 ]
            IF [ GREATER ] THEN [ SH32 ]
IF [ LESS ] THEN [ AD32 ]
WHILE [ ST32 ]
            IF [ GREATER ] THEN [ SH16 ]
IF [ LESS ] THEN [ AD16 ]
WHILE [ ST16 ]
            IF [ GREATER ] THEN [ SHB ]
IF [ LESS ] THEN [ ADB ]
WHILE [ ST8 ]
            IF [ GREATER ] THEN [ SH4 ]
IF [ LESS ] THEN [ AD4 ]
WHILE [ ST4 ]
            IF [ GREATER ] THEN [ SH2 ]
IF [ LESS ] THEN [ AD2 ]
WHILE [ ST2 ]
            IF [ GREATER ] THEN [ SH1 ]
IF [ LESS ] THEN [ AD1 ]
            IF [ GREATER ] THEN [ SHO ]
IF [] THEN [END]
```

541

June 1988

AN28

APPENDIX B: PIN LISTS

```
File Name : ADCB2
Date : 10/21/1986
Time : 10:58:26
                ########

** FNC **PIN ---

** CK ** 1-:

** I ** 2-:

** I ** 3-:

** I ** 4-: P

** 5-: L

6-: S
** FNC **PIN ----- PIN** FNC **
                                                !-24 ** +5V **VCC
!-23 ** /B **/DONE_OC
CLOCK
/START
COMPARE
                                                1-22 ** B
                                                                 **N/C
                                               1-22 ** B
1-21 ** 0
1-20 ** 0
1-19 ** 0
                                                                 **/HLD
**BIT4
/HOLD
/TRACK
BIT5
N/C
N/C
                 ** I
                           ** 7-1
** 8-1
                                                :-18 ** 0
:-17 ** 0
                                                                 **BIT2
**BIT1
                                                :-16 ** 0
:-15 ** 0
:-14 ** /0
N/C
                           ** 9-1
                                                                 **BITO
                 ** /B ** 10-;
** 0 ** 11-;
RC.
                                                                 **DONE
CLOCK1
                                                                 **CLOCK2
GND
                 ** OV
                                                1-13 ** /OE **N/C
                                                                                TB03340S
```

```
File Name : ADCB1
Date : 10/21/1986
Time : 10:53:7
LABEL
                ** FNC **PIN ----- PIN** FNC **
                ** CK ** 1-;

** I ** 2-;

** I ** 3-;
CLOCK
                                             !-24 ** +5V **VCC
!-23 ** /B **N/C
/ST
                                             | -23 ** /B
| -22 ** 0
| -21 ** 0
| -20 ** 0
| -19 ** 0
| -18 ** 0
| -17 ** 0
COMPARE
                                                              **/START
/HLD
                                                              **BIT11
/TRACK
                          ** 5-1
** 6-1
                                                              **BIT10
                               6-1
7-1
                                       S
                                                              **BIT9
BITT
                                                              **BIT8
BIT2
                          **
                               8-:
9-:
                                             (-16 ** 0
(-15 ** 0
                                                              **BIT6
BITO
                ** T
                          ** 10-1
                                                              **BIT5
                          ** 11-!
                                             1-14 ** /B **N/C
1-13 ** /OE **N/C
GND
                                                                             TB03370S
```

AN28

APPENDIX C: BOOLEAN EQUATIONS OF UP/DOWN COUNTER AND INPUT LATCH

```
File Name : ADCB1
Date : 10/21/1986
Time: 10:54:48
@DEVICE TYPE
PLS179
EDRAWING
eREVISION
esymbol
         FILE NAME : ADCB1
@COMPANY
@NAME
@DESCRIPTION
@COMMON PRODUCT TERM
@COMPLEMENT ARRAY
@I/O DIRECTION
@OUTPUT POLARITY
@FLIP FLOP CONTROL
            FC = 1;
                                                       "SET ALL FLIP FLOP TO BE J/K"
COUTPUT ENABLE
@REGISTER LOAD
 @ASYNCHRONOUS PRESET/RESET
@FLIP FLOP MODE
 @LOGIC EQUATION
   "NON-INVERTING INPUT LATCH: /START = /ST "
     START : J = ST ;
                         K = /ST ;
   "UP/DOWN COUNTER ROUTINE"
     /BIT5 : T = /START * TRACK * DONE * /HLD * COMPARE * /BIT0 * /BIT1 *
                                       /BIT2 * /BIT3 * /BIT4 +
                                      /START * TRACK * DONE * /HLD * /COMPARE * BITO * BIT1 *
    /START * IRALK * DUNE * /NLD * /OSH NHL BIT2 * BIT3 * BIT4 * /NLD * COMPARE * /BIT0 * /BIT1 * /BIT2 * /BIT3 * /BIT4 * /BIT5 + /START * TRACK * DONE * /HLD * /COMPARE * BIT0 * BIT1 * BIT2 * BIT3 * BIT4 * BIT5 * (COMPARE * BIT0 * BIT1 * BIT2 * BIT3 * BIT4 * BIT5 * (COMPARE * BIT5 * BIT4 * BIT5 * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * COMPARE * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HLD * /HL
     /BIT7 : T = /START * TRACK * DONE * /HLD * COMPARE * /BIT0 * /BIT1 * /BIT2 * /BIT3 * /BIT4 * /BIT5 * /BIT6 +
     /START * TRACK * DONE * /HLD * /COMPARE *

BITO * BIT1 * BIT2 * BIT3 * BIT4 * BIT5 * BIT6;

/BIT8 : T = /START * TRACK * DONE * /HLD * COMPARE * /BIT0 * /BIT1 *
                                      /BIT2 * /BIT3 * /BIT4 * /BIT5 * /BIT6 * /BIT7 +
                                      /START * TRACK * DONE * /HLD * /COMPARE *
                                                                                                                                                  BITO * BIT1 *
     BIT2 * BIT3 * BIT4 * BIT5 * BIT6 * BIT7 ;

/BIT9 : T = /START * TRACK * DONE * /HLD * COMPARE * /BIT0 * /BIT1 * /BIT2 * /BIT3 * /BIT4 * /BIT5 * /BIT6 * /BIT7 * /BIT8 +
                                      /START * TRACK * DONE * /HLD * /COMPARE * BITO *
     BIT2 * BIT3 * BIT4 * BIT5 * BIT6 * BIT7 * BIT8 ;
/BIT10 : T = /START * TRACK * DONE * /HLD * COMPARE * /BIT0 * /BIT1 *
/BIT2 * /BIT3 * /BIT4 * /BIT5 * /BIT6 * /BIT7 * /BIT8 *
                                      /BIT9 +
                                      /START * TRACK * DONE * /HLD * /COMPARE * BITO * BIT1 *
                                        BIT2 * BIT3 * BIT4 * BIT5 * BIT6 * BIT7 * BIT8 *
                                        BIT9 ;
     /BIT11 : T = /START * TRACK * DONE * /HLD * COMPARE * /BIT0 * /BIT1 *
                                      /BIT2 * /BIT3 * /BIT4 * /BIT5 * /BIT6 * /BIT7 * /BIT8 *
                                      /BIT9 #
                                      /BIT10 +
                                      /START * TRACK * DONE * /HLD * /COMPARE * BITO * BIT1 *
                                        BIT2 * BIT3 * BIT4 * BIT5 * BIT6 * BIT7 * BIT8 *
                                        BIT9 * BIT10 ;
                                                                                                                                                                                 TB03390S
```

AN28

APPENDIX C: BOOLEAN EQUATIONS OF UP/DOWN COUNTER AND INPUT LATCH (Continued)

```
File Name : ADCB2
          Date : 10/21/1986
          Time : 10:58:56
          @DEVICE TYPE
          PI 5179
          @DRAWING
          @REVISION
@DATE
          esymbol
            FILE NAME : ADCB2
          @COMPANY
          GNAME
          @DESCRIPTION
          @COMMON PRODUCT TERM
          @COMPLEMENT ARRAY
          @I/O DIRECTION
                 DO = RC ;
D3 = DONE :
                                              "RC OSCILLATOR"
                                             "ENABLE /DONE_OC TO OUTPUT A LOGIC LOW."
          @OUTPUT POLARITY
          @FLIP FLOP CONTROL
FC = 1 ;
@OUTPUT ENABLE
          @REGISTER LOAD
@ASYNCHRONOUS PRESET/RESET
          @FLIP FLOP MODE

"MO, M1, M2, M3, M4, M5 = 1; SET FO - F5 TO J/K FLIP FLOPS."
          @LOGIC EQUATION
  "NON-INVERTING INPUT LATCH : /HLD = /HOLD "
            HLD : J = HOLD ;
K = /HOLD ;
           "UP/DOWN COUNTER ROUTINE"
           "UP/DOWN COUNTER ROUTINE"

/BITO : T = /START * TRACK * DONE * /HLD * /COMPARE * BITO * /START * TRACK * DONE * /HLD * /COMPARE * /BITO ;

/BIT1 : T = /START * TRACK * DONE * /HLD * COMPARE * /BITO ;

/BIT2 : T = /START * TRACK * DONE * /HLD * /COMPARE * BITO * BIT1 * /START * TRACK * DONE * /HLD * COMPARE * BITO * /BIT1 ;

/BIT3 : T = /START * TRACK * DONE * /HLD * /COMPARE * BITO * BIT1 *
BIT2 +
                               /START * TRACK * DONE * /HLD * COMPARE * /BITO * /BIT1 * /
BIT2 ;
           /BIT4 : T = /START * TRACK * DONE * /HLD * /COMPARE * BITO * BIT1 *
BIT2 *
                                BIT3 +
                               /START * TRACK * DONE * /HLD * COMPARE * /BITO * /BIT1 * /
BIT2 *
                              /BIT3 ;
           /DONE_OC = /( 1 ) ;
            "RC OSCILLATOR"
                        = /(1);
= RC;
= /( CLOCK1 );
             CLOCK1
                                                            "BUILT-IN DELAY OF 1 tPD"
```

AN28

APPENDIX D: U1 ADCB1 FUSE MAP

```
File Name : ADCB1
Date : 10/21/1986
Time: 10:56:5
Cust/Project -
Date
Rev/I. D.
PLS179
                                  0|A|---,---!A-A-A!
1|A|---,---!A-A-A!
  21A1L L L,L H H -!- - H L!L - - -,- - - -!- - - -,- - - 01A A A A!
  2:A:H H H H,L H L -!- - H H:L - - -,- - - - -!- - - -,- - - 0:A A A A!
4:A:L L L,L H H -!- - H L:L - - -,- - - H!- - - -,- - 0 -!A A A A!
5:A:H H H H,L H L -!- - H H:L - - -,- - - L!- - - -,- - 0 -!A A A A!
  6:A:L L L,L H H -!- - H L:L - - -,- - H H!- - - -,- 0 - -!A A A A!
  7!A!H H H H,L H L -!- - H H!L - - -,- - L L!- - - -,- Q - -!A A A A!
  BIAIL L L L, L H H -!- - H L!L - - -, - H H H!- - - -, 0 - - -!A A A A!
  91A1H H H H,L H L -!- - H H!L - - -,- L L L!- - -,0 - - -!A A A A!
 10!A!L L L L,L H H -!- - H L!L - - -,H H H H!- - - 0,- - - -!A A A A!
 11:A:H H H H,L H L -!- - H H!L - - -,L L L L!- - - 0,- - - -!A A A A!
 12!A!L L L,L H H -!- - H L!L - - H,H H H H!- - 0 -,- - - -!A A A A!
 13!A!H H H H,L H L -!- - H H!L - - L,L L L L!- - 0 -,- - - -!A A A A!
 14:ALL L L,L H H -!- - H L!L - H H,H H H H!- 0 - -,- - - -!A A A A!
15:A!H H H H,L H L -!- - H H!L - L L,L L L L!- 0 - -,- - - -!A A A A!
 16!A!- - - -,- - - -!- - - -!H - - -,- - - -!- L H H,H H H H!A A A A!
 17:A:L L L L,- - H -!- - L L!L L H H,H H H H!- H L -,- - - -!A A A A!
18:A:L L L L,- - L -!- - L L!L L H H,H H H H!- - L -,- - - -!A A A A!
 19:A:L L L,- - H -!- - L L!L - L H,H H H H!- - H L,- - - -!A A A A!
19181 L L L, - H -!- L L!L - L H, H H H H!- - H L, - - -!A A A A!
20181 L L L, - L -!- L L!L - L H, H H H H!- - L, - - -!A A A A!
21181 L L L, - H -!- L L!L - L H, H H H!- - H, L - -!A A A A!
22181 L L L, - H -!- L L!L - L, H H H H!- - -, L - -!A A A A!
23181 L L L, - H -!- L L!L - - L, H H H H!- - -, H L -!A A A A!
23181 L L L, - H -!- L L!L - -, L H H H!- - -, L -!A A A A!
25181 L L L, - H -!- L L!L - -, L H H H!- - -, H L -!A A A A!
 26!A!L L L,- - L -!- - L L!L - - -,- L H H!- - - -,- - L -!A A A A!
 27!A!L L L,- - H -!- - L L!L - - -,- - L H!- - - -,- - H L!A A A A!
 281ALL L L, - L -!- - L L!L - - -, - - L H!- - - -, - - - L!A A A A!
291ALL L L, - - H -!- - L L!L - - -, - - - L!- - - -, - - - H!A A A A!
 Fc!A!- - - - - - - - - - - - - - -
 Pb!.!0 0 0 0,0 0 0 0!0 0 0 0!0 0 0 0,0 0 0 0!
 Rb!.!0 0 0 0,0 0 0 0!0 0 0 0!0 0 0 0,0 0 0 0!
 Lb!.!0 0 0 0,0 0 0 0!0 0 0 0!0 0 0 0,0 0 0 0!
 Pa!.!0 0 0 0,0 0 0 0!0 0 0 0!0 0 0 0,0 0 0 0!
 Ra! . ! 0 0 0 0,0 0 0 0!0 0 0 0!0 0 0 0,0 0 0 0!
 La!.!0 0 0 0,0 0 0 0!0 0 0 0!0 0 0 0,0 0 0 0!
 D3!.!O O O O,O O O 0!O O O!O O O,O O O!
 D2!.!O O O O,O O O O!O O O O!O O O O,O O O O!
 D1:.!0 0 0 0,0 0 0 0!0 0 0!0 0 0 0,0 0 0 0!
 DO!.!O O O O,O O O O!O O O!O O O,O O O
       B B B B / / C / N N D B / B B B B B B B B B B B B B N N D B
       I I I I T H O S / / D I S T I I I I I I S I I I I I I I / / O I
       TTTTRLMTCCNTTTTTTTTTTTTTTTCCN
                        E 0 A 1 1 9 B 7 6 5 A 1 1 9 B 7 6 5
                                   R 1 0
                                                     R 1 0
                   A
```

AN28

APPENDIX D: U2 ADCB2 FUSE MAP (Continued)

```
File Name : ADCB2
Date: 10/21/1986
Time: 11:0:7
Cust/Project -
Date
Rev/I. D.
PLS179
                   A:A:A:A:A:A:A:A: O ! O !L:L:H:L!
R!! I ! B(i) ! Q(p) !
  _!7_6_5_4_3_2_1_0!3_2_1_0!7_6_5_4_3_2_1_0!7_6_5_4_3_2_1_0!3_2_1_0!
 2!A!----,L--H!----!-L--,---L!0---,-
 3!A!----,L - L H!----!- L --,-- L L!O ---,- O --!. .
 4!A!- - - -,L - H H!- - - -!- L - -,- - H L!O - - -,- O - -!. . . .
 5!A!- - - -,L - L H!- - - -!- L - -,- L L L!O - - -,O - - -!. ...
131A!----,---!--H-!----,----!. A
14!А!- - - -,- - - L!- - - -!- - - -,- - - -!0 - н н,н н н н!. . .
17!A!- - - -,- - H H!- - - -!- - L H,H H H H!O - H L,- - - -!. .
18!A!----L H!----L H,H H H H!O -- L,----!. .
271010 0 0 0,0 0 0 010 0 0 010 0 0 0,0 0 0 010 0 0 0,0 0 0 01A A A
28:0!0 0 0 0,0 0 0 0!0 0 0 0!0 0 0 0,0 0 0 0!0 0 0 0,0 0 0 0!A A A A!
29!0!0 0 0 0,0 0 0 0!0 0 0 0!0 0 0 0,0 0 0 0!0 0 0 0,0 0 0 0!A A A A!
30!0!0 0 0 0,0 0 0 0!0 0 0 0!0 0 0 0,0 0 0 0!0 0 0 0,0 0 0 0!A A A A!
31!0!0 0 0 0,0 0 0 0!0 0 0 0!0 0 0 0,0 0 0 0!0 0 0 0,0 0 0 0!A A A A!
Pb!.!0 0 0 0,0 0 0 0!0 0 0 0!0 0 0 0,0 0 0 0!
Rb!.!0 0 0 0,0 0 0 0!0 0 0 0!0 0 0 0,0 0 0
Lb!.!0 0 0 0,0 0 0 0!0 0 0 0!0 0 0 0,0 0 0 0!
Pat. 10 0 0 0,0 0 0 010 0 0 010 0 0 0,0 0 0 0
Ra!.!0 0 0 0,0 0 0 0!0 0 0 0!0 0 0 0,0 0 0 0!
La!.!0 0 0 0,0 0 0 0!0 0 0 0!0 0 0 0,0 0 0 0!
D3!-!- - - -,- - - -!- - - -!- - - -,- - - -!
N N N B / / C / / C C R N / B B B B B D N / B B B B B D / C C R
   ///ITHOSDLLC/HIIIIIO/HIIIIIODLL
   CCCTROMTOOO CLTTTTTNCLTTTTTNOOO
       SALPANCC
                    D 4 3 2 1 0 E
                              D 4 3 2 1 0 E N C C
         CDAREKK
           RT
                                         ō
           Ε
              ō
```

Signetics

AN29 PLHS501 Programmable Macro Logic Primer

Application Note

Application Specific Products

SUMMARY

The evolution of Programmable Logic Devices (PLD's) has led to the birth of a new generation of programmable devices designated as PML (Programmable Macro Logic). The immense versatility of these devices brings them closer as plausible alternatives to semicustom design approaches in low-to-medium ranges of applications. The following paper begins with a background on PML and a brief description of the PML basic architecture (See Reference 1.) Next, the first PML devices are introduced with a detailed discus-

sion of the PLHS501. The implementation of PML in the AMAZE software package is presented. A system level example intends to demonstrate the capabilities of PML as an eloquent and efficient design alternative.

THE EMERGENCE OF THE THIRD GENERATION PLD ARCHITECTURE

PML was introduced at WESCON '85 by Signetics Corporation. The unique architecture of PML breaks away into a new era of programmable logic devices. The purpose of the PML architecture is to overcome the two level AND-OR bottleneck and provide the user with a higher level of logic integration. Current PLD's rely on two levels of logic transformation to implement combinational logic in Sum-Of-Products (SOP) form. In addition various PLD's make use of higher level macros such as flip-flops to form sequential logic functions. These macros connect the AND-OR chain to dedicated I/O pins.

Figure 1 show the basic architecture of one of the most recent PALTM devices. It is clear that this architecture is inefficient in making full use of the available on-chip resources. This is due to the fact that an unused I/O macro will be wasted and remains futile.


For example, if an I/O pin is used as an input, the output macros are all wasted. Obviously, such an architecture cannot provide the user with an increase in the levels of logic integration. The PML device takes advantage of the fundamental architecture shown in Figure 2 to overcome these deficiencies and waste of on-chip resources. As shown in Figure 2, PML incorporates the NAND-NAND gate equivalence to break the AND-OR bottleneck.

The core of the PML is the programmable NAND-NAND network which connects the input and output macros to each other. Thus the inputs, outputs, and function macros are all connected by a single array.

At the present, two devices are under development which employ the above architecture. Both devices are fabricated by the Signetics state-of-the-art oxide isolation process and are packaged in 52-pin PLCC.

The first device available will be the PLHS501. The seemingly simple structure of this device can implement every logic function furnished by the current PALTM/PLA devices. Although the PLHS501 is principally a combinational logic device, its unique architecture makes it an ideal tool for applications involving asynchronous state machines (See Reference 2.)


The PLHS502 is a sequential logic device. It supplements the PLHS501 features with sixteen edge-triggered flip-flops. The device can provide diverse applications encompassing synchronous and asynchronous state machine designs.



AN29

Table 1. Functional Description of PLHS501 I/O Pins

PIN NO.	IDENTIFIER	FUNCTION
41-45, 47-52, 1-7, 9-14	10-123	Dedicated inputs
37-40	/B0-/B3	Fuse-programmable bidirectional I/Os with Active-Low outputs. Can be configured as open-collector outputs.
15-18	B4-B7	Logic controlled bidirectional I/Os with Active-High Tri-state outputs.
28-29 30-31 32-33 35-36	X0-X1 X2-X3 X4-X5 X6-X7	Pairs of Tri-state Exclusive-OR outputs that have common Output Enable.
19, 21 22-23	O0-O1 O2-O3	Pairs of dedicated Active-Low Tri-state output buffers. Each pair has common Output Enable control.
24-25 26-27	O4-O5 O6-O7	Pairs of dedicated Active-High Tri-state output buffers. Each pair has common Output Enable control.



AN29


THE PLHS501 PML

The PLHS501 architecture in Figure 3 exhibits an exquisite logic tool. The device provides a combination of 72 NAND terms, 24 dedicated inputs (I0-I23), eight bidirectional I/O's (B0-B7), eight exclusive-OR outputs (X0-X7),

and eight dedicated outputs (O0-O7). Figure 4 shows the PLHS501 logic diagram and Table 1 illustrates the functional breakdown of the PLHS501 I/O pins.

Since the output of each NAND term feeds back to the inputs of the NAND array, intri-

cate logic functions can be implemented without wasting valuable I/O pins. For example, in order to implement an internal 'RS' latch in a combinational PALTM/PLD, at least two inputs and two outputs are required. The same internal latch can be configured by the PLHS501 without using any I/O pins.



AN29






Figure 5 illustrates how 'RS' and 'D' latches are implemented in the PLHS501.

Another eminent application of the PLHS501 is in generating asynchronous state machines.

The blend of internal feedback paths together with the abundant number of gates makes this device suitable for designing asynchronous state machines which employ propagation delays of feedback paths as memory elements as shown in Figure 6. (See Reference 2.)



AN29



PML DEVELOPMENT SOFTWARE

Programmable logic development software has become an integral part of the PLD design process. Without software tools PLDs become perplexing devices which are inconvenient to use. Development software enables the user to take full advantage of the programmable logic's resources. The complexity of the PML devices makes software an indispensable element in the design process.

The AMAZE PLD design software, as noted in Reference 3, has been developed for Signetics programmable logic devices. PML

design and development will be fully supported by AMAZE. Figure 7 shows the AMAZE configuration for supporting PML. The structure of the software is based on the following modules:

.BLAST (Boolean Logic And State Transfer entry)

.DPI (Device Programmer Interface)
.SIM (PLD functional SIMulator)

.PI (PML Integrator)

The foundation for the above modules is an AMAZE standard fuse file (STD). The STD file is the common means of communication between all the modules. The following para-

graphs briefly explain the implementation of PML in the AMAZE structure.

BLAST


The basic elements of BLAST are:

- 1. Boolean Equation Entry (BEE).
- 2. State Equation Entry (SEE).
- 3. Schematic To Boolean Converter (STBC).
- BEE accepts user defined logic in the form
 of boolean equations and produces an
 AMAZE standard fuse file. The boolean notation in BEE will account for the following PML
 features.
- a. The single array architecture provides an option to specify the number of logic (gate) levels that accommodate a specified function. The number of gate levels dictate the delay between the inputs and outputs. The number of logic levels for each function can be specified using the following notation:

LABEL [number of logic levels] = equation; where LABEL is the user designated name of the output pin.

b. Some outputs have more than one gate associated with them (for example registered or EXOR outputs). The input SIDE of these outputs can be specifically defined. For example:

- c. User definable CLOCK Logic (e.g. as in the PLHS502) can be specified.
- d. For PML devices the Sum-of-Products (SOP) can be defined as common terms.



AN29

- SEE accepts state machine definitions and produces the AMAZE standard fuse file. Particularly, SEE will include asynchronous state machine implementations utilizing the PLHSS01.
- STBC converst schematic netlists produced by CAD systems such as FuturenetTM,
 Daisy, and Mentor into an AMAZE BEE file.
 STBC will fully embody the PML in the following manner:
- a. De Morgan's theorem is applied to produce equations in SOP form. All the functions in SOP form are then converted into their NAND- NAND equivalent.
- The converter will determine the polarity and the number of levels in each equation and will automatically determine the correct output polarity.

DPI

Device Programmer Interface provides the interface between the AMAZE standard fuse file and a commercial programmer. It allows the transmission of data to and from the device programmer.

SIM

The functional simulator uses the AMAZE standard fuse file in the following manner:

- a. An event driven simulator will assess the delays within the PML in order to properly simulate the pattern.
- b. Automatically generates test vectors for the pattern simulation.

PI

The PML Integrator is a conversion that transforms various PALTM or PLD circuits into a PML device. It will automatically fit multiple PALTM/PLD devices into a single PML. It is capable of automatically receiving patterns from a commercial device programmer and downloading it back to the programmer after the PML transformation. The implementation of an 'Integrator' will allow the automatic conversion of numerous PALTM/PLDs into a single PML device.

AMAZE will not be the total extent of development software available for the PML devices. The task of implementing PML design software is already underway by a number of different vendors of CAD software.

PLHS501 DESIGN EXAMPLE


The following example intends to manifest the capabilities of the PLHS501. Figure 8 shows a system formed with TTL logic. The system requirements make it imperative only to use discrete asynchronous latches. Thus, none of the 7 latches in the system can be directly replaced by registers. The system diagram is drafted using FuturenetTM DASH-2 Schematic Designer. The system is partitioned into two PLS173s and one PLS153. In order to convert the system into its targeted PLD's, the PINLIST (see Figures 9a-9c) has to be defined. Using the AMAZE PIN-LIST editor, the specified PLD's are labeled with the same labels as those on the system schematic (Figure 8). After the declaration of labels, AMAZE automatically converts the system to the designated PLDs. The AMAZE

generated boolean equation files are shown in Figures 9a, 9b, and 9c. Figure 10 shows the overall system implemented with PLDs. The logic condensation capabilities of PML makes it feasible to replace the whole system by a single PLHS501 (Figure 11). The PLHS501 in this design will still have ample space for any future additions.

The above example demonstrates only part of the PLHS501 capabilities. The introduction of PML devices and their immense logic power will pave the way for a new generation of efficient and elegant systems.

REFERENCES


- Cavlan, Napoleone 1985. "Third Generation PLD Architecture Breaks AND-OR Bottleneck", WESCON 1985 Conference Proceedings.
- 2. Wong, David K. "Third Generation PLS Architecture and its Applications", Electro 1986 Conference Proceedings.
- 3. "1986 PLD Data Manual", Signetics Corporation



AN29

```
File Name : PART1
Date: 12/10/1986
Time: 18:25:54
** FNC **PIN ------ PIN** FNC **
                                             LABEL
          ** I ** 1-!
                            1-24 ** +5V **VCC
INIA
          ** I ** 2-1
** I ** 3-1
INIB
                             1-23 ** 0
                                       **OUT1I
0136
                            1-22 ** 0 **OUT1H
                ** 4-! P !-21 ** 0 **OUT1G
INID
                ** I
INIE
          ** I
OT3AIN1F
                                        **OT1EIN3B
IN16
          ** I
                ** 8-1 7 1-17 ** 0 **OT1C
INIH
          ** I
          ** I ** 9-! 3 !-16 ** 0 **OT1BIN3A
IN1I
          ** I
                ** 10-1
LIMI
                             1-15 ** 0
                                       **OUT1A
OT3EIN1K
          ** I
                ** 11-1
                             1-14 ** I **OT2CIN1M
         ** OV ** 12~!
                             1-13 ** I
GND
                                       **IN1L
File Name : FART1
Date: 12/10/1986
Time: 18:26:56
@DEVICE TYPE
 PLS173
@DRAWING
GREVISION
@DATE
@SYMBOL_
@COMPANY
@NAME
 PART1
@DESCRIPTION
@I/O DIRECTION
@LOGIC EQUATION
     OUT1A =/IN1A*/IN1B*(IN1J+/OT3AIN1F);
     OTIBIN3A =/IN1B*IN1I:
     OTIC =/IN1H+OT2CIN1M+/IN1D*/OT3AIN1F+OT3EIN1K;
     OUTID = INIB+/INIJ:
     OTIEIN3B =/IN1B*IN1J+OT2CIN1M+/OT3G*IN1A+/IN1A*/IN1G;
     OTIF =OT2CINIM*/INIG*/INIL:
     OUT16 =OT2CIN1M+/IN1G*IN1E+IN1B+/OT3G*IN1A;
     OUTIH =/INIH*(INIE)+OT3AINIF+/INIA+INIB+INID;
     OUT11 = (/IN1E) *OT3G:
                    Figure 9a. Part 1: PLS173
```


AN29



AN29

```
File Name : PART2
   Date : 12/10/1986
   Time: 18:30:42
   ** FNC **FIN ----- PIN** FNC **
      LABEL
                                                   LABEL
   INIA
                     ** 1---
              ** T
                                 1-24 ** +5V **VCC
                        2-1
   IN2B
              ** I
                     **
                                  1-23 ** B
                                             **N/C
              ** I
   IN2C
                    ** 3-1
                                  1-22 ** B
                                            **N/C
                    INIG
              ** 1
                                           **OT2GIN3E
   INII
              ** I
                                            **/OT2FIN3D
   INIJ
              ** I
                                             **OT2CINIM
   INIB
              ** I
                                            **OUT2E
   OUT 1G
              ** I
                    ** 8-1 7
                                 1-17 ** 0 **OUT2D
                       9-1 3 1-16 ** 0 **OUT2C
   OUT1H
              ** I
   OTIC
              ** I
                    ** 10-1
                                 1-15 ** 0
                                             **OUT2B
   OT3AIN1F
              ** I
                    ** 11-1
                                  1-14 ** /O **/OUT2A
              ** OV ** 12-1
                                 1-13 ** I
                                            **OT3G
File Name : PART2
Date : 12/10/1986
Time: 18:31:49
@DEVICE TYPE
PLS173
@DRAWING
@REVISION
CDATE
@SYMBOL.
@COMPANY
@NAME
PART2
@DESCRIPTION
@I/O DIRECTION
@LOGIC EQUATION
    /OUT2A = /((OUT2B*/OUT1G)):
    OUT2B =OUT1H+OUT2A:
    OUT2C =OT2CIN1M+/IN1G+OT2FIN3D;
    OUT2D =OT3AIN1F*/IN1G+(/OT3AIN1F*((IN1B+/IN1J)*/IN1I))*IN1B
            +(OT2FIN3D*/OT3G*/IN1A)*((/IN1A*/IN1B*(IN1J+/OT3AIN1F))
            *(/IN1B*IN1J))+/OT2GIN3E:
    OUT2E =/OT2CIN1M*/IN2C:
    OT2CIN1M =IN1G*/OUT2E;
    /OT2FIN3D =/((OUT2C*(IN2B))):
    OT2GIN3E =/OUT2D+OT1C:
                                                            TB03430S
                        Figure 9b. Part 2: PLS173
```


AN29




AN29

```
File Name : PARIS
Date: 12/10/1986
Time: 18:35:38
** FNC **PIN ----- PIN** FNC **
  LABEL
OTIBIN3A
          ** I ** 1-1
                           1-20 ** +5V **VCC
          * * I
                ** 2-1
OTTEINSB
                            1-19 ** B
                                      **N/0
               ** 3-1 P
** 4-1 L
INBC
          ** I
                            1-18 ** B
          ** [
OT2IN3D
                           1-17 ** ()
                                      **013H
          ** I ** 5-1 S 1-16 ** /0 **/0T36
OT2GIN3E
         OLLE
                                     **OUTSE
THIL
                                     **OTSEIN1K
HIMI
                                      **OUT3D
/OT3AIN1F **-/O ** 9-1
                            1-12 ** O
                                     **OUT30
GND
         ** OV ** 10-1
                           \--|| ** [
                                      **IN1G
                File Name : PART3
                Date: 12/10/1986
                Time: 18:36:18
                @DEVICE TYPE
                PLS153
                @DRAWING
                @REVISION
                @DATE
                @SYMBOL.
                @COMPANY
                @NAME
                 @DESCRIPTION
                 @COMMON PRODUCT TERM
                 @I/O DIRECTION
                 COUTPUT POLARITY
                 @LOGIC EQUATION
                   Figure 9c. Part 3: PLS153
```


AN29



AN29



AN29



Signetics

Designing with Programmable Macro Logic

Application Specific Products

INTRODUCTION TO PML DESIGN CONCEPTS

Programmable Macro Logic, an extension of the Programmable Logic Array (PLA) concept combines a programming or fuse array with an array of wide input NAND gates wherein each gate folds back upon itself and all other such NAND gates. This is called a foldback NAND structure and its basic elements have been outlined previously (Cavlan¹, Wong², Gheissari and Safari³).

The choice of an internal NAND logic cell is appropriate because the cell is functionally complete, requiring but a single cell type to generate any Boolean function. A cell within the PLHS501 may be configured to accommodate from one to 32 inputs from the outside world, and up to 72 inputs from within the chip. Because the user can select either direct or inverted input variables, and either a direct or complemented output, the NAND function can generate, with a single pass through the programming array, the basic four logic functions of AND, OR, NAND, NOR. All these basic functions, can be extremely wide, of course (see Figure 1.1). This convenient structure allows efficient exploitation of all widely used minimization techniques (Karnaugh Maps, Quine-McCluskey, Boolean Algebra, etc.).

The obvious extensions to additional combinational functions for decoding, multiplexing and general Boolean functions is straightforward. Adding feedback to the system expands the range of realizeable functions to include sequential as well as combinational functions. Figure 1.2 illustrates the basic arrangement of the PLHS501. Because of the large number of inputs each NAND gate has available, logic functions that require several levels of conventional 4 or 8 input gates may be able to be reduced to 1 or 2 levels. However, it is important to realize that unlike AND-OR PLD architectures, more than 2 levels of logic may be implemented in the PLHS501 without wasting output or input pins. Up to 72 levels of logic may be implemented due to each of the 72 foldback NAND

So far, the concept of a "macro" is still not evident. Two ways for the generation of a macro exist — namely, hard and soft. Borrowing from the concept in computer programming wherein a section of code (called a macro) is repeated every time its use is required, we can establish subfunctions which can be repeated each time required. The user defined or soft macro can be one which will generate a function by fused interconnect. When a fixed design function is provided, it is a hard macro. This may be an optimized structure like a flip-flop or an adder,

or some other function which is generated on the foundation, by the manufacturer. Soft macros are seldom optimized or precisely consistent, but hard macros are both optimized and unalterable.

When a user function for a particular use is isolated, defined and repetition of the function is required, special software constructs are provided which will allow it to be defined as a soft macro and efficiently replicated. For higher performance and functional density, an array of choices which contain optimized functions or hard macros will be offered in successor chips. In particular, the PLHS502 (described in Section 4) will include an array of flip-flops for high performance state machine design.


Optimizing combinational functions in PML consists largely in making choices and tradeoffs. For single output logic functions, the choice is obvious from the truth table. If a particular function's truth table has fewer entries that are logical zeroes than logical ones, product of sums should be chosen and the appropriate OR-AND structure generated. Otherwise, the usual sum of products should be chosen, minimizing as usual, before dropping into the two level AND-OR structure (using the NAND-NAND realization). Combining the availability of inversion at the input and output of the chip, the NAND-NAND structure can perform either the OR-AND or the AND-OR rendition of a function with equal ease, using precisely the same number of logic levels. The designer needs only to choose the optimal rendition to suit his needs (see Table 1.1). Truth tables with 50% ones can use either version at the designers whim unless other uses arise.

A+B+...+Z IB B B C(OR) AB - Z (NAND) IZ AB - Z (NOR) A+B+...+Z (NOR) AB - Z (NOR) AB - Z (NOR) AB - Z (NOR) AB - Z (NOR) AB - Z (NOR) AB - Z (NOR) AB - Z (NOR) AB - Z (AND) ID092205 Figure 1.1 PML Basic Functions


PERFORMANCE

The PLHS501 (Figure 1.2) is a high speed, oxide isolated, vertically fused PML device containing 72 internal NAND functions which are combined with 24 dedicated inputs, 8 bidirectionals and 16 dedicated outputs. A large collection of applications, both combinational and sequential, may be configured using this part which looks roughly like a small, user definable gate array. For the sake of clarity, worst case passing a signal from an input, making one pass through the NAND array (output terms) and exiting an output takes around 25 nanoseconds with each incremental pass through the NAND foldback array taking about 8 nanoseconds.


TABLE 1.1 EXAMPLE DEMONSTRATION




If we group on the <u>one</u> entries we shall get: $F_1 = AB^- + \overline{B}C + BC$



If we group on the $\underline{\text{zero}}$ entries we get instead: $F_1 = (B + C) (A + B + C)$






The data sheet first lists some maximum propagation delays from an input, through a NAND output term and out through various output gates. Secondly, it lists maximum propagation delays from an input, through a NAND foldback term, through a NAND output term and out through the different output gates.

It is intriguing that subtracting one from the other yields a NAND foldback gate delay of 5 to 6ns when the worst case gate delay of an internal foldback gate is listed as 8ns. This is due to the fact that a gate has less of a delay when it's output is falling (tPHL) than when it's output is rising (tPLH). When passing a signal through two NAND gates one gate will


have less of a delay than the other, and since the individual rise and fall delays are not specified, this causes the apparent discrepancy between the two delays.

Figure 1.3, Figure 1.4, Figure 1.5 and Figure 1.6 show graphically the timing paths listed in the PLHS501 data sheet.


PLHS501 TIMING




PLHS501 TIMING (Continued)



PLHS501 TIMING (Continued)



PLHS501 TIMING INTERNAL



NAND GATE FLIP-FLOPS

Various types of flip-flops and latches may be constructed using the NAND gate building blocks of the PLHS501. A typical 7474 type of edge-triggered D flip-flop requires 6 NAND gates as shown in Figure 1.7.

No additional gates are required to implement asynchronous set and reset functions to the flip-flop. The equations necessary for AMAZE to implement the D flip-flop are shown in Figure 1.8. However, please note that the equations of Figure 1.8 define a D flip-flop configured as a divide by 2 (i.e., QN is connected to the data input) whereas Figure 1.7 shows a general case. Also note that flipflops with some additional features may be constructed without using more than the six NAND gates. This is possible because of the large number of inputs associated with each NAND gate. For instance, a flip- flop may be required to have a clock gated by one or more signals. Using the PLHS501, it may be implemented by adding additional input signal


names to NAND gate equations of gates #2 and #3 of Figure 1.7. If the data input is to the AND of several signals, extra inputs to NAND gate #4 may be used. Or if additional set or reset lines are required, they may be added simply by using more of the inputs of each NAND gate connected to the main set or reset.

Figure 1.10 shows two simulations of the same flip-flop. The first one is at a little less than maximum frequency, for clarity in following the waveforms, and the second is at the maximum toggling frequency. For these simulations each NAND gate has a maximum tpHL or tpLH of 8nsec (which is the gate delay of a NAND gate in the PLHS501's foldback array). First of all, it can be seen from these simulations that for proper simulation or testing of such a device a set or reset input is mandatory. Both Q and QN outputs are unknown no matter what the inputs do, until they are put into a known state by either a set or reset input. Secondly, various timing parameters

such as propagation delay, as well as setup and hold times may be determined. For the general case, referring to Figure 1.7:


Tsetup = tpd4 + tpd1, Thold = tpd3 + tpd4 and Clock to Q = tpd3 + tpd6 + tpd5.

Therefore, performance of the flip-flop depends a great deal on which gates in the PLHS501 are used, either NAND gates in the foldback array or output NAND gates, connected to bidirectional pins. As a test of the simulation, a D flip-flop connected as a divide by 2 was constructed using only the foldback NAND terms (see Figure 1.8). An output NAND term was used to invert the QN output and drive an output buffer. The only inputs were the clock and a reset. The data input to the flop was driven internally by the QN output. According to the simulation, it was possible to drive the clock at a frequency of 25Mhz and this small circuit also functioned at that frequency.



```
############### PIN LIST ##############
Left
                                   PIN** FNC **
LABEL ** FNC **PIN
                                                      LABEL
        ** +5V ** 8-
** I ** 9-
                                   J-46 ** +5V **VCC
VCC
                                   -45 ** I **N/C
       ** I
N/C
                 ** 10-
                                   -44 ** I
                                               **N/C
       ** I
N/C
                            P | -43 ** I **N/C
L | -42 ** I **N/C
H | -41 ** I **N/C
       ** I
                 ** 11-
N/C
                 ** 12-
N/C
                 ** 13-
CLK
                                  |-41 ** I **N/C
|-40 ** /0 **N/C
|-39 ** /0 **N/C
|-38 ** /0 **N/C
|-37 ** /0 **00
|-36 ** 0 **N/C
|-35 ** 0 **N/C
                 ** 14-
RST
                 ** 15-
N/C
N/C
                 ** 16-
                 ** 17-
N/C
        ** I
                 ** 18-
        ** 0
                 ** 19-
                                   -34 ** OV **GND
        ** 0V
                 ** 20-1
GND
File Name : 1flop
Date : 12/3/1987
Time: 10:1:22
@DEVICE TYPE PLHS501
@DRAWING
@REVISION
@DATE
@SYMBOL
@COMPANY
@NAME
@DESCRIPTION
Single D flip-flop connected as
divide-by-two for test
@INTERNAL NODE
CSN0,CRN0,CQ0,CQN0;
@COMMON PRODUCT TERM
@I/O DIRECTION
@I/O STEERING
@LOGIC EQUATION
O0 = /(CQN0);
CSN0 = /(CLK*RST*(/(CSN0*(/[CQN0*RST*CRN0]))));
CRN0 = /(CSN0*CLK*(/[CQN0*RST*CRN0]));
COO = /(CSNO*CQNO)
CQN0 = /(CRN0*CQ0*RST);
          Figure 1.8 PLHS501 Test Flip-Flop
```

776666	666666555555	5555444444	144443333	333333	22222	2222211	11111110000	000000	
109876	543210987654	3210987654	32109876	543210	98765	43210987	765432109876	543210	
IIIIII	IIIIIIIIIII	IIIIIIBBBE	BBBBB						
222211	111111110000	0000000000	00000						
321098	765432109876	5432107654	3210						
				ol for	/B	0			
								A	
нн			(col for	P	0			
								A	
-H			(col for	P	1			
								. A A	
H			(col for	P	2			
								AA.	
			(col for	P	3			
						·		. A A	
H			(col for	P	4			
								AA.	
				col for	P	5			
								A.A	
								TB03640S	



Designing with Programmable Macro Logic

Application Specific Products

FUNCTIONAL FIT

In the late 1960's and early 1970's designers used SSI, MSI and small amounts of early LSI to generate logic solutions. Frustrated by the lack of wide input gates to accommodate a lot of product terms for two level solutions, they turned toward the budding ROM and PROM products. These devices relied on literally realizing a function by generating its truth table in silicon. The logic function had to have each logical one and zero realized distinctly as an entry for a particular combination of input variables, usually supplied on the address lines of the memory. Observing that many such truth tables were dense in ones or zeroes and sparse in the remainder, a cadre of initial manufacturers emerged with focus on supplying a programmable product with a few AND gates and OR gates which were versatile enough to compete against the ROM/PROM parts. The gimmick supplied by these PLA manufacturers was to illustrate the functional equivalency of the PLA to the PROM by comparing the number of product terms (to be shortened to "p-terms") the PLA supplied and comparing this to the width and depth of available PROMs. P-terms became the "currency" of the PLA world and a designer only had to assess the equivalent number of Boolean product terms required by his function to determine whether a particular PLA was a suitable candidate for his design.

Almost in parallel, gate arrays became available. These provided an array of identical, fixed input gates (usually two input NANDs or NORs). These were generated in a regular fashion on a substrate which had a fixed input/output pin arrangement. Also recognizing that all logic functions could be built from the appropriate two input gates, when interconnected correctly, manufacturers offered these devices to customers who required increased density.

The designer's responsibility was to generate what would ultimately be a metal interconnect pattern of his design. Special tools were required to allow an untrained system designer to do this successfully. Flip-flops, decoders, registers, adders, etc., could all be generated from the low level gate building blocks.

The currency of gate arrays became known as gate equivalent functions. That is, with a limited number of available gates on a substrate, the user needed to know precisely how many gates were used up, on a function by function basis, to generate each piece of his design. A D flip-flop requires about six gates, a D latch four, a 3 to 8 decoder takes about 14 gates and so forth. This allowed estimation regarding whether the function could conceivably be fit onto a particular substrate or not. Manufacturers had to offer multiple foundations so that a designer could be assured that his design would result in a working LC.

The classic method of estimating whether a logic function would fit into a PLA was to determine the number of I/O pads required and the number of product terms required to generate the logical function, then select the PLA. For a gate array, the required measure included the I/O pad arrangement but substituted the number of available gates to generate the logical function (usually by table lookup). In an attempt to reconcile the two measures, Hartman4 has evolved a formula for his product line. A calculation using this method and developing an appropriate "exchange rate" is shown in Table 2.1 for the PLHS501 and PLHS502. An alternate method of generating an estimate is to consider the gate equivalent of generating, say for the PLHS501, a gate equivalent of the part in an optimistic functional configuration (72 occurrences of a 32 input NAND gate). Figure 2.1

shows how this will result in over 2000 equivalent gates. Conversely, by stacking the NAND gates into D flip-flops, its least efficient function, the PLHS501 will have a gate equivalent of only about 100 gates.

The most rational method of assessing fit is to isolate functions and identify the correct configuration in terms of gates, to allow direct tally of the gates used, to generate the proposed configuration. Table 2.2 may assist in doing this analysis. Note that all basic gates require precisely one gate to generate the function. Also note the occurrence of functions in the table which could never be generated as standard I.C.'s previously. The procedure is to tally the design against a total budget of 72 multiple input NAND gates.

Table 2.2 is illustrative only, and should by no means be taken as complete. It may be simply expanded by designing the proposed function with disregard to the usual restrictions on the number of inputs to a gate, realize the function as one, two, three, or more levels of interconnected logic and count the number of gate ocurrences required. Special software has been provided to allow pyramided logic structures to be generated under the designer's control. These structures may, however, be no deeper than 72 levels for the PLHS501. Functions should be generated in accord with the guidelines mentioned before, for selecting an optimal 2 level logical solution.

It is an interesting observation that manufacturers of gate arrays and standard cell products which offer embedded PROMS, ROMS or RAMS have not successfully described these embedded functions in terms of equivalent gates, but rather resort to other means (such as divulging their relative area with respect to the area of a basic gate). There is, as yet, no standard in this arena.

TABLE 2.1 EQUIVALENCY RATIO

Hartman's method is based on a CMOS gate array equivalency wherein 4 transistors constitute a 2 input NAND or NOR gate, equal to one gate. Thus, his "exchange rate" is as follows:

E.R. = $4 \times \#$ inputs

+9 × # FFs

+7 × # 3-State outputs

+(15 to 30) \times # OR outputs from the AND/OR array.

For the PLHS501: (using CMOS numbers which may be inappropriate)

E.R. = 4×32

 $+9 \times 0$

+7 × 24

 $+(15 \text{ to } 30) \times 50\%$ of 72 feedbacks = 836 to 1376 gates

For the PLHS502:

E.R. = 4×32

+9 × 16

+7 × 12

 $+(15 \text{ to } 30) \times 50\%$ of 64 feedback = 962 to 1502 gates

Being for two bipolar I.C.'s, in this case, the method may be inappropriate, but may be taken as an estimating procedure.




Figure 2.1 16 Input NAND Formed from 2 Input Gates

TABLE 2.2 PLHS501 GATE COUNT EQUIVALENTS

FUNCTION	PLHS501 INTERNAL NAND EQUIVALENT	COMMENTS					
Gates							
NANDs	1	For 1 to 32 input variables.					
ANDs	1	For 1 to 32 input variables.					
NORs	1	For 1 to 32 input variables.					
ORs	1	For 1 to 32 input variables.					
Decoders							
3 to 8	8	Inverted inputs available.					
4 to 16	16	Inverted inputs available.					
5 to 32	32	Inverted inputs available (24 chip					
	02	outputs only).					
Encoders							
8 to 3	15	Inverted inputs, 2 logic levels.					
16 to 4	32	Inverted inputs, 2 logic levels.					
32 to 5	41	Inverted inputs, 2 logic levels,					
02 10 3	71	factored solution.					
Multiplexers							
4 to 1	5	Inverted inputs available.					
8 to 1	9						
16 to 1	17						
27 to 1	28	Can address only 27 <u>external</u> inputs — more if internal.					
Flip-Flops							
D-FF	6	With asynch S-R					
T-FF	6	With asynch S-R					
J-K-FF	8	With asynch S-R					
Adders							
8-bit	45	Full carry look-ahead (four levels of logic)					
Barrel Shifters	•						
8-bit	72	2 levels of logic					

Designing with Programmable Macro Logic

Application Specific Products

DESIGN EXAMPLES


Most designers tend to view a PLD as a mechanism for collecting logical glue within a system. That is, those pieces which tie together the larger LSI microprocessors, controllers, RAMs, ROMs, UARTs, etc. However, there is a tendency of viewing a gate array as an entire system on a chip. PML based products will fit well in either casting as will be demonstrated by a series of small but straightforward examples. For starters, we shall examine how the fusing process embeds functions, progress to glue-like decoding operations and finally demonstrate some

coprocessor like functions as well as home-made ''standard products''.


The method of associating gates within the NAND foldback structure is depicted in Figure 3.1 wherein a simple three to eight decoder is fused into the array. The corresponding inputs are on the left and outputs at the top. This figure shows inputs and their inverse formed in the array resulting in a solution that requires 6 inverting NANDs that would probably be best generated at the input receivers. Hence, this diagram could be trimmed by six gates, down to eight to achieve the function. Figure 3.2 shows two consecutive D-flip-flop

fusing images. Note that asynchronous sets and resets may be achieved for free, in this version. In both Figures 3.1 and 3.2 the gates are numbered in a one-to-one arrangement. As well, the accompanying equations are in the format used by Signetics AMAZE design software. For clarity, consider the gate labeled 2A in Figure 3.1. Schematically, this is shown as a 3 input NAND. However, in the fused depiction, it combines from three intermediate output points with the dot intersect designation. Hence, all gates are drawn as single input NANDs whose inputs span the complete NAND gate foldback structure.

1 OF 8 DECODER/DEMULTIPLEXER





TWO EDGE-TRIGGERED FLIP-FLOPS



One straightforward example of using a PLHS501 is shown in Figure 3.3. Here, the device is configured to accept the 23 upper address lines generated by a 68000 microprocessor. By selecting the direct and complemented variables, at least 16 distinct address selections can be made using only the dedicated outputs. The designer can combine additional VME bus strobes, or other control signals to qualify the decode or, define 8 additional outputs for expanded selection. As well, the designer could transform the bidirectionals to inputs and decode over a 32 bit

space, selecting combinations off of a 32 bit wide address bus. Because this simple level of design requires only NAND output terms plus 4 NAND gates in the foldback array (for inversion of signals connected to O3.O0), there may be as many as 68 remaining gates to accomplish additional handshaking or logical operations on the input variables.






An eight bit barrel shifter exploits most of the PLHS501 as depicted in Figure 3.4. This implementation utilizes all 72 internal foldback NANDs in a relatively brute force configuration as well as 8 output NANDs to generate transparent latched and shifted results. The shift position here is generated by the shift 0, shift 1 and shift 2 inputs which are distinguished and selected from the input cells. Variations on this idea of data manipulation could include direct passing data, mirror

imaged data (bit reversal) or byte swapping to name a few.

Part of an eight bit, look-ahead parallel adder is shown in Figure 3.5. Gates necessary to form the level-0 generate and propagate, as well as the XOR output gates generating the resulting sum are not shown. The reader should be aware that this solution exploits four layers of pyramided gates and only utilizes a total of about 58 gates. Additional

comparison or Boolean operations could still be generated with remaining NAND functions to achieve additional arithmetic operations. This application should make the reader aware of a new class of applications achieveable with third generation PLDs—user defineable I/O coprocessors. The approach of increasing microprocessor performance by designing dedicated task coprocessors is now within the grasp of user defineable single chip solutions.



An example of one of the least efficient structures realizeable on the PLHS501 is shown in Figure 3.6. Here, a cascade of 12 Dflip-flops are formed into a toggle chain that uses all available NAND gates in the main logic array. In the PLHS501 simple cross coupled latches or transparent D latches are preferred over edge triggered flip flops simply because they conserve NAND gates. Applications for structures like this include timing generators, rate multiplication, etc. Additional output gates exist on the output terms as shown in Figure 1.2, which could gate the output in multiple state detection configurations. As well, rearranging Figure 3.6 as a 12-bit shifter, picking off states at the output terms could result in a general purpose sequence recognizer capable of recognizing binary string sequences. These strings could be up to 13 bits long (in a Mealy configuration) and 24 distinct sequences could be sensed and detected.





Figure 3.7 shows a 32 to 5 – bit priority encoder. This sort of device could generate encoded vector interrupts for 32 contending devices. Of particular interest is the fact that ordinary encoders are not this wide. The designer is, of course, not constrained to generating combinational functions in even powers of two. Thus, the PLHS501 can easily perform customized functions like a 5 to 27 decoder or a 14 to 4 encoder or, even an 18 to 7 multiplexor. For the sake of optimization, the designer is encouraged to implement precisely the function he needs, no more and no less!

The design examples given are illustrative of some typical operations used in ordinary systems. In each case, the example could be thought of as simply an "off the shelf" standard solution to an every day problem (i.e., a de facto standard product).



579

June 1988

Designing with Programmable Macro Logic

Application Specific Products


SUCCESSOR ARCHITECTURES

The design examples described and Table 2.2 illustrate the combinational power and the sequential limitations of the PLHS501 – Signetics first PML entry. Clearly, the next family members must address the flip-flop issue, and they do. The PLHS502 (Figure 4.1) shows a similar NAND function array of 64 gates with the vital addition of 8 buried D-flip-flops and 8 buried S – R flip-flops. Again, 16 pins are devoted to dedicated outputs, 20 straight inputs, 4 clock or general

inputs and 8 bidirectionals can be configured to expand input or output capabilities. Slated to operate in the middle 30MHz clocking range, this part greatly expands the sequencer capability beyond the initial PLHS501. The PLHS502 application range will include state machines like CRC generation/detection, Bus handshakers, LAN handshaking, arithmetic coprocessors, single chip systems and a complete bevy of general sequencer operations such as sequence generation and detection. It should be emphasized that the

NAND array is fully connected and circumvents limitations on connectivity as found in other PLD products.

Almost simultaneous with the arrival of the PLHS502 (a bipolar part) will be the first CMOS PML entry. Expanding on the functional capabilities of the PLHS502, the CMOS part will offer 52 flip-flops in a variety of natural configurations with a NAND array near 200 gates. Due to complexity and density, the part will combine a distinctive power-save option and the benefits of scan-design.



Designing with Programmable Macro Logic

Application Specific Products

SUPPORT ISSUES

The current PML architecture, the PLHS501, is adequately supported by Signetics AMAZE software. Offered free to qualified users, AMAZE can generate the required design files, fusemaps and simulations within the appropriate modules of AMAZE. From a simple menu driven environment on an IBM personal computer (or compatible under MS/ DOS), the user can generate a design with logic equations, state equations or schematic entry (using FutureNet Dash or ORCAD SDT software). Once the design is entered, the user must "assemble" it prior to fusing the PML product. If required, the user may simulate the assembled file to determine the accuracy and functional operation of his design. Iteration between design entry, assembly and simulation may be required, depending on the users expectations and the completeness of design. Automatic test vector generation is a simulation option. Currently, the designer may fuse his design using either a DATA I/O Unisite programmer, a Stag ZL – 30A or a STREBOR fusing system with corresponding configuration modules.

The AMAZE product is fully contained and complete except for the schematic capture program. Although it is used for the complete line of Signetics PLD products (PLAs, Sequencers and PROMs), it has undergone additional modification to support special features required by the nature of the PML products. These include the following:

- Internal Nodes the ability to define and refer to nodes completely within the array and isolated from direct contact with the device I/O pins.
- Bracket Freezing the ability to tag (with square brackets) a Boolean subfunction which is not to be optimized by the AMAZE assembler but is to be realized within the design explicitly as described by equation.

Both features are key to the AMAZE approach to macro generation. In particular, "bracket freezing" allows the designer to make tradeoffs between wide and shallow combinational paths and long, narrow combinational paths.

In the current rendition of AMAZE, automatic placement and interconnect of the fused Boolean functions is the recommended approach. Should the user decide to intervene, a special fuse table editor exists for manual alteration of the design file. This is not the recommended approach, but it also serves as a diagnostic tool to review design placement and interconnect.

Future directions for software support include enhanced simulation, exhaustive automatic Boolean optimization, the development of a full library of macros, automatic design partitioning and a wide assortment of bells and whistles.

Designing with Programmable Macro Logic

Application Specific Products

PLHS501 EXAMPLES USING AMAZE REVISION 1.6

- Simple gate implementations
- 8-bit barrel shifter
- 12-bit comparator with dual 1 of 8 decoders
- 8-bit carry look-ahead adder
- 32 to 5 priority encoder
- 8-bit shift register with 3-bit counter and sequence detector
- 4-bit synchronous counter

Following are six example applications for the PLHS501 using AMAZE Rev. 1.6. They should not be viewed as showing all possible capabilities of the device. They have been designed to demonstrate some of the PLHS501 features, syntax of AMAZE, and to give the reader some ideas for possible circuit implementations.

Note that these examples were written using AMAZE Rev. 1.6. Although Signetics will try to keep succeeding versions of AMAZE compatible, it may be necessary to change some syntax rules. Therefore, please refer to your AMAZE manual for any notes on differences, if using a revision later than Rev. 1.6.

SIMPLE GATE IMPLEMENTATIONS

In this example six functions were implemented for each of the three major types of output structures. The six functions are AND/OR, AOI, NAND, AND, OR and NOR. A requirement for the AND/OR and AOI gates was to use only two gates each from the foldback array and to combine these product terms in one NAND output gate. To achieve this result, it was necessary for the /B and /O outputs to write equations using internal nodes and brackets around the equation. Refer to Figures 6.1 and 6.2.

For the simulation (Figures 6.3 and 6.4) a binary count of 0 through 15 hex was applied to the input D-A. Each output of the log file was checked against anticipated and other device outputs of the same function for correct operation.

File Name : GATES Date: 9/15/1987 Time : 9:30:16 ########### PIN LIST ########## ** FNC **PIN PIN** FNC ** LABEL LABEL |-46 ** +5V **VCC ** +5V ** 8-VCC -45 ** I **N/C ** I ** 9-** 10--44 ** I **N/C ** T В -43 ** I ** 11-**N/C ** I ** 12--42 ** I **N/C n ** 13--41 ** I **N/C ** I N/C ** 14--40 ** /0 **F1 N/C -39 ** /0 ** 15-**F3 ** 0 F2 -38 ** /0 ** 16-**F5 F4 -37 ** /0 **N/C F6 -36 ** 0 **N/C ** 18-N/C -35 ** O ** 19-**F7X F20 -34 ** OV ** OV ** 20-**GND GND Top Bottom LABEL ** FNC **PIN PIN** FNC ** **N/C - 7 ** T ** 0 ** 21-- 6 ** **N/C ** 0 ** 22-F60 - 5 ** **N/C ** 23-** 0 - 4 ** I **N/C ** /0 ** 24-- 3 ** **N/C ** /0 ** 25-F30 - 2 ** I **N/C F50 ** /0 ** 26н - 1 ** ** /0 ** 27-**N/C N/C -52 ** I **N/C ** 0 ** 28-FlX ** 0 -51 ** I **N/C ** 29-0 F2X -50 ** I **N/C ** 0 ** 30-F3X ** 0 -49 ** I **N/C ** 31-F4X **N/C ** 32-** O F5X ** 0 ** 33-**N/C F6X

Figure 6.1 Gates Pin List

```
File Name : GATES
Date : 9/15/1987
Time : 9:30:35
                                                                                    "AND-OR using XOR output"
@DEVICE TYPE
                                                                                    flx = (a*b)+(c*d);
PLHS501
                                                                                    "AND-OR-INVERT using XOR output"
@DRAWING
                                                                                    f2x = /[(a*b) + (c*d)];
@REVISION
                                                                                    "NAND using XOR output
CDATE
                                                                                    f3x = /(a*b*c*d);
(CSYMBOL
                                                                                    "AND using XOR output"
(COMPANY
                                                                                    f4x = a*b*c*d:
@NAME
                                                                                     'OR using XOR output"
@DESCRIPTION
                                                                                    f5x = /(/a*/b*/c*/d);
"NOR using XOR output"
Various single and two level gate implementations using
                                                                                    f6x = /a*/b*/c*/d;
different output structures
                                                                                    "XOR using XOR output"
f7x : xrl = a;
xr2 = b;
GINTERNAL NODE
@COMMON PRODUCT TERM
@I/O DIRECTION
                                                                                    "AND-OR using /O output" flo = /(/[a*b] * /[c*d]);
@I/O STEERING
@LOGIC EQUATION
                                                                                    "AND-OR-INVERT using O output"
                                                                                    f20 = /[(a*b) + (c*d)];
"AND-OR using /B output" fl = /(/[a*b] * /[c*d]);
                                                                                    "NAND using /O output
                                                                                    f30 = /(a*b*c*d);
"AND-OR-INVERT using B output"
                                                                                     "AND using 0 output"
f2 = /[(a*b) + (c*d)];
                                                                                    f40 = a*b*c*d;
"NAND using /B output
                                                                                    "OR using /O output"
f5o = /(/a*/b*/c*/d);
f3 = /(a*b*c*d);
"AND using B output"
                                                                                     "NOR using O output"
f4 = a*b*c*d;
                                                                                    f60 = /a*/b*/c*/d;
 'OR using /B output"
f5 = /(/a*/b*/c*/d);
"NOR using B output"
f6 = /a*/b*/c*/d;
                                       Figure 6.2 Gates Boolean Equations
```

```
Simulation input file for GATES
<----> < B,/B >
222211111111111
321098765432109876543210 76543210
 DCBA A is MSB, D is LSB
ННЦЦЦИННИННИННИННИННИН ----- Through...
нинитининининининини -----
ННІДНІННИНИНИНИНИНИНИН ------
НННГИГИННИНИНИНИНИНИНИН -----
НИГНИЧИННИННИННИННИННИН -----
ниннгининининининин -----
нитттининининининини -----
нинттинининининининин ------
НИТИТИНИНИНИНИНИНИНИНИ -----
ниницининининининин -----
ниттинининининининин -----
нницининининининини
нигинининининининин -----
НННННННННННННННННННН ----- "Count 15 hex"
     Figure 6.3 Gates Simulation Input File
```


```
PLHS501
                  GATES
                                  Time = 13:59:42 Date = 9/14/1987
       ----INPUTS-----> < B,/B > < XOR > < /O,O > TRACE TERMS
  222211111111111
" 321098765432109876543210 76543210 76543210
  11000011111111111111111 HHLHLHLL LLHLHHL LLHLHHLH ;
  11100011111111111111111 HILHLHHL LILHHHL LHHLHLH
  110100111111111111111111 HILHIHL LILHIHL LHHIHLLH
  11110011111111111111111 HLLLHHHL LLLHLHLH LHHHHLLL
  11001011111111111111111 HILHLHHL LHLHHHL LHHLHILH
  110110111111111111111111 HLLHLHHL LHLHLHL LHHLHLLH
  11111011111111111111111 HLLLHHHL LHLHLHL LHHHHLLL
  11000111111111111111111 HILHLHHL LHLHLHL LHHLHILH
  11100111111111111111111 HLLHLHHL LHLHLHHL LHHLHLLH
  11010111111111111111111 HILHLHHL LHLHLHL LHHLHLH
  1111011111111111111111 HLLLHHHL LHLHLHLH LHHHHLLL
  11001111111111111111111 HLLLHHHL LILHLHLH LHHHHLLL
  1110111111111111111111 HLLLHHHL LLLHLHLH LHHHHLLL ;
  1101111111111111111111 HLLLHHHL LLLHLHLH LHHHHLLL
  11111111111111111111111 HLHLHLHL LILHHILH LHLHHLHL ;
                                      I/O CONTROL LINES
                           OCCOCCO DESIGNATED I/O USAGE
OCCOCCO ACTUAL I/O USAGE
" PINLIST...
" 14 13 12 11 10 09 07 06 05 04 03 02 01 52 51 50 49 48 47 45 44 43 42 41
" 18 17 16 15 40 39 38 37 36 35 33 32 31 30 29 28
* 27 26 25 24 23 22 21 19 ;
                                                                      TB03690S
                  Figure 6.4 Gates Simulation Log File
```

8 BIT BARREL SHIFTER

This 8-bit shifter will shift to the right, data applied to A7 – A0 with the result appearing on OUT7 – OUT0. Data may be shifted by 1 to 7 places by indicating the desired binary count on pins SHIFT2 – SHIFT0. Data applied to the OUT0 position for a shift of 1. For a shift of 0, A7 will appear on OUT7.

Also included is a transparent latch for the output bits. The input 'COMPLMTO' will invert all output bits simultaneously and input /OE will 3-State all outputs.

```
File Name : BRLSHFT
Date : 9/15/1987
Time : 9:31:58
PIN** FNC **
   LABEL
            ** FNC **PIN
                                                 LABEL
                                 -46 ** +5V **VCC
            ** +5V ** 8-
VCC
                                 -45 ** I
                  ** 9-
                                           **N/C
A2
                  ** 10-
                                 -44 ** I
A3
            ** I
                                            **N/C
                                 -43 ** I
            ** T
                  ** 11-
                                            **N/C
A4
                                 -42 ** I
            ** I
                  ** 12-
                                            **N/C
A5
                                 -41 ** I
            ** I
                  ** 13-
                                            **N/C
A6
                            Η
            ** I
                  ** 14-
                                 -40 ** /0
                                           **L0
A7
            ** 0
                  ** 15-
                                 -39 ** /0
                                            **L1
L4
            ** 0
                  ** 16-
                                 -38 ** /0
                                            **L2
            ** 0
                                 -37 ** /0
                  ** 17-
L6
                                 -36 ** 0
|-35 ** 0
                  ** 18-
                                            **OUT7
            ** 0
                  ** 19-
                                            **OUT6
                                -34 ** OV
            ** 0V
                  ** 20-
GND
                                            **GND
        Bottom
                                  PIN** FNC **
            ** FNC **PIN
   LABEL
                                                 LABEL
            ** 0
                  ** 21-
                                 - 7 ** I
                                            **A1
N/C
            ** 0
                  ** 22-
                                            **A0
N/C
                  ** 23-
                                 - 5 **
                                            **SHIFT2
N/C
            ** 0
            ** /0
                  ** 24-
                                 - 4 **
                                            **SHIFT1
N/C
N/C
            ** /0
                  ** 25-
                                            **SHIFTO
N/C
            ** /0
                  ** 26-
                                 - 2 **
                                            **COMPLMTO
            ** /0
                  ** 27-
               10
                                            **/LE
                  ** 28-
                                            **/OE
OUTO
                                 -52 ** I
            ** 0
                  ** 29-
OUT1
                                 -51 **
                                            **N/C
            ** 0
                  ** 30-
                                 -50 **
                                            **N/C
OUT2
                  ** 31-
                                 -49 ** I
OUT3
            ** 0
                                            **N/C
                  ** 32-
                                 -48 **
                                            **N/C
            ** 0
OUT4
                  ** 33-
                                 -47 **
                                            **N/C
            ** 0
OUT5
                                                      TB03700S
             Figure 6.5 Barrel Shifter Pin List
```



```
File Name : BRLSHFT
Date: 9/15/1987
Time : 9:32:14
@DEVICE TYPE
PLHS501
@DRAWING
GREVISION
@DATE
@SYMBOL
@COMPANY
@NAME
@DESCRIPTION
8 Bit Barrel Shifter
with 3-state latched outputs
nod1, nod2, nod3, nod4, nod5, nod6, nod7, nod8;
nod9,nod10,nod11,nod12,nod13,nod14,nod15,nod16;
 nod17, nod18, nod19, nod20, nod21, nod22, nod23, nod24;
 nod25, nod26, nod27, nod28, nod29, nod30, nod31, nod32;
i3,12,11,10;

@COMMON PRODUCT TERM

rot0 = /shift2 * /shift1 * /shift0;

rot1 = /shift2 * /shift1 * shift0;

rot2 = /shift2 * shift1 * /shift0;

rot3 = /shift2 * shift1 * /shift0;

rot4 = shift2 * /shift1 * /shift0;

rot5 = shift2 * /shift1 * /shift0;

rot6 = shift2 * /shift1 * /shift0;

rot7 = shift2 * shift1 * /shift0;
 i3,i2,i1,i0;
 @I/O DIRECTION
xe0 = oe;
xe1 = oe;
xe2 = oe;
xe3 = oe;
 @I/O STEERING
 @LOGIC EQUATION
 17 = /[a7 * rot0 * /le +
            /[a/ * rot0 * /le +
a6 * rot1 * /le +
a5 * rot2 * /le +
a4 * rot3 * /le +
a3 * rot4 * /le +
a2 * rot5 * /le +
a1 * rot6 * /le +
     Figure 6.7 Barrel Shifter Boolean Equations
```

```
a0 * rot7 * /le +
le * /17];

16 - (la6 * rot0 * /le +
a5 * rot1 * /le +
a4 * rot2 * /le +
a3 * rot3 * /le +
a1 * rot5 * /le +
a2 * rot4 * /le +
a1 * rot5 * /le +
a3 * rot6 * /le +
a5 * rot0 * /le +
a6 * rot0 * /le +
a6 * rot0 * /le +
a6 * rot1 * /le +
a1 * rot2 * /le +
a2 * rot4 * /le +
a3 * rot2 * /le +
a3 * rot5 * /le +
a1 * rot5 * /le +
a1 * rot5 * /le +
a1 * rot5 * /le +
a1 * rot6 * /le +
a3 * rot6 * /le +
a3 * rot7 * /le *
le * /l5];

14 - /l64 * rot0 * /le +
a3 * rot1 * /le +
a1 * rot3 * /le +
a1 * rot3 * /le +
a1 * rot3 * /le +
a1 * rot3 * /le +
a1 * rot5 * /le +
a1 * rot5 * /le +
a1 * rot5 * /le +
a1 * rot5 * /le +
a1 * rot5 * /le +
a1 * rot5 * /le +
a1 * rot5 * /le +
a1 * rot5 * /le +
a1 * rot5 * /le +
a1 * rot5 * /le +
a1 * rot5 * /le +
a1 * rot7 * /le |
a1 * rot2 * /le |
a1 * rot2 * /le |
a2 * rot0 * /le |
a3 * rot1 * /le |
a4 * rot7 * /le |
a5 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a7 * rot6 * /le |
a8 * rot6 * /le |
a8 * rot6 * /le |
a9 * rot6 * /le |
a1 * rot7 * /le |
a2 * rot6 * /le |
a3 * rot6 * /le |
a4 * rot7 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a6 * rot6 * /le |
a7 * rot6 * /le |
a8 * rot6 * /le |
a9 * rot6 * /le |
a1 * rot7 * /le |
a1 * rot7 * /le |
a2 * rot6 * /le |
a3 * rot6 * /le |
a4 * rot7 * /le |
a5 * rot6 * /le |
a6 * rot6 * /le |
a7 * rot6 * /le |
a8 * rot6 * /le |
a9 * rot6 * /le |
a1 * rot7 * /le |
a1 * rot7 * /le |
a2 * rot6 * /le |
a3 * rot6 * /le |
a4 * rot7
```

```
nodll= [a0 * rot2 * /le];
nodl2= [a7 * rot3 * /le];
nodl3= [a6 * rot4 * /le];
nodl4= [a5 * rot5 * /le];
nodl5= [a4 * rot6 * /le];
nodl6= [a3 * rot7 * /le];
i2 = [le * l2];
 12 = /([/nod9*/nod10*/nod11*/nod12*/nod13*/nod14*/nod15*/nod16*/i2]);
                   nod17- [a1 * rot0 * /le];
nod18- [a0 * rot1 * /le];
nod19- [a7 * rot2 * /le];
nod20- [a6 * rot3 * /le];
nod21- [a5 * rot4 * /le];
nod22- [a4 * rot5 * /le];
nod23- [a3 * rot6 * /le];
nod24- [a2 * rot7 * /le];
i1 - [le * ll];
  11 = /([/nod17*/nod18*/nod19*/nod20*/nod21*/nod22*/nod23*/nod24*/il]);
                    nod25= [a0 * rot0 * /le];
nod26= [a7 * rot1 * /le];
nod27= [a6 * rot2 * /le];
nod28= [a5 * rot3 * /le];
nod29= [a4 * rot4 * /le];
nod30= [a3 * rot5 * /le];
nod31= [a2 * rot6 * /le];
nod32= [a1 * rot7 * /le];
                     i0 = [le * 10];
   10 = /([/nod25*/nod26*/nod27*/nod28*/nod29*/nod30*/nod31*/nod32*/i0]);
                    xr2 = complmto;
out6 : xr1 = /16;
xr2 = complmto;
                    xr2 = complmto;

out5 : xr1 = /15;

xr2 = complmto;

out4 : xr1 = /14;

xr2 = complmto;

out3 : xr1 = 13;

xr2 = complmto;

out2 : xr1 = 12;

xr2 = complmto;

out1 : xr1 = 11;
                     outl : xrl = 11;
                                                                                                                                                                         TB03730S
xr2 = complmto;
out0 : xr1 = 10;
xr2 = complmto;
                 Figure 6.7 Barrel Shifter Boolean Equations (Continued)
```

```
" Simulation input for BRLSHFT
 hlhlhlllllhlhhhhhhhhh -----
                                             AA"
                                             55"
 lllllllhlllhlhhhhhhhhhhhh ----- "Shift0 - Input 01"
 llllllhllhlhhhhhhhhhhh ----- "
 1111111hlhlhlhhhhhhhhhhh ------ "
 1111111hlhhlhlhhhhhhhhhh ----- ~
  1111111hh111hhhhhhhhhhhh ----- "
  lllllllhhlhlhhhhhhhhhhh ----- "
  1111111hhhl1hlhhhhhhhhhh ----- "
  1111111hhhhlhlhhhhhhhhhh ----- ~
 llllhhhhhlllhlhhhhhhhhhh ------ "Shift4 - Input OF"
hlhhlhllhllhlhhhhhhhhhh ------ "Shift1 - Input AA"
llllllllllllllhlhhhhhhhhhh ------ "Shift0 - Input 00"
  llllllllllllhhhhhhhhhhhhh ----- "Complement output"
  llllhhhhllllhhhhhhhhhh ----- "ShiftO - Input OF
 hlhlhlllllllhhhhhhhhhh ----- "start latch test"
  llllllhlllllhhhhhhhhhh ----- "continue...
  111111h1111111hhhhhhhhhhh
  11111h11111111hhhhhhhhhh
  1111h111111111hhhhhhhhhh ------
 111h1111111111hhhhhhhhhh -----
  llhllllllllllhhhhhhhhh -----
 1h111111111111hhhhhhhhhhh -----
 hlllllllllllllhhhhhhhhhh ----- "end"
 QUIT
    Figure 6.8 Barrel Shifter Simulation Input File
```

```
PLHS501
                              Time = 14:12:36 Date = 9/14/1987
  <-----INPUTS-----> < B,/B > < XOR > < /O,O > TRACE TERMS
  222211111111111
 321098765432109876543210 76543210 76543210 76543210
  OOOOOOOOOOOOOOIIIIIIIIIII HHHHLLLL LIJJIJIL LLLLHHHH ;
  111111110000101111111111 LLLLHHHH HHHHHHHH LLLLHHHH
  1010101000001011111111111 LHLHTHLH HLHLHLHL LILLHHHH ;
  010101010000101111111111 HLHLHLHL LHLHLHLH LLLLLHHHH
  00000001001011111111111 HHHHLHIT ITITITH ITITHHHH
  000000011000101111111111 HHHLTTTT TTTHTTT TTTTHHHH
  OOOOOOOIIOIOIOIIIIIIIIIII HHTHTTT TTHTTTT TTTTHHHH
  000000011100101111111111 HLHHLLLL LHLLLLLL LLLLHHHH
  000000011110101111111111 THHHTTTT HTTTTTTT TTTTHHHH
  000011111000101111111111 LITITIT HHHHITIT ITTTHHHH
  101010100010101111111111 HLHLHLHL LHLHLHLH LILLLHHHH
  OOOOOOOOOOIIOIIIIIIIIII HHHHLLLL HHHHHHHH LLLLHHHHH ;
  000011110000101111111111 НИНИНИНИ IIIIHHHH IIIIHHHH
  101010100000001111111111 НННННННН LILLHHHH LLLLHHHH
  OOOOOOOOOOOOIIIIIIIIII НИНИНИНИ LLLLИНИН LLLLИНИН ;
  000000100000001111111111 НИННИННИ LLILHHHH LLILHHHH
  000001000000001111111111 НИНННИН LLLLHHHH LLLLHHHH
  000010000000011111111111 ННННННН LLLLHHHH LLLLHHHH ;
  OOO10000000001111111111 НННННННН LILLHHHH ;
  OOLOOOOOOOOOIIIIIIIIII ННИНИННИ LLLLИНИН LLLLИНИН ;
  010000000000001111111111 НИННИНН ГТТТИННИ ГТТТИННИ
  10000000000001111111111 HHHHHHHH LLLLHHHHH ;
  000000000000101111111111 HHHHLTTT ITTTTTT ITTTHHHH
 OOOOOOOOOOOIIIIIIIIIIII HHHHLLLL ...... LLLLHHHH
                                  I/O CONTROL LINES
                        00000000 DESIGNATED I/O USAGE
00000000 ACTUAL I/O USAGE
 PINLIST...
 14 13 12 11 10 09 07 06 05 04 03 02 01 52 51 50 49 48 47 45 44 43 42 41 18 17 16 15 40 39 38 37 36 35 33 32 31 30 29 28
" 27 26 25 24 23 22 21 19 ;
             Figure 6.9 Barrel Shifter Simulation Log File
```

```
File Name . 12RTTCMP
Date : 9/15/1987
Time : 9:36:0
Left
                                               Right
   LABEL
            ** FNC **PIN
                                   PIN** FNC **
VCC
            ** +5V ** 8-
                                 -46 ** +5V **VCC
            ** I
B6
                   ** 9-
                                  -45 ** I
                                             **A4
в7
                   ** 10-
                                  -44 **
                                             **A3
                   ** 11-
                                 -43 ** I
                                             **A2
В9
                  ** 12-
                                  -42 ** I
                                             **A1
            ** I
B10
                  ** 13-
                                 -41 ** I
                                             **A0
B11
            ** I
                  ** 14-
                                  -40 ** /0
                                             **CMPOUT
                  ** 15-
                                  -39 ** I
ENCOMP
            ** T
                                             **DA2
                                 -38 ** T
DCDREN
            ** I
                   ** 16-
                             0
                                             **DA1
                  ** 17-
                                 -37 ** T
DW
            ** T
                                             **DA0
            ** B
                  ** 18-
                                 -36 ** 0
                                             **R7
N/C
                  ** 19-
                                 -35 ** 0
WO
            ** 0
                                             **R6
                  ** 20-
                                 -34 ** OV
GND
            ** OV
                                             **GND
       Bottom
                                               Top
   LABEL
            ** FNC **PIN
                                   PIN** FNC **
                                                   LABEL
Wl
            ** 0
                   ** 21-
                                  - 7 ** I
                                             **B5
                   ** 22-
W2
              0
                                  - 6 **
                                             **B4
                                  - 5 **
W3
            ** 0
                   ** 23-
                                             **B3
            ** /0
                   ** 24-
                                  - 4 **
W4
                                             **B2
                                             **Bl
W5
            ** /0
                   ** 25-
                   ** 26-
            ** /0
                                  - 2 **
              /0
                   ** 27-
                                  - 1 **
                                             **All
            ** 0
                   ** 28-
                                  -52 **
                                             **A10
            ** 0
                   ** 29-
                                  -51 **
                                             **A9
Rl
            ** 0
                   ** 30-
                                  -50 **
                                             **A8
                   ** 31-
            ** 0
                                  -49 ** I
                                             **A7
            ** 0
                   ** 32-
                                  -48 ** I
                                             **A6
                   ** 33-
                                  -47 ** I
                                             **A5
                                                        TB02770S
          Figure 6.10 12-Bit Comparator Pin List
```

12 BIT COMPARATOR WITH DUAL 1 OF 8 DECODERS

Two functions that are very often associated with controlling I/O parts are address comparison and address decoding. In this example, both functions are programmed into a PLHS501 using 52 out of the 72 foldback NAND terms.

The comparator compares 12 bits on inputs A11 – A0 to inputs B11 – B0 when the input 'ENCMP'' is High. Output 'CMPOUT' will become active-Low when all 12 bits of the A input match the B. Selection between the two decoders is done with input 'R/W'. Only one output may be active (Low) at a time. Although currently separate functions, the decoder enable may be derived internally from 'CMPOUT' freeing 2 bidirectional pins which together with available foldback NAND terms, may be used to incorporate a third function.




Figure 6.11 12-Bit Comparator with Dual 1 – 8 Decoders Block Diagram

```
File Name : 12BITCMP
        Date : 9/15/1987
        Time: 9:36:17
        @DEVICE TYPE
        PLHS501
        @DRAWING
        @REVISION
        @DATE
        (dsymbol
        @COMPANY
        @NAME
        @DESCRIPTION.
        12-bit address comparator and dual 1 of 8 decoders
        GINTERNAL NODE
        axb0, axb1, axb2, axb3, axb4, axb5, axb6;
        axb7,axb8,axb9,axb10,axb11;
        @COMMON PRODUCT TERM
        ad0=/da2*/da1*/da0*dcdren;
        adl=/da2*/da1* da0*dcdren;
        ad2=/da2* da1*/da0*dcdren;
        ad3=/da2* da1* da0*dcdren;
        ad4= da2*/da1*/da0*dcdren;
        ad5= da2*/da1* da0*dcdren;
       ad6= da2* da1*/da0*dcdren;
ad7= da2* da1* da0*dcdren;
        @I/O DIRECTION
        @I/O STEERING
       @LOGIC EQUATION
       "12-Bit Address Comparator"
       axb0 = a0*/b0 + /a0*b0;
       axb1 = a1*/b1 + /a1*b1;

axb2 = a2*/b2 + /a2*b2;
       axb3 = a3*/b3 + /a3*b3;

axb4 = a4*/b4 + /a4*b4;
       axb5 = a5*/b5 + /a5*b5;
       axb6 = a6*/b6 + /a6*b6;

axb7 = a7*/b7 + /a7*b7;
       axb8 = a8*/b8 + /a8*b8;

axb9 = a9*/b9 + /a9*b9;
       axbl0 = al0*/bl0 + /al0*bl0;
axbl1 = al1*/bl1 + /al1*bl1;
cmpout = /(/axb0*/axb1*/axb2*/axb3*/axb4*/axb5*/axb6*/axb7*/axb8*/axb9*
                    /axbl0*/axbl1*encomp);
       "Dual 1 of 8 decoders
        - da2-da0 are address inputs
        - dcdren is an enable input
        - rw selects which group of 8 outputs r7-r0 or w7-w0
              will have the decoded active low output"
        w7 = /(ad7*/rw);
        w6 = /(ad6*/rw);
        w5 = /(ad5*/rw);
        w4 = /(ad4*/rw);
        w3 = /(ad3*/rw);
        w2 = /(ad2*/rw);
w1 = /(ad1*/rw);
        w0 = /(ad0*/rw);
        r7 = /(ad7* rw);
        r6 = /(ad6* rw);
        r5 = /(ad5* rw);
        r4 = /(ad4* rw);
        r3 = /(ad3* rw);
        r2 = /(ad2* rw);
        rl = /(adl* rw);
          Figure 6.12 12-Bit Comparator Boolean Equations
```

```
Simulation inputs for 12BITCMP
       --INPUTS-----> < B,/B >
2222ННННННННН
32HL98765432HL98765432HL 765432HL
HLHLHLHLHLHLHLHLHLHLHL -LLH-LLL "comp AA"
LHLHLHLHLHLHLHLHLHLHLHLH -LLH-LLL "comp 55"
НИНИНИНИНИНИНИНИНИН -LLH-LLL 'Comp FF'
LILLILLILLILLILLL -LHL-LLL "enable decoder W"
LILLILLILLILLILLLL -HHL-LLL "enable decoder R"
LIJIJILLLIJIJIJIJIJILLI -HHL-ILH 'count 1'
LIJIJIJILLIJIJIJIJIJILLI -HHL-LHL ' 2'
TITITITITITITITITIT -HHT-HTT .
ITITITITITITITITITI -HHL-HTH .
TTITITITITITITITI - HHL-HHL .
LILLILLILLILLILLILL -HHL-HHH "
Figure 6.13 12-Bit Comparator Simulation Input File
```


```
Time = 15:0:58 Date = 9/14/1987
              12BTTCMP
PLHS501
   -----INPUTS-----> < B,/B > < XOR > < /O,O > TRACE TERMS
 222211111111111
 321098765432109876543210 76543210 76543210 76543210
 000000000000000000000 нооонооо ннннннн ннннннн
 000000000000000000000000 Н001Г000 ННННННН ННННННН
 101010101010101010101010 н001L000 ннннннн ннннннн
 010101010101010101010101 H001L000 ННННННН ННННННН
 1111111111111111111111 HOO1LOOO HHHHHHHH HHHHHHHH
 00000000000000000000000 н110н000 ннннннн ннннннн
 00000000000000000000000 н110н001 нннннны ннннннн
 00000000000000000000000 н110н010 ннннншнн ннннннн
 00000000000000000000000 н110н100 ннныннин нннннннн
 00000000000000000000000 н110н101 нншннннн нннннннн
 000000000000000000000000 н110н110 нLннннн ннннннн
 I/O CONTROL LINES
                      OIIIOIII DESIGNATED I/O USAGE
OIIIOIII ACTUAL I/O USAGE
PINLIST...
14 13 12 11 10 09 07 06 05 04 03 02 01 52 51 50 49 48 47 45 44 43 42 41
18 17 16 15 40 39 38 37 36 35 33 32 31 30 29 28
                                                          TB03810S
          Figure 6.14 12-Bit Comparator Simulation Log File
```

8-BIT CARRY LOOK-AHEAD

This function may be used as part of an ALU design or simply to off-load a microprocessor. Figure 6.16 is a block diagram showing the individual components needed for each bit.

A carry input (C0) is provided along with a carry output (C8). The result of an addition between the inputs A7 – A0 and B7 – B0 occurs on outputs SUM7 – SUM0.

```
File Name : 8BITADDR
Date: 9/15/1987
Time : 9:37:21
Left
  LABEL
           ** FNC **PIN
                                 PIN** FNC **
                                               LABEL
VCC
           ** +5V **
                               1-46 ** +5V **VCC
                    8-
A2
                  ** 9-
                                -45 ** I
                                          **N/C
                  ** 10-
                               -44 ** I
                                          **N/C
A4
                 ** 11-
                               -43 ** I
                                          **N/C
A5
                 ** 12-
                               -42 ** I
                                          **N/C
A6
           ** T
                 ** 13-
                           Н
                               -41 ** I
                 ** 14-
Δ7
                           S
                               -40 ** /0
                                          **N/C
N/C
           ** B
                 ** 15-
                               -39 ** /0
                                          **N/C
           ** B
                 ** 16-
                               -38 ** /O
N/C
                           0
                                          **N/C
                               -37 ** /0
           ** B
                 ** 17-
                                          **N/C
           ** B
                 ** 18-
                               -36 ** O
                                          **SUM7
           ** 0
                 ** 19-
                               I-35 ** O
                                          **SIM6
GND
                               -34 ** OV
                                          **GND
  LABEL
           ** FNC **PIN
                                PIN** FNC **
                                                LABEL.
           ** 0
N/C
                 ** 21-
                                          **A1
                 ** 22-
                                          **A0
N/C
           ** 0
                               - 6 **
           ** 0
N/C
                 ** 23-
                                - 5 **
                                          **B7
N/C
           ** /0 ** 24-
                               - 4 ** I
                                          **B6
N/C
           ** /0 ** 25-
           ** /0 ** 26-
N/C
                           Н
                               - 2 ** I
                                          **B4
N/C
           ** /0 ** 27-
                           S
                               - 1 ** T
                                          **B3
SUM0
           ** 0
                 ** 28-
                           5
                               1-52 ** I
                                          **B2
SUM1
           ** 0
                 ** 29-
                               -51 ** T
                           0
                                          **Bl
SUM2
           ** 0
                 ** 30-
                               -50 ** T
                                          **B0
           ** 0
SUM3
                 ** 31-
                               -49 ** T
                                          ****
SUM4
           ** 0
                 ** 32-
                               1-48 ** T
                                          **N/C
           ** 0
                 ** 33-
SUM5
                               -47 ** T
                                          **N/C
             Figure 6.15 8-Bit Adder Pin List
```



```
File Name : 8BITADDR
Date : 9/15/1987
Time: 9:37:36
@DEVICE TYPE
PLHS501
@DRAWING
@REVISION
@DATE
@SYMBOL
(COMPANY
@NAME
@DESCRIPTION
8 Bit Carry Look-Ahead Adder
@INTERNAL NODE
 g8, g1, g2, g3, g4, g5, g6, g7;
p8, p1, p2, p3, p4, p5, p6, p7; gn8,gn1,gn2,gn3,gn4,gn5,gn6,gn7;
cl,c2,c3,c4,c5,c6,c7;
gl_1,g2_1;
@COMMON PRODUCT TERM
@I/O DIRECTION
@I/O STEERING
@LOGIC EQUATION
"level-0 functions"
gnl = /(a0*b0);
pl = /(/a0*/b0);
gl = /gnl;
gn2 = /(al*bl);
p2 = /(/al*/bl);
g2 = /gn2;
gn3 = /(a2*b2);
p3 = /(/a2*/b2);
g3 = /gn3;
gn4 = /(a3*b3);

p4 = /(/a3*/b3);

g4 = /gn4;
gn5 = /(a4*b4);
p5 = /(/a4*/b4);

g5 = /gn5;
gn6 = /(a5*b5);
```

Figure 6.17 8-Bit Adder Boolean Equations

```
p6 = /(/a5*/b5);
g6 = /gn6;
gn7 = /(a6*b6);
p7 = /(/a6*/b6);
g7 = /gn7;
gn8 = /(a7*b7);

p8 = /(/a7*/b7);
g8 = /gn8;
"level-1 functions"
gl_l = g4 + p4*g3 + p4*p3*g2 + p4*p3*p2*g1;
g2_l = g8 + p8*g7 + p8*p7*g6 + p8*p7*p6*q5;
"carry information"
cl = gl + pl*c0;
c1 = g1 + p2*c0,

c2 = g2 + p2*g1 + p2*p1*c0;

c3 = g3 + p3*g2 + p3*p2*g1 + p3*p2*p1*c0;
c4 = gl_1 + p4*p3*p2*p1*c0;
c5 = g5 + p5*g1_1 + p5*p4*p3*p2*p1*c0;

c6 = g6 + p6*g5 + p6*p5*g1_1 + p6*p5*p4*p3*p2*p1*c0;

c7 = g7 + p7*g6 + p7*p6*g5 + p7*p6*p5*g1_1 +
             p7*p6*p5*p4*p3*p2*p1*c0;
c8 = g2_1 + p8*p7*p6*p5*g1_1 + p8*p7*p6*p5*p4*p3*p2*p1*c0;
"addition functions"
sum0 : xrl = c0;
        xr2 = pl * gnl;
suml : xrl = cl;
         xr2 = p2 * gn2;
sum2 : xrl = c2;
         xr2 = p3 * gn3;
sum3 : xrl = c3;
         xr2 = p4 * gn4;
sum4 : xrl = c4;
         xr2 = p5 * gn5;
sum5 : xrl = c5;
         xr2 = p6 * gn6;
sum6 : xrl = c6;
         xr2 = p7 * gn7;
sum7 : xrl = c7;
         xr2 = p8 * gn8;
    Figure 6.17 8-Bit Adder Boolean Equations (Continued)
```

```
PLHS501
                     8BITADDR
                                       Time = 15:41:33 Date = 9/14/1987
" <-----INPUTS-----> < B,/B > < XOR > < /0,0 > TRACE TERMS
  222211111111111
321098765432109876543210 76543210 76543210 76543210
  OOOOOOOOOOOOOOOIIIIII HHHHLLLL LLLLLLLL LLLLHHHL ;
  111111100000000101111111 HHHHLLLL HHHHHHHH LLLLHHHL
  111111100000001001111111 HHHHLLLL LILLILHHHH
  Olllilllooooooollllllll HHHHLLLL HLLLILL LLLLHHHL ;
  101010100101010101111111 HHHHLLLL HHHHHHHH LLLLLHHHL ;
  101010100101010111111111 HHHHLLLL LILLLILL LLLLHHHHH ;
  OOIIII110001111101111111 HHHHLLLL LHLHHHHL LLLLHHHL ;
                              ------ I/O CONTROL LINES

00000000 DESIGNATED I/O USAGE

00000000 ACTUAL I/O USAGE
PINLIST...

14 13 12 11 10 09 07 06 05 04 03 02 01 52 51 50 49 48 47 45 44 43 42 41


18 17 16 15 40 39 38 37 36 35 33 32 31 30 29 28

27 26 25 24 23 22 21 19 ;
                  Figure 6.19 8-Bit Adder Simulation Log File
```

```
File Name : ENCODER
Date : 9/15/1987
Time: 9:38:43
Right
  LABEL
           ** FNC **PIN
                                 PIN** FNC **
                                               LABEL
           ** +5V ** 8-
                               -46 ** +5V **VCC
I18N
                  ** 9-
                                -45 ** I
                                          **I4N
                  ** 10-
119N
                                -44 ** I
                                          **I3N
                 ** 11-
                                -43 ** I
                                          **I2N
I21N
                 ** 12-
                               -42 ** I
                                          **I1N
122N
                 ** 13-
                                -41 ** I
                                          **ION
123N
           ** I
                 ** 14-
                               -40 ** I
                                          **I31N
I24N
                 ** 15-
                                -39 ** I
                                          **I30N
                 ** 16-
125N
           ** I
                               -38 ** I
                                          **I29N
           ** I
                 ** 17-
                                -37 ** I
T26N
                           1
                                          **I28N
                               -36 ** 0
127N
           ** I
                 ** 18-
                                         **N/C
           ** 0
                 ** 19-
                               -35 ** 0
N/C
                                          **A4N
           ** OV ** 20-
GND
                               -34 ** OV **GND
                                Top
PIN** FNC **
       Bottom
  LABEL
           ** FNC **PIN
                                               LABEL
           ** 0 ** 21-
N/C
                                - 7 ** T
                                          **T17N
                 ** 22-
N/C
           ** 0
                                - 6 ** I
                                          **I16N
N/C
           ** 0
                  ** 23-
                                - 5 ** I
                                          **I15N
                 ** 24-
N/C
           ** /0
                                - 4 ** I
                                          **T14N
           ** /0
                 ** 25-
                               |- 3 ** T
N/C
                          L
                                          **I13N
N/C
           ** /0
                 ** 26-
                           Н
                               - 2 ** I
                                          **I12N
N/C
           ** /0
                 ** 27-
                           S
                                - 1 ** I
                                          **T11N
GSN
           ** 0
                  ** 28-
                               -52 ** I
                                          **I10N
EON
           ** 0
                  ** 29-
                                -51 ** I
                                          **I9N
AON
           ** 0
                  ** 30-
                                -50 ** I
                                          **I8N
                                          **I7N
AlN
           ** 0
                  ** 31-
                                -49 ** I
A2N
           ** 0
                  ** 32-
                                -48 ** I
                                          **I6N
              Figure 6.20 Encoder Pin List
```

32- to 5-BIT PRIORITY ENCODER

This relatively simple example demonstrates the capability of the PLHS501 to be programmed with functions that are not available in 'standard' device libraries. The equations may look difficult at first glance. However, there is a pattern to the encoding. Referring to Figure 6.21, Lab4 – Lab1 are terms that are common to several outputs (A4n – A0n). Separating them from the main equations allows a total reduction in the numbers of gates used



```
File Name : ENCODER
Date : 9/15/1987
Time : 9:39:1
@DEVICE TYPE
PLHS501
@DRAWING
@REVISION
@DATE
@SYMBOL
@COMPANY
@NAME
@DESCRIPTION
32 TO 5 PRIORITY ENCODER
(acommon product term
cptl = i26n*i27n*i28n*i29n*i30n*i3ln;
cpt2 = i20n*i2ln*i22n*i23n*i24n*i25n;
cpt3 = il4n*il5n*il6n*il7n*il8n*il9n;
cpt4 = i8n*i9n*il0n*illn*il2n*il3n;
@INTERNAL NODE
eo labl lab2 lab3 lab4
@I/O DIRECTION
@I/O STEERING
@LOGIC EQUATION
labl = ( /i3ln
         + [/i27n*i28n*i29n*i30n*i3ln]
         + [/i23n*i24n*i25n*cptl]
         + [/il9n*cpt2*cpt1]
        + [/il5n*il6n*il7n*il8n*il9n*cpt2*cpt1]
        + [/illn*il2n*il3n*cpt3*cpt2*cpt1]
        + [/i7n*cpt4*cpt3*cpt2*cpt1]
        + [/i3n*i4n*i5n*i6n*i7n*cpt4*cpt3*cpt2*cpt1]);
lab2 = ( [/i23n*i24n*i25n*cpt1]
          [/i22n*i23n*i24n*i25n*cpt1]
        + [/i2ln*i22n*i23n*i24n*i25n*cptl]
        + [/i20n*i2ln*i22n*i23n*i24n*i25n*cptl]);
lab3 = ( [/il5n*il6n*il7n*il8n*il9n*cpt2*cpt1]
        + [/il4n*il5n*il6n*il7n*il8n*il9n*cpt2*cpt1]
        + [/il3n*cpt3*cpt2*cpt1]
        + [/il2n*il3n*cpt3*cpt2*cpt1]);
lab4 = (/i3ln
        + [/i30n*i31n]
        + [/i29n*i30n*i3ln]
        + [/i28n*i29n*i30n*i31n]
       Figure 6.22 Encoder Boolean Equations
```

```
+ [/i27n*i28n*i29n*i30n*i31n]
         + [/i26n*i27n*i28n*i29n*i30n*i31n]
          + [/i25n*cptl]
          + [/i24n*i25n*cptl]);
    -/(i0n*iln*i2n*i3n*i4n*i5n*i6n*i7n
          *i8n*i9n*il0n*illn*il2n*il3n*il4n*il5n
         *i16n*i17n*i18n*i19n*i20n*i21n*i22n*i23n
         *i24n*i25n*cptl);
 eon - eo;
 a0n = /( labl
            [/i29n*i30n*i31n]
         + [/i25n*cpt1]
         + [/i2ln*i22n*i23n*i24n*i25n*cptl]
         + [/il7n*il8n*il9n*cpt2*cpt1]
         + [/il3n*cpt3*cpt2*cpt1]
         + [/i9n*il0n*illn*il2n*il3n*cpt3*cpt2*cpt1]
         + [/i5n*i6n*i7n*cpt4*cpt3*cpt2*cpt1]
         + [/iln*i2n*i3n*i4n*i5n*i6n*i7n*cpt4*cpt3*cpt2*cpt1]);
aln - /( labl
         + [/i30n*i3ln]
         + [/i26n*i27n*i28n*i29n*i30n*i31n]
         + [/i22n*i23n*i24n*i25n*cptl]
         + [/122n*123n*124n*123n*ecpt1]
+ [/i18n*i19n*ept2*ept1]
+ [/i14n*i15n*i16n*i17n*i18n*i19n*ept2*ept1]
+ [/i10n*i1ln*i12n*i13n*ept3*ept2*ept1]
         + [/i6n*i7n*cpt4*cpt3*cpt2*cpt1]
         + [/i2n*i3n*i4n*i5n*i6n*i7n*cpt4*cpt3*cpt2*cpt1]);
a2n = /( /i3ln
         + [/i30n*i31n]
         + [/i29n*i30n*i31n]
         + [/i28n*i29n*i30n*i31n]
         + lab2
         + lab3
         + [/i7n*cpt4*cpt3*cpt2*cpt1]
         + [/i6n*i7n*cpt4*cpt3*cpt2*cpt1]
         + [/i5n*i6n*i7n*cpt4*cpt3*cpt2*cpt1]
         + [/i4n*i5n*i6n*i7n*cpt4*cpt3*cpt2*cpt1]);
a3n = /( lab4
         + 1ab3
         + [/illn*il2n*il3n*cpt3*cpt2*cpt1]
         + [/il0n*illn*il2n*il3n*cpt3*cpt2*cpt1]
+ [/i9n*il0n*illn*il2n*il3n*cpt3*cpt2*cpt1]
         + [/i8n*i9n*il0n*illn*il2n*il3n*cpt3*cpt2*cpt1]);
a4n = /(lab4)
         + lab2
         + [/i19n*cpt2*cpt1]
         + [/il8n*il9n*cpt2*cpt1]
         + [/il7n*il8n*il9n*cpt2*cpt1]
         + [/il6n*il7n*il8n*il9n*cpt2*cpt1]);
                     Figure 6.22 Encoder Boolean Equations (Continued)
```

```
" 32 to 5 Priority Encoder Simulation Input
 НИННИНИНИНИНИНИНИНИНИН "131 - LSB low" нининининининининининин "10 - MSB low"
 нининининининининин нининин 130 low нинининининининининин нининин 129°
 нинининининининининининин инининиL "128"
 нинининининининин тинини теле
 нининининининининин нінинин "126"
 ннининининининининин ингинин "125"
 нининининининининин инигини
                              "I24"
 НГИНИНИНИНИНИНИНИНИНИНИ ИНИНИНИ "153
 ннгинининининининин ининини 131.
 ннигиннининнинниннин ининнин 120
 нингининининининин ининини 119
 нинининининининин ининини "118"
 ннининининининин ининини *117
 ннинингининининин ининини тile.
 ннининицининининин ининини "115"
 нинининининининин ининини "114"
 ННИНИННИН «113
 нинининининининин ининини 112
 ннининининин
 нининининининининин ининини "110,
 НИНИНИНИНИНИНЕНИЕННИНИ ИНИМИВА 12
ИНИВИНИНИНИНИНИНИНИНИ ИНИМИНИНИ "18"
17"
 нинининининининин ининини "16"
 нинининининининин ининини 15
 нининининининининин ининини "13"
 ннинининининининин ининини "12"
 нининининининининин
 нинининининининининини инининин
                             "IO"
 ННННННННННННННННННН ННННННН "ALL HIGH
 LITELLITE THE TALL ALL LOW.
 HHHLHHHLHHHLHHHLHHHLHH HHHLHHLH "Several simultaneously"
       Figure 6.23 Encoder Simulation Input File
```


```
Time = 15:50:28 Date = 9/14/1987
PT.HS501
              ENCODER
   -----INPUTS-----> < B,/B > < XOR > < /O,O > TRACE TERMS
 222211111111111
 321098765432109876543210 76543210 76543210 76543210
 11111111111111111111111 11111111 LHHHHHLH LLLLHHHH ;
 111111111111111111111111 11110111 LILLLHL LILLHHHH
 11111111111111111111111 11111111 LHHHHHHL LLLLHHHH
 11111111111111111111111 11111011 LLLLLHHL LLLLHHHH
 11111111111111111111111 11111110 LLLLHHHL LLLLHHHH
 11111111111111111111111 O1111111 LLLHLLHL LLLLHHHH
 11111111111111111111111 10111111 LILHLHHL LILLHHHH
 Ollillillillillillillilli lllilli LLHLLLHL LLLLHHHH
 1011111111111111111111 11111111 LLHLLHHL LLLLHHHH
 JIOJIJIJIJIJIJIJIJIJIJI JIJIJIJI LLHLHLHL LIIILHHHH
 11110111111111111111111 11111111 LLHHLLHL LLLLHHHH
 11111011111111111111111 11111111 LLHHLHHL LLLLHHHH
 11111101111111111111111 11111111 LLHHHLHL LLLLHHHH
 11111110111111111111111 11111111 LLHHHHHL LLLLHHHH
 11111111011111111111111 11111111 LHLLLLHL LLLLHHHH
 11111111101111111111111 11111111 LHLLLHHL LLLLHHHH
 11111111110111111111111 11111111 LHLLHLHL LLLLHHHHH
 11111111111011111111111 11111111 LHLLHHHL LILLHHHH
  111111111111101111111111 11111111 LHLHLLHL LILLHHHH
 1111111111111101111111111 11111111 LHLHLHHL LLLLHHHH
 1111111111111110111111111 11111111 LHLHHLHL LILLHHHH
 111111111111111011111111 11111111 THTHHHHT TTTTHHHH
 111111111111111101111111 11111111 LHHLLLHL LLLLHHHH
 111111111111111110111111 11111111 LHHLLHHL LLLLHHHH
 111111111111111111011111 11111111 THHTHTHT TTTTHHHH
 111111111111111111111111 11111111 LHHHHHHL LLLLHHHH
  11111111111111111111111 11111111 LHHHHHLH LLLLHHHH ;
  111011101111011110111011 11101101 LLLLHLHL LLLLHHHH ;
                                I/O CONTROL LINES
                       IIIIIIII
                               DESIGNATED I/O USAGE
                      IIIIIIII ACTUAL I/O USAGE
- 14 13 12 11 10 09 07 06 05 04 03 02 01 52 51 50 49 48 47 45 44 43 42 41 18 17 16 15 40 39 38 37 36 35 33 32 31 30 29 28
~ 27 26 25 24 23 22 21 19 ;
              Figure 6.24 Encoder Simulation Log File
```

8-BIT SHIFT REGISTER WITH SEQUENCE DETECTOR

This example demonstrates an application using D type edge-triggered flip-flops. Six NAND gates are used for each flip-flop (Figure 3.2). Note that to add an asynchronous reset and/or set to any flip-flop requires no additional gates. Also, every flip-flop must have a reset or set line to initialize it. Without being initialized, the simulator will not be able to determine the output states as it could power-up in either a set or reset condition. An uninitialized flip-flop will cause AMAZE 1.6 to display a message indicating the outputs are not stabilized within a certain time period.

As can be seen from the block diagram (Figure 6.26) this design consists of an 8-bit shift register, 3-bit ripple counter and 2 flipflops that are set only upon detection of specific patterns. The patterns are read from the Q and QN outputs of the shift register. Since the input to the second flip-flop has the output of the first flip-flop as a product term, detection of the first pattern is a requirement for the detection of the second.

```
File Name : 8BTSHFT
Date: 9/15/1987
Time : 9:41:16
PIN** FNC **
  LABEL
            ** FNC **PIN
                                                  T.ARFT.
                                 -46 ** +5V **VCC
              +5V **
                      8-
                                 -45 ** T
                                            **N/C
                   ** 9-
N/C
                                             **N/C
                                 -44 ** T
N/C
                   ** 10-
                   ** 11-
                                  -43 ** I
                                             **N/C
N/C
                                            **N/C
                                 -42 ** I
DATA
                   ** 12-
                                  -41 ** I
                                             **N/C
                   ** 13-
CIK
                            Н
                   ** 14-
                                  -40 ** /0
                                             **N/C
                            S
RST
                                            **CQ2
            ** 0
                   ** 15-
                                  -39 ** /0
DET1
                                            **CQ1
                                  -38 ** /0
            ** 0
                   ** 16-
DETIN
            ** 0
                                  -37 ** /0
                                             **CQ0
                   ** 17-
DET2
            ** 0
DET2N
                                  -36 ** 0
            ** 0
                                  -35 ** O
                                             **06
N/C
            ** OV
                                 -34 ** OV
                                             **GND
   LABEL
            ** FNC **PIN
                                   PIN** FNC **
                                                  LABEL
N/C
            ** 0
                   ** 21-
                                  - 7 ** I
                                             **N/C
                                  - 6 ** I
N/C
            ** 0
                   ** 22-
                                             **N/C
                                  - 5 ** I
N/C
            ** 0
                   ** 23-
                                             **N/C
            ** /0
                  ** 24-
                                  - 4 ** T
                                             **N/C
N/C
            ** /0
                                  - 3 ** T
                                             **N/C
N/C
                  ** 25-
                            L
            ** /0
                  ** 26-
                                  - 2 ** T
                                             **N/C
N/C
                             Н
            **
                                  - 1 ** I
                  ** 27-
                                             **N/C
N/C
               /0
                             S
            ** 0
                   ** 28-
                                  -52 **
                                             **N/C
00
            ** 0
                   ** 29-
                                  -51 **
                                             **N/C
01
            ** 0
                   ** 30-
                                  -50 **
                                             **N/C
            ** 0
                   ** 31-
                                  -49 ** I
                                             **N/C
                                 -48 **
                                             **N/C
            ** 0
                   ** 32-
04
                                             **N/C
                   ** 33-
            ** 0
              Figure 6.25 8-Bit Shifter Pin List
```



```
File Name : 8BTSHFT
Date : 9/15/1987
Time : 9:41:35
@DEVICE TYPE
PLHS501
@DRAWING
@REVISION
@DATE
@SYMBOL
@COMPANY
@NAME
@DESCRIPTION
8 Bit Shift Register with 16 bit Sequence Detector
@INTERNAL NODE
SNO,RNO,QO;
SN1,RN1,Q1;
SN2,RN2,Q2;
SN3, RN3, Q3;
SN4, RN4, Q4;
SN5, RN5, Q5;
SN6, RN6, Q6;
SN7, RN7, Q7;
CSN0, CRN0, CQN0;
CSN1, CRN1, CQN1;
CSN2, CRN2, CQN2;
PSN0, PRN0;
PSN1, PRN1;
@COMMON PRODUCT TERM
PAT1 = Q7*Q6*Q5*Q4*Q3*Q2*Q1*Q0;
PAT2 = Q7*Q6*Q5*Q4*Q3*Q2*Q1*Q0;
@I/O DIRECTION
@I/O STEERING
@LOGIC EQUATION
"8 D-TYPE FLIP FLOPS CONNECTED AS SHIFT REGISTER"
SNO = /(CLK*RST*(/(SNO*(/[DATA*RST*RNO]))));
RNO = /(SNO*CLK*(/[DATA*RST*RNO]));
QO = /(SNO*(/[RNO*QO*RST]));
SNl = /(CLK*RST*(/(SNl*(/[QO*RST*RN1]))));
RNl = /(SNl*CLK*(/[QO*RST*RN1]));
Ql = /(SNl*(/[RNl*Ql*RST]));
    Figure 6.27 8-Bit Shifter Boolean Equations
```

```
SN2 = /(CLK*RST*(/(SN2*(/[Ql*RST*RN2]))));
RN2 = /(SN2*CLK*(/[Ql*RST*RN2]));
Q2 = /(SN2*(/[RN2*Q2*RST]));
        SN3 = /(CLK*RST*(/(SN3*(/[Q2*RST*RN3]))));
        RN3 = /(SN3*CLK*(/[Q2*RST*RN3]));
        O3 = /(SN3*(/[RN3*O3*RST]));
        SN4 = /(CLK*RST*(/(SN4*(/[Q3*RST*RN4]))));
RN4 = /(SN4*CLK*(/[Q3*RST*RN4]));
        Q4 = /(SN4*(/[RN4*Q4*RST]));
        SN5 = /(CLK*RST*(/(SN5*(/[Q4*RST*RN5]))));
        RN5 = /(SN5*CLK*(/[Q4*RST*RN5]));
        Q5 = /(SN5*(/[RN5*Q5*RST]));
        SN6 = /(CLK*RST*(/(SN6*(/[Q5*RST*RN6]))));
        RN6 = /(SN6*CLK*(/[Q5*RST*RN6]));
Q6 = /(SN6*(/[RN6*Q6*RST]));
        SN7 - /(CLK*RST*(/(SN7*(/[Q6*RST*RN7]))));
        RN7 = /(SN7*CLK*(/[Q6*RST*RN7]));
Q7 = /(SN7*(/[RN7*Q7*RST]));
         00 = Q0;
         01 - Q1;
         02 - 02;
         03 = Q3;
         04 - Q4;
         05 = Q5;
         06 = Q6;
         "3 D-TYPE FLIP FLOPS CONNECTED AS A RIPPLE COUNTER"
         CSNO = /(CLK*RST*(/(CSNO*(/[CQNO*RST*CRNO]))));
         CRN0 = /(CSN0*CLK*(/[CQN0*RST*CRN0]));
CQ0 = /(CSN0*CQN0);
         CQN0 = /(CRN0*CQ0*RST);
        CSN1 = /(CQN0*RST*(/(CSN1*(/[CQN1*RST*CRN1]))));
CRN1 = /(CSN1*CQN0*(/[CQN1*RST*CRN1]));
CQ1 = /(CSN1*CQN1);
CQN1 = /(CRN1*CQ1*RST);
         CSN2 = /(CQN1*RST*(/(CSN2*(/[CQN2*RST*CRN2]))));
        CRN2 = /(CSN2*CQN1*(/[CQN2*RST*CRN2]));
CQ2 = /(CSN2*CQN2);
CQN2 = /(CRN2*CQ2*RST);
"2 D-TYPE FLIP FLOPS USED FOR PATTERN SEQUENCE DETECTION.
Sequence to be detected is 16 bits - 55AA Hex.
When the pattern is detected, pin det2 will go high.
In this example, both pattern 1 and pattern 2 are set to FF hex.
change the pattern to 55AA, the STD file (P68 and P70) was edited using FTE. This was necessary because AMAZE 1.6 only allows 40 internal labels,
so it was not possible to reference the QN nodes of the shift register
flip-flops.
         PSN0 = /(CQN2*RST*(/(PSN0*(/[PAT1*RST*PRN0]))));
         PRNO = /(PSNO*CQN2*(/[PAT1*RST*PRNO]));
DETIN = (PSNO*/DET1);
         DET1 = (PRNO*/DET1N*RST);
         PSN1 = /(CQN2*RST*(/(PSN1*(/[PAT2*DET1*RST*PRN1]))));
         PRN1 = /(ESN1*CQN2*(/[PAT2*DET1*RST*PRN1]));

DET2N = (PSN1*/DET2);

DET2 = (PRN1*/DET2N*RST);
                     Figure 6.27 8-Bit Shifter Boolean Equations (Continued)
```

Col for P 67
A
H Col for P 68
Col for P 69
.AA
HH Col for P 70
Col for P 71
ннн
Original STD file showing P 68 and P 70
Col for P 67
A
H Col for P 68
Col for P 69
.A
H
AAAAAAA
Col for P 71
ннн
TB0970S
Figure 6.28 Portion of STD Files

```
8 Bit Shift Register Simulation Input
LLLнинининининининин -----
LHLНИНИНИНИНИНИНИНИН -----
ІДНИНИНИНИНИНИНИНИНИН -----
нттининининининини -----
ННДНИНИНИНИНИНИНИНИНИН ----- "BIT 7 L"
ндинининининининин -----
ННИНИНИНИНИНИНИНИНИНИН ----- "BIT 6 H"
нттинининининининин -----
ННЦНИНИНИНИНИНИНИНИНИН ----- "BIT 5 L"
НДИНИНИНИНИНИНИНИНИНИН ------
ННИНИНИНИНИНИНИНИНИНИНИН ----- "BIT 4 H"
НІДИНИНИНИНИНИНИНИНИНИ -----
ННІННИННИННИННИННИННИН ----- "BIT 3 L"
ндинининининининин -----
НІДИНИНИНИНИНИНИНИНИНИНИ -----
НДИНИНИНИНИНИНИНИНИНИНИН -----
нинининининининин ----- "віт 7 н"
нгтинининининининин -----
ИНІЛИННИНИНИНИНИНИНИНИНИ ----- "BIT 6 L"
ніннининнинниннинни -----
НІДИННИНИНИНИНИНИНИНИН -----
ННДНИНИНИНИНИНИНИНИНИН ----- "BIT 4 L"
ндинининининининин -----
ННИНИНИНИНИНИНИНИНИНИН ----- "BIT 3 H"
нттининининининини
ННІННИННИННИННИННИННИН ----- "BIT 2 L"
нт.нининининининининин ------
ИНИНИНИНИНИНИНИНИНИНИН ----- "BIT 1 H"
нтлининининининин ------
нигинининининининин -----
Figure 6.29 8-Bit Shifter Simulation Input File
```

```
PLHS501
                              Time = 16:34:21 Date = 9/14/1987
    -----INPUTS-----> < B,/B > < XOR > < /O,O > TRACE TERMS
222211111111111
 321098765432109876543210 76543210 76543210 76543210
 OOOIIIIIIIIIIIIIIIIIIII HLHLLLLL LLLLLLLL LLLLHHHH ;
 110111111111111111111111 HLHLILLH LITTITT TITTHHHH
 101111111111111111111111111111 HLHITTTH TITITIT TITTHHHH
 111111111111111111111111 HTHTTTHT TTTTTTH TTTTHHHH
  10011111111111111111111 HTHTTTHT TTTTTTH TTTTHHHH
 11011111111111111111111 HLHLLLHH LLLLLHL LLLLHHHHH
  1011111111111111111111 HTHTTTHH TTTTTHT TTTTHHHH
  11111111111111111111111 HTHITHIT ITITHIH ITITHHHH
  10011111111111111111111 HTHTTHIT TITITHTH TITTHHHH
  11011111111111111111111 HEHELHEH LELLHEHE LELLHHHHH
  JOIIIIIIIIIIIIIIIIIIII HLHLLHLH LLLLHHHH
  111111111111111111111111 HEHEEHHE ELEHEHEH ELEEHHHHH ;
 10011111111111111111111 HEHEEHHE ETTHEHHH
  1101111111111111111111 HLHLLHHH LLHLHLHL LLLLHHHH ;
  10111111111111111111111 HLHILHHH ILHLHLHL LILLHHHH ;
  11111111111111111111111 HILHLILL LHLHLHLH LILLHHHH ;
 10111111111111111111111 HLLHLLLL LHLHLHLH LLLLHHHH ;
  11111111111111111111111 HILHLILH HIHLHHH LILLHHHH ;
 10011111111111111111111 HLLHLLLH HLHLHLHH LLLLHHHH
  11011111111111111111111 HLLHLLHL LHLHLHHL LLLLHHHH ;
 10111111111111111111111 HLLHLLHL LHLHLHHL LLLLHHHH ;
  11111111111111111111111 HLLHLLHH HLHLHHLH LLLLHHHH ;
  10011111111111111111111 HLLHLLHH HLHLHHLH LLLLHHHH ;
  11011111111111111111111 HLLHLHLL LHLHHLHL LLLLHHHH ;
 10111111111111111111111 HLLHLHLL LHLHHLHL LLLLHHHH
  111111111111111111111111 HLLHLHLH HLHHLHLH LLLLHHHH
  10011111111111111111111 HLLHLHLH HLHHLHLH LLLLHHHH
  11011111111111111111111 HLLHLHHL LHHLHLH LLLLHHHH
  10111111111111111111111 HLLHLHHL LHHLHLHL LLLLHHHH
  11111111111111111111111 HLLHLHHH HHLHLHLH LLLLHHHH ;
  10011111111111111111111 HLLHLHHH HHLHLHLH LLLLHHHH ;
  11011111111111111111111 LHHLLLLL HLHLHLHL LLLLHHHH ;
  10011111111111111111111 LHHLLLLL HLHLHLHL LLLLHHHH ;
  11011111111111111111111 LHHLLLLH LHLHLHLL LLLLHHHH ;
 Olllillillillillillilli HLHLLLLL LLLLLLL LLLLHHHH ;
                                  I/O CONTROL LINES
                         00000000 DESIGNATED I/O USAGE
00000000 ACTUAL I/O USAGE
 14 13 12 11 10 09 07 06 05 04 03 02 01 52 51 50 49 48 47 45 44 43 42 41
18 17 16 15 40 39 38 37 36 35 33 32 31 30 29 28 27 26 25 24 23 22 21 19 ;
               Figure 6.30 8-Bit Shifter Simulation Log File
```

4-BIT SYNCHRONOUS COUNTER

This counter produces a binary count on outputs Count3 – Count0. Note the required reset (RST) input to initialize all of the flipflops. The inputs for each flip-flop were first determined by drawing the desired output waveforms. Next, Karnaugh maps were used to reduce the number of terms and determine the logic equations for the input to each flipflop. This technique could be used to construct a counter whose outputs produce some count other than binary.

The simulation only consists of a reset, followed by a number of clocks to count from 0 through 15 and back to 0.

```
File Name : 4BTCOUNT
Date: 9/15/1987
Time : 9:57:5
|-46 ** +5V **VCC
         ** FNC **PIN
  LABEL
VCC
           ** +5V ** 8-
** I ** 9-
                               -45 ** I
                                         **N/C
CLK
                 ** 10-
                               -44 ** I
                                          **N/C
           ** I
RST
           ** T
                ** 11-
                          P
                               -43 ** I
                                          **N/C
N/C
                               -42 ** I
           ** I
                ** 12-
                                          **N/C
N/C
           ** I
                ** 13-
                               -41 ** I
                                          **N/C
N/C
                          Н
                 ** 14-
                               -40 ** /O
                                          **N/C
N/C
COUNTO
           ** 0
                 ** 15-
                               J-39 ** /O
                                          **N/C
           ** 0 ** 16-
                               -38 ** /0
                                          **N/C
COUNT1
           ** 0
                               |-37 ** /0
                                          **N/C
COUNT2
                               -36 ** 0
COUNT3
           ** 0
                ** 18-
                                          **N/C
           ** 0
                 ** 19-
                               -35 ** 0
                                          **N/C
           ** OV ** 20-
                               -34 ** OV
GND
                                          **GND
                                PIN** FNC **
           ** FNC **PIN
                                               LABEL
  LABEL
           ** 0 ** 21-
** 0 ** 22-
                               |- 7 ** I
                                          **N/C
N/C
                                          **N/C
                               - 6 ** I
N/C
                 ** 23-
                               |- 5 ** I
           ** 0
                                          **N/C
N/C
           ** /0 ** 24-
                               - 4 ** I
                                          **N/C
N/C
           ** /0 ** 25-
                               - 3 ** I
                                          **N/C
N/C
                          L
           ** /0 ** 26-
                               - 2 ** I
                                          **N/C
N/C
                          Н
           ** /0 ** 27-
                          S
                                          **N/C
N/C
           ** 0 ** 28-
** 0 ** 29-
                                          **N/C
                               -52 ** I
N/C
                               -51 ** I
                                          **N/C
N/C
           ** 0
                ** 30-
                               -50 ** I
                                          **N/C
N/C
                 ** 31-
                               -49 ** I
                                          **N/C
                 ** 32-
                               -48 ** I
                                          **N/C
           ** 0
                 ** 33-
                               |-47 ** I
                                          **N/C
            Figure 6.31 4-Bit Counter Pin List
```

```
File Name : 4BTCOUNT
Date : 9/15/1987
Time : 9:57:28
@DEVICE TYPE
PT.HS501
@DRAWING
GREVISION
(dDATE
@SYMBOL
(COMPANY
(dNAME
(@DESCRIPTION
   4 bit synchronous counter
@INTERNAL NODE
datal, data2, data3;
csn0,crn0,cq0,cqn0;
csnl,crnl,cql,cqnl;
csn2,crn2,cq2,cqn2;
csn3,crn3,cq3,cqn3;
@COMMON PRODUCT TERM
@I/O DIRECTION
@I/O STEERING
@LOGIC EQUATION
"INPUTS FOR EACH FLIP-FLOP"
DATA1 = [(CQ1*CQN0)+(CQN1*CQ0)];
DATA2 = [(CQ0*CQ1*CQN2)+(CQN0*CQ2)+(CQN1*CQ2)];
"4 D-TYPE FLIP FLOPS CONNECTED AS A SYNCHRONOUS COUNTER"
CSN0 = /(CLK*RST*(/(CSN0*(/[CQN0*RST*CRN0])));
CRN0 = /(CSN0*CLK*(/[CQN0*RST*CRN0]));
CQ0 = /(CSN0*CQN0);
CQN0 = /(CRN0*CQ0*RST);
CSNl = /(CLK*RST*(/(CSNl*(/[DATAl*RST*CRN1]))));
CRN1 = /(CSN1*CLK*(/[DATA1*RST*CRN1]));
CQ1 = /(CSN1*CQN1);
CQN1 = /(CRN1*CQ1*RST);
CSN2 = /(CLK*RST*(/(CSN2*(/[DATA2*RST*CRN2]))));
CRN2 = /(CSN2*CLK*(/[DATA2*RST*CRN2]));
CQ2 = /(CSN2*CQN2);
CQN2 = /(CRN2*CQ2*RST);
CSN3= /(CLK*RST*(/(CSN3*(/[DATA3*RST*CRN3]))));
CRN3 - /(CSN3*CLK*(/[DATA3*RST*CRN3]));
CQ3 - /(CSN3*CQN3);
CQN3 - /(CRN3*CQ3*RST);
"Connection to output pins"
count0=cq0;
countl-cql;
count2=cq2;
count3=cq3;
"TERMINAL COUNT PIN"
TC=(CO0*CO1*CO2*CO3);
           Figure 6.32 4-Bit Counter Boolean Equations
```

*		
" 4 Bit Synchronous Counte	er Simulat	ion Input
M		
ннинттининининниннин		
ннинниннинниннин		
ннинининниннинни		
ннннгинннинннинн		
ннинниннинниннинн		
нинитининининин		
ннинниннинниннинн		
нниндининининин		
ннинниннинниннин		
ннинтиннининнинн		
ннинниннинниннинн		
ннинининниннинн		
ннинининининнин		
ннннгинннннннннн		
ннининининининин		
ннининнинниннин		
ннинниннинниннинн		
ННННИННННННННН		
ниннинининниннинн		
ннининниннинн		
ннинниннинниннин		
нннитиннинниннинн		
ннинниннинниннинни		
ннинининининнин		
ннинниннинниннинн		
нниннинниннинни		
ннининининининин		
нннниннннннннн		
ннинининнинниннин	·	"COUNT14"
ннннг	·	
нннининнинннинн	I	"COUNT15"
нннытиннниннннн		
ннинининининнинн	·	"COUNTO"
QUIT		
		TB04040S
Fig 0.00 4 Bit 0 to 4		L
Figure 6.33 4-Bit Counter S	simulation	input File

```
PLHS501
                       Time = 16:57:51 Date = 9/14/1987
             4 BTCOUNT
       --INPUTS-----> < B,/B > < XOR > < /O,O > TRACE TERMS
 222211111111111
 321098765432109876543210 76543210 76543210 76543210
 11110011111111111111111 LILLILL LILLILL LILLHHHL ;
 111110111111111111111111 LILLLLL LLLLLLL LLLLHHHL;
 111111111111111111111111 LILHLLLL LILLLLL LILLHHHL ;
 111110111111111111111111 LILHKLILL LILLKHHL
 111111111111111111111111 LLHILLIL LLILILL LILLHHRE ;
 11111011111111111111111 LLHLLLL LLLLLLL LLLLHHHL ;
 111110111111111111111111 LIHHLILL LILLLILL LILLHHHL
 11111111111111111111111 LHLLLLL LLLLLLL LLLLHHHL ;
 111110111111111111111111 LHLLLLLL LLLLLLL LLLLHHHL
 11111111111111111111111 LHLHLLLL LLLLLLL LLLLHHHL ;
 111110111111111111111111 LHLHLILL LILILLI LILLHHHL
 11111111111111111111111 LHHLLLLL LLLLLLL LLLLHHHL ;
 111110111111111111111111 LHHLLLLL LLLLLLLL LLLLHHHL ;
 11111111111111111111111 THHHTTTT TTTTTTT TTTTHHHT
 111110111111111111111111 LHHHLLLL LLLLLLL LLLLHHHL
 111110111111111111111111 HILLILLE LILLILL LILLHHHL
 11111111111111111111111 HHLLLLL LLLLLLL LLLLHHHL ;
 111110111111111111111111 HHLLLLLL LLLLLLL LLLLHHHL
 11111111111111111111111 HHLHLLLL LLLLLLL LLLLHHHL ;
 111111111111111111111111 HHHLLLLL LLLLLLL LLLLHHHL ;
 111110111111111111111111 HHHLLLLL LILLLILL LILLHHHL ;
 111111111111111111111111 HHHHLLLL LLLLLLL LLLLHHHH ;
 111110111111111111111111 HHHHLLLL LLLLLLL LLLLHHHH
 111111111111111111111111 LILILLL LILLILL LILLHHHL ;
                             I/O CONTROL LINES
                    OOOOOOOO DESIGNATED I/O USAGE
                    OOOOOOOO ACTUAL I/O USAGE
 PINLIST.
 14 13 12 11 10 09 07 06 05 04 03 02 01 52 51 50 49 48 47 45 44 43 42 41
* 18 17 16 15 40 39 38 37 36 35 33 32 31 30 29 28
* 27 26 25 24 23 22 21 19 ;
           Figure 6.34 4-Bit Counter Simulation Log File
```

Bibliography

- Cavalan, N., 1984, Third Generation PLD Architecture Breaks AND-OR Bottlenecks. Proceedings of WESCON.
- 2. Wong, D., 1985, New Developments in Programmable Logic Devices. MIDCON Session 19. Chicago
- Gheissari, A and Safari, B., 1987, High Speed, High Complexity PLDs and Applications. ELECTRO-87 Session 35.
- 4. Hartman, Robert, May 1984, Estimating Gate Complexity of Programmable Logic Devices. VLSI Design. PP 100 103
- 5. Minnick, R.C., Dec. 1964, Cutpoint Cellular Logic, I.E.E.E. Transactions on Electronic Computers, PP 685 698.
- 6. Minnick, R.C., 1965, Cobweb Cellular Arrays, Proceedings of the Fall Joint Computer Conference, PP 327 341. Las Vegas, NV.
- 7. Canaday, R., 1965, Two-Dimensional Iterative Logic, Proceedings of the Fall Joint Computer Conference, PP 343-353. Las Vegas, NV.
- 8. Gardner, P.L., Dec. 1970, Functional Memory and Its Microprogramming Implications, Technical Report TR.12. 091, IBM United Kingdom Laboratories Limited. Hursley Park, Winchester Hampshire.
- 9. Roth Jr., C.H. Fundamentals of Logic Design, Second Edition, West Publishing Co., 1979, PP: 136.144. St. Paul, MN.

Signetics

PLHS501 Application Notes Vol. 2

Programmable Logic Devices

INTRODUCTION

This document is written assuming the reader is familiar with Signetics PLHS501. As well, we shall assume familiarity with the predecessor document "Designing with PML" and some exposure to Signetics AMAZE software. The goal of this document (i.e., Vol. 2) is to expand on the original ideas and present some cookbook solutions to some useful design problems. Vol. 2 also reflects nearly a year of experience through the multitude of design-ins achieved with the PLHS501. In fact, several of the design solutions

presented here were contributions from our customers through our field applications organization. Designs we have encountered fell into a couple of interesting categories. First, many users view the part as a natural step in eliminating extraneous board "glue" (10 or more chips) or eliminating multiple programmable array logic devices (usually 3 to 5 units). Others recognized the PLHS501 capabilities of extremely wide logic functions and still others chose to invent their own solutions to standard bus interfaces. Commercially available bus interfaces often "miss the

mark" and creative designers wish to implement exactly the functions they need in a concise, effective manner. To date, we have seen PLHS501 interfaces to the VME Bus II, FAST Bus, NuBus, GPIB and the IBM Micro Channel for the PS/2 system.

Before presenting these solutions however, it is appropriate to review the PML basics and expand on a number of issues which have been found to be important but which were previously treated lightly.

Signetics

PLHS501 Application Notes Vol. 2

Programmable Logic Devices

PLHS501 REVIEW


The PLHS501 is a 52-Pin, bipolar programmable logic device with a very powerful architecture. Unlike classic AND/OR based architectures, its basic building block is the NAND function which is configured in a foldback programming array. By cascading successive NAND functions through the array, both combinational and sequential structures may be obtained. The PLHS501 has 24 dedicated inputs, 16 outputs (with several varieties) and eight bidirectional pins. The internal NANDs may be cascaded to any depth needed, to achieve effective solutions using logic structures such as muxes, decoders and flip-flops without going off chip and wasting I/O pins to achieve cascading. To use the PLHS501 effectively, the designer should attempt to fold in function and remain within the chip as much as possible before exiting.

Figure 2–1 shows the PLHS501 architecture and illustrates several of the timing paths for internal signals to give the designer a feeling for maximum time delay within the part. These numbers are worst case maximums, regardless of switching directions, so the user may be assured that in general, the PLHS501 will be faster than these numbers.

The shorthand notation of Figure 2–1 hides something with which many designers have been impressed in the PLHS501, the wide input NAND gates. Figure 2–2 shows just how wide the internal NANDs are, from a logical viewpoint. Each NAND can accommodate up to 32 external inputs

and 72 internal inputs. Hence the part is ideal for wide decoding of 32-bit address and data busses. With 72 copies of the wide NAND, the PLHS501 is often compared against low-end gate arrays. While flatter4ing, this gives no usable method to determine the degree to which functions can be fit into the device. As a rule of thumb, the PLHS501 can accommodate three or more PLA devices and usually four to five PAL® devices.


For any particular design, the user should refer to Table 2–1 and evaluate his/her design incrementally, tallying against a 72 gate budget. This is a ballpark estimation against the NAND capacity of the core of the part. The clever designer will find additional function by correctly exploiting the output logic.



PAL is a registered trademark of Monolithic Memories, Inc., a wholly owned subsidiary of Advanced Micro Devices, Inc.

Table 2-1. PLHS501 Gate Count Equivalents

FUNCTION	INTERNAL NAND EQUIVALENT	COMMENTS
Gates: NANDs ANDs NORs	1 1 1	For 1 to 32 input variables For 1 to 32 input variables For 1 to 32 input variables
ORs	1	For 1 to 32 input variables
Decoders 3-to-8 4-to-16 5-to-32	8 16 32	Inverted inputs available Inverted inputs available Inverted inputs available (24 chip outputs only)
Encoders 8-to-3 16-to-4 32-to-5	15 32 41	Inverted inputs, 2 logic levels Inverted inputs, 2 logic levels Inverted inputs, 2 logic levels, factored solution.
Multiplexers 4-to-1 8-to-1 16-to-1 27-to-1	5 9 17 28	Inverted inputs available Inverted inputs available Inverted inputs available Can address only 27 external inputs – more if internal
Flip-Flops D-type Flip-Flop T-type Flip-Flop J-K-type Flip-Flop Transparent-D Latch S-R Latch	6 6 10 4 2	With asynchronous S-R With asynchronous S-R With asynchronous S-R With asynchronous S-R With asynchronous S-R
Adders 8-bit	45	Full carry-lookahead (four levels of logic)
Barrel Shifters 8-bit	72	2 levels of logic



Signetics

PLHS501 Application Notes Vol. 2

Programmable Logic Devices

FLIP-FLOP BASICS

Most designers view flip—flops as black boxes with data inputs and outputs as well as additional control inputs. Some flip—flops are designed as primitive transistor structures, but in the past, gate array designers used their elementary building block, the NAND gate, to make flip—flops. Because the PLHS501 is also largely structured from NANDs, we can draw upon years of well known NAND-based flip—flop designs to readily implement flip—flops within the PLHS501.

Figures 3–1, 3–2, 3–3 and 3–4 give single sheet summaries of several flip–flop configurations. It should be noted that the transparent latch is recommended for data capturing, but not for state machines due to potential glitching. The edge triggered D–type is a convenient building block. Although external gates are saved with the J–K structure, it is at the expense of additional NANDs within the J–K flip–flop itself.

Notation

The delay of a NAND gate is most often designated as t_{PLH} or t_{PHL} , indicating that the gate output makes a High-to-Low (t_{PHL}) or Low-to-High (t_{PLH}) transition. For the flip-flops' transition, the High-to-Low ID is D0 and the Low-to-High ID is D1. This also holds true for structures fully contained within the foldback core, because input and output time delays will

differ and change the performance. Knowing the basic concepts, the designer can expand these structures to include I/O pins and generate flip—flops wrapped around the part – but, he must derate his parameters accordingly to reflect the slower paths.

Because it will be lengthy to explain all of the flip—flop configurations given, we will show only one in some detail. The interested reader can verify the rest by manual analysis or by digital simulation. The Table 3–1 gives the typical and worst case values for an internal foldback NAND gate.

The single D-latch with enable Active-HIGH can be described in terms of the propagation delay formula given in Figure 3-1. For instance, the first propagation is for D to Q, where the Q output transitions from High-to-Low (i.e., tPDO). To do this, assume Q is high so the /Q term is Low. To switch the state, /Q must be flipped first. Hence, the logic variable enters G2, then passes through G7, G4 and finally G3. This presents four transitions, two from Low-to-High (G2 and G4 outputs) and two from High-to-Low (G1 and G3 outputs). Hence, the formula reflects 2(d1&d0) which, using Table 3-1, gives 2(8+6.5)=29ns.

This is the worst case value, using typicals will give a value of 2(5.5+6.5)=24ns.

Switching in the other direction is a little different. Assuming t_{PD1} goes from Q=0 to

Q=1, the /Q signal must be initially 1. Hence, G3 is armed for immediate transition. Hence, the time delay is simply traversing G2 and G3. One of them will go High-to-Low (G2) and the other Low-to-High (G3). The formula reflects the sum of the two transitions: tpD1 = d1+d0. From the table, this is 14.5ns (worst case) or 12ns (typical). The rest of the formula must be similarly analyzed, but the method is straightforward.

Flip-Flop Merging


Figure 3–5(A) shows the positive edge triggered D flip–flop structure. By putting a two–level AND/OR structure in front of the data input, the D flip–flop can be steered from state to state.


Figure 3–5(B) shows such an input structure realized from a two–level NAND gate section.


Figure 3–5(C) shows this "AND–OR" structure rolled inside of the flip–flop. The gating was merged with the flip–flop inwards to make a faster, composite function. Whereas this may appear as a trick to the uninitiated, this degree of flexibility allowed gate array designers to merge a multitude of logic into a fixed foundation. For highest efficiency, similar thinking allows the designer to break up decoders and multiplexers into their building blocks and generate only the pieces needed.

Table 3-1. Internal Fold Back NAND Gate

	INPUT		<u> </u>	ОИТРИТ	
	PARAMETER LIMITS				
SYMBOL	TO (OUTPUT)	FROM (INPUT)	Min	Max	UNIT
t _{PHL}		ANY	5.5	6.5	ne
t _{PLH}		AINT	6.5	8.0	ns








Propagation Delay Formulas:

FROM	то	FORMULAS
C	0	tpD1 = 2d1+d0
	ų ,	tpD0 = 2(d1+d0)
C	ō	tpD1 = 2d1+d0
	· ·	tpD1 = 2(d1+d0)
R	Q	tpD0 = d1+d0
R	Q	tpD1 = d1
D (SETUP 1	ГІМЕ)	= d0
D (HOLD TI	ME)	= d1 + d0
CL WIDTH	(HIGH)	= d1 + 2d0
RESET WID	TH (LOW)	R ->Q

Propagation Delays:

PARAMETER	FROM	то	DELAY in ns	
tPD1	C C R	0 0		
tpD0 -	C C R	<u>a</u>		
D (SETUP TIME)	ns Min			
D (HOLD TIME)	ns Min			
MINIMUM CLOCK WIDTH	ns			
MINIMUM R WIDTH	ns			

NAND Gate Diagram



Function (Truth) Table

С	D	Q _{n+1}	□ _{n+1}
_	0	0	1
_	1	1	0
_	0	0	1
_	1	1	0
NOTES:			

- NOTES:

 1. Data is transferred to the outputs on the negative—going edge of the clock; reset "R" (Active—LOW) is asynchronous and independent of
- Q_{n+1} = state after High-to-Low transition of C.
- of C.

 3. X = don't care.

Timing Waveforms:





Figure 3-3. D Flip-Flop with Reset




Propagation Delay Formulas:

FROM	то	FORMULAS
С	۵,۵	tpD0 = 3d0+2d1
		$t_{PD1} = 3(d1+d0)$
S	Q	tpD1 = d1
R	Q	tpD1 = d1
		IfC = 0
S	ā	tpD0 = d1+d0
		IfC = 1
R	Q	$t_{PD0} = 2(d1+d0)$
J-K SETUP	TIME	0
J-K HOLD TIME		= d0
PULSE WID	TH C (MIN)	= d1 + d0
S.R (MIN)		= (d1+d0)

Propagation Delays:

PARAMETER	FROM	то	DELAY in ns
	С	Q & Q	
tpD0 ¬	S	۵	
400	S	Q	
	R	Q	
	R	₫	
tPD1 ~	С	Q & Q	
1	S	Q	
_	R	۵	
J-K SETUP TIME	0		
J-K HOLD TIME	2 Mi	n	
MINIMUM PULSE WIDTH	20		
MINIMUM PULSE WIDTH S&R (LOW)	16		×


NAND Gate Diagram



Function (Truth) Table

J	K	S	R	Q _{n+1}	_{0n+1}
0	0	1	1	Qn	$\overline{\alpha}_n$
1	0	1	1	1	0
0	1	1	1	0	1
1	1	1	1	Q	۵
J	К	S	R	Q	۵
х	Х	1	0	0	1
Х	Х	0	1	1	0
	0 1 0 1 J	0 0 1 0 0 1 1 1 1 1 X X X	0 0 1 1 0 1 0 1 1 1 1 1 1 X S X X 1	0 0 1 1 1 0 1 1 0 1 1 1 1 1 1 1 X S R X X 1 0	0 0 1 1 Q _n 1 0 1 1 1 0 1 1 1 0 1 1 1 Q J K S R Q X X 1 0 0


Timing Waveforms:



- NTES:
 Master/slave data is pulse-triggered and enters the J-K flip-flop when the clock (C) goes Low; the entered data is transferred to the outputs on the positive going edge of °C". Set (S) and Reset (R) inputs are asynchronous, independent signals and, when either is Active—LOW, the J-K and C inputs are overridden.
- Q_{n+1} = next state of Q. X = don't care.

Figure 3-4. J-K Flip-Flop with Set and Reset

April 1989 619



Signetics

PLHS501 Application Notes Vol. 2

Programmable Logic Devices

VME Bus EXAMPLES

Omnibyte VSBC20 Mailbox Interrupt Structure

One of the more popular uses for the PLHS501 is interfacing with 32-bit microprocessors. This section illustrates some of the ways the part has been used with the popular VME Bus. The Omnibyte Corporation manufactures many VME Bus products (as well as others) and was kind enough to release a portion of their VSBC20 board design as an example of using the PLHS501 in a very flexible, user configurable interrupt generation device. The VSBC20 employs two PLHS501 parts, as shown in Figure 4-1. One device is used largely as an address decoder, the other, which is the object of this Section, is the configurable interrupt generator. The target microprocessor here is a 25MHz 68020 and the application is interrupt generation. The explanation is in the words of Glenn Case, the designer:

"Following the design philosophy of giving the user as much flexibility as possible, the local interrupt structure of the VSBC20 is implemented in a PLD. It is impossible to "optimize" the assignment of the local interrupts to the interrupt levels of the processor since they are application specific. One system may want the Serial I/O and Parallel I/O to have higher levels than the Omnimodule Interrupts while yet another,

using a SCSI Omnimodule, may want it to have higher level interrupts. Arbitrarily assigning and hard wiring these levels would unnecessarily constrain the use of the VSBC20 for any given application. By using the Signetics PLHS501, the entire logic to implement the interrupt structure fits into one PLD. Furthermore, the AMAZE software to program the part is available free from Signetics. The PLHS501 can be reprogrammed until the unused feedback gates are all used. So, the user can get the software free and change the interrupt levels a couple of times before having to replace the PLHS501 with a new part. This appendix describes how the PLHS501 is used and how to change the interrupt levels.

There are a total of 17 possible interrupt sources to the processor on the VSBC20. There are up to seven possible VMEbus interrupts, nine possible local interrupts, and a Front Panel Non-Maskable interrupt. The local interrupts include: ACFAIL*, SYSFAIL*, parity error, mailbox interrupt, two Omnimodule interrupts, 24 bit timer interrupt, Parallel I/O, and Serial interrupts. Although ACFAIL*, SYSFAIL* and mailbox interrupts are generated by VMEbus, they are referred to as local interrupts because they are acknowledged locally. That is, no VMEbus IACK cycle takes place. The local interrupts are latched during an IACK

cycle to "freeze" the state of the interrupts. This allows the correct acknowledgement of the interrupts. The ACFAIL*, SYSFAIL* and Front Panel Non-Maskable Interrupt are assigned to Level 7. The Front Panel NMI has the highest priority followed by ACFAIL*, parity error, and SYSFAIL*. The front Panel interrupt is acknowledged by an autovector while the other three generate a vector that is encoded as described in the Error Interrupt Vector CSR. The local interrupts for the mailbox interrupt. Omnimodule Interrupt 0, Omnimodule Interrupt 1, 24 bit timer interrupt, Parallel I/O Interrupt, and Serial I/O Interrupt have been assigned by the user to the level best suited for the user's application. The mailbox interrupt uses the auto vector while the others provide interrupt acknowledge vectors. However, these may also be changed to generate autovectors. For example, if a unique Omnimodule is designed by the user and there is not enough room to provide an interrupt vector on the module, the PLD can be changed to issue an autovector instead of generating an IACK cycle to the Omnimodule. It is also possible to have two interrupts share the same level, although this seems unnecessary, since there are enough available interrupt levels.

The following examples illustrate how easy it is to change the local interrupt levels."

EXAMPLE 1:

Put the P10 interrupt in level 4 and the Omnimodule 0 interring on level 2.


```
LIRQ4 = /LIRQPIO; |->
LIRQ2 = /LIRQ0OM; |-> change these
IACKOOM = /(/LIRQOM*/A3*A2*/A1*//IACK*/BAS); <-| equations to
IACKPIIO = /(/LIRQPIO*A3*/A2*/A1*/IACK*/BAS); <-|
```

EXAMPLE 2:

Make both the Omnimodule Interrupt Autovectored instead of bus-vectored. (LITRQ0OM uses level 4 and LIRQIOM uses level 5.)

```
AUTOVECTOR = [/FPNMIRQ*A3*A2*A1*/IACK*/BAS*RESET]
+ [/LIRQMBOX*A2*A2*/A1*/IACK*/BAS*RESET]
+ [/LIRQOOM*A3*/A2*/A1*/IACK*/BAS*RESET]
+ [/LIRQIOM*A3*/A2*A1*/IACK*/BAS*RESET]
+ [autovector* /BAS*RESET];

IACKIOM = /(0); <-- change
IACKOOM = /(0); <-- equation
```



```
File Name : vsbc20is
Date: 9/13/1988
Time : 9:4:2
Left
                                        Right
          ** FNC **PIN
                            PIN** FNC **
          ** +5V ** 8-|
                           |-46 ** +5V **VCC
VCC
          ** I ** 9-|
                            |-45 ** I **A1
VTRO1
          ** I
                            |-44 ** I
VIRQ2
               ** 10-|
                                      **A2
                            |-43 ** I
VIRO3
          ** I
               ** 11-
          ** I ** 12-
                            -42 ** I
                                      **BAS
VIRO4
          ** I ** 13-| H
                           |-41 ** I
                                      **IACK
VIRO5
         ** I ** 14-| S |-40 ** /O **IACKF
         ** I ** 15-| 5 |-39 ** /0 **N/C
BRDFAIL
          ** I
               ** 16-| 0 |-38 ** /0 **N/C
RESET
         ** I
FPNMIIN
               ** 17-| 1 |-37 ** /0
                                      **N/C
         ** I
VIRQ7
               ** 18-|
                            1-36 ** 0
                                      **IPL2
               ** 19-|
                            |-35 ** 0 **IPL1
          ** 0
N/C
          ** 0V ** 20-1
                           |-34 ** /O **GND
GND
     Bottom
                            PIN** FNC ** LABEL
  LABEL ** FNC **PIN
          ** 0
               ** 21-|
                            |- 7 ** I **LIRQSIO
N/C
DSACK0
         ** 0
               ** 22-|
                            |- 6 ** I
                                      **LIRQPIO
         ** 0
               ** 23-|
                            |- 5 ** I
N/C
                                      **LIROTMR
          ** /O ** 24-| P
                           |- 4 ** I
IACK00M
                                     **LIRQOOM
          ** /O ** 25-| L
IACK10M
                           |- 3 ** I **LIRQ10M
          ** /O ** 26-| H |- 2 ** I **LIRQMBX
IACKTMR
          ** /O ** 27-| S |- 1 ** I **LIRQPE
IACKPIO
          ** 0
               ** 28-| 5
                           |-52 ** I
                                      **LACFAIL
         ** 0
               ** 29-|
                                     **LSYSFAIL
                            |-51 ** I
IACKSIO ** 0 ** 30-|
                       1 |-50 ** I
                                    **N/C
OFFBRDIACK ** O ** 31-1
                            |-49 ** I **ACFM
AUTOVEC
         ** 0 ** 32-1
                           |-48 ** I **SYSFM
         ** 0 ** 33-|
IPL0
                            |-47 ** I **PRRM
     Figure 4-2. PLHS501 Pinlist for VSBC20 Interrupt Structure
```

```
@DEVICE TYPE
PLHS501
@DRAWING 1155
@REVISION A
@DATE
                         9-9-88
@SYMBOL
@COMPANY
                         OMNIBYTE CORP.
GNAME
                         GLENN CASE
@DESCRIPTION
                  VSBC20 INTERRUPT STRUCTURE PLD
@INTERNAL NODE
LIRQ7 ALLIRQ7 AHIACKF AHFPNMIRQ AUTOVECTOR FPNMIRQ
@COMMON PRODUCT TERM
LIRQ6 = /LIRQMBX;
                          "LIRQ6 goes high when LIRQMBX goes low"
LIRQ5 = /LIRQ10M;
LIRQ4 = /LIRQ00M;
LIRQ3 = /LIRQTMR;
LIRQ2 = /LIRQPIO;
LIRQ1 = /LIRQSIO;
                                   Figure 4-3. VSCB20IS .BEE File (begins)
```

```
@I/O DIRECTION
DB4 = 0;
DB5 = 0;
DB6 = 0;
DB7 = 0;
XE0 = /IACKF;
XE1 = 1:
XE2 = 1;
XE3 = 1;
OE1 = /IACKF;
OE2 = 1;
OE3 = 1;
@I/O STEERING
@LOGIC EQUATION
LIRQ7 = [/LACFAIL * ACFM]
                                        "LIRQ7 goes high when"
      + [/LYSFAIL * SYSFM * BRDFAIL]
      + [/LIRQPE * PERRM];
ALLIRQ7 = /[/[/LACFAIL * ACFM]
        + /[/LSYSFAIL * SYSFM * BRDFAIL]
        + /[/LIRQPE * PERRM]];
AHFPNMIRQ = [/FPNMIIN */IACK * RESET]
          + [AHFPNMIRQ */IACK * RESET]
          + [AHFPNMIRQ *IACK * BAS * RESET]
          + [AHFPNMIRQ *IACK * /BAS * /A1 * RESET]
          + [AHFPNMIRQ *IACK * /BAS * /A2 * RESET]
          + [AHFPNMIRQ *IACK * /BAS * /A3 * RESET]
          + [AHFPNMIRQ *IACK * /BAS * A3 * A2 * A1 * /AUTOVECTOR * RESET];
FPNMIRQ = / (AHFPNMIRQ);
IPLO: XR1= /VIRO7
         + LIRO7
         + /FPNMIRQ
         + /LIRQ7 * /LIRQ6 * VIRQ7 * VIRQ6 * LIRQ5
         + /LIRQ7 * /LIRQ6 * VIRQ7 * VIRQ6 * /VIRQ5
         + /LIRQ7 * /LIRQ6 * /LIRQ5 * /LIRQ4 * VIRQ7 * VIRQ6 * VIRQ5 * VIRQ4 * LIRQ3
         + /LIRQ7 * /LIRQ6 * /LIRQ5 * /LIRQ4 * VIRQ7 * VIRQ6 * VIRQ5 * VIRQ4 * /VIRQ3
         + /LIRQ7 * /LIRQ6 * /LIRQ5 * /LIRQ4 * /LIRQ3 * /LIRQ2 * VIRQ7 * VIRQ6 * VIRQ5 * VIRQ4 *
VIRQ3
                     * VIRQ2 * LIRQ1
         + /LIRQ7 * /LIRQ5 * /LIRQ4 * /LIRQ3 * /LIRQ2 * VIRQ7 * VIRQ6 * VIRQ5 * VIRQ4 *
VIRQ3
                     * VIRQ2 * /IRQ1;
XR2 = 1;
IPL1: XR1 = /VIRQ7
          + LIRQ7
          + /FPNMIRQ
          + /LIRQ7 * VIRQ7 * LIRQ6
          + /LIRQ7 * VIRQ7 * /VIRQ6
          + /LIRQ7 * /LIRQ6 * /LIRQ5 * /LIRQ4 * VIRQ7 * VIRQ6 * VIRQ5 * VIRQ4 * LIRQ3
          + /LIRQ7 * /LIRQ6 * /LIRQ5 * /LIRQ4 * VIRQ7 * VIRQ6 * VIRQ5 * VIRQ4 * /VIRQ3
          + /LIRQ7 * /LIRQ6 * /LIRQ5 * /LIRQ4 * /LIRQ3 * VIRQ7 * VIRQ6 * VIRQ5 * VIRQ4 * /VIRQ3
                                             * LIRQ2
          + /LIRQ7 * /LIRQ6 * /LIRQ5 * /LIRQ4 * /LIRQ3 * VIRQ7 * VIRQ6 * VIRQ5 * VIRQ4 * /VIRQ3
                                              * /VIRQ2;
XR2 = 1;
                                  Figure 4-3. VSCB20IS .BEE File (continued)
```

```
ILP2: XR1 = /VIRQ7
          + LIRO7
          + /FPNMIRQ
          + /LIRQ7 * VIRQ7 * LIRQ6
          + /LIRQ7 * VIRQ7 * /VIRQ6
          + /LIRO7 * /LIRO6 * VIRO7 * VIRO6 * LIRO5
          + /LIRQ7 * /LIRQ6 * VIRQ7 * VIRQ6 * /VIRQ5
          + /LIRQ7 * /LIRQ6 * /LIRQ5 * VIRQ7 * VIRQ6 * VIRQ5 * LIRQ4
          + /LIRQ7 * /LIRQ6 * /LIRQ5 * VIRQ7 * VIRQ6 * VIRQ5 * /VIRQ4;
XR2 = 1;
IACKF = /([A3 * A2 * A1 * FPNMIRQ * /LACFAIL * IACK * /BAS]
         [A3 * A2 * A1 * FPNMIRQ * /LSYSFAIL * IACK * /BAS]
[A3 * A2 * A1 * FPNMIRQ * /LIRQPE * IACK * /BAS]);
OFFBRDIACK: XR1 = /LIRQ7 * A3 * A2 * A1 * IACK * /BAS * FPNMIRQ * /AUTOVECTOR
                + /LIRQ6 * A3 * A2 * /A1 * IACK * /BAS
                + /LIRQ5 * A3 * /A2 * A1 * IACK * /BAS
                + /LIRQ4 * A3 * /A2 * /A1 * IACK * /BAS
                + /LIRQ3 * /A3 * A2 * A1 * IACK * /BAS
                + /LIRQ2 * /A3 * A2 * /A1 * IACK * /BAS
                + /LIRQ1 * /A3 * /A2 * A1 * IACK * /BAS;
XR2 = 1;
AUTOVECTOR = [/FPNMIRQ * A3 * A2 * A1 * IACK * /BAS * RESET]
          + [/LIRQMBX * A3 * A2 * /A1 * IACK * /BAS * RESET]
           + [ AUTOVECTOR
                                               * /BAS * RESET];
AUTOVEC; XR1 = AUTOVECTOR;
XR2 = 1;
D24: XR1 = /LACFAIL * ACFM
        + /LIRQPE * PERRM;
XR2 = 1;
D25: XR1 = /LACFAIL * ACFM
       + LIRQPE * PERRM * /LSYSFAIL * SYSFM
                     /PERRM * /LSYSFAIL * SYSFM;
XR2 = 1;
IACK1OM = /(/LIRQ1OM * A3 * /A2 * A1 * IACK * /BAS);
IACKOOM = /(/LIRQOOM * A3 * /A2 * /A1 * IACK * /BAS);
IACKTMR = /(/LIRQTMR * /A3 * A2 * A1 * IACK * /BAS);
IACKPIO = /(/LIRQPIO * /A3 * A2 * /A1 * IACK * /BAS);
IACKSIO = /(/LIRQSIO * /A3 * /A2 * A1 * IACK * /BAS);
DSACKO = BAS;
                                    Figure 4-3. VSCB20IS .BEE File (end)
```

VME Bus EPROM Interface


The idea for this VMEbus EPROM board came from WIRELESS WORLD CIRCUIT IDEAS, January, 1988. The implementation was done by a Philips' FAE, John McNally.


The board contains two banks of EPROMs. Each bank consists of either two 27128s or two 27256s; each of which can be enabled by comparing the address location fo the board. Decoding three other address bits selects which of the banks is accessed. A 4-bit shift register combined with four jumpers provide wait states.


The circuit drawing was entered onto a PC using FutureNet DASH, a schematic capture package (Figures 4–4, 4–5, and 4–6). It was then converted to logic equations using AMAZE (Figure 4–9) and then assembled into a PLHS501.


This application, which needs eight ICs, used forty—four of the available seventy—two NAND Foldback Terms and forth of the available fifty—two pins. As the PLHS501 contains no registers, an edge—triggered D—type flip—flop was designed using NAND gates and this is used as a soft macro in order to implement the shift register function (Figure 4—6).

As suggested in the original article, the circuit could be expanded to access up to eight ROM banks (Figure 4–8). This was achieved by editing the logic equation file and adding extra equations (Figure 4–9). Modifying the drawing, although fairly easy to do, was not considered necessary as the object was to design with PML and not TTL. The expanded circuit would require another three TTL IC packages, brining the total to eleven. The number of foldback terms increased to fifty—five, with the number of pins rising to fifty. Figure 4–10 shows the pinout of both versions.









```
File Name : VMEEXP
Date : 2/13/1988
Time : 10:23:5
LABEL ** FNC **PIN
                           PIN** FNC ** LABEL
          ** +5V ** 8-|
                          |-46 ** +5V **VCC
VCC
A21
         ** I ** 9-|
                           |-45 ** I **WAIT
          ** I ** 10-|
A22
                           |-44 ** I
          ** I ** 11-| P |-43 ** I
                                      **CKBMZ
A23
         ** I
         ** I ** 12-| L |-42 ** I

** I ** 13-| H |-41 ** I

** I ** 14-| S |-40 ** /0
/DSO
                                      **N/C
                           |-40 ** /O **/R-W
R-WN
         ** 0 ** 15-| 5 |-39 ** /0 **DTAK
0.0
         ** I ** 16-| 0 |-38 ** /O **/DTACK
Q1
         ** I ** 17-| 1 |-37 ** /0 **/MASEL
Q2
Q3
         ** I ** 18-| |-36 ** 0 **N/C

** 0 ** 19-| |-35 ** 0 **N/C

** 0V ** 20-| |-34 ** 0V **GND
/ROMOLO
GND
     Bottom
        ** FNC **PIN
                            PIN** FNC **
  LABEL
                                           LABEL
         ** 0 ** 21-|
/ROMOHI
                          |- 7 ** I **A20
          ** 0 ** 22-1
                                      **A19
                           |- 6 ** I
/ROM1LO
         |- 5 ** I
/ROM1HI
                                      **A18
                           |- 4 ** I
                            |- 3 ** I
N/C
                                      **A16
         ** /O ** 26-| H
                           |- 2 ** I
                                      **/A5
N/C
         ** /0 ** 27-| S |- 1 ** I
N/C
         ** 0 ** 28-| 5 |-52 ** I
ENADD
         **S19
ENDATLO
          ENDATHI
                                      **S20
               ** 31-| |-49 ** I
N/C
          ** 0
         ** 0 ** 32-1
                            |-48 ** I
                                     **S22
N/C
          ** 0 ** 33-|
                            |-47 ** I
N/C
                                     **S23
             Figure 4-8. VMEEXP PLHS501 Pinlist
```

```
File Name: VMEEXP
Date: 2/13/1988
Time: 10:23:41
@DEVICE TYPE
    PLHS501
@DRAWING
    VMEEXP.DWG
@REVISION
    2/12/1988
@SYMBOL
@COMPANY
    VMEEXP
@DESCRIPTION
@INTERNAL NODE
    RO3 SO3 DO3 RO2 SO2
    DO2 Q0 RO1 SO1 DO1
    ROO SOO DOO
@I/O DIRECTION
    DB5 = 1;
    DB6 = 1;
    DB7 = 1;
    OE0 = 1 ;
    OE1 = 1 :
@I/O STEERING
@LOGIC EQUATION
    RO3 = (/((//MASEL)*SO3*CK8MZ*DO3));
     SO3 = (/(CKBMZ*(/(SO3*DO3*(//MASEL)))));
    DO3 = (/(Q2*RO3));
     RO2 = (/((//MASEL)*SO2*CKBMZ*DO2));
     SO2 = (/(CKBMZ*(/(SO2*DO2(//MASEL)))));
    DO2 = (/(Q1*RO2));
    RO1 = (/((//MASEL)*SO1*CKBMZ*DO1));
     SO1 = (/(CKBMZ*(/(SO1*DO1(//MASEL))))));
    DO1 = (/(Q0*RO1));
     ROO = (/((//MASEL)*SOO*CKBMZ*DOO));
     SOO = (/(CKBMZ*(/(SOO*DOO*(//MASEL))))));
    DO0 = (/(Q*RO0));
     /ROMOLO = (/DSO+(/(/A16*/O*1*//MASEL)));
     /ROMOHI = (/DS1+(/(/A16*/0*1*//MASEL)));
     /ROM1LO = (/DS0+(/(A16*/0*1*//MASEL)));
     /ROM1HI = (/DS1+(/(A16*/0*1*//MASEL)));
     Q0 = (/((/(RO0*Q0))*SO0*(//MASEL)));
     Q1 = (/((/(RO1*Q1))*SO1*(//MASEL)))
     Q2 = (/((/(RO2*Q2))*SO2*(//MASEL)));
     Q3 = (/((/(RO3*Q3))*SO3*(//MASEL)));
     /MASEL = /(/(/((A17*S17+/A17*/S17)*(A18*S18+/A18*/S18)*(A19*S19+
                    /A19*/S19) * (A20*S20+/A20*/S20) * (A21*S21+/S21*/S21) *
                    (A22*S22+/A22*/S22)*(A23*S23+/A23*/S23)*//A5)])) ;
     /DTACK = /((/(/MASEL+WAIT))*R-WN);
     DTACK = /(/DTACK);
     /R-W = /(R-WN);
    ENADD = (//A5);
    ENDATLO = ((/R-W+/MASEL)+/DSO);
    ENDATHI = (/DS1 + (/R - W + /MASEL));
                                 Figure 4-9. VMEEXP PLHS501.BEE File
```

```
File Name : FULLEXP
Date : 2/13/1988
Time : 10:11:28
Right
FINC **PIN PIN** FNC ** I

** +5V ** 8-| |-46 ** +5V **VCC

** I ** 9-| |-45 ** T
  LABEL ** FNC **PIN
                             PIN** FNC ** LABEL
          |-44 ** I **W1
A22
         ** I ** 11-| P |-43 ** I **CRB*

** I ** 12-| L |-42 ** I **N/C

** I ** 13-| H |-41 ** I **N/C

** I ** 14-| S |-40 ** /0 **/R-W
A23
                                        **CKBMZ
/DS1
R-WN
         ** 0 ** 15-| 5 |-39 ** /0 **DTAK
REG
         ** O ** 16-| 0 |-38 ** /O **/DTACK
ENADD
         ENDATLO
ENDATHI
         ** 0 ** 18-| |-36 ** 0 **ROM7HI

** 0 ** 19-| |-35 ** 0 **ROM7LO

** 0V ** 20-| |-34 ** 0V **GND
/ROMOLO
GND
     Bottom
PIN** FNC ** LABEL
          ** /0 ** 24-| P |- 4 ** I

** /0 ** 25-| L |- 3 ** I
/ROM1LO
                                        **A17
/ROM1HI
                                        **A16
         ** /0 ** 26-| H |- 2 ** I
                                        **/A5
/ROM3LO
         ** /0 ** 27-| S |- 1 ** I
                                       **S17
/ROM3HI
         **S18
/ROM4LO
                                        **S19
/ROM4HI
                                        **S20
/ROM5LO
         ** 0 ** 31-|
                             |-49 ** I
                                       **S21
/ROM5HI
                        ** 0 ** 32-1
/ROM6T.O
         ** 0 ** 33-|
                             |-47 ** I
/ROM6HI
                Figure 4-10. FULLEXP Pinlist
```

```
File Name: FULLEXP
Date: 2/13/1988
Time: 10:11:30
@DEVICE TYPE
     PLHS501
BORAWING
     VMEEXP.DWG
@REVISION
     2/12/1988
@SYMBOL
@COMP ANY
@NAME
     VMEEXP
@DESCRIPTION
@INTERNAL NODE
     RO3 SO3 DO3 RO2 SO2
     DO2 RO1 SO1 DO1 RO0
     SOO DOO
     00 01 02 03
@I/O DIRECTION
     DB4 = 1 :
     DB5 = 1 ;
     DB6 = 1 :
     DB7 = 1 ;
     OE0 = 1 ;
     OE1 = 1 ;
     OE2 = 1 ;
     OE3 = 1 ;
     XE0 = 1;
     XE2 = 1;
     XE3 = 1 ;
@STEERING
     SO = Q;
     S1 = Q;
     S2 = Q;
```

Figure 4-11. FULLEXP PLHS501 .BEE File

```
@LOGIC EQUATION
    RO3 = (/((//MASEL)*SO3*CKBMZ*DO3));
    SO3 = (/(CKBMZ*(/(SO3*DO3*(//MASEL)))));
    DO3 = (/(Q2*RO3));
    RO2 = (/((//MASEL)*SO2*CKBMZ*DO2));
    SO2 = (/(CKBMX*(/SO2*DO2*(//MASEL)))));
    DO2 = (/(Q1*RO2));
    RO1 = (/((//MASEL)*SO1*CKBMZ*DO1)) ;
    SO1 = (/(CKBMZ*(/(SO1*DO1*(//MASEL)))));
    DO1 = (/(Q0*RO1));
    ROO = (/((//MASEL)*SOO*CKBMZ*DOO)) ;
    SOO = (/(CKBMZ*(/SOO*DOO*(//MASEL)))));
    D00 = (/(Q*R00));
    /ROMOLO = (/DSO+/(/A16*/A17*/A18*//MASEL)) :
    /ROMOHI = (/DS1+/(/A16*/A17*/A18*//MASEL));
    /ROM1LO = (/DSO+/(A16+/A17*/A18*//MASEL));
    /ROM1HI = (/DS1+/(A16*/A17*/A18*//MASEL));
    /ROM2LO = /(/(DSO+/(/A16*A17*/A18*//MASEL)));
    /ROM2HI = /(/(/DS1+/(/A16*A17*/A18*//MASEL)));
    /ROM3LO = /(/(DSO+/(A16*A17*/A18*//MASEL)));
    /ROM3HI = /(/(/DS1*/(A16*A17*/A18*//MASEL)));
    /ROM4LO = (/DS0+/(A16*/A17*A18*//MASEL));
    /ROM4HI = (/DS1+/(A16*/A17*/A18*//MASEL));
    /ROM5LO = (/SAO + / (A16*/A17(A18*//MASEL)));
    /ROM5HI = (/DS1+/(A16*/A17*A18*//MASEL)) :
    /ROM6LO = (/DS0+/(A16*A17*A18*//MASEL));
    /ROM6HI = (/DS1+/(A16*A17*A18*//MASEL));
    /ROM7LO = (/DS0+/(A16*A17*A18*//MASEL));
    /ROM7HI = (/DS1+/(A16*A17*A18*//MASEL));
     ENADD = (//A5);
    ENDATLO = ((/R-W+/MASEL)+/DSO);
    ENDATHI = (/DS1 + (/R - W + /MASEL));
    Q0 = /((/(RO0*Q0))*SO0*(//MASEL))
    Q1 = /((/(RO1*Q1))*SO1*(//MASEL))
    Q2 = /((/(RO2*Q2))*SO2*(//MASEL));
    Q3 = /((/(RO3*Q3))*SO3*(//MASEL));
    /MASEL = /(/([/((A17*S17+/A17*/A17*/S17*(A18*S18+/A18*/S18)
                  *(A19*S19+/A19*/S19)*(A20*S20+/A20*/S20)*(A21*S21
                 +/A21*/S21) * (A22*S22+/A22*/S22) * (A23**S23
                 +(A23*S23)*//A5)]));
    /DTACK = /((/(/MASEL+/((/Q0*W0*/W1)+(/Q1*W0*/W1)+(/Q2*/W0*W1))))
                  +(/Q3*W0*W1))))*R-WN);
     DTAK = / (DTACK) ;
    /R-W = /(R-WN);
    REG = Q0*Q1*Q2*Q3;
```

Figure 4-11. FULLEXP PLHS501 .BEE File (Continued)

Signetics

PLHS501 Application Notes Vol. 2

Programmable Logic Devices

MICRO CHANNEL INTERFACE

IBM's new Micro Channel Architecture (MCA) bus implements new features not found on the XT/AT bus. One new requirement for adapter designers is that of Programmable Option Select (POS) circuitry. It allows system software to configure each adapter card upon power on, thereby eliminating option select switches or jumpers on the main logic board and on adapter cards.

Each adapter card slot has its own unique –CDSETUP signal routed to it. This allows the CPU to interrogate each card individually upon power up. By activating a card's –CDSETUP line along with appropriate address and control lines two unique 8 bit ID numbers are first read from the adapter. Based upon the ID number, the system then writes into the card's option latches configuration information that has been stored in the system's CMOS RAM. The CPU also activates POS latch address 102h bit 0, which is designated as a card enable bit.

If a new card is added to the system, an auto-configuration utility will be invoked. Each adapter card has associated with it a standardized Adapter Description File with filename of @XXXX.ADF, where XXXX is the hex ID number of the card.

The configuration utility prompts the user according to the text provided in the .ADF file and updates the card's latches and the system's CMOS RAM.


IBM reserves 8 addresses for byte—wide POS latches, however, depending on the card's function, not all addresses need to be used. In addition, of those addresses that are used, only the bits used need to be latched. The first two addresses which are reserved for reading the ID bytes, and bit 0 of the third address, which is defined as a card enable bit, are mandatory. Some of the remaining bits of the third address are suggested by IBM to be used as inputs to an I/O or memory address comparator to provide for alternate card addresses. Many adapter cards will not use more than these three POS locations.


The following example describes an implementation of POS circuitry realized in a PLHS501. It uses only 56 of the possible 72 internal foldback NAND gates and only a portion of the device pins, allowing additional circuitry to ba added. Figure 5–1 shows a block diagram of the circuit, and Figures 5–3 and 5–4 are the AMAZE files. Pins labeled DOO–D7O must be connected externally to pins D01–D7I. They also must be connected through a 74F245 transceiver to the Micro Channel. External transceiver direction and enable control is

provided for by circuitry within the PLHS501. The external transceiver may also be used by other devices on the adapter card.

In this application, edge-triggered registers are not required and therefore should not be used, as transparent latches use fewer NAND gates to implement. Figure 5-2 shows the various latch circuits described by the AMAZE equations. POS byte 2 was made using four of the /B device pins and four of the B pins. Notice however, from Figure 5-2(B) that the bits on the /B pins used the complement of the input pin, thereby implementing a noninverting latch. Also, all 8 bits of this byte were brought to output pins. If some of the bits are not used by external circuitry, then the specific bit latch may not be needed or may be constructed entirely from foldback NAND gates freeing additional pins.

An external F521 may be added to provide for I/O address decoding. As the MCA bus requires all 16 bits of the I/O address to be decoded, 8 bits may be assigned to the F521 and 8 bits to the 501. Bit fields decoded in the 501 may be done so in conjunction with bits from POS byte 2 to provide for alternate I/O addressing. Additionally, some of the available 501 outputs may be used as device enables for other devices on the card.





```
File Name : MCPOSREG
Date : 5/31/1988
Time : 11:50:2
Right
PIN** FNC ** LABEL
|-46 ** +5V **VCC
      Left
         ** FNC **PIN
 LABEL
         ** +5V ** 8-|
** I ** 9-|
VCC
N/C
                           |-45 ** I **D4I
              ** 10-|
                           |-44 ** I
                                    **D3I
         ** I
N/C
         ** I ** 11-| P |-43 ** I **D2I
N/C
         ** I ** 12-| L |-42 ** I **D1I
N/C
         ** I ** 13-| H |-41 ** I **D0I
N/C
N/C
         ** I ** 14-| S |-40 ** /O **L3
         /L4
               ** 16-| 0
** 17-| 1
                          |-38 ** /0 **L1
|-37 ** /0 **L0
         ** 0
/L5
         ** 0
              ** 17-|
/L6
         ** 0 ** 18-1
                           1-36 ** 0 **D70
/L7
         ** 0 ** 19-1
                           |-35 ** 0 **D60
N/C
          ** OV ** 20-|
GND
                          |-34 ** /O **GND
     Bottom
                           PIN** FNC ** LABEL
 LABEL
         ** FNC **PIN
         ** 0 ** 21-|
                          |- 7 ** I **SS1
BUFEN
         ** 0 ** 22-1
                           |- 6 ** I
N/C
                                    **SS0
         ** 0 ** 23-1
                           |- 5 ** I **SETUP
N/C
IOWB
         ** /O ** 24-| P |- 4 ** I **CMD
         ** /O ** 25-| L
                          |- 3 ** I
                                     **A2
N/C
         ** /O ** 26-| H
                          |- 2 ** I
                                     **A1
N/C
                          |- 1 ** I
         ** /0 ** 27-| S
N/C
         ** 0
                           |-52 ** I
D00
               ** 28-1
                        5
                                     **MIO
                          I-51 ** I
         ** 0 ** 29-1 0
D10
                                    **ADL
D20
         ** 0 ** 30-| 1 |-50 ** I **RST
         ** 0 ** 31-|
D30
                          |-49 ** I **D7I
         ** 0 ** 32-|
                          |-48 ** I **D6I
D40
          ** 0 ** 33-1
                           |-47 ** I **D5I
D50
           Figure 5-3. PLHS501 MCPOSREG Pinlist
```

```
File Name: MCPOSREG
Date: 5/31/1988
Time: 11:50:17
@DEVICE TYPE
     PLHS501
@DRAWING
GREVISION
@DATE
@SYMBOL
@COMPANY
GNAME
     Basic Programmable Option Select circuitry
         for a Micro Channel Adaptor card
@INTERNAL NODE
     /setup1,/mio1,a01,a11,/a21,ss01,ss11;
     /en.outen./iow:
@COMMON PRODUCT TERM
     read0 = (setup1*/ss11*ss01*mio1*/cmd*a21*/a11*/a01);
     read1 = (setup1*/ss11*ss01*mio1*/cmd*a21*/a11* a01);
     read2 = (setup1*/ss11*ss10*mio1*/cmd*a21* a11*/a01);
     NOTE: In the above equations, setupl, miol and a21 all should be
     preceded by a slash (/). The slash was omitted to correct for
     a mapping error in AMAZE 1.65 when using active low internal node
     definitions in common product terms.
     b7h = 0; " Define high ID byte "
     b6h = 1; " (POS byte #1)
     b5h = 1;
                       7E hex
     b4h = 1;
     b3h = 1;
     b2h = 1:
     b1h = 1;
     b0h = 0;
     b71 = 1; " Define low ID byte "
b61 = 1; " (POS byte #0) "
b51 = 1; " FF hex "
     b41 = 1:
     b31 = 1;
     b21 = 1;
     b11 = 1;
     b01 = 1:
@I/O DIRECTION
       "3-state output control of d7o-d0o"
     xe0 = (/setup1*/ss11*ss01*/mio1*/cmd*a21*outen);
     xel = (/setup1*/ss11*ss01*/mio1*/cmd*a21*outen);
     xe2 = (/setup1*/ss11*ss01*/mio1*/cmd*a21*outen);
     xe3 = (/setup1*/ss11*ss01*/mio1*/cmd*a21*outen);
@I/O STEERING
                              Figure 5-4. PLHS501 MCPOSREG .BEE File (begins)
```

```
@LOGIC EQUATION
      " 7-Bit Input Latch for Control Signals "
    /setupl = /setup*/adl + /setupl*adl;
    /moil = /mio */adl + /miol *adl;
    ssl1 = ssl */adl + ssl1 *adl;
    ss01 = ss0 */ad1 + ss01 *ad1;
    /a21 = /a2 */ad1 + /a21 *ad1;
                  */ad1 + a11
    a11
           = a1
                                   *ad1:
    a01
            = a0
                  */ad1 + a01
                                   *ad1;
      " Option Select Octal Data Latch (POS byte #2) "
      " 10 is to be used as a card enable signal"
    /en = /[/setupl*/ss01*ss11*/mio1*/cmd*/a21*a11*/a01]; "write to latch"
    /17 = /[/d7i * en] * /[17 * /en] * [/rst];
    /16 = /[/d6i * en] * /[16 * /en] * [/rst];
    /15 = /[/d5i * en] * /[15 * /en] * [/rst];
    /14 = /[/d4i * en] * /[14 * /en] * [/rst];
    13 = /(/[ d3i * en * /rst] * /[13 * /en * /rst]);
    12 = /(/[d2i * en * /rst] * /[12 * /en * /rst]);
    11 = /(/[ dli * en * /rst] * /[11 * /en * /rst]);
    10 = /(/[ d0i * en * /rst] * /[10 * /en * /rst]);
      " Octal 3 to 1 Multiplexer "
      " This miltiplexer selects between reading
        POS[0], POS[1] or POS[2] onto the data bus"
    d7o = (b7h*read1 + b71*read0 + /17*read2);
    d6o = (b6h*read1 + b61*read0 + /16*read2);
    d50 = (b5h*read1 + b51*read0 + /15*read2);
    d4o = (b4h*read1 + b4l*read0 + /14*read2);
    d3o = (b3h*read1 + b31*read0 + 13*read2);
    d2o = (b2h*read1 + b21*read0 + 12*read2);
    dlo = (blh*read1 + bll*read0 + l1*read2);
    d0o = (b0h*read1 + b01*read0 + 10*read2);
      "3-State output control for d7o-d0o:
    outen =/[all*a01];
      "External F245 transceiver control"
    iowb = /(/a21 * /setupl * miol * ss11 * /ss01);
    /iow = /(/a2l * /setupl * miol * ssll * /ss0l);
    bufen = cmd * /iow;
                              Figure 5-4. PLHS501 MCPOSREG .BEE File (end)
```

Signetics

PLHS501 Application Notes Vol. 2

Programmable Logic Devices

NuBus INTERFACE


In Apple Computer's book" "Designing Cards and Drivers for Macintosh II and Macintosh SE", an application was described for interfacing an 8-bit I/O controller to the NuBus. The controller used was a SCSI controller of the type used on the main Macintosh logic board. Seven devices (three of which were PAL architecture) were used as control circuitry interfacing the SCSI controller and two RAM chips to the bus.

This example of using the PLHS501 shows a method of interfacing the same SCSI controller and RAM chips to the NuBus using only three parts. The adapter card schematic is shown in Figure 6–2 and the AMAZE listing is in Figure 6–6. Although the AMAZE listing may seem


confusing at first glance, the circuitry fused into the PLHS501 can be broken down into small blocks of latches, flip-flops, and schematically in Figures 6–4 and 6–5. Circuit timing is shown in Figure 6–3.


Referring to Figure 6–4 and Figure 6–5, the circuitry starts a transaction by first detecting a valid address in either the slot or super slot range. The detection is accomplished by two wide–input NAND gates, and controlled by the /CLK signal. Following each NAND gate is an S–R latch to hold the signal until near the end of the cycle. The two S–R latch signals are combined into one signal named STO such that if either NAND gate output was low, then some delay time after the rising edge of /CLK, STO will go low. The next


rising edge of /CLK will cause signal ST1 to go low. This sets signal DE2 low, which is an input to an external flip-flop to cause ST2 to go low at the next rising /CLK edge terminating the cycle. An external flip-flop was necessary to achieve a high-speed /CLK to /IOR and /ACK transition. Also, an external FI25 buffer was added to meed the soon to be approved IEEE P1196 specification requirement of 60mA lol for signal /NMRQ and 24mA IoL for signals /TM0/TM1 and /ACK. Figure 6-5(B) shows an easily implemented latch which controls interrupts generated by the SCSI controller passing onto the bus. Upon /RESET the latch is put into a known state. Under software control, by writing to a decoded address, the latch may be set or reset, thereby gating or blocking the interrupt signals.




^{*} Designing Cards and Drivers for Macintosh II and Macintosh SE, Addison-Wesley Publishing Company, Inc. 1987.









```
Right
                      LABEL ** FNC **PIN
                                                   PIN** FNC ** LABEL
                              ** +5V ** 8-|
                                                 |-46 ** +5V **VCC
                              ** I ** 9-|
** I ** 10-|
                                                 |-45 ** I **D1
                              |-44 ** I
P |-43 ** I
                    /ID3
                    DRO
                              ** I ** 12-| L |-42 ** I
                                                            **A18
                    IRO
                              ** I ** 13-| H |-41 ** I **A9
                    ST2
                              ** I ** 14-| S |-40 ** /O **STO
                              ** 0 ** 15-| 5 |-39 ** /0 **N/C
                    N/C
                               ** 0
                                     ** 16-| 0 |-38 ** /0 **N/C
                    N/C
                               ** 0
                    N/C
                                     ** 17-| 1 |-37 ** /0 **N/C
                              ** 0
                                    ** 18-|
                    N/C
                                                  1-36 ** 0
                                                             **N/C
                               ** 0 ** 19-|
                                                  |-35 ** 0 **N/C
                    N/C
                               ** OV ** 20-1
                                                 |-34 ** /O **GND
                    GND
                              Top

rNC **PIN PIN** FNC ** LABEL

** 0 ** 21-| |- 7 ** I **/ID1

** 0 ** 22-| |- 6 ** I **/***

** 0 ** 23-| |- "
                          Bottom
                      LABEL ** FNC **PIN
                    N/C
                    N/C
                    ACLK
                    /ROMCS
                    /RAMCS
                              ** /O ** 25-| L |- 3 ** I **/ACK
                               ** /O ** 26-| H |- 2 ** I
                                                             **/START
                    N/C
                               ** /O ** 27-| S |- 1 ** I
                                                             **/CLK
                    /NMRO
                                                 1-52 ** I
                              ** 0
                                     ** 28-| 5
** 29-| 0
                    DE2
                              ** 0
                                    ** 29-|
                    /RESET
                                                  I-51 ** I
                                                             **D6
                              /SCSI
                                                            **D5
                    /DACK
                              ** 0 ** 31-1
                                                 I-49 ** I **D4
                             ** 0 ** 32-|
                    /IORR
                                                 |-48 ** I **D3
                              ** 0 ** 33-|
                    /IOW
                                                 1-47 ** I **D2
@DEVICE TYPE
   PT.HS501
@DRAWING
@REVISION
BDATE
@SYMBOL
@COMPANY
GNAME
@DESCRIPTION
    SCSI-NuBus Interface
@INTERNAL NODE
    /sl,/sp,/SLOT,/SUPER;
sn1, sn2, rn1, rn2;
sn3, rn3, st1;
sn4, rn4, tmll, tmlln;
CMP3a, CMP2a, CMP1a, CMP0a;
CMP3b, CMP2b, CMP1b, CMP0b;
/slt,/sup,stln,adclk;
setad, rstad, inten;
slotn, supern;
@COMMON PRODUCT TERM
@I/O DIRECTION
@I/O STEERING
@LOGIC EQUATION
    "Address Decode"
cmp0a = (d0*id0+/d0*/id0):
cmpla = (d1*id1+/d1*/id1);
                                Figure 6-6. AMAZE Listing (begins)
```

```
cmp2a = (d2*id2+/d2*/id2);
cmp3a = (d3*id3+/d3*/id3);
cmp0b = (d4*id0+/d4*/id0);
cmp1b = (d5*id1+/d5*/id1);
cmp2b = (d6*id2+/d6*/id2);
cmp3b = (d7*id3+/d7*/id3);
/sl = /(d7*d6*d4*cmp0a*cmp1a*cmp2a*cmp3a*start*/ack*clk);
/sp = /(cmp0b*cmp1b*cmp2b*cmp3b*start*/ack*clk);
     "latch slot signal"
/slt = /(/reset*st2*/[/sl*/slt]);
     "latch super signal"
/\sup = /(/\operatorname{reset*st2*}/[/\operatorname{sp*}/\operatorname{sup}]);
     "Let /slt or /sup through only
      until after the rising edge
      of /clk"
st0 = /(/[/slt*/sup*clk] * /[st0*clk] * /[/slt*/sup*st0] * /reset);
     "Slot signal D-type Flip-Flop"
sn1 = /(/clk*slt*(/[sn1*/reset*/super*(/[st0*rn1*/slt])]));
rn1 = /(/clk*sn1*(/[st0*rn1*/slt]));
/slot = /(/reset*/super*sn1*slotn);
slotn = /(//slot*rnl*/slt);
     "Super signal D-type Flip-Flop"
sn2 = /(/clk*/sup*(/[sn2*/reset*/slot*(/[st0*rn2*/sup])]));
rn2 = /(/clk*sn2*(/[st0*rn2*/sup]));
/super = /(/reset*/slot*sn2*supern);
supern = /(/super*rn2*/sup);
     "State 1 D-type Flip-Flop"
sn3 = /(/clk*(/[sn3*/reset*(/[st0*rn3])]));
rn3 = /(/clk*sn3*(/[st0*rn3]));
st1 = /(/reset*sn3*st1n);
st1n= /[st1*rn3];
     "output to external flop"
de2 = /(stln * st2);
     "address latch clock"
adclk = clk*st0*st1;
     = clk*st0*st1;
     "latch tml signal for r/w info"
sn4 = /(adclk*/reset*(/[sn4*(/[/tm1*rn4*/reset])]));
rn4 = /(adclk*sn4*(/[/tml*rn4*/reset]));
tmll = /(sn4*tmlln);
tmlln= /(rn4*/reset*tmll);
     tmll -> 1 read, 0 write
     tmlln -> 0 read, 1 write
    "straight decode stuff"
/iorr = /(/st0*tmll)
                                              * /reset);
/iow = /(/tm1ln*st0)
                                              * /reset);
/scsi = /(slotn*/a19*/a18*/a9
                                              * /reset);
/dack = /(slotn*/a19*/a18* a9
                                              * /reset);
/romcs= /(slotn* a19* a18
                                              * /reset);
/ramcs= /(supern
                                              * /reset);
/resetb= /reset;
     "interrupt control latch"
setad = /(tmlln*/st0*slotn* al9*/al8* a9);
rstad = /(tmlln*/st0*slotn* al9*/al8*/a9);
inten = /(setad*(/[inten*rstad*/reset]));
/nmrq = /(inten*drq+inten*irq);
                                     Figure 6-6. AMAZE Listing (end)
```

PLHS501 Application Notes Vol. 2

Programmable Logic Devices

NUGGETS

Much current focus for microprocessor design is on the address bus. Typically, most designers assume the processor will handle the data manipulation and the data bus is assumed to be a straight, clean path to and from the memory. Data transformations may be accomplished for specific purposes when the application requires it. For instance, a classic transformation from the early 70's was the bit reversal required to address operands for a Fast Fourier Transformation. When designers implemented bit reversal as a separate hardware process, the whole system improved. Likewise for hardware multipliers.

Also, a hidden "transformation" is the appending of parity and the calculation of E.C.C. polynomials. Clearly, when the designer recognizes that significant performance improvement can be achieved by realizing the payoff attainable with a special purpose hardware device, he should design it. For example, let's consider parity generation:

Data Bus Parity

The PLHS501 can span 32 bits of input data. It has four output Ex-OR gates, and the ability to generate literally any function


of the inputs. It would seem that there must be some "best" way to generate and detect parity. Recall that the PLHS501 can generate both deep logic functions (lots of levels) and wide logic functions (lots of inputs). The best solution would require the fewest gates and the fewest number of logic levels. Let's review the basics, first. Table 7–1 (A) shows the parity function for two variables and Table 7–1 (B) shows it for three variables. The Ex–OR function generates even parity.


It is noticeable that there are precisely 50% logical 1 entries in the truth tables. This yields the famous checkerboard Karnaugh Maps. With a checkerboard K-map, no simplification of Ex-OR functions is possible by Boolean simplification. The two variable Ex-OR has two ones (implying 3 gates to generate), the 3 variable has four ones (implying 5 gates to generate). In general, 2ⁿ⁻¹+1 product terms could generate Ex-OR functions in two levels of NAND gates (assuming complementary input variables exist). You must have an unlimited number of gate inputs for this to hold


The PLHS501 could do this for 7 input variables in two levels (2⁶+1=65), but


cannot support 8 (2⁷+1=129). Hence, it is appropriate to seek a cascaded solution, hopefully taking advantage of the available output Ex-OR functions. Let's solve a 16 input Ex-OR function, by subpartitioning. First, consider Figure 7-1(A) where two literals are Exclusive-ORed to generate an intermediate Ex-OR function. This requires available complementary inputs and generates even parity in two levels. Figure 7-1(B) also does this (by factoring), requiring 3 gate levels, but does not require complementary inputs.

Assuming inputs must get into the PLHS501 through the pin receivers, it is best to generate as wide of an initial Ex-OR as possible, so a structure like Figure 7-1(A) expanded is appropriate. Figure 7-1 shows a 2-level 4 input Ex-OR function which may be viewed as a building block. This structure may be repeated four times, across four sets of four input bits generating partial intermediate parity values which may then be treated through two boxes similar to Figure 7-1(B). These outputs are finally combined through an output Ex-OR at a PLHS501 output pin. Figure 7-3 shows the complete solution which requires 44 NANDs plus one Ex-OR.









Two examples follow which were supplied by one of our European Sales Engineers, Nils Lindgren. The first, called 'paritet', calculates even and odd parity for 24 input literals. Several output options are available and the design uses a cascade with a different partitioning than just previously discussed.

The second example "compare" implements, a 16-bit comparator over 32 input bits. The design generates outputs for conditions representing the classic "EQUAL", "AGTB" (A>B) and BGTA (B>A). The long, triangularized equation for T42 suggests that Nils found a clever editing approach to accurately enter a

relatively long design equation into Signetics

```
File Name : PARITET
Date : 5/31/1988
Time : 10:26:22
Right
      Left
  LABEL
          ** FNC **PIN
                           PIN** FNC **
          ** +5V ** 8-|
VCC
                           |-46 ** +5V **VCC
          ** I ** 9-|
                           |-45 ** I **K
A
         ** I
               ** 10-1
                           |-44 ** I
         ** I ** 11-1
                           |-43 ** I
         ** I ** 12-| L |-42 ** I
                                    **H
D
         ** I ** 13-| H |-41 ** I
E
         ** I ** 14-| S |-40 ** /O **N/C
         ** B ** 15-| 5 |-39 ** /0 **N/C
N/C
          ** B ** 16-| 0 |-38 ** /0 **N/C
N/C
N/C
          ** B
               ** 17-| 1 |-37 ** I
         ** B
N/C
               ** 18-1
                           1-36 ** 0
                                     **N/C
         ** 0 ** 19-1
                           I-35 ** O
                                    **N/C
N/C
GND
         ** 0V ** 20-1
                           I-34 ** OV **GND
      Bottom
  LABEL ** FNC **PIN
                            PIN** FNC **
                                          LAREL.
          ** 0 ** 21-1
                           |- 7 ** I
         ** 0 ** 22-1
                           |- 6 ** I
N/C
         ** 0 ** 23-1
                           |- 5 ** T
ODD OC
          ** /0 ** 24-1 P
                          |- 4 ** I
ODD
EVEN
          ** /0 ** 25-| L |- 3 ** I
         ** /O ** 26-| H |- 2 ** I
EVEN OC
          ** /0 ** 27-| S |- 1 ** I
N/C
                                     **R
                      5
N/C
         ** 0
               ** 28-1
                           I-52 ** I
                                      **0
         ** 0
               ** 29-|
                           |-51 ** I
N/C
                        0
                                     **p
         ** 0 ** 30-| 1
                          1-50 ** I
                                     **0
N/C
                                     **N
         ** 0 ** 31-1
                           |-49 ** I
N/C
N/C
         ** 0 ** 32-1
                           |-48 ** I
                                     **M
N/C
         ** 0 ** 33-|
                           |-47 ** I
            Figure 7-4. PARITET PLHS501 Pinlist
```

```
File Name : PARITET
@DEVICE TYPE
  PLHS501
@DRAWING
@REVISION
@DATE
@SYMBOL
@COMPANY
  Philips
@NAME
  Nils Lindgren
@DESCRIPTION
  24 bit parity circuit
@INTERNAL NODE
  JO J1 J2 J3 J4 J5 J6 J7 J8 J9 T0 T1 T2 T3
@COMMON PRODUCT TERM
@I/O DIRECTION
  OE1=T2*T3*/OEN;
  OE2=/OEN;
  OE3=T0*T1*/OEN;
@I/O STEERING
@LOGIC EQUATION
     "FIRST LEVEL: 'EVEN' FROM GROUPS OF THREE INPUTS"
   J0=/A*/B*/C + /A*B*C + A*/B*C + A*B*/C;
   J1=/D*/E*/F + /D*E*F + D*/E*F + D*E*/F;
   J2=/G*/H*/I + /G*H*I + G*/H*I + G*H*/I;
  J3=/J*/K*/L + /J*K*L + J*/K*L + J*K*/L;
  J4=/M*/N*/O + /M*N*O + M*/N*O + M*N*/O;
   J5=/P*/Q*/R + /P*Q*R + P*/Q*R + P*Q*/R;
   J6=/S*/T*/U + /S*T*U + S*/T*U + S*T*/U;
   J7=/V*/X*/Y + /V*X*Y + V*/X*Y + V*X*/Y;
     "SECOND LEVEL: 'EVEN' FROM FOUR GROUPS AT A TIME"
   J8=/J0*/J1*/J2*/J3 + /J0*/J1*J2*J3 + J0*J1*/J1*/J3 + /J0*J1*J2*J3
     + J0*/J1*/J2*J3 + /J0*J1*/J2*J3 + J0*/J1*J2*/J3 + J0*J1*J2*J3;
   J9=/J4*/J5*/J6*/J7 + /J4*/J5*J6*J7 + J4*J5*/J6*/J7 + /J4*J5*J6*J7
      + J4*/J5*/J6*J7 + /J4*J5*/J6*J7 + J4*/J5*J6*/J7 + J4*J5*J6*J7;
   T0=/(J8*J9);
   T1=/(/J8*/J9);
   T2=/(J8*/J9);
  T3=/(/J8*J9);
  ODD=/(T2*T3);
  EVEN=/(T0*T1);
  ODD OC=O;
   EVEN OC=/(1);
                                Figure 7-5. PARITET PLHS501 .BEE File
```

```
File Name : compare
Date : 5/31/1988
Time: 10:25:29
LABEL ** FNC **PIN
                          PIN** FNC ** LABEL
         ** +5V ** 8-1
                          1-46 ** +5V **VCC
         ** I ** 9-1
                          I-45 ** I **B2
         ** I ** 10-|
                          |-44 ** I
Δ1
                      P
                          1-43 ** I
         ** I ** 11-|
A2
         ** I
               ** 12-1
                       L
                          |-42 ** I
                     H
              ** 13-1
         ** I
                          |-41 ** I
A4
                                    **AF
A.5
         ** I ** 14-| S |-40 ** I
                                    **AD
         ** I ** 15-| 5 |-39 ** I
         ** I ** 16-| 0 |-38 ** I
                                    **AB
A7
         ** I ** 17-| 1 |-37 ** I
                                    ** 4 4 4
A8
         1-36 ** O
                                    **N/C
A9
N/C
                          1-35 ** 0
                                    **N/C
         ** 0V ** 20-1
                          |-34 ** OV **GND
GND
      Bottom
                          PIN** FNC **
         ** FNC **PIN
 LABEL
                                         LABEL
         ** 0 ** 21-1
                          I- 7 ** I **BF
EQUAL
         ** 0
               ** 22-|
                          |- 6 ** I
         ** 0
              ** 23-|
                          |- 5 ** I
BGTA
                                    **BD
         ** /0 ** 24-1
                          |- 4 ** I
                                    **BC
N/C
N/C
         ** /0 ** 25-1 L
                         1-3 ** I
N/C
         ** /O ** 26-| H |- 2 ** I
         ** /0 ** 27-| S |- 1 ** I
N/C
         N/C
                                    **B8
         ** 0
N/C
               ** 29-1
                          |-51 ** I
         ** 0 ** 30-1
                          |-50 ** I
                                    **B6
N/C
         ** 0 ** 31-|
                          |-49 ** J
N/C
                                    **R5
         ** 0 ** 32-1
                          1-48 ** I
                                    **B4
N/C
N/C
         ** 0 ** 33-|
                          |-47 ** I
        Figure 7-6. PLHS501 Pinlist for 16-Bit Comparator
```

```
File Name : compare
Date : 5/31/1988
Time: 10:25:43
@DEVICE TYPE
  PLHS501
@DRAWING
@REVISION
@DATE
@SYMBOL
@COMPANY
  PHILIPS
@NAME
  NILS LINDGREN
@DESCRIPTION
  16 BIT COMPARATOR WITH THREE OUTPUTS:
    EQUAL, AGTB (A>B), AND BGTA (B>A)
                              Figure 7-7. Compare PLHS501 .BEE File (begins)
```

```
@INTERNAL NODE
   T1 T2 T3 T4 T5 T6 T7 T8
   T9 T10 T11 T12 T13 T14 T15 T16
   T17 T18 T19 T20 T21 T22 T23 T24
   T25 T26 T27 T28 T29 T30 T31 T32
   T41 T42
@COMMON PRODUCT TERM
@I/O DIRECTION
@I/O STEERING
@LOGIC EQUATION
                 T2=/(/AF*BF);
  T1=/(AF*/BF);
   T3=/(AE*/BE); T4=/(/AE*BE);
   T5=/(AD*/BD); T6=/(/AD*BD);
   T7=/(AC*/BC); T8=/(/AC*BC);
   T9=/(AB*/BB); T10=/(/AB*BB);
   T11=/(AA*/BA); T12=/(/AA*BA);
   T13=/(A9*/B9); T14=/(/A9*B9);
   T15=/(A8*/B8); T16=/(/A8*B8);
   T17=/(A7*/B7); T18=/(/A7*B7):
   T19=/(A6*/B6); T20=/(/A6*B6);
   T21=/(A5*/B5); T22=/(/A5*B5);
   T23=/(A4*/B4); T24=/(/A4*B4);
   T25=/(A3*/B3); T26=/(/A3*B3);
   T27=/(A2*/B2); T28=/(/A2*B2);
   T29=/(A1*/B2); T30=/(/A1*B1);
   T31=/(A0*/B0); T32=/(/A0*B0);
   T41=T1*T2*T3*T4*T5*T6*T7*T8*T9*T10*T11*T12*T13*T14*T15*T16*T17*
       T18*T19*T20*T21*T22*T23*T24*T25*T26*T27*T28*T29*T30*T31*T32;
   T42=
                                                                 /T1+
                                                               /T3*T2+
                                                           /T5*T4*T2+
                                                        /T7*T6*T4*T2+
                                                     /T9*T8*T6*T4*T2+
                                                /T11*T10*T8*T6*T4*T2+
                                            /T13*T12*T10*T8*T6*T4*T2+
                                        /T15*T14*T12*T10*T8*T6*T4*T2+
                                    /T17*T16*T14*T12*T10*T8*T6*T4*T2+
                                /T19*T18*T16*T14*T12*T10*T8*T6*T4*T2+
                            /T21*T20*T18*T16*T14*T12*T10*T8*T6*T4*T2+
                        /T23*T22*T20*T18*T16*T14*T12*T10*T8*T6*T4*T2+
                    /T25*T24*T22*T20*T18*T16*T14*T12*T10*T8*T6*T4*T2+
                /T27*T26*T24*T22*T20*T18*T16*T14*T12*T10*T8*T6*T4*T2+
            /T29*T28*T26*T24*T22*T20*T18*T16*T14*T12*T10*T8*T6*T4*T2+
        /T31*T30*T28*T26*T24*T22*T20*T18*T16*T14*T12*T10*T8*T6*T4*T2;
EQUAL=T41;
AGTB=T42;
BGTA=/(T41+T42);
                              Figure 7-7. Compare PLHS501 .BEE File (end)
```


Data Bus Operations

The following is basically an academic example, posed for the sake of illustration. Suppose some special data bus operations are desirable. For the purpose of illustration, let's label the microprocessor bus output side as ODAT0-ODAT15 and the output of our PLHS501 as D0-D15. Basically, the microprocessor will output straight data and the PLHS501 will alter it according to some plan.

We will replicate multiple identical cells, but they need not be identical in practice. Table 7–2 shows the operations to be done (just about any could be chosen, provided they meet the gate budget).

Table 7-2. Data Operations

l ₂	I ₁	D _{OUT}	
0	0	ODATI (pass)	
0	1	ODATI (complement)	
1	0	SWITCH	
1	1	DOUBLE SHIFT	



It may be observed that in one mode, the data passes directly, it complements in another, switches bits in another and rotates right in the last. Four input gates per bit are required to map the bits, and one output gate. Clearly, the straight PLHS501 NAND outputs can be judiciously used, but care must be taken when using other output functions. A 16-bit data bus requires 16 cell configuration where each cell is essentially identical to Figure 7-8, but its internal structure may be altered to account for the particular output pins logic function.

PLHS502 Application Notes Vol. 1


Programmable Logic Devices

INTRODUCTION

Certain design techniques are used repeatedly by nearly all digital systems designers. If these useful building blocks occur with enough volume production. they become special purpose contenders for silicon manufacturers to justify rendering as standard products. Some building blocks, however, are never viewed as likely candidates because the performance requirements may be too high, the volumes not high enough, or it never occurred to marketeers that these subsystems would be valuable. System designers could fashion solutions to these building blocks from glue logic or PLDs and sometimes small gate arrays. Several typical building blocks will be illustrated here - including a 4-byte datapipe, a small content addressable memory (CAM), a system resource scoreboard and a synchronous receiver/transmitter. The generation of each building block will be demonstrated with a Signetics PLHS502 (Figure 1-1). This device is rendered in the Programmable Macro Logic (PML) architecture which deftly bridges the gap between gate arrays and ordinary PLDs.

Designed with a high-speed bipolar process, the PLHS502 combines 64 extremely wide foldback NAND gates with two types of internal flip-flops. The PLHS502 provides 8 internal D flip-flops and 8 internal S-R flip-flops. Each flipflop can toggle in excess of 50MHz. These flip-flops are called "hard macro" flip-flops. Unique among such programmable devices, each flip-flop has completely independent clocking. This allows either external clocking (from four different pins) or internally derived clocking events. Ripple and synchronous controllers may be freely mixed. It should be remembered that additional flip-flops and specially custom designed flip-flops may be configured from the NAND array. Clock independence is a requirement for generating distinct internal sequencers and controllers. Additionally, it should be noted that the flip-flop Q outputs cross the clock fusing array, but \overline{Q} outputs do not. The PLHS502 is packaged in a 68-pin PLCC.

This application note consists of several sections. The next section briefly describes Signetics SNAP software package for implementing PML designs. Section 3 describes the basic process for estimating whether a design will fit into a PLHS502. In Section 4, some guidelines for designing synchronous state machines are given with focus on efficient counter and shifter design. Specific examples are included which may be easily mimiced for successful state machine design. Additional guidelines are then provided in Section 5, for optimizing a design before it is implemented with SNAP. These guidelines will help guarantee that SNAP implements the function precisely as needed. In Section 6, some larger examples are provided which illustrate some interesting and unique capabilities of the PLHS502. Section 7 details a procedure for merging logic functions into flip-flops for faster, more efficient structures.



PLHS502 Application Notes Vol. 1

Programmable Logic Devices

DEVELOPMENT SUPPORT

Because the architecture encourages deep functional nesting, a new support tool has been developed. Synthesis, Netlist, Analysis and Program (SNAP) software defines a gate array type development environment. SNAP permits several forms of design capture (schematic, Boolean equations, state equations, etc.), a gate array simulator with back annotation, waveform display and a complete fault analyzer and final fusemap compilation and model extraction. SNAP comes with a library of cells, and designs may be captured independently of the ultimate device that will implement the design. This permits the designer to migrate his design among a family of PML devices just as gate array designs can be moved to larger foundations when they do not route on smaller ones. Figure 2-1 shows the SNAP user interface "Shell" which dictates one sequence of operations to complete a design. Other sequences may be used.

The top portion of the shell depicts the paths available for design entry. Any de-

sign may be implemented in any one or a blend of all methods. For instance, a shift register might best be described schematically but a decoder by logic equations. These may be united with a multiplexor described by a text netlist as well. Ultimately, each form of input will be transformed to a function netlist and passed either to the simulation section or to the compiler section. Waveform entry is for simulation stimuli.


The simulator portion of SNAP is a 5—State gate array simulator with full timing information, setup and hold time checking, toggle and fault grade analysis and the ability to display in a wide range of formats, any set of nodes within the design. This permits a designer to zoom in with a synthetic logic state analyzer and view the behavior of any point in the design. Simulations can occur with unit delays, estimations or exact delays. The sequence of operations depicted in Figure 2–1 is entirely arbitrary, as many other paths exist.

It should be noted that the output of the

"merger" block represents the composite design, but as yet is not associated to a PML device. This occurs in the compiler portion wherein association to the device occurs and a fusemap is compiled. This is analogous to placement and routing in a gate array environment. Because of the interconnectibility of PML, this is not difficult. Once compiled, the exact assignment of pins, gates and flip-flops is known, so timing parameters may be associated and a new simulation model generated with exact detailed timing embedded. The design may be simulated very accurately at this point, and if correct, a part should be programmed.

To facilitate future migration to work-stations, SNAP has been written largely in C. The internal design representation is EDIF (Electronic Design Interchange Format) compatible which permits straightforward porting to many commercially viable environments. SNAP currently utilizes OrCAD for schematic entry with eminent availability of FutureNetTM DASH.

FutureNet and DASH are trademarks of DATA I/O



PLHS502 Application Notes Vol. 1

Programmable Logic Devices

CAPACITY AND PARTITIONING CONSIDERATIONS

One of the dominant attributes of PML architecture is its complete interconnectibility. Any function – NAND, flip—flop, input and output structures, can be connected to any other. PML devices do not exhibit the restricted interconnect bottleneck like other programmable gate arrays. If there is capacity within the part for a function, it can be connected without the sad surprise ending of "nonroutability". Estimation for design fit is simply a matter of tallying function usage against a fixed set of resources using a table lookup. An elementary table

of typical useful functions is provided in Table 3–1. Clearly Table 3–1 shows only a few of the typical functions achievable and their relative "expense" from the total function budget. As with gate arrays, the designer needs only to implement the portion of his chosen function that is to be actually used.

Fortunately, if the designer is using SNAP, all unused functions will be automatically eliminated. This is done by netlist analysis where SNAP observes an output within your circuit which is unconnected. It eliminates the unconnected gate and

reanalyzes to see if there are more unconnected gates in the design. The procedure iterates until there are no more unconnected gates. When estimating whether a function will fit or not, the values in Table 3–1, if used without modification, should result in a high gate count. So, to more accurately assess fit, they should be derated to account for automatic netlist trimming. As well, the estimator should consider logic functions which can be obtained for "free" from input buffers and output functions. Guidelines, provided in Section 5, will illustrate this process.

TABLE 3-1. PLHS502 GATE EQUIVALENT TABLE

FUNCTION		INTERNAL NAND EQUIVALENT	COMMENTS
Gates:			
	NANDs ANDs NORs ORs	1 1 1 1	For 1 to 32-pin input variables Add'I internal inputs can be used as needed Add'I internal inputs can be used as needed Add'I internal inputs can be used as needed
Gate Macro F	lip-Flops:		
	D-FF SR-FF	N/A N/A	Total Budget = 8 Total Budget = 8
Gate Impleme	ented Flip-Flops:		
	D–FF T–FF J–K–FF Transparent–D Latch S–R Latch	6 6 10 4 2	With async S-R With async S-R With async S-R With async S-R With async S-R
Decoders:			
	3 to 8 4 to 16 5 to 32	8 16 32	Inverted inputs available Inverted inputs available Inverted inputs available (24 chip outputs only)
Encoders:			
	8 to 3 16 to 4 32 to 5	15 32 41	Inverted inputs, 2 logic levels Inverted inputs, 2 logic levels Inverted inputs, 2 logic levels
Multiplexors:			
	4 to 1 8 to 1 16 to 1 27 to 1	5 9 17 28	Inverted inputs available Inverted inputs available Inverted inputs available Can address only 27 externally inputs – more if internal only. This disallows clock inputs to flip—flop.

PLHS502 Rough Resource Budget = 64 NANDs, 8 D, 8 SR, 24 inputs, 16 outputs, 8 bidirect.

PLHS502 Application Notes Vol. 1

Programmable Logic Devices

STATE MACHINE DESIGN


Synchronous state machines can be classified in roughly three practical categories sequence generators, sequence detectors and controllers. These can also be subcategorized as Mealy, Moore, finite state, linear, etc. A very large application market is covered, by considering the basic design of counters and shifters because a counter (with possible decoding) can be viewed as a generalized sequence generator and a shifter (with decoding) can be viewed as a sequence detector. A couple of small examples should illustrate the basic principles of flip-flop selection, picking optimal solutions and trading off hard macro and soft macro functions. First, a few small counters will be discussed in detail from a logic viewpoint. Then, small shifters will be shown. These basic designs are extendible so that a designer can recognize the patterns to make the counters and shifters bigger if necessary. In the next section, some general guidelines for getting "smaller, tighter" designs will be given.


Counter Design Notes


A straightforward 3-bit up/down counter transition table is depicted in Figure 4-1(a). The state variables are designated A, B, C and the direction control is U. Up counting occurs when U = 1 and down counting occurs when U = 0. Figure 4-1(b) shows four variable maps with the next state transitions at the current state

and input intersections. These transitions will be useful in reference to Figures 4–2, 4–3 and 4–4 where the design is cast onto D, S–R and J–K flip–flop solutions.

We will not initially be interested in the full design details but rather, only on the number of product terms and sum terms for each solution. Figure 4–2(b) shows the K-map loops for a D flip-flop solution. Figure 4–2(a) shows the required transitions used to generate the three maps in Figure 4–2(b). There are 9 loops for the A and B variables requiring 9 product terms and 2 sum terms for driving the A and B flip-flops. The C flip-flop requires no additional logic. Note the "SUM" terms are free on PLHS502 D flip-flops because of the embedded NANDs.











Figure 4–3 shows the same design implemented with S–R flip–flops. Figure 4–3 (a) shows the required S–R transitions and Figure 4–3(b) maps them onto the corresponding state variable maps. Tallying the loops, we find a total of 8 product terms and 4 sum terms. Again, the sum terms are free.

Figure 4-4 shows the design again on J-K flip-

flops. Figure 4–4(a) shows the transitions and Figure 4–4(b) the K–map loops. Again tallying yields 4 product terms and 4 sum terms. The C variable is realized by J=K=1 using no product terms, or sum terms.

From standard logic design we know that D flipflops will increase product terms (no don't care transitions), S–R flip-flops are less dramatic and J-Ks increase product terms the least (i.e., maximum don't cares).

However, the PLHS502 has no J–K flip–flops. For simple toggling, the D flip–flop requires no additional circuitry and is the smallest (usually fastest) implementation. So, Ds should always be assigned for the least significant bit.



If required, J–K flip–flops can be constructed from D flip–flops by utilizing the structure shown in Figure 4–5, as a substitution. The sum term is taken from the NAND physically connected to the D flip–flop and the K input may be derivable from either an input inverter or a \square from a flip–flop. There will be a penalty for using this structure from a speed point, but it may save gates if used judiciously.

This example assumes the designer is implementing the counter with the internal hard macro flip—flops. If the design is being generated from the NAND array only, it should be noted that the payoff will be interestingly different. The D flip—flop requires 6 NANDs and the J—K flip—flop will require 10 NANDs. In this version, the sum terms cost an additional NAND gate

each. So, the 3-bit up/down counter will require:


quire: Flip-flops:	3 x 6 =	18	
Sum terms	:	2	
Prod. terms	:	9	
	Total -	20	antos


The same design built from J-Ks configured from NANDs will require:


Flip-flops :	3 x 10 =	: 30	
Sum terms	.:	3	
Prod. terms	:	<u>4</u>	
	Total -	- 37	nates

The all D version looks pretty good at this point from a total gate count view. Let's take a closer look at the D flip—flop solution:

Figure 4–6 shows the D flip–flop solution with all prime implicants looped and the corresponding transition equations are below. This is implemented in Figure 4–7 using conventional D flip–flops in the PLHS502. An alternate solution would be to substitute the 6 NAND D flip–flop for each D–box in Figure 4–7, but a better (only 25 gates!) solution can be achieved by merging the logic gates on the input of the flip–flops right into the NAND flip–flop structure as shown in Figure 4–8. This technique was described in PLHS501 Applications Notes Volume 2.








A couple of final notes on counter design. The basic structure for a simple up counter is shown in Figure 4–9. This one uses a D flip—flop least significant bit and a generic format for high order bits, as shown. Note that only 2 product terms per bit are needed.

Down counters can be treated similarly. Fairly

general sequence generators can be configured from counters by simply adding a combinational decoder, as needed. One final counter example is shown in Figure 4–10 wherein a 10–bit counter is defined using the SNAP Boolean equation format. Note that the logic equations follow the format described in

Figure 4–9. All resets are shared as well as all clocks. This design would require eight hard macro S–R flip–flops, one hard macro D flip–flop and one additional S–R flip–flop which SNAP would automatically configure from a hard macro D flip–flop.



```
@PINLIST
CLOCK I; RESET I; A 0; B 0; C 0; D E 0; F 0; G 0; H I 0; L 0;
                                                                                                       0;
                                                                                                          0;
@LOGIC EQUATIONS
A.D = /A;

B.S = /B*B
               /B*A;
B.R = B*A;
C.S = /C*A*B;
C.R = C*A*B;
C.R = C^A^B;

D.S = /D*A*B*C;

D.R = D*A*B*C;

E.S = /E*A*B*C*D;

E.R = E*A*B*C*D*E;

F.S = /F*A*B*C*D*E;

F.R = F*A*B*C*D*E;
G.S = /G*A*B*C*D*E*F;
G.R = G*A*B*C*D*E*F;
H.S = /H*A*B*C*D*E*F*G;
H.S = /H*A*B*C*D*E*F*G;

I.S = /I*A*B*C*D*E*F*G*H;

I.R = I*A*B*C*D*E*F*G*H;

I.R = I*A*B*C*D*E*F*G*H;

L.S = /L*A*B*C*D*E*F*G*H*I;

L.R = L*A*B*C*D*E*F*G*H*I;
A.RST = /RESET;
B.RST = /RESET;
C.RST = /RESET;
D.RST = /RESET;
E.RST = /RESET;
F.RST = /RESET;
G.RST = /RESET;
H.RST = /RESET;
I.RST = /RESET;
L.RST = /RESET;
A.CLK = CLOCK;
B.CLK = CLOCK;
C.CLK = CLOCK;
D.CLK = CLOCK;
E.CLK = CLOCK;
F.CLK = CLOCK;
G.CLK = CLOCK;
H.CLK = CLOCK;
I.CLK = CLOCK;
L.CLK = CLOCK;
                                                        Figure 4-10. 10-Bit Up Counter - SNAP Style
```

Shifter Design Notes


Efficient shifter design is critical to achieve the fastest, most economical PLHS502 sequence recognizers. For ideal shifters, no additional gates should be required if the designer correctly exploits the hard macro flip—flops for the part. Normally, one views a shifter as an input to D, Q to D, Q to D, etc., like circus elephants walking nose to tail. But, the PLHS502 D flip—flop has an embedded NAND gate which, for this type of design, appears to "get in the way".

By recognizing the availability of the $\overline{\Omega}$ output, if it is used instead, the design procedure remains "nose to tail" substituting $\overline{\Omega}$ for Ω into the NAND (using only one input). Should a fancier shifter be required (see the Synchronous Receiver/Transmitter design at the end), the designer may choose to even implement soft macro "merged" shifter flip-flops.

The maximum internal "all shifter" capacity of the PLHS502 is 26 bits, assuming conventional

structure flip–flops. If one were to design a schematic with 26 D flip–flop cells in cascade, SNAP would configure the first 8 from the hard macro Ds, the next 8 from the hard macro S–Rs and the last 10 from the NAND array.

An example illustrating a nonschematic captured 3-bit shifter follows. Figure 4-11 illustrates its' state diagram, Figure 4-12 shows the state equation solution and Figure 4-13 shows the very compact Boolean equation solution.



```
@PINLIST
CLOCKI; QA
              0;
RESETI; QB
              0;
DATA
          I;
               QC
@INPUT VECTORS
          DATA;
          /DATA;
@OUTPUT VECTORS
@STATE VECTORS
          [QA, QB, QC];
          000
               В;
         001
S1
               B;
          010 B;
               B;
          100 B;
          101 B;
110 B;
S5
S6
S7
@TRANSITIONS
WHILE [ ]
IF RESET
          THEN [SO]
WHILE [S0]
          THEN [S4]
IF
     ΙO
          THEN [SO]
WHILE
          [51]
   I1
I0
IF
          THEN [S5]
          THEN [SO]
WHILE [S2]
   I1
TF
          THEN [S5]
          THEN [S1]
WHILE [S3]
IF I1
IF I0
          THEN [S5]
          THEN [S1]
WHILE [S4]
          THEN [S6]
IF
          THEN [S2]
WHILE [S5]
         THEN [S6]
   ΙO
         THEN [S2]
WHILE [S6]
         THEN [S7]
TF
IF
     IO
         THEN [S3]
WHILE [S7]
IF I1
          THEN [S7]
    IO
          THEN [S3]
 Figure 4-12. 3-Bit Shifter -
       State Equations
```

```
@PINLIST
CLOCKI;
DATA
RESETI;
        0;
OA
QB
@LOGIC EQUATIONS
QA.D = DATA;
QB.D = QA;

QC.D = QB;
QA.RST = RESET;
QB.RST = RESET;
QC.RST = RESET;
QA.CLK = CLOCK;
QB/CLK = CLOCK;
QC.CLK = CLOCK;
  Figure 4-13. 3-Bit Shifter -
```

Boolean Solution

August 1989 667

PLHS502 Application Notes Vol. 1

Programmable Logic Devices

ADDITIONAL DESIGN GUIDELINES


The following guideline summary is by no means complete. Rather, it is a list of straightforward substitutions which the designer can make to help guarantee that the design fits. The basic approach is to build the design using the basic building blocks of the architecture. For the PLHS502 this means using NAND gates, D flip-flops and S-R flip-flops. To make this clear, we will enumerate and illustrate good basic design substitutions.

- 1. Use NAND gates whenever possible.
- 2. Use S–R flip–flops for counters over 4 bits long.
- 3. Use D flip-flops (if possible) for the

least significant counter bit.

- If possible eliminate NOR functions by converting to AND with complemented input (use Q on flip—flops and available input complements).
- AND gates which feed NAND gates can be replaced by wider NAND gates (exploit NAND width).
- Eliminate all extra inversions by exploiting input complements and flipflop /Q outputs.
- If you exceed your flip-flop budget of hard flip-flops, put the most complex flip-flop configurations into soft macros (see Section 6). Fold the gating function into the flip-flop.
- 8. Careful output pin assignment can result in a free logic function as the signal

- leaves the device. So, assign complemented, buffered outputs accordingly. Exclusive—OR/parity controlled outputs are slower, so assign them accordingly.
- Build toggle chains out of D flip-flops, then S-R flip-flops, to conserve NAND gates.
- 10.The NAND-feeding D-FF structure may be thought of as an AND-feeding D-FF with Q and Q reversed.
- 11. For very large counters, converting D– FFs to J–K FFs may be appropriate. If necessary, then do so.
- Efficient methods for implementing Exclusive—OR functions are described in PLHS501 Applications Notes Volume 2.



PLHS502 Application Notes Vol. 1

Programmable Logic Devices

ADDITIONAL PLHS502 APPLICATIONS

These examples illustrate various applications the PLHS502 is capable of, which are guite interesting.

Byte Data Pipe

A common system building block is the byte data pipe illustrated in Figure 6–1. This elementary structure illustrates a parallel cascade of octal registers where each tier is independently clocked. Data arrives at the input pins and is clocked in by clock A. After settling, this is clocked into the second tier by clock B, the third tier by clock C and the output tier by clock D.


The two center registers are generated from NAND gate transparent latches comprised of three gates. This classic threegate latch has a static hazard in the ones, but careful timing and masking the input and output logical image to the outside world, with edge triggered registers, essentially eliminates this evidence. This consumes 48 of the 64 gates budget in the PLHS502. The remaining gates may now be used as needed to configure this data path for a more specific applications such as:

a. A distributed decoder as in a RISC pipeline. Each remaining gates can de-

tect 32-bit internal state combinations (expanded to 40 bits if simultaneous examination of the input pins is desired).

- A 4-byte queue for interprocessor and processor to bus communications and synchronization.
- c. A 3-, 4-, or 5-byte sequence detector for byte oriented protocols.

Clearly, one of the internal register tiers could be freed up or the arrangement altered to have a three position data pipe and a group of S–R registers to implement a bus handshaker or internal counters for a queue pointer, etc.



Custom CAMS


Another common block used in memory and I/O systems today is the content addressable memory (CAM), illustrated in Figure 6-2. These are used for associative searching and often implement the TAG structure or VALID bit structure for the translation lookaside buffer in a cache system. CAMs more closely resemble a small register array where each cell has an independent data compare operation with a global polling mechanism. This example illustrates the PLHS502's ability to realize a small, relatively fast 4X4 CAM. In this example, the 16 register cells are made with the D flip-flop and the S-R flip-flops configured as Ds. Each flipflop output is compared to a corresponding data input with a coincidence function which is

generated from three NANDs. Groups of four comparators are then ANDed together to generate the HIT signals indicating the presence of a 4-bit item. If speed and gate economy are required, the composite compare function can be generated, exploiting wide gates rather than deep cascades.

The CAM operation is simple. The CAM must first be loaded, with four bits in each tier. Loading was chosen to be 4-bit parallel with independent clocking. This allows "one transaction" replacement and is the most flexible approach for implementing arbitrary updating policies. Once it is loaded, the 4-bit data is applied on the same lines (this could easily be changed to four different lines). When a value is applied, a

"HIT" is generated if the current value matches one of the stored 4-bit items. How the "HIT" is used by the outside system is system dependent. If a value is applied and there is no "HIT," there is no response. Again, there are a number of remaining internal NAND gates as well as most of the gates tied to the I/O pins to perform additional tasks and adapt the behavior of this building block.

This is a very efficient structure to implement a direct mapped cache, where four 1—megaword regions could create the logical image of a 16—megaword region. The time from valid address to valid "HIT" is about 20 nanoseconds—max.



System Scoreboard


High digital system throughput may be achieved by allowing high-speed processors to run independently at their own rate. Hence, operation speed is only limited when data or function dependencies occur. This requires a special sort of synchronization mechanism to allow independent processes to realign when necessary. A classic solution to this is the Scoreboard concept, illustrated in Figure 6–3. In essence, this is an overall system register with independent status bits assigned to specific functional units and data registers. The idea is an old one, but has recently resurfaced since modern RISC designers have begun resurrecting highly parallel CISC architectured artifacts.

The concept is valid for a computer system where resources are all viewed as independent processors

Basically, one bit in the Scoreboard is assigned to each distinct functional unit or independent data register. When a request (from anywhere) arrives for that unit, it is assigned unless the unit is busy. This locks out future assignment until that resource is released. For an elementary Scoreboard, the basic requirement is independent registers cells (i.e., must be able to request, assign and release each one, essentially asynchronously). Figure 6–5 shows an implementation of a 9–element Scoreboard. This requires 27 inputs and 9 outputs (using cell

version 1) and leaves 5 bi–directional lines, 7 outputs and most of the foldback NANDs. A global reset may be added by logically ORing each release signal with a global reset through the NAND function tied to each flip–flop. This design uses the 8 D flip–flops and one S–R flip–flop per status sentinel. This leaves 7 flip–flops to implement additional functions as well.

Input pins can be freed up if an external clock is assigned to all of the allocate signals and each request is gated with the flip-flops current status (cell version 2). The rendition using cell version 2 still permits independent release of each cell



Synchronous Receiver/ Transmitter

This system building block is an elementary synchronous receiver and transmitter. This example will illustrate multiple independent state machine designs as well as some standard design techniques to utilize every available function component out of the PLHS502. Figure 6-4 shows the elementary structure of the synchronous serial communication device. Basically, it is two independent machines where each half is comprised of a counter and shifter. Figure 6-5 depicts the high-level schematic of Figure 6-4. The transmitter must load a byte in parallel and ship the contents out serially. The receiver must receive serial data and indicate the presence of a correctly framed byte. From partitioning considerations, the counters will be be generated from the internal S-R flip-flops. The shifters can be made from the internal D flip-flops but the requirement is for at least 16 D flip-flops — which means at least 8 must be constructed from NANDs. Intuitively, it would be best to exploit the free NAND on the hard macro D flip-flops to construct a simple MUX for each D-cell as shown in Figure 6-6a. This would use 16 NANDs. Then, the receive register could be constructed from an octal cascade of flip-flops constructed from six NANDs each (Figure 6-6b). This would use 48 NAND gates and expend the rest of foldback array. This would create a problem to complete the design


of the byte counters because they each require four gates to construct the drive terms for the S-R flip-flops. An old gate array trick is very appropriate here. Figure 6-6c shows a 2-input multiplexor driving a 6-gate D flip-flop. By logical merging and exploiting the width and nesting depth of PML, one can get the entire function realized by the final cell version of Figure 6-6d, which takes only seven gates to do the entire cell. Hence, making the transmitter from 56 NANDs (8 copies of the 7-gate cell) gives 8 left over foldback NANDs for the generation of two 3-bit counters. It should be noted that this is a faster solution because the D signal passes through as many gates as without the multiplexor. Two levels of time delay are achieved instantaneously, as shown in Figure 6-6, T1 = T3 which is less than T2. The receive register is simply constructed from the hard macro D flip-flops in direct cascade. This leaves many remaining input and output pins which can be used elsewhere (i.e., fast I/O decode and such) for other system needs. One obvious addition would be to implement decode of specific characters from the receive buffer using the many remaining output pins.


Figure 6–7 shows the schematic of one of the 3–bit counter modules which permit byte framing in the receiver and transmitter. Figure 6–8 through 6–10 detail the exact schematics


used to complete the receiver/transmitter ("RECTRAN") design.


Figure 6–11 shows the SNAP simulation of the 7–gate composite cell alternately loading and shifting. In Figure 6–11, the text shown at the top is the Simulation Control File which constitutes the stimuli vectors for the simulation. The waveform below depicts the stimuli and corresponding response vectors. Incidentally, the two remaining S–R flip–flops can be used for anything, but one can signal a data available condition to the outside world for the receiver and the other can indicate Busy or Done for the transmitter to reflect some status to the outside world.


A complete series of simulation is presented in Figures 6-12 through 6-15. The simulation control file depicted in Figure 6-16 performs the operations whose result waveforms are shown in Figures 6-13 through 6-15. Figure 6-17 shows the SNAP macro netlist which binds the smaller pieces of the overall design together. Figure 6-18 provides the netlist which constitutes the receiver piece of RECTRAN while Figure 6-19 gives the same for the transmitter. Expanding the hierarchy, Figure 6-20 displays the exact netlist for the "flopcell" and Figure 6-21 shows how the netlist for one of the three bit counters appears. The entire RECTRAN design was captured schematically using OrCAD/ SDT





























```
S 1(20,40,1000) RESETR
S 0(50,100,ETC)CLKR
S 0(100,150,300,350,500,550,700,750)SDIN
S 1(20,40,1000)resetT
S 0(50,100,etc)clkT
 S 0(45,70,1025,1050)lodshf
S 0(1000)pdin1,pdin2,pdin5,pdin6
 S 1(100)pdin3,pdin4,pdin7,pdin8
S 0(20)CLR
* S 1(2000) VCC
p resetT, clKT, lodshf, pdin1, pdin2, pdin3, pdin4, pfin5, pdin6
# ,pdin7,pdin8,qprev,sdout,SDIN,RESETR,CLKR,PDOUT1,
# PDOUT2, PDOUT3, PDOUT4, PDOUT5, PDOUT6, PDOUT7, PDOUT8,
# Q1,Q2,Q3,Q4,Q5,Q6
PCO
sutime=2000
                                      Figure 6-16. RECTRAN.SCL Text
```

```
Output of Netgene
                                           Version 1.0
* Date: 5/ 3/1989
                                          Time: 18:36:25 *
***********
* Input File Name : RECTRAN.EDF
* Netlist File : RECTRAN.MAC
MACRO
Z RECTRAN_SCH I (CLKR, CLKT, CLR, LODSHF, PDIN1, PDIN2, PDIN3, PDIN4,
# PDIN5, PDIN6, PDIN7, PDIN8, QPREV, RESETR, RESETT, SDIN) O (PDOUT1,
# PDOUT2, PDOUT3, PDOUT4, PDOUT5, PDOUT6, PDOUT7, PDOUT8, Q1, Q2,
# Q3,Q4,Q5,Q6,SDOUT)
CELL REC 0 0 REC I (CLKR, RESETR, SDIN) O (PDOUT1, PDOUT2, PDOUT3,
# PDOUT4, PDOUT5, PDOUT6, PDOUT7, PDOUT8)
BLK01 TRANS I (CLKT, LODSHF, PDIN1, PDIN2, PDIN3, PDIN4, PDIN5,
# PDIN6, PDIN7, PDIN8, QPREV, RESETT) O(SDOUT)
BLK02 COUNTER3 I (CLKR, CLR) O (Q1, Q2, Q3)
BLK03 COUTNER3 I(CLKT, CLR) O(Q4,Q5,Q6)
MEND
                                 Figure 6-17. High-Level RECTRAN Macro File
```

```
* Date: 5/ 2/1989
************
* Input File Name : REC.EDF
* Netlist File : REC.MAC
MACRO
Z REC SCH I (CLOCKR, RESETR, SDOUTR) O (PDOUT1, PDOUT2, PDOUT3,
# PDOUT4, PDOUT5, PDOUT6, PDOUT7, PDOUT8)
Ul DFFR I(SDOUTR, CLOCKR, RESETR) O(PDOUT1, DMO1)
U2 DFFR I (PDOUT1, CLOCKR, RESETR) O (PDOUT2, DMO2)
U3 DFFR I (PDOUT2, CLOCKR, RESETR) O (PDOUT3, DMO3)
U4 DFFR I (PDOUT3, CLOCKR, RESETR) O (PDOUT4, DMO4)
U5 DFFR I (PDOUT7, CLOCKR, RESETR) O (PDOUT8, DMO5)
U6 DFFR I (PDOUT6, CLOCKR, RESETR) O (PDOUT7, DMO6)
U7 DFFR I (PDOUT5, CLOCKR, RESETR) O (PDOUT6, DMO7)
U8 DFFR I (PDOUT4, CLOCKR, RESETR) O (PDOUT5, DMO8)
MEND
                                     Figure 6-18. Receiver Macro File
```

```
Output of Netgene
                                 Version 1.0
                                  Time: 13:37:13 *
* Date: 1/ 5/1989
**********
* Input File Name : TRANS.EDF
, Netlist File
                   TRANS.MAC
MACRO
Z TRANS SCH I (CLOCK, LODSHF, PDIN1, PDIN2, PDIN3, PDIN4, PDIN5,
# PDIN6, PDIN7, PDIN8, QPREV, RESET) O(SDOUT)
U1 IN I(LODSHF) O(SN01)
U2 NIN I(LODSHF) O(SN09)
BLK01 FLOPCELL I(CLOCK, PDIN1, SN01, QPREV, RESET, SN09) O(SN02,
# DM01)
BLK02 FLOPCELL I(CLOCK, PDIN2, SN01, SN02, RESET, SN09) O(SN03,
BLK03 FLOPCELL I(CLOCK, PDIN3, SN01, SN03, RESET, SN09) O(SN04,
BLK04 FLOPCELL I(CLOCK, PDIN4, SN01, SN04, RESET, SN09) O(SN05,
BLK05 FLOPCELL I(CLOCK, PDIN8, SN01, SN08, RESET, SN09) O(SDOUT,
BLK06 FLOPCELL I (CLOCK, PDIN7, SN01, SN07, RESET, SN09) O(SN08,
BLK07 FLOPCELL I(CLOCK, PDIN6, SN01, SN06, RESET, SN09) O(SN07,
BLK08 FLOPCELL I (CLOCK, PDIN5, SN01, SN05, RESET, SN09) O (SN06,
# DM08)
MEND
                          Figure 6-19. Transmitter Macro File
```

August 1989 686

```
***********
        Output of Netgene
                             Version 1.0
* Date: 1/ 5/1989
                               Time: 13:34:36 *
**********
* Input File Name : FLOPCELL.EDF
* Netlist File
            : FLOPCELL.MAC
**********
MACRO
Z FLOPCELL SCH I (CLOCK, DATIN, LOAD, QPREV, RESET, SHIFT) O (Q,
# QN)
U1 NA3 I(SN05, SN01, SN03) O(SN02)
U2 NA3 I (SN02, RESET, CLOCK) O (SN03)
U3 NA4 I(SN03, CLOCK, SN05, SN01) O(SN04)
U4 NA4 I (RESET, SN04, LOAD, DATIN) O(SN05)
U5 NA4 I (RESET, SNO4, SHIFT, QPREV) O(SNO1)
U6 NA2 I(SN03,QN) O(Q)
U7 NA3 I(Q, RESET, SN04) O(QN)
MEND
                          Figure 6-20. Flopcell Macro File
```

```
***********
        Output of Netgene
                              Version 1.0 *
                               Time: 13:42:14 *
* Date: 1/ 5/1989
**********
* Input File Name : COUNTER3.EDF
* Netlist File : COUNTER3.MAC
***********
MACRO
Z COUNTER3 SCH I (CLOCK, CLR) O (Q1, Q2, Q3)
U1 NA3 I(SN03,Q2,Q3) O(SN01)
U2 NA3 I(Q1,Q2,Q3) O(SN04)
U3 NA2 I(SN09,Q3) O(SN06)
U4 NA2 I(Q2,Q3) O(SN10)
U5 INV I(SN01) O(SN02)
U6 INV I(SNO4) O(SNO5)
U7 INV I(SNO6) O(SNO7)
U8 INV I(SN10) O(SN08)
U9 INV I(Q3) O(SN11)
U10 INV I(SN12) O(SN13)
Ull SRFF I(SNO2, SNO5, CLOCK, CLR) O(Q1, SNO3)
U12 SRFF I(SN07, SN08, CLOCK, CLR) O(Q2, SN09)
U13 SRFF I(SN11, SN13, CLOCK, CLR) O(Q3, SN12)
MEND
                        Figure 6-21. 3-Bit Counter Macro File
```

Signetics


PLHS502 Application Notes Vol. 1

Programmable Logic Devices

ADVANCED FLIP-FLOP MERGING

Folding logic functions directly into the workings of a flip—flop has a unique pay—off with PML. (As illustrated in Sections 4 and 6). Since the basic approach may be extended to other flip—flop structures, this technique may be used more "generally". The figures provided in this section illustrate examples of simple and complicated structures.


Consider the D-latch in Figure 7-1:




If the data input point is driven from a twolevel logic function as shown in Figure 7–2(a), the gate count is six with one inverter. The input signals pass through two logic layers before entering the latch, then through two more to reach the Q output.

From Figure 7-2(a), note that the data input to gate G4 is driven High from the G3 output when either G1 or G2 (or both) is driven Low. Also, note that when Data is High, and Enable is High, the output of G4 will be Low. Under these conditions, the outputs of G1 or G2 are driven in a direction similar to the output of G3 and G4. By eliminating G3 and G4 and substituting G1 and G2 where G4 was, some gate and speed saving is gained as shown in Figure 7-2(b). Note that the Enable signal has to be reinserted carefully. This permits a faster, cheaper, and more efficient merged latch. This is the simplest structure and the reader is encouraged to prove the operation by simulation or construction. The general approach is a simple expansion of these steps.

- Isolate the positive asserted flip-flop input.
- 2. Isolate the two-level AND/OR driving function.
- 3. Eliminate the NAND gate in step 1 but preserve inputs and outputs.
- Eliminate the second-level NAND from step 2, but preserve inputs in the step 2 AND/OR structure.
- Place the corresponding intermediate outputs to replace the eliminated flip flop input gates output.
- Place any inputs which fed the flipflop input gate onto the new input points from step 5 (i.e., the input points of the step 2 AND/OR structure)



Let's illustrate the procedure by applying it to a more complicated flip—flop — the dreaded J—K! Figure 7—3 depicts a J—K with a two—level logic function tied to J and a different function tied to K. J gets the sum of three product terms and K gets the sum of two.



Because the inputs to gates A, B, C, D, E will be maintained, we don't care what they are. From the recipe:

Step 1. Isolate the positive asserted flip-flop


For J this is gate G2. For K this is gate G3

Step 2. Isolate the two-level AND/OR driving function.

(see function 1 and 2)

Step 3. Eliminate the NAND inputs in step 1 but preserve inputs and outputs. (Figure 7–4(a))

Step 4. Eliminate the second–level NAND from step 2. (Figure 7–4(a))



It is hoped that the reader can, in general, avoid the use of the J-K structures built from gates as shown due to their inefficiency of gate usage. There is also a potential timing liability

in that the clock path G1 to GA is faster than the data input paths and creates a possible race. However, this example serves to illustrate that

a merging process can be applied systematically, with success, to even relatively complicated structures.

Signetics

Programmable Logic Design and Application Notes

Programmable Logic Devices

Today's engineer is constantly striving to consolidate higher complexity and more feature—intensive circuits into designs without sacrificing flexibility. In a competitive marketplace, designs need to be brought to market quickly. The Signetics solution is to provide high—performance Programmable Logic Devices (PLDs) that can be quickly and easily integrated into system designs.

In using this manual, some familiarity with PLDs is helpful. In addition, we recommend the recently published text books, Programmable Logic Devices, by Geoff Bostock (McGraw-Hill, copyright 1988), and Programmable Designer's Guide by Roger Alford (Howard W. Sams & Co., copyright 1989).

This document provides complete, straightforward application examples. The first three sections describe Signetics PLDs. Sections four through eight provide application examples. Most applications are accompanied by one or two pages of text. Some also include a circuit or block diagram and an AMAZE design file listing to implement that application. To save time, the files are available on diskette or by accessing the Signetics toll-free bulletin board: (800) 451–6644.

ACKNOWLEDGEMENTS

In appreciation for their contributions:

Dimitrious Douros Mike Gershowitz Ali Gheissari Jim Green Neil Kellet Jerry Liebler Bob Lundeberg John McNalley Tony Parisi

AMAZE SOFTWARE

Design, simulation and device-programming support for all Signetics PLD families is provided by Signetics AMAZE PLD design software. AMAZE, which supports many of Signetics programmable products, includes Boolean logic and direct state-equation entry. Functional and AC timing simulation models and an automatic test vector generator are included in the AMAZE PLD design package. The software runs with MS-DOS 2.0 or newer operating systems and is available free of charge to qualified users. Schematic capture capability is available in conjunction with Data I/O's FutureNet Dash System and the OrCad Systems Corporation OrCAD/SDTTM schematic capture software packages.

The Signetics families of PLDs are also supported by Data I/O®'s design software package, ABEL™, and the P-CAD and CUPL™ design software.

Automatic Map and Zap Equation Entry (AMAZE) software designed by Signetics will interface with most commercial programmers.

AMAZE consists of five modules:

- BLAST (Boolean Logic and State Transfer entry program)
- PTE (Program Table Editor)
- PTP (PAL to PLD conversion program)
- DPI (Device Programmer Interface program)
- PLD SIM (PLD Simulator program)

The software modules allow expansion for future requirements. They are user friendly with both HELP and ERROR messages. Simulator programs provide applications assistance and automatic test vector generation.

Equipment requirements, products supported and details of product modules are contained in the AMAZE design software manual. AMAZE is available at no charge by request to the Signetics factory.

Additional design support is usually available with the commercially available packages ABEL, CUPL PLDesigner, LOG/iC, etc. Programming support is always available through DATA I/O, STAG Microsystems, and several other programmers.

PRODUCT SECTION INTRODUCTION

Signetics manufactures a wide range of PLDs and Programmable Logic Sequencers. In the area of PLDs, there are two basic architectures: Programmable Logic Arrays (PLAs) and Programmable Array Logic (PAL[®]).

The PLA architecture consists of two interconnectable arrays with programmable connections between the input pins and a group of AND gates. Another programmable array exists between the AND gate outputs and the inputs to a group of OR—gates. Complete freedom of interconnection is possible with this arrangement.

PAL-type devices, on the other hand, provide programmable interconnection between the input pins and the AND gates, but the outputs of the AND gates are tied to specific OR gates, then finally routed to output pins. By eliminating the programmability between the AND—OR area, some speed savings are achieved at the expense of interconnect freedom.

Signetics Programmable Logic Sequencers combine the versatility of the PLA with flip-flops to achieve powerful state machines in a variety of user configurations.

This section is designed to familiarize design engineers with the Signetics lines of PLAs, PALs, and Sequencers available, and acquaint them with their general capabilities and features. Each architecture is briefly showcased in an initial rendering with a short capsule description of the part. The serious reader should consult the data sheet sections of this PLD Data Handbook for full electrical details on any part

Signetics

Programmable Logic Devices

PLA DEVICES

Signetics PLAs are particularly useful in the design of wide address decoders and random logic replacement. The primary advantage Signetics brings to these applications with their PLA devices is product term sharing, which is made possible via the two programmable arrays. The familiar PAL architecture supports a programmable AND array, followed by a fixed OR array. Better than 90% of the PAL devices that are available today are limited to 7 input wide gates. When pursuing a solution to a complex address decoding scheme, this restriction is prohibitive. The Signetics PLA devices support 100% of all product terms. Once a term is created, it can be shared with any or all of the output functions. No duplication of resources is incurred. The popular PLXX153 family support 32-input wide OR gates which are ideal for memory I/O decoders. The addition of programmable output polarity also enhances design efficiency and logic minimization.

The 2 programmable array concept dominates the Signetics PLD product line. With the exception of the PAL—type devices which have been geared for ulitmate performance, all Signetics PLDs have been architected with efficient and flexible PLA structures. With the largest breadth programmable product line in the industry, Signetics believes the designer can truly fill his requirements from the several product lines—PLA, PAL, and PLS. PLA device descriptions follow.

Signetics PLUS153D

Figure 1-1 depicts the Signetics PLUS153D. This bipolar PLA is pin and functionally equivalent to all other

Programmable Logic Design and Application Notes

Signetics 153 type PLAs (i.e., the PLS153, PLC153, PLHS153), but requires no more than 12 nanoseconds to generate a stable output.

The PLUS153D has eight dedicated inputs and 10 bidirectional pins. The bidirectional pins may be adapted to suit the user's specific needs. 20—pin DIP or PLCC packages are available.

The output structure of the PLUS153D includes programmable polarity control on each output. Either active HIGH (non-inverting) or active LOW (inverting) outputs are configurable via the EX-OR gate associated with each I/O. Individual 3—State control of the I/O is also supported with the ten direction control AND terms (D1-D9).

Other benefits to the PLUS153D include full pin compatibility with most 20-pin combinational PAL® parts. The natural product term sharing capabilities of the PLA architecture yield complete freedom of configuration should the engineer implement a particularly creative decode configuration.

Signetics PLUS173D

Figure 1-2 depicts the Signetics PLUS173D. This bipolar PLA is functionally equivalent to the Signetics PLS173. The 24—pin PLUS173 has four more input pins than the PLUS153. The user may adapt the bidirectional pins to suit particular decoding needs, but the propagation delay time is still no more than 12 nanoseconds from stabilized input to stable output.

By having more inputs than the 153 part, the 173 can either resolve more input lines or generate more outputs functions for the same number of inputs. Distinct 3—State control over each output may be useful for controlling chip enables where contention (i.e., multiple access) may exist.

For speed and input width, the PLUS173D is probably the best single PLA available today for both memory and I/O decoding. Combining the 12 nanosecond tpD with the distinguishable range of 12 to 21 inputs, the designer can easily decode say 16 input addresses as well as read/write qualifiers or encoded status signals. Output polarity control (active—High or active—Low) is achieved by programming the Exclusive—OR gate associated with each output.


The flexibility achieved with a PLA structure can be quickly appreciated by the designer who has experienced the frustration of the dedicated "OR" structures in PAL ICs. Currently, the only time penalty for the freedom granted by a PLA is a few nanoseconds!


The PLHS473


The PLHS473 devices are 24—pin PLAs. Each has 24 product terms, 11 inputs, 9 bidirectional pins and 2 dedicated outputs. Each output and bidirectional pin is independently tri—stateable from the OR array.

Unlike the traditional PLA, the 3–State control of the 473 devices is accomplished with an OR function. This feature supports more complex (sum of products) logical control of the outputs. Output polarity is programmable (active–High or Low) via the 11 EX–OR gates that precede the output pins.

The PLHS473 is TTL compatible, with a worst-case propagation of 22ns.







Signetics

Programmable Logic Design and Application Notes

Programmable Logic Devices

PAL®-TYPE DEVICES

Signetics provides state-of-the-art industry standard PAL devices, both bipolar and CMOS. The range of offers spans the entire gamut of performance options; zerostandby power generic devices specified over the commercial, industrial and military temperature ranges, or the ultimate in high speed, an ECL compatible 20EV8 device. Almost every option in between is also offered.

The PAL architecture consists of a programmable AND array, followed by a fixed OR array. The somewhat rigid architecture lends itself to less complex, narrower logic functions. There are three basic PAL-type device configurations. The XXL8 devices are strictly combinatorial. The XXRX series offers a range of registered and combinatorial outputs.

The XXV8 series is considered to be generic in nature, in that the output macros are variable (hence the "V") as combinatorial or registered. Most frequent applications include counters and shifters (the RX series), and small decoders and multiplexers (the L8 series).

Industry standard software can be used with Signetics PAL-type devices. Full support is also provided via the Signetics AMAZE Design software.


The Signetics PAL-type device descriptions follow. The line is being expanded continuously. If you don't find the device you need for your circuit, please contact Signetics toll-free at (800)227-1817, Extension 900.

Signetics PLHS18P8B

Figure 2–1 depicts the Signetics PLHS18P8B which is a bipolar, PAL–type device. The propagation delay time will be 15 nanoseconds maximum from stable inputs to stable outputs. The part has 10 inputs, eight bidirectional pins, and 72 product terms. Due to the programmable output polarity, the PLHS18P8B can functionally replace 13 other standard PAL devices. Being pin compatible to all 20–pin combinational PALs increases the parts' versatility considerably. The PLHS18P8B can sink $I_{OL} = 24$ mA (max).

Output polarity control for this PAL-type part is achieved identically to the procedure for the PLUS153D and PLUS173D.


The PLHS18P8B is ideal for address and I/O decode for moderately fast micro-processors from both a speed and current drive capability.



The PLUS16L8D and -7

The PLUS16L8D and –7 PAL–type devices are functionally identical to other commercially available 16L8 PAL ICs. Figure 2–2 shows an extremely simplified version. Less flexible than a PLA, the PLUS16L8D/–7 provides raw speed and current drive so important for driving SRAM arrays on RISC processors or the control/data lines on rapid bus structures. The PLUS16L8D has a worst–case propagation delay of 10ns. The worst–case T_{PD} of the –7 is 7.5ns. 24mA output drive is guaranteed.


The PLUS16L8D/-7 have seven product terms per OR function and one per 3–State control. Six of the eight outputs can be configured as inputs or outputs. The PLUS16L8D/-7 are available in 20–pin plastic DIL or 20–pin PLCC packages.



The PLUS16R8D and -7

The PLUS16R8D and -7, like the PLUS16L8D and -7 is identical to other manufacturers' registered PAL devices. The parts have eight inputs, eight outputs, and eight D-flip-flops. Each flip-flop feeds an output pin through a 3–State buffer. The output of each D-flip-flop, \overline{Q} , is also fed back to the AND array. Each output is capable of driving 24mA I_{OL} max, with all ouputs simultaneously asserted.

The PLUS16R8D has a worst–case propagation delay of 10ns. The worst–case t_{PD} of the -7 is 7.5ns. The PLUS16R8D and -7 are available in 20–pin plastic DIP and 20–pin PLCC.





The PLUS20L8D and -7

The PLUS20L8D and -7 devices have 14 inputs, two dedicated outputs and six bidirectionals. The $t_{\rm PD}$ are 10ns max and 7.5ns max, respectively. The 24mA of output low current of these devices can drive capacitive address line inputs and pc—board traces through long layouts. This makes the particularly suitable for driving SRAM, video DRAM, and FAST dynamic RAM arrays in 32-bit microprocessor environments.

Identical to other commercially available 20L8 PAL devices, the PLUS20L8D and -7 have 56 functional product terms which are hard-wired to eight OR gates. Each OR gate drives an Active-Low output. The tri-state control of each output is from a dedicated AND product term

The worst-case propagation delays for the PLUS20L8D and 20L8-7 are 10ns and 7.5ns, respectively.





The PLUS20R8D and -7

The PLUS20R8D and —7 are 24—pin versions of the 16R8 PAL device. With propagation delays of 10ns and 7.5ns max, the parts deliver 24mA of output low current drive. Eight D—flipflops share a common clock and output enable line. The output of each flip-flop is dedicated to a separate output pin and is also fed back to the AND array.


The PLUS20R8D and -7 are available in 24-pin plastic DIL and 28-pin PLCC.

The PLC18V8Z

The PLC18V8Z is a multi-function, generic PAL—type device. It is pin—compatible with, and can replace 22 different 20—pin registered and combinatorial PAL devices. To accomplish this, the conventional 'single function' output pin has been replaced by a configurable Output Macro Cell. Each Macro Cell contains a D—flip-flop or a combinatorial I/O path. Output polarity and tri—state control functions are also individually configurable. Each OMC is fed by nine AND

product terms, which are hard-wired in the classic PAL fashion.

One of the key features of the part is its ability to sink 24 milliamps I_{OL}, compatible with other bipolar PAL devices—yet still comply with internal CMOS circuitry. The UV erasable version is available in 20–pin ceramic DIL with a quartz window.



Signetics

Programmable Logic Design and Application Notes

Programmable Logic Devices

SEQUENCER DEVICES

Introduction

Ten years ago, in their search for a straightforward solution to complex sequential problems, Signetics originated Programmable Logic Sequencers. Signetics Programmable Sequencers represent a product line which combines the versatility of two programmable arrays (PLA concept) with flip-flops, to achieve powerful state machine architectures.

Each arrangement or "architecture" offers a variation of the basic concept which combines two programmable logic arrays with some flip-flops, in an undedicated fashion. The PLA product terms are <u>not</u> specifically dedicated to any particular flip-flop. All, none, or any mix in between may be connected to any flip-flop the designer chooses. The PLA structure therefore supports 100% product termsharing as well as very wide OR functions preceding the flip-flops.


Signetics line of Programmable Logic Sequencers has been further customized to accommodate specific types of state machine designs. Some have both registered and combinatorial outputs, specifically for synchronous and asynchronous Moore–type state machines. Others have state or buried registers, as well as output registers. These devices (PLUS105, PLC42VA12 and PLUS405) are ideal for synchronous Mealy–type applications.

J–K and S–R register functions are another benefit. The logic functions provided by these types of registers far exceed the capability of a D–type register. The functionality of the J–K allows the designer to optimize the logic used in generating state transitions. Ninety percent of PAL devices have D–type registers. All the sequencers are equipped with three state options for bussing operations, JK or SR flip-flops and some form of register Preset/Reset functions

Finally, all PLS devices have a Transition Complement Array. This asynchronous feedback path, from the OR array to the AND array, generates "complement" transition functions using a single term. Virtually hidden in between the AND array and the OR array is the Complement Array. This single NOR gate is not necessarily "an array," however the inputs and outputs of this complement gate span the entire AND array. The input(s) to the Complement Array can be any of the product terms from the AND array. The output of the Complement Array will be the 'complement' of the product term input. If several product terms are connected to the Complement Array, their respective complements can also be generated. The output of the Complement Array is fed back to the AND array, whereby it can be logically gated through another AND gate and finally propagated to the OR array. The significance being that the complement

state of several product terms can be generated using one additional AND product term. For example, if an efficient method of sensing that no inputs were asserted was needed, the designer could connect the output of appropriate AND gates to the complement NOR gate. The output of the NOR gate could then be used to condition and then set or reset a flip-flop accordingly. As well, he could detect a particular state variable combination and force a transition to a new state, independent of the inputs. Or he could combine input signals and state (AND) terms to generate a new composite term. In any of these applications, the Complement Array greatly reduces the number of state transition terms required.

In order to present the material in the most concise fashion, a brief state equation tutorial is presented first. The PLUS105 description immediately follows. In this capsule description, the level of detail is expanded, so read it first for basic understanding. Each additional presentation will be done with regard to the fundamentals described for the PLUS105. Figure 3-3 shows the detailed drawing of the PLUS105 in full detail. Figure 3-4 shows a compressed rendition of the same diagram so that the reader can understand the diagram notation. The compressed shorthand version will be used for the rest of the sequencers.



While	[STATE IF IF		THEN THEN	[STATE 1] [STATE 3]	
While	[STATE	1]			
	IF	[U]	THEN	[STATE 2]	
	IF	[/D]	THEN	[STATE 0]	
While	[STATE	2]			
	IF	[U]	THEN	[STATE 3]	
	IF	[/D]	THEN	[STATE 1]	
When	[STATE	3]			
	IF	[U]	THEN	[STATE 0]	
	IF	[/D]	THEN	[STATE 2]	

State Equation Tutorial

STATE equation entry is a convenient way to describe elementary sequential machines in a manner which is directly related to a state diagram of the machine. The basic commands are few, but can be combined in a powerful fashion. Figure 3-1 shows a 4 state up—down counter for a machine with an U(up)/D(down) input line. Figure 3-2 shows the state equation syntax to implement Figure 3-1.

The basic meaning can be summarized in the following way. Simply, "while in state X" if input "Y" occurs, "transverse to state Z". This is a Moore machine model. Mealy may be accommodated by addition of the "with" operation which designates an output variable being associated as shown below:

A.) While [CURRENT STATE]
with [OUTPUT VARIABLE]
IF [INPUT VARIABLE]
then [NEXT STATE]

10

B.) While [CURRENT STATE]

IF [INPUT VARIABLE]
then [NEXT STATE]
with [OUTPUT VARIABLE]


If a latched output variable is desired, the addition of a prime notion (/) to the right of the output variable is required.


The designer must assign the binary values of choice to specific states for a state equation function to be implemented. The Signetics AMAZE manual details state equation solutions with more examples, but the advantage of state equations is that the designer can be less involved with the internal structure of the sequencer than required by other methods.

The PLUS105

This part (Figure 3-3) has sixteen logic inputs and eight outputs. It also has eight S-R flipflops tied directly to those output pins through 3-State buffers (common control from pin 19). The user may select pin 19 to be an Output Enable signal or an asynchronous preset (PR) signal which is common to all flip-flops. Embedded into the device are 48 AND gates. All flip-flops are S-R type with an OR gate on both S and R. The designer may choose any number of product terms and connect them with any OR gate. The product terms can also be shared across any OR gate, as needed. Six of the 14 flip-flops are termed "buried registers" as their outputs are fed back to the AND array, regenerating both the Q and /Q state variables. There is no direct connection to an output. Both the input signals and the state variables Q and /Q are fed to the AND array through buffers which provided the TRUE (or noninverted) and Complement (inverted) renditions of the variable. This is critical for the efficient use of the AND array. The designer has all state and input variables necessary to generate any state transition signal to set and/or reset commands to the flip-flops. Because of this AND/OR arrangement, combined with complete freedom of configuration, all sequential design optimization methods are applicable.

There are many other feature capabilities suitable for creative usage. For example, it is common practice to use the 48 product terms with the 6-bit buried register, treating the output 8-bit register as an intermediate, loadable data register only. This provides a very good bus "pipeline" for the internal 6-bit machine. However, other logic options can be accomplished by combining internal state information (present state) with current input information, generating a next state which is different from the current internal state.






The PLS155, 157, and 159A constitute a three part family of 20—pin sequencers that are well suited for high speed handshakers, counters, shift registers, pattern detectors and sequence generators. Additional applications include testability enhancement, demonstrated in the application examples of signature analysis and pseudo random number generation. The three devices are very similar in architecture. All have a total of 12 possible outputs. The difference is the ratio of combinational I/O to registered outputs available.

The PLS155

The PLS155 is a sequencer providing four J–K flip-flops with a PLA having 32 logic product terms and 13 control product terms. Eight combinational I/O are available in addition to the

four registered outputs. All of the state variables and combinational variables are presented to the output pins by way of 3-State inverting buffers. The combinational and state variable outputs are fully connected (fed back) back to the AND array in both the True and Complemented form of the variable. The product includes a special feature that allows the user to configure the flip-flops as either J-K or D flip-flops on an individual basis. A Register Preload feature is supported via two product terms (La, Lb) which permit "back loading" of data into the flip-flops, directly from the output pins. The part can now be easily forced into any known state by enabling La, Lb, applying data at the outputs (previously "3-Stated"), and applying a clock pulse. Register Preset and Reset functions are controlled in 2 banks of 2 registers each. Note that control product terms are from the OR array.

The outputs of all variables are 3–State controlled by a unique partition. Pin 11 provides an Output Enable input (OE) which can be asserted with the EA and EB control product terms. EA controls the flip-flops F0 and F1, and EB controls F2 and F3. Each combinational output term has a distinct 3–State control term (D0 – D7) originating from the AND array of the PLA. Each combinational output variable can be programmed as inverting (active LOW) or non–inverting (active HIGH) by way of the output polarity EX–OR gate associated with each I/O pin.




The PLS157

This sequencer features all the attributes of the aforementioned PLS155, however, two flipflops have been added, at the expense of two of the combinational outputs. Pins 13 and 18 on the PLS157 are flip-flop driven, where the same pins on the PLS155 are combinatorial, driven from the PLA. Again, all variables (input, output, or state variables) fully connect over the PLA portion with both True and complemented

versions supplied. The number of product terms, the Complement array, Output Enable, 3–State configurations, Register Preload, etc., track the PLS155 part. As with the PLS155, distinct clock input on pin 1 is provided for synchronous operation. Register Preset and Reset are available in 2 banks. Pin F_4 and F_5 are controlled from the AND array (Product Terms P_B and R_B). The remaining 4 registers, F_0-F_3 , are controlled by the sum terms (from

the OR array) PA and RA.

Designs requiring more than 16 states but less than or equal to 64 states are solid candidates for realization with the PLS157. It can be configured as a Moore machine for counter and shifter designs from the flip-flop outputs, or as high speed pulse generators or sequence detectors with the combinational outputs. Mixed solutions are also possible.




The PLS159A

By extending the PLS157 arrangement even further, the PLS159A can be derived. Again, maintaining identical input, product terms, Complement array and similar 3–State partitioning, the PLS159A also resides in a 20–pin package. The expansion to dual 4–bit banks of flip-flops, at the expense of 2 combinational

outputs, enhances the number of available internal states while maintaining product term and pin compatibility. Note that all registers are controlled from the AND array in 2 groups of four.

The PLS159A is an <u>octal part</u>. It readily enters the environment of the 8-bit data operand as

well as the bus oriented system. For enhanced performance, the flip-flop outputs are inverted. To provide positive outputs for shifters and counters, the input variables and state feedback variables can be selectively inverted through an input receiver or the feedback path through the AND gate array.



There are three basic members in the 24-pin package family: The PLS167A, the PLS168A, and the PLS179. The PLC42VA12 is discussed elsewhere.


The PLS167A

The PLS167A has 14 logic inputs and six registered outputs (S–R flip-flops). Six additional buried flip-flops reside beside the 48 product term AND array. This device can support state

machine designs of up to 256 states—as two outputs feed back into the AND array, making a total of eight buried registers. There is complete feedback connectivity of the inputs and the state flip-flop outputs to the PLA AND gates. Organizationally it has much more in common with the PLS105A than the aforementioned 20-pin parts. The asynchronous Preset and the Output Enable are identical

to the PLS105A.

By having the output latched state variable capability, it provides an automatic buffer for bus based systems. The current state may be presented, fully stable and synchronized to a bus—while the internal buried machine is transitioning to the next state based on currentinput conditions.




The PLS168A

This sequencer is a down–scaled version of the PLS105A. Having identical product terms, Complement array, asynchronous PRESET7 Output Enable options, and 3—State controls, its primary difference is having 12 inputs compared to the PLS105A's 16 inputs. However, the PLS168A can become a state machine

of up to 1024 states due to internal feed back of its six state registers, plus the feedback of four of the eight output registers. The PLS168A is packaged in a 300mil—wide 24—pin DIP or 28—pin PLCC.

This is also an octal part, providing an 8-bit register to a bus based system. State registers,

interrupt vector synchronizers, counters, shifters, or just about any basic state machine can be generated and 3–State interfaced to a computer bus with a PLS168A. Outputs provided by the positive asserted sense make state transitioning and loading of state variables straightforward.




The PLS179

The PLS179 is architecturally similar to the PLS159A. The 3–State enable, number of product terms, flip-flop mode controls, register preload, etc., are all identical to the PLS159A. The four additional inputs are the dominant differentiating feature for this part as compared to the PLS159A. As with the PLS159A, the PLS179 Preset and Reset functions are

controlled from the AND array in 2 groups of 4 registers each.

The PLS179 is also an <u>octal</u> part. Providing the state contents directly to the pin through 3–State buffers allows counters and other sequence generators direct access to an asserted low octal bus. Some design creativity will

generate positive assertion through the pin inverters, for positive driven busses. Additional input pins expand the capability of the part beyond the PLS159A. Input combinations may be presented in a wider format, more fully decoded to the sequencer for faster reaction and less external circuitry than the PLS159A requires.



712

The PLUS405

The PLUS405 is a functional superset of the PLUS105. It is also much faster. The performance of the PLUS405 has been dramatically improved relative to the PLS105A. Available in two speed versions, the operating frequencies (1/t_{IS}+t_{CKO}) range from 37 to 45MHz (minimum guaranteed frequency). The clock frequencies, or toggle rate of the flip-flops, are 50MHz and 58.8MHz, respectively. The PLUS405 has 16 more product terms and two more buried state registers than the PLUS105. Equipped with two independent clocks, it is partitionable into two distinct state machines with independent clocks. And, it contains two independent


Complement arrays, allowing full benefits over both machines.

The PLUS405 can be partitioned as one large state machine (16FFs) with 64 available p-terms using one clock and 16 inputs or alternately two state machines (8FFs each) with independent clocks, sharing 64 p-terms with 15 inputs in any combination the user desires. The Complement arrays can be used to generate the "else" transition over each state machine or alternately used as NOR gates. They can be coupled into a latch if needed.

The Asynchronous Preset option of the

PLS105/167/168 architectures has been replaced with a Programmable Initialization feature. Instead of a Preset to all logic "1"s, the user can customize the Preset/Reset pattern of each individual register. When the INIT pin (Pin 19) is raised to a logic "1", all registers are preset/or reset. The clocks are inhibited (locked out) until the INIT signal is taken Low. Note that Pin 19 also controls the OE function. Either Initialization or OE is available, but not both.

A CMOS extension to the PLUS405 is Signetics PLC415, which is pin compatible and a functional superset of the PLUS405 architecture.



The Future is Here Now.

Recent architectural extensions are currently available from Philips Components—Signetics. These include the PLC415 and PLC42VA12. These new "Super Sequencers" are available now for high-end new designs. Please check the data sheet section of this handbook for more information.

Signetics

Programmable Logic Design and Application Notes

Programmable Logic Devices

APPLICATION SECTION INTRODUCTION

This section provides examples of the wide ranging applications for Signetics PLD products. In microprocessors, for example, PLDs can solve complex interfacing problems. Their wide input gates make them ideal for microprocessor decoding, memory and I/O functions.

Communication is another key area where PLDs can solve difficult problems. Here PLDs simplify the process of developing products to an emerging standard. Signetics has provided a series of examples to show PLDs make it possible to change a design the same instant the standard changes. The examples contain a range of applications from whole protocols and simple scramblers to a customizable speech synthesis system.

Other examples in this section illustrate applications in home security and instrumentation.

The applications in this section are designed to show how Signetics PLDs can solve many classic design problems. However, it is important to note that each example exploits only one of the many facets of the product.

MICROPROCESSOR INTERFACING WITH SIGNETICS PLDS

Microprocessor interfacing is the art of connecting the attributes of a microprocessor, very skillfully to its surrounding environment. They must lineup carefully and match the appropriate timing, address and data signals to achieve an effective interaction. This section illustrates multiple interfacing examples.

Introduction

Architectural bottlenecks have migrated from one point to another within a system throughout the history of computer design. Currently, processor speeds and memory cycles have become so tightly designed that little margin exists should any incompatibility arise between them. Driven for both speed and pin compatibility. DRAM manufacturers have added additional modes to their designs such as the nibble and page modes. Processor designers have resurrected the multiple bus Harvard architectures, as evident in some of the commercially available RISC chips. And, by using small block read ahead caches, the processors hide slower DRAM accesses typically by bursting as many as four words in a read cycle. Attempting to match the DRAM to the processor, or perform parity or ECC at full speed (i.e., no wait states) requires a fine balance of time budgeting, cost tradeoff and impedance matching among other issues. Performing all of these functions has resulted in an address decode time between 10 and 20 nanoseconds, depending on the required set of tradeoffs. For example, a tight 80386 memory cycle atfull speed may require 10 nanoseconds. which could be accomplished with a Dspeed PLD, or with a fast PROM. Less than 10ns is desirable, so 7.5ns PAL-type devices will help. The new PHD16N8 and PHD48N22 are ideal.

System Partitioning

Currently, most 32-bit processors generate an address capable of logically spanning four gigabytes. This is accomplished with 32 bits of distinct address lines. Available memories occupy much less (i.e., 1 megabit or less). A 1 megabit DRAM requires twenty bits of address, so selecting across twelve bit fields may be appropriate. Single module selection (or common address banks) could be accomplished with any logic device which can decode (i.e., generate a select condition) over the

12 high order address bits. Many contenders exist for this reason. The classic solution would be the 74S133 (t_{PD} = 4ns) 13 input NAND gates with an additional 74S04 inverter to decode. Total decode time is at least eight nanoseconds. Depending on the cycle requirements, this may be required, but typically is not. A more efficient method is simply a PLD which combines the wide logic gate with "free" input inverters where required.

Additional select qualifiers may be needed to distinguish the precise assertion time of the select signal. The total number of decoding inputs will exceed the applied address signals.

Given the memory choices selected, the designer must choose a decoding device which meets his criteria. A typical system would have a mix of PROM (system functions), STATIC RAM (no wait memory or cache), DRAM (slower bulk store) or dual port memory (video RAM or shared store). Each will have different timing constraints. Most systems today will have much less than the four gigabytes they can address, but for software expansion reasons (or other system considerations) the memory may not run contiguously and small patches might be spread over the entire range. It will be important to decode precisely to known regions and avoid accidental reference to nonexistent regions.

In selecting a decode device, assuming one is required, several considerations become key. Should the software allow it, or the performance require it, the fastest decode is by distinct selection via direct connection to high order address lines. In today's organizations this will be the fastest, most fragmented memory space. Electrical drive pitfalls can exist here.

Tight layout of the board is also important so that precious, paid for nanoseconds are not given up to long PC connect lines, input capacitance and voltage reflections. Many of the Signetics candidates illustrated in this discussion are limited to speed applications requiring no more than 16mA output drive. They may be inappropriate for extremely dense RAM arrays with long pc—trace interconnects. For simple, fast decode purposes, the D—speed PAL—type devices are good, with a logical choice being the 7.5ns PAL ICs. The new PHD family of parts is even better.

Some straight forward decoding examples follow with criteria for selecting specific Signetics PLD products for decode. These examples exploit only one of many facets offered by these products. Other examples illustrate


the use of Signetics PLDs for customized interrupt handling and a most extensive example shows a powerful solution to a SCSI bus interface

Bus Size Decoding for the 68020 — PLUS18P8B

Address decode for this class of processor is shown in successive sections (i.e., 68030 and 80386). This example depicts a slightly different problem—"data bus sizing" which is accomplished by decoding the address and control signals replicated in the logic diagram in Figure 4-1. Basically the 68020 device will strobe data onto the 32—bit databus in byte oriented subfields of the large word. Sixteen bit ports can receive either the upper or lower 16 data lines. Other ports can respond to LLD

(Data 0–7), LMDF (Data 8–15), UMD (Data 16–23), or UUD (Data 24–31). All subfields can be simultaneously asserted as dictated from decoding the size control lines (SIZ0, SIZ1) in conjunction with the low order address lines (A0, A1).

Because the solution requires no product term sharing and is intensive on neither input nor output pins, a simple fast PAL device is the best choice—the PLHS18P8B is designated. The basic operation is to decode the input lines to indicate whether the bus should have 8, 16, or 32 bits driven onto it. These signals are supplied to a device external to the microprocessor which then asserts the corresponding data. Figure 4-2 shows an appropriate pinlist under AMAZE with Figure 4-2 showing the logic equation file.



```
File Name
                   : BYTESEL
                   : 4/31/1988
       @DEVICE
       PLHS18P8
       @DRAWING
       GREVISION
       @DATE
       @SYMBOL
       @COMPANY
       @NAME
       @DESCRIPTION
      @PINLIST
"<----> <--REFERENCE-->"
"PINLABEL PIN # PIN FCT
                            PIN_ID OE_CTRL"
A0
                             I0
A1
SIZO
SIZ1
           4
                   I
                             I3
N/C
           5
                   I
                             I4
N/C
                             15
                   Ι
N/C
                             16
N/C
           8
N/C
           9
                             T 8
          10
                  0 V
GND
                             GND
N/C
                             I9
N/C
          12
                   /B
                             BO
N/C
          13
                  /B
                             В1
T.D
          14
                  0
                            B2
          15
                             B3
                            R4
                                       D4
          16
                  0
          17
                             B5
                                       D5 ;
LMD
UMD
          18
                   0
                             В6
                                       D6
          19
                  0
                             В7
VCC
                 +5V
       @COMMON PRODUCT TERM
          "CPT label = (expression)"
       @I/O DIRECTION
       @LOGIC EQUATION
        UUD= /A0*/A1;
        UMD= /SIZ0*A1+A1*A0+SIZ1*/A1;
        LMD= /A0*A1+/A1*/SIZ1*/SIZ0+SIZ1*SIZ0*/A1+/SIZ0*/A1*A;
        LLD= A0*SIZ0*SIZ1+SIZ0*/SIZ1+A0*A1+A1*SIZ1;
        UD = /A0;
        LD = A0 + SIZ1 + / SIZ0;
                    Figure 4-2. BYTESEL Design File
```


Interfacing to SPARC — PLUS20L8-7


The SPARCTM processor is a modern RISC device configured from a popular CMOS gate array. Architectural details can be found in data sheets and literature. Supporting a full 32 bit address decode at full speed requires a 60 nanosecond instruction or data cycle. We will consider a 60ns part although a 30ns one is available. Figure 4-3 shows the pin definition and Figure 4-4 the basic timing. The address is driven out in two phases (low and high) and the data must be present 54 nanoseconds after the rising edge of clock 1. To meet the access time will require an SRAM of less than 60ns. In fact, the address generation requires 30ns from when the low address is valid to when the high


address is valid. This is almost untenable and most designs will rely on the high order address lines seldom changing with respect to the low order ones. Therefore, assuming the high order lines are static and basing address calculations on the low order transitions seems reasonable. Detecting a change from one "segment" to another in the high lines can key a "wait" condition when addresses make big jumps. By not doing this, will force a very expensive SRAM solution if zero waits are required. Assuming zero wait states are desired, this will require a memory less than 20ns access, if the fastest (7.5ns) PLD is chosen. By virtue of its restricted width and even more restricted speed option for a zero wait state solution, the PLUS20L8-7 is the only contender. This restricts the SPARC

address space to 32 independent modules. The low order address lines must be latched within the RAM or externally.

Full performance can be achieved for 32, 64K—bit static RAMs comprising \$^1/2\$—mega word store at full speed. By allowing a single wait state, the options open enormously to include a full spectrum of SRAMs, PROMs, even DRAMs with any of the other decode devices. Figure 4-5 shows four such modules selecting off of AL17\$—AH21 address lines into 16K y 4\$—bit, 35ns SRAMs. This populates the entire lower two megaword space with high performance static RAM. The high order address lines (AH22\$—AH31) can select other such modules for expansion purposes.







The 80386 Pipeline Decoder — PLUS153D

For example, select a mix of memory that will be located in small addressing chunk segments within the lower 16 megabytes of the 80386 four gigabyte address space. See Figure 4-6.

This decoding method will impact the memory addressing, but in a different way. The 80386 supports a mode whereby a next address can be asserted early (1 clock cycle) if the user asserts the NA# pin. The interleaved slower memory may be sued by getting the nest

address earlier than normal to trigger an early memory cycle. Because we will be driving a single signal, NA#, a PLUS153 can be configured with eight inputs and nine of the bidirectionals configured as inputs (i.e., 17 inputs, one output). By decoding addresses 31–17 with the status signal M asserted high and ADS# asserted low, an NA# will assert early to initiate a pipelined early transfer with a slower RAM. This approach allows designers to tune their specific memory speeds to the processor,

according to timing needs.

Figure 4-10 shows NA# generated for a pipelined address located in the lowest 128K of the address space. In Figure 4-11, the PLUS153D is shown as a single 17–input NAND function, most of the remaining portion of the part is unused. The address strobe and M signals are included to correctly qualify the address and not generate glitches into the NA# pin. Unless the p.c. board is poorly designed, the output drive of the PLUS153D will be adequate to drive the NA# pin and any additional PC—metal. Figure 4-12 shows the AMAZE equation to decode.




Figure 4-7 illustrates the 80386 signal groups.


Figure 4-8 illustrates various bus cycles with no wait states, and no pipelining.


Figure 4-9 illustrates bus cycles with and without pipelining.


Figure 4-10 illustrates the CLK2 time spans.


Figure 4-11 illustrates the NA# pinlist

Figure 4-12 illustrates the .BEE file for NA# generation.










```
File Name : NA 386
Date : 5/16/88
Time : 16:38:8
@DEVICE TYPE
  PLUS153
@DRAWING
@REVISION
@DATE
@SYMBOL
@COMPANY
 /NA386
@DESCRIPTION
THIS DESIGN DRIVES THE NA# SIGNAL LOW WHEN ASSERTED ON AN
80386 PROCESSOR FOR A MEMORY REGION SPANNING THAT DECODED
BY THE EQUATION CONTAINED HEREIN.
@COMMON PRODUCT TERM
@I/O DIRECTION
@LOGIC EQUATION
   /NA=/(/AD31*/AD30*/AD29*/AD28*/AD27*/AD26*/AD25*/AD24*/AD23
      */AD22*/AD21*/AD20*/AD19*/AD18*/AD17*/ADS*M);
                   Figure 4-12. NA_386 .BEE File
```

68030 Address Decoding — PLUS173D

Although designers generally try to optimize every nanosecond of microprocessor performance, it is typically not necessary for the CPU to always operate at full speed. Operating the CPU, when acceptable, at a slower speed can bring about a more economical and compact system. This is due to higher costs associated with fast memory and greater board area usage of very wide memory configurations.

Some software routines in which slower performance may be acceptable are during power up initialization, diagnostic routines, or possibly some exception processing routines. Where speed is not critical, an 8-bit bus is the most economical and compact because of readily available byte wide memory components and buffers. The 68030 is easily interfaced to 8, 16, or 32-bit ports because it dynamically interprets the port size of the addressed device during each bus cycle. Figure 4-13 shows an example of interfacing both a relatively slow 200ns 8-bit EPROM and fast 35ns 32-bit RAM to a 68030. A PLUS173D was chosen for its high speed and large number of inputs and outputs. Figure 4-14 shows the AMAZE pinlist and Boolean equations for the device. The EPROM occupies memory space 0-32K while the RAM occupies addresses 64K-128K. However, please note that because not all of the upper memory address bits were decoded, the memory arrays will also appear at other addresses.



```
LABEL** FNC ** PIN -----PIN ** FNC **
                                                           LABEL.
DLYIN** I **
                          1-24
                                           ** +5V
                    1-|
                                           ** /0
/AS ** T
                    2-1
/AS ** I ** 2-| |-23 ** /0 **

A31 ** I ,** 3-| P |-22 ** 0 **

A30 ** I ** 4-| L |-21 ** /0 **

A19 ** I ** 5-| U |-20 ** /0 **

A18 ** I ** 6-| S |-19 ** /0 **

A17 ** I ** 7-| 1 |-18 ** /0 **

A16 ** I ** 8-| 7 |-17 ** /0 **

A1 ** I ** 9-| 3 |-16 ** /0 **

A0 ** I ** 10-| |-15 ** /0 **
                                                           DSTRT
                                                           /UMCS
                                                           /LMCS
A1 ** I
A0 ** T
                                                           /ACK1
A1 ** 1 ** 9-|

A0 ** 1 ** 10-|

SIZ0** 1 ** 11-|
                                          ** /0
                            1-15
                                                    **
                                                           /ACK0
GND ** 0V ** 12-
                                 |-13 ** I
@DEVICE TYPE
PLUS173
@LOGIC EQUATION
  "EPROM enable"
/epcs = /(/a31*/a30*/a19*/a18*/a17*/a16*as):
  "start shift register during EPROM access"
dstrt = /a31*/a30*/a19*/a18*/a17*/a16*as;
  "DSACKO after 4 clock cycles for EPROM access"
/ack0 = /(dlyin);
   "immediate STERM upon RAM access"
/ack1 = /(/a31*/a30*/a19*/a18*/a17*a16);
   "Byte select signals for RAM writes"
/uucs = /(a0*/a1* /rw*a16*/a17*/a18*/a19*/A30*/a31);
/ nu-/al* /rw*al6*/al7*/al8*/al9*/A30*/a31 /rw*al6*/al7*/al8*/al9*/A30*/a31 /rw*al6*/al7*/al8*/al9*/A30*/a31 /rw*al6*/al7*/al8*/al9*/A30*/a31; /lmcs = /( a0*/al* /rw*al6*/al7*/al8*/al9*/A30*/a31;
            +/a1*/siz0*/siz1*/rw*a16*/a17*/a18*/a19*/A30*/a31
            +/a1* siz0* siz1*/rw*a16*/a17*/a18*/a19*/A30*/a31
            +/a1*a0*/siz0* /rw*a16*/a17*/a18*/a19*/A30*/a31);
/11cs = /(a0*a1*
                                /rw*a16*/a17*/a18*/a19*/A30*/a31
           +/a0* siz0* siz1*/rw*a16*/a17*/a18*/a19*/A30*/a31
            + /siz0*/siz1*/rw*a16*/a17*/a18*/a19*/A30*/a31
                        siz1*/rw*a16*/a17*/a18*/a19*/A30*/a31);
/rmcs = /(
                                  rw*a16*/a17*/a18*/a19*/A30*/a31);
               Figure 4-14. AMAZE Pinlist and Boolean Equations
```


1


The 29000, SRAM and the PLUS20L8D


The 29000 processor can, in theory, access instruction memory every 40 nanoseconds (Figure 4-15) at top speed. The natural tendency is to place this part into the highest performance environment possible. This is still a very difficult problem. Similar to the SPARC, a

simple brute force SRAM will yield no "wait states" by correctly combining, for instance, a 25ns access time with the instruction cycle. One additional, and very important requirement will be a current drive of 24mA. The PLUS20L8D PAL (Figure 4-16) can decode up to 20 inputs in 10 nanoseconds with 24mA of

output drive. Making some assumptions about SRAM input capacitance, p.c. board trace capacitance, etc., will assure the reader that the PLUS20L8D will not waste valuable time needed to achieve the maximum possible performance. The following outlines verification that the PLUS20L8D will meet timing requirements.







Consider, for example, the configuration depicted in Figure 4-17 with Motorola MCM 6288 SRAMs. As depicted, there are eight modules forming a 16K word space. The 29000 is targeted to drive 80pf according to the data manual at full speed (25MHz clock). How much additional time delay will be attributed to the bus and RAM loading?

For the chosen RAM configuration $C_{in} = 8$ (5pf) = 40pf. We will have to <u>assume</u> some values for p.c. wiring. One common one today is about 20pf/ft. Placing our RAM on the same board,

near the processor should require about a foot of trace/address line. The average $C_L=(40\pm20)\,pf$. This is just beyond the 10ns specified for testing the 20L8 (i.e., 50pf), however, if we ignore it, the extra loading will not significantly impact this small system.

To include it would incur additional assumptions about the pull up and pull down resistance of the 20L8 (these values are typically between 5 and 20 ohms), but are not strictly specified. The result is that we are within 2 nanoseconds of time delay by ignoring the capacitance.

Adding anything into the data path or a poor circuit layout can take the design out of spec., but by these assumptions, is can succeed. Design slack may be generated simply by inserting the 20L8–7 and one gets 2.5ns of free time margin.

Interrupt Handler — PLS179

In the 1970's I.C. manufacturers made the error of introducing microprocessor chips without having family support chips available. Often, months or years passed before relatively simple family additions arrived. Later, a similar situation arose when bus standards, LAN standards, and disk standards failed to settle down for system designers to get sufficient market lead without LSI solutions. PLDs could have helped much here! As an example of designing a microprocessor family part, consider Figure 4-18, which depicts an interrupt handler. In particular, note that interrupt inputs will be latched into an 8-bit register. This in turn will be encoded to a 3-bit vector which may be appropriately enabled and applied to the microbus. Figure 4-18 shows the eight flip-flops as having J-K and /D inputs which will be generated with a PLS179 by switching the flip-flop control. Appropriate control signals for the various transactions might be as follows:

- CLOCK the system synchronous time
 base
- Interrupt Enable when asserted high from the microprocessor, allows interrupts to be generated to the microprocessor.
- Interrupt a strobe or level defined to indicate a pending interrupt and a valid encoded vector.


- Interrupt Acknowledge a response signal from the microprocessor which may be used to enable the 3-bit vector onto the bus. As well, it may initiate clearing the currently asserted interrupt latch.
- /INTO-/INT7 eight possible interrupt request signals which must be asserted low and held there until service for that device has occurred.
- Reset this is a system override signal which will clear all flip-flops during initial operation.


Basic Operation

Initially, the part should be reset by asserting the RESET pin high, asynchronously. Then, when interrupts are enabled, the /D-inputs to the 8 flip-flops will be synchronously scanning for interrupt inputs (asserted low). This will put a nonzero value into the eight bit register which will generate an interrupt output, combinationally through the Complement array. In parallel, a 3-bit encoded vector will be applied on the VECO, VEC1, VEC2 lines. Asserted high logic will be assumed for the vector. Presumably, a microprocessor will interrupt this, transfer control to a service routine and clear the interrupt. The clear will be accomplished by disabling interrupts and strobing the vector value back

into the PLS179, using the IACK signal. Disabling the interrupts will put the registers into J–K mode. J is tied to zero and K is decoded from the specifically strobed vector. Therefore, synchronous clear of the high priority bit is done. Interrupts are then re–enabled and the process continues

The PLS179 solution offers room for user alteration. For example, the IACK condition could be redefined as a combination of the Z80 IO-REQ and M1 signals, or any specific splitting of internal signals could be easily done. The design could fit into a PLS159A, but there would be less room for variation for specific users exact needs. Figure 4-20 shows the pinlist for the handler. Figure 4-21 gives the corresponding design file. A simulation Ruler template is given in Figure 4-22, and Figure 4-23 shows a simulation log file for some example interrupt transactions. In Figure 4-23, the simulation begins by asserting RESET followed by successive assertion of each interrupt bit to demonstrate the vector encoding. The second half begins with all eight interrupts asserted simultaneously and each is cleared successively in descending priority. /INTO is the highest priority. The interrupt is actually asserted through the PLS179 Complement array behaving as a simple NOR gate.





```
@DEVICE TYPE
   PLS179
   @DRAWING
   @REVISION
  @DATE
  @SYMBOL
   @COMPANY
  JOE USER
  GNAME
  GENERIC INTERRUPT VECTOR GENERATOR
  @DESCRIPTION
@PINLIST

"<-----FUNCTION----->
"PINLABEL PIN # PIN_FCT PIN_ID OE_CTRL"
CLOCK 1 CR CLK -;
ENA 2 I IO -;
RESET 3 I II -;
IACK 4 I I2 -;
N/C 5 I I3 -;
N/C 6 I I4 -;
N/C 7 I I5 -;
N/C 8 I I6 -;
N/C 9 I I7 -;
INTERUPT 10 B B0 D0;
VECO 11 B B1 D1;
GND 12 OV GND -;
OTE 13 /OE /OE -;
VECI 14 B B2 D2;
/INTO 15 /B F0 EA;
/INT1 16 /B F1 EA;
/INT2 17 /B F2 EA;
/INT3 18 /B F3 EA;
/INT4 19 /B F4 EB;
/INT5 20 /B F5 EB;
/INT6 21 /B F6 EB;
/INT7 22 /B F7 EB;
VEC2 23 B3 D3;
VCC 24 +5V VCC -;
  @PINLIST
                                                   Figure 4-20. Interrupt Pin List
```

```
@COMMON PRODUCT TERM
        /INTO*/INT1*/INT2*INT3;
         /INTO*/INT1*/INT2*/INT3*/INT4*INT5;
        /INTO*/INT1*/INT2*/INT3*/INT4*/INT5*INT6;
/INT0*/INT1*/INT2*/INT3*/INT4*/INT5*/INT6*INT7;
CPT3=
CPT4=
KLEAR0 =/VEC*/VEC1*/VEC0*IACK; "DECODE VECTOR 0"
KLEAR1 =/VEC2*/VEC1*VEC0*IACK; "DECODE VECTOR 1"
         =/VEC2*VEC1*/VEC0*IACK; "DECODE VECTOR 2"
        =/VEC2*VEC1*VEC0*IACK; "DECODE VECTOR 3"
KLEAR3
KLEAR4 =VEC2*/VEC1*/VEC0*IACK; "DECODE VECTOR 4"
KLEAR5 =VEC2*/VEC1*VEC0*IACK; "DECODE VECTOR 5"
KLEAR6 =VEC2*VEC1*/VEC0*IACK; "DECODE VECTOR 6"
KLEAR7 =VEC2*VEC1*VEC0*IACK; "DECODE VECTOR 7"
@COMPLEMENT ARRAY
/C = /(INTO + INT1 + INT2 + INT3 + INT4 + INT5 + INT6 + INT7);
@I/O DIRECTION
D3 = ENA;
D2 = ENA;
D1 = ENA;
D0 = ENA;
@FLIP FLOP CONTROL
FC = /ENA;
@OUTPUT ENABLE
EA=OTE;
EB=OTE:
@REGISTER LOAD
I.A-ENA:
LB=ENA;
@ASYNCHRONOUS PRESET/RESET
RA = RESET;
RB = RESET;
PA = 0;
PB = 0;
@FLIP FLOP MODE
M0, M1, M2, M3, M4, M5, M6, M7 = 1;
@LOGIC EQUATION
VEC0 = (/INT0*INT1 + CPT1 + CPT2 + CPT4);
VEC1 = (/INTO*/INT1*INT2 + CPT1 + CPT3 +CPT4);
VEC2 = (/INT0 * /INT1 * /INT2 */INT3*INT4 + CPT2 + CPT3 + CPT4);
INTERRUPT = (/C);
INTO:
        J=0;
         K=KLEAR0;
INT1:
         J=0;
         K=KLEAR1;
INT2;
         J=0;
         K=KLEAR2;
INT3:
         K=KLEAR3;
TNT4:
         K=KLEAR4;
TNT5 .
         J=0;
         K=KLEAR5;
INT6:
         K=KLEAR6;
TNT7:
         J=0;
         K=KLEAR7;
                    Figure 4-21. Interrupt Design File
```

```
@INPUTS
13 /OTE
3 RESET
2 INTENABLE
22 /INT7
21 /INT6
20 /INT5
19 /INT4
18 /INT3
17 /INT2
16 /INT1
15 /INTO
4 IACK
14 VEC1
11 VEC0
@OUTPUTS
10 INTERRUPT
23 VEC2
14 VEC1
11 VEC0
22 /INT7
21 /INT6
20 /INT5
19 /INT4
18 /INT3
17 /INT2
16 /INT1
15 /INTO
Figure 4-22. Interrupt Ruler File
```

```
PLS179 INTERRUP
                       Time = 14:53:31 Date = 8/5/1987
    C / INP
                      I/O <=PREV=> <=NEXT=> <=FOUT=> TRACE TERMS
   L O
   K E 76543210 3210 76543210 76543210
                                                        76543210
   NNNNNNN
                                                        нинининн
                                                        . . . . . . . .
                                                        LLLLLLLH
                                                        LLLLLLHH
                                                        LLLLLHHH
   C 0 11111100 010. HHHHHHLL HHHHHLLL
C 0 11111100 100. HHHHHLLL HHHHLLL
C 0 11111100 100. HHHHLLLL HHHLLLL
C 0 11111100 101. HHHLLLL HHLLLLL
C 0 11111100 110. HHLLLLL HLLLLLL
C 0 11111100 111. HLLLLLLL HLLLLLLL

                                                        LLLLHHHH
                                                        LLLHHHHH
                                                        LLHHHHHH
                                                        LHHHHHHH
    C 0 11111100
                       111. HLLLLLL LLLLLLL HHHHHHHH ;
                                  I/O CONTROL LINES
                       BBBB DESIGNATED I/O USAGE
BBBO ACTUAL I/O USAGE
   PINLIST...
   01 13 09 08 07 06 05 04 03 02 23 14 11 10
   22 21 20 19 18 17 16 15 ;
                                    Figure 4-23. Interrupt Simulation Log File
```

SCSI TARGET INTERFACE — PLUS105 AND PLUS153B Overview

This application provides a complete solution to the SCSI Target Interface. As well, it includes a detailed rendering of the PLUS 105 controlling transaction with a complete state equation solution.

Introduction

From its first introduction, the SCSI Bus (known as SASI in its initial days), has gained wide acceptance as a small computer peripheral bus. As the performance capabilities of mass storage peripheral devices increased, other bus specifications came into being to handle the increased performance requirements. Interfaces such as the High Speed SCSI, ESDI, and proposed byte/word wide bus for high performance mass storage devices (to replace the de facto standard SMD Interface) are gaining acceptance. Though different from each other, they present the system designer with surprisingly similar handshake requirements for the transfer of command, status, data and other information among hosts and/or targets connected to the bus

In recent years several IC manufacturers have introduced single—chip controllers for the SCSI Bus, but none yet for the new proposed buses. The purpose of this application note is to use the SCSI Bus, known to most designers, as the vehicle to demonstrate the ease with which such buses can be handled by high performance, low cost programmable sequencers. The design described is based on the PLUS105 (or the higher performance PLUS405).

High performance programmable sequencers using the architecture exemplified in the PLUS105 have been available since Signetics invented and introduced the PLS105 in 1980.

Functional Description

The SCSI Interface described in this document is a Full Target Implementation that includes the following features:

- Arbitration Capability
- Reselect Capability
- Software Programmable Target I.D.
- Full DMA Interface
- Interrupt Generator

The Reselect and Arbitration capabilities enable the implementation of an efficient, intel-

ligent target controller. Once a command is received, the target can disconnect from the SCSI Bus, execute the command and reconnect to the SCSI when data or status needs to be transferred to the requester. This reduces the amount of idle time on the bus; it also enables the target to receive multiple commands and execute them in the most efficient manner.

The software programmable Target I.D. allows the same design to be used for multiple targets sharing the same SCSI Bus. The DMA Interface is based on a straight–forward DMA Request/DMA Acknowledge Handshake protocol, enables fast data transfers without undue burden on the local intelligence.

An open collector, active low interrupt is provided to request service by the local intelligence at the completion of transfers or in the event of errors.

Programmer's Interface

The SCSI Port is operated through the use of five independently addressed registers: STATUS, COMMAND, TARGET ID, DATA IN, DATA OUT.

ADDRESS	REGISTER	ACCESS MODE
Base + 0	STATUS	Read only
Base + 0	COMMAND	Write only
Base + 1	TARGET ID	Write only
Base + 2	DATA IN	Read only
Base + 2	DATA OUT	Write only

The 5 registers are 8 bits wide with bit definitions as described below:

COMMAND REGISTER

IRQE	PORTE	DMAE	CTLS	MESG	CTRL	SFC	
7	6	5	4	3	2	1	0

IRQE

SET to enable the generation of interrupts from the Port.

PORTE

 SET to enable operation of the SCSI Port. Negation of this signal is required to clear the interrupt generated at the completion of every command.

DMAE

SET to enable the DMA Interface of the SCSI Port.

CTLE

Defines the direction of transfers on the SCSI Bus 0 : From SCSI to TARGET

1 : From TARGET to SCSI

MESG

SET for MESSAGE Transfers on the SCSI Bus

CTRL

Defines the type of transfer on the SCSI Bus

0 : DATA Transfer

1 : COMMAND or STATUS Transfer

SFC

Two bit Function Code:

0 0 - Disconnect 0 1 - Transfer 1 0 - Reselect

11 - Arbitrate

STATUS REGISTER

CMPL	PARE	SRST	ATTN	SLCT	BUSY	ARBT	SLCD
7	6	5	4	3	2	1	0

CMPL

 Function Completed. This signal gated with BIT 7 (IRQE) of the Command Register generates an Interrupt to the local intelligence.

PARE

Parity Error. The source of the error can be determined from the state of BIT 4 (CTLS) in the COMMAND

CTLS=0 - Error on SCSI Bus CTLS=1 - Error in local memory

SRST

Status of RESET signal on SCSI Bus

ATTN

Status of ATTENTION signal on SCSI Bus

SLCT

Status of SELECT signal on SCSI BusStatus of BUSY signal on SCSI Bus

BUSY

ASSERTED to indicated that the controller has won Arbitration and is in control of the SCSI Bus.

SLCD

 SELECTED. If both SLCD and SLCT are ASSERTED, the controller is being selected by another device on the SCSI Bus.

TARGET ID REGISTER

TATIOET ID REGISTER								
	not used				TID			
	7	6	5	4	3	2	1	0

TID

Three bit code that defines the Target I.D.

Port Operation

As described in the previous section, the port can execute 4 commands:

Arbitrate, Reselect, Transfer and Disconnect.

Arbitrate

The port monitors the SCSI Bus for the "bus free" state. When the bus is free, the port starts the Arbitration sequence to gain bus mastership. If arbitration is won, the port will generate an interrupt with the appropriate status in the STATUS Register. If arbitration is lost, the port returns to the monitoring of the SCSI Bus.

Reselect

Transfer

The port transfers the desired ID Byte from local memory (through DMA) to the SCSI Bus and waits for the appropriate response from the desired controller. When the desired controller responds, the Port generates an interrupt with the appropriate status in the STATUS Register.

The port transfers data between local memory and the selected controller on the SCSI Bus until the DMA Termination Signal (DMACNTO) is asserted. At completion, the port generates an interrupt with the proper

status in the STATUS Register.

Disconnect

The port relinquishes Bus mastership. This results in the "bus free" state allowing other controllers to use the SCSI Bus. This is also the IDLE state for the Port. The port should be programmed for this state when there is no SCSI work in progress.

736

August 1989

```
Arbitration Software Sequence
PROC (arbitrate)
  negate DMAE, PORTE
  set SFC to ARBITRATE; assert PORTE
          - wait for completion
  negate PORTE
  IF port won arbitration
     THEN exit with normal status
    ELSE DO
       IF SRST
         THEN exit with RESET status
         ELSE DO
            set-up single byte DMA transfer
            negate CTLS; assert DMAE, PORTE

 wait for completion -

            negate DMAE, PORTE
            exit with Port Selected status
         END
    END
  END
RESELECT Software Sequence
PROC (reselect)
  negate DMAE, PORTE
  place reselect ID byte in local memory
  set-up single byte DMA transfer
  set SFC to RESELECT; assert DMAE, PORTE
          - wait for completion
  negate DMAE, PORTE
  IF good completion
     THEN exit with normal status
     ELSE IF SRST
       THEN exit with reset status
       ELSE exit with error status
END
TRANSFER Software Sequence
PROC (transfer)
  negate DMAE, PORTE
  set-up DMA controller
  set SFC to TRANSFER; set-up CTRL, CTLS, MESG; assert DMAE, PORTE
           wait for completion
  negate DMAE, PORTE
  IF good completion
    THEN exit with normal status
    ELSE IF SRST
       THEN exit with reset status
       ELSE exit with error status
DISCONNECT Software Sequence
PROC (disconnect)
  negate DMAE, PORTE
  set SFC to DISCONNECT; assert PORTE
          - wait for completion
  negate PORTE
  exit with normal status
END
```

Hardware Description

The SCSI Interface described in this document is implemented using three Programmable Logic Devices and a hand–full of FAST SSI/Octals. Referring to the schematic in Figure 4-30 (page 4–46), the functions of the different components are as follows:

U6 - (74F244) Port STATUS Register

U7 - (74F273) Port COMMAND Register

U1 - (74F374) DATA OUT Register

U2 - (74F374) DATA IN Register

U8 - (74F273) : SCSI Bus signals Synchronization

: Partial Status Latch

U4 - (74145) Asserts proper signal on SCSI bus during Arbitration.

U5 - (PLUS153B): Register Decode

: 3-bit TARGET ID Register.

U3 – (PLUS153B) :Parity Generator/Checker :Arbitration Win Detection

:Port Selected Detection

U9 - (PLUS105) : Executes all commands

: Controls handshake with DMA controller

: Controls REQ/ACK Handshake with SCSI Bus

: Detects "bus free" state : Implements "arbitration delay"

74F38's - High Current, Open Collector Drivers for SCSI Bus

74F14's - Schmitt Trigger Input Receivers for SCSI Bus

NOTES:

- The interface requires an 8MHz Clock. The throughput of the interface can be increased by operating this circuit at 24MHz by using the PLUS405.
- 2. The interface is initialized by an active low signal: /SYSRESET
- 3. The DMA Interface consists of four signals:

DMAENBL - Software controlled DMA Enable

DMAREQ – asserted by the port (PLS105A) for each byte transfer /DMACYCLE – asserted by DMA controller as a response to DMAREQ /DMACNT0 – asserted when the DMA transfer count reaches 0

4. The processor (local intelligence) interface consists of 5 signals

A1, A0 – The two least significant address bits

/SYSSEL - A block decode signal for the SCSI Port

/SYSREAD – Active low, READ signal 0 – READ

1 - WRITE

/INTERRUPT- Active low, Open collector Interrupt

PLUS105						
@DRAWING			DNW-SIG-	.05		
@REVISION			A			
@DATE			11-29-87			
@SYMBOL			U9			
@COMPANY				SIGNETICS		
@NAME			DIMITRIOU			
@DESCRIPTIC	N		SCSI CONT	SCSI CONTROLLER		
@PINLIST						
" <f< td=""><td>UNCTION-</td><td>></td><td><refere< td=""><td>ENCE>"</td><td></td></refere<></td></f<>	UNCTION-	>	<refere< td=""><td>ENCE>"</td><td></td></refere<>	ENCE>"		
"PINLABEL	PIN #	PIN_FCT	PIN_ID	OE_CTRL"		
8MHZ	1	CK	CLK	- ;		
/DMACNTO	2	I	I7	- ;		
PORTENB	3	I	16	- ;		
SELECTED	4	I	I5	- ;		
WONARB	5	I	I4	- ;		
BBUSY	6	I	13	- ;		
BSELECT	7	I	12	- ;		
BACK	8	I	I1	- ;		
BRESET	9	I	10	- ;		
CBUSY	10 11	0	F7 F6	/OE ; /OE ;		
REOUEST	12	0	F5	/OE ;		
/ARBITRATE			F4	/OE ;		
GND	14	0.0	GND	- ;		
SFCMPL	15	0	F3	/OE ;		
SPARERR	16	0	F2	/OE ;		
SDRVENB	17	0	F1	/OE ;		
DMAREO	18	0	FO	/OE ;		
LOW	19	/OE	PR/OE	- ;		
ICBUSY	20	I	I15	- ;		
ICSELECT	21	I	I14	- ;		
IREQUEST	22	I	I13	- ;		
PARERROR	23	I	I12	- ;		
CTLSCSI	24	I	I11	- ;		
SFC1	25	I	I10	- ;		
SFC0	26		I9	- ;		
/DMACYCLE	27	I	18	- ;		
VCC	28	+5V	VCC	- ;		

```
@INTERNAL SR FLIP FLOP LABELS
Q0 Q1 Q2 Q3 Q4 Q5
@COMMON PRODUCT TERM
@COMPLEMENT ARRAY
@LOGIC EQUATION
@DEVICE SELECTION
SCSI CTL/PLS105
@INPUT VECTORS
[PORTENB, SFC1, SFC0]
     "COMMAND CODE DEFINITIONS"
DISCONNECT = 100B;

DATA_XFER = 101B;

RESELECT = 110B;

ARB_COMMAND = 111B;
@OUTPUT VECTORS
[CBUSY, CSELECT, REQUEST, / ARBITRATE, SFCMPL, SPARERR,
SDRVENB, DMAREQ]
     "DISCONNECT STATE OUTPUTS"
DISCNCT OUT' = 00011000B;
     "POWER-UP STATE OUTPUTS"
POWER UP OUT' = 00010000B;
@STATE VECTORS
[Q5,Q4,Q3,Q2,Q1,Q0]
     "INITIALIZATION, IDLE, AND DON'T CARE STATES"
POWER UP
                = 3FH;
IDLE= 1FH;
ANY STATE
               = ----B;
    "PORT SELECTED RESPONSE STATES"
SELECTED 1
                = 3CH;
SELECTED_1 = 3CH;

SELECTED_2 = 18H;

SELECTED_3 = 19H;

SELECTED_4 = 1AH;
    "RESELECT STATE SEQUENCE"
RESELECT 1
              = 10H;
= 11H;
RESELECT 2
RESELECT 3
                = 12H;
RESELECT 4 = 13H;
RESELECT 5 = 3BH;
RESELECT_5 = 3BH;
RESELECT_6 = 33H;
            Figure 4-25.1 PLUS105 SCSI_CTL .SEE File (continued)
```

```
"ARBITRATION STATE SEQUENCE"
ARBITRATE_1 = 00H;
ARBITRATE 2 = 0FH;
ARB DELAY GO = 20H;
ARB DELAY IP = 10----B;
ARB DELAY QU = 2EH;
    "DATA TRANSFER SEQUENCE"
DATA_XFER_1 = 14H;

DATA_XFER_2 = 15H;

DATA_XFER_3 = 16H;

DATA_XFER_4 = 17H;

DATA_XFER_5 = 34H;
DATA_XFER_SL = 1AH;
   "EVENT COMPLETION SEQUENCE"
COMPLETE_1 = 1CH;
COMPLETE_2 = 1EH;
COMPLETE_2
@TRANSITIONS
 "----" POWER-UP RESET RESPONSE -----"
WHILE [POWER UP]
    IF []
         THEN [IDLE] WITH [POWER UP OUT']
    "----" SCSI BUS RESET RESPONSE -----"
    LE [ANY_STATE]
IF [BRESET]
WHILE
         THEN [COMPLETE 1] WITH [DISCNCT OUT']
           "----" DISCONNECT SEQUENCE ----"
WHILE
       [IDLE]
    IF [/BRESET*DISCONNECT*ICBUSY]
         THEN [COMPLETE 1] WITH [DISCNCT OUT']
           Figure 4-25.2 PLUS105 SCSI_CTL .SEE File (continued)
```

```
"----- RESELECT SEQUENCE -----"
WHILE
        [IDLE]
         [/BRESET*/BSELECT*/BBUSY*RESELECT*ICBUSY*ICSELECT]
        THEN [RESELECT 1] WITH [CBUSY', CSELECT', SDRVENB', DMAREQ']
   WHILE
            [RESELECT_1]
[/BRESET*DMACYCLE]
            THEN [RESELECT 2] WITH [/DMAREQ']
   WHILE
            [RESELECT_2]
             [/BRESET]
            THEN [RESELECT 3]
   WHILE
            [RESELECT_3]
            [/BRESET]
            THEN [RESELECT 4]
            [RESELECT_4]
   WHILE
            [/BRESET*ICBUSY]
            THEN [RESELECT 5]
   WHILE
            [RESELECT 5]
            [/BRESET*ICBUSY]
            THEN [RESELECT 5] WITH [/CBUSY']
            [/BRESET*/ICBUSY]
            THEN [RESELECT 6]
   WHILE
            [RESELECT 6]
             [/BRESET*/ICBUSY*BBUSY]
            THEN [COMPLETE 1] WITH [CBUSY',/CSELECT',SFCMPL']
 "----" PORT SELECTED RESPONSE ----"
         [/BRESET*PROTENB*/ICBUSY*/ICSELECT*/BBUSY*BSELECT*SELECTED*/PARERROR]
        THEN [SELECTED 1] WITH [SFCMPL', DMAREQ']
   WHILE
            [/BRESET*/PORTENB*DMACYCLE]
            THEN [SELECTED 2] WITH [CBUSY',/SFCMPL',SDRVENB',/DMAREQ']
   WHILE
            [SELECTED 2]
            [/BRESET]
       IF
            THEN [SELECTED 3]
            [SELECTED 3]
   WHILE
             [/BRESET]
            THEN [SELECTED 4] WITH [SFCMPL']
   WHILE
            [SELECTED 4]
             [/BRESET*PORTENB]
            THEN [COMPLETE 1]
                            Figure 4-25.3 PLUS105 SCSI CTL .SEE File (continued)
```

```
"----- ARBITRATION SEQUENCE -----"
WHILE
         [IDLE]
         [/BRESET*ARB COMMAND*/ICBUSY*/BBUSY*/BSELECT]
        THEN [ARBITRATE 1]
    WHILE
             [ARBITRATE 1]
             [/BRESET*(BBUSY+BSELECT)]
      IF
             THEN [IDLE]
       IF
             [/BRESET*/BBUSY*/BSELECT]
             THEN [ARB_DELAY_GO] WITH [CBUSY', ARBITRATE', SDRVENB']
   WHILE
             [ARB DELAY IP]
             [/BRESET*Q0]
       IF
             THEN [/Q0]
       IF
             [/BRESET*/Q0]
            THEN [Q0]
       TF
             [/BRESET*Q1*Q0]
             THEN [/Q1]
       TF
             [/BRESET*/Q1*Q0]
            THEN [Q1]
       IF
             [/BRESET*Q2*Q1*Q0]
             THEN [/Q2]
       IF
             [BRESET*/Q2*Q1*Q0]
             THEN [Q2]
       IF
             [/BRESET*/Q3*Q2*Q1*Q0]
            THEN [Q3]
       IF
             [/BRESET*ARB DELAY QU]
             THEN [ARBITRATE 2]
        [ARBITRATE_2]
WHILE
         [/BRESET*/BSELECT*WONARB]
        THEN [COMPLETE 1] WITH [CSELECT', /ARBITRATE', SFCMPL']
    IF [/BRESET*BSELECT]
        THEN [IDLE] WITH [/CBUSY',/ARBITRATE',/SDRVENB']
   ----- DATA TRANSFER SEQUENCE -----"
WHILE
        [IDLE]
         [/BRESET*ICBUSY*/ICSELECT*DATA XFER*CTLSCSI]
         THEN [DATA XFER 1] WITH [REQUEST']
         [/BRESET*ICBUSY*/ICSELECT*DATA XFER*/CTLSCSI]
        THEN [DATA_XFER-1] WITH [DMAREQ']
    WHILE
             [DATA XFER 1]
       IF
             [BRESET*PROTENB*IREQUEST*BACK]
             THEN [DATA XFER 1] WITH [DMAREQ']
       IF
             [/BRESET*PORTENB*DMACYCLE]
             THEN [DATA XFER 2] WITH [/DMAREQ']
    WHILE
             [DATA XFER 2]
             [/BRESET]
             THEN [DATA XFER 3]
    WHILE
             [DATA_XFER_3]
             [/BRESET]
             THEN [DATA XFER 4]
                           Figure 4-25.4 PLUS105 SCSI_CTL .SEE File (continued)
```

```
WHILE
            [DATA XFER 4]
            [/BRESET*PORTENB*/PARERROR*DMACNTO*/CTLSCSI]
            THEN [COMPLETE 1] WITH [SFCMPL']
       IF
            [/BRESET*PORTENB*/PARERROR*SMACNTO*CTLSCSI]
            THEN [DATA XFER 5] WITH [REQUEST']
       IF
            [/BRESET*PORTENB*/PARERROR*/SMACNTO]
            THEN [DATA XFER 1] WITH [REQUEST']
            [/BRESET*/PORTENB]
       IF
            THEN [DATA_XFER_SL] WITH [SFCMPL']
       IF
             [/BRESET*PORTENB*PARERROR]
            THEN [COMPLETE_1] WITH [SFCMPL', SPARERR']
   WHILE
            [DATA XFER 5]
            [/BRESET*IREQUEST*BACK]
            THEN [COMPLETE_1] WITH [SFCMPL']
   ----- COMMAND COMPLETION SEQUENCE -----
WHILE [COMPLETE 1]
        [/BRESET*/PORTENB]
        THEN [COMPLETE_2] WITH [/SFCMPL',/SPARERR']
WHILE
        [COMPLETE 2]
        [/BRESET*PORTENB]
        THEN [IDLE]
WHILE
         [IDLE]
         [/BRESET*/BSELECT*/ICBUSY*/SFC1*/SFC0]
        THEN [IDLE]
                              Figure 4-25.5 PLUS105 SCSI CTL .SEE File (end)
```

```
@DEVICE TYPE
 PLUS153
 @DRAWING.....SIG APN88 02
 @REVISION......A
 @DATE.....8-8-88
 @SYMBOL.....U3
 @COMPANY......signETics
 @NAME.....ASP APPLICATIONS GROUP
 "<----> <--REFERENCE-->"
 "PINLABEL PIN # PIN_FCT PIN_ID OE_CTRL"
SD0 1 I
SD1 2 I
                                     10
11
12
13
14
15
16
SD1 2 I III -
SD2 3 I II2 -
SD3 4 I I3 -
SD3 4 I I3 -
SD4 5 I I4 -
SD5 6 I I5 -
SD6 7 I I6 -
SD7 8 I I77 -
PAR1 9 O BO DO
GND 10 OV GND -
PAR2 11 O B1 D1
ID0 12 I B2 D2
ID1 13 I B3 D3
ID2 14 I B4 D4
A-WONARB 15 O B5 D5
A-SELECTED 16 O B6 D6
PAREROR 17 O B7 D7
GEN-PAR 18 O B8 D8
REC-PAR 19 I B9 D9
REC-PAR 19
                                                   D9
            20 +5V
 VCC
                                      VCC
                                      Figure 4-26. PLUS153 SCSI ARB Pinlist
```

```
@COMMON PRODUCT TERM
MAX-ID-MATCH = ID1 * ID1 * ID2 * SD7;
@I/O DIRECTION
@LOGIC EOUATION
            = ID0 * /ID1 * /ID2 * SD1
A-SELECTED
             + /ID0 * ID1 * /ID2 * SD2
             + ID0 * ID1 * /ID2 * SD3
             + /ID0 * /ID1 * ID2 * SD5
+ /ID0 * /ID1 * ID2 * SD5
+ /ID0 * ID1 * ID2 * SD6
             + MAX-ID-MATCH ;
            = ID0 * /ID1 * /ID2 * SD1 * /SD2 * /SD3 * /SD4 * /SD5 * /SD6 *
A-WONARB
/SD7
             + /ID0 * ID1 * /ID2 * SD2 * /SD3 * /SD4
                                                                  * /SD5
                                                                            * /SD6
                                                                                     * /SD7
             + ID0 * ID1 * /ID2 * SD3 * /SD4 * /SD5
                                                                  * /SD6
                                                                            * /SD7
             + /ID0 * /ID1 * ID2 * SD4 * /SD5 * /SD6
                                                                  * /SD7
                     * /ID1 * ID2
* ID1 * ID2
                                       * SD5
             + IDO
                                                 * /SD6
                                                          * /SD7
             + /ID0
                                       * SD6
             + MAX-ID-MATCH ;
             " PARITY GENERATOR ( PAR1 AND PAR2 ARE PARTIAL TERMS )."
PAR1
            = SD0 * /SD1 * /SD2
+ /SD0 * SD1 * /SD2
             + /SD0 * /SD1 * SD2
             + SD0 * SD1 * SD2;
            = SD3 * /SD4 * /SD5
+ /SD3 * SD4 * /SD5
+ /SD3 * /SD4 * SD5
PAR2
             + SD3 * SD4 * SD5;
            PAR1 * PAR2 * /SD6 * /SD7
+ PAR1 */PAR2 * SD6 * /SD7
+ PAR1 */PAR2 * /SD6 * SD7
GEN-PAR
             + PAR1 * PAR2 * SD6 * SD7
             + /PAR1 */PAR2 * /SD6 * /SD7
                              * SD6 * /SD7
* /SD6 * SD7
             + /PAR1 * PAR2
             + /PAR1
                      * PAR2
             + /PAR1 */PAR2 * SD6 * SD7;
"PARITY ERROR GENERATOR. ERROR FLAGGED IF RECEIVED PARITY IS DIFFERENT
                      FROM CALCULATED PARITY."
PARERROR = /GEN-PAR * REC-PAR
             + GEN-PAR * /REC-PAR ;
                                 Figure 4-27. PLUS153 SCSI ARB .BEE File
```


+ /(/DMACYCLE * SYSSEL

```
@COMMON PRODUCT TERM
@I/O DIRECTION
@LOGIC EQUATION
BUFENBL = SDRVENB ;
                        SCSI CONTROLLER REGISTER MAP
                       /SYSSEL /SYSREAD
  /DMACYCLE
              CTLSCSI
                                          A1
                                                A0
                                                          FUNCTION
                                           0
                                                 0
                                                     READ STATUS REG.
     Н
                 X
                          L
                                    Τ.
     Η
                 Χ
                          L
                                    Н
                                           0
                                                 0
                                                     WRITE CONTROL REG.
                          L
                                   L
                                           0
                                                1
                                                     DATA BUFFER - READ
                 Χ
                                           0
                                                                    - WRITE
     Н
                          L
                                   Н
                                                1
                                                     -- NOT VALID --
                 Х
                                           1
     Н
                          L
                                                X
     Н
                 Χ
                                    Н
                                           1
                                                 Χ
                                                     SET TARGET ID
                                           Χ
                                                 Х
                                                     DMA : SCSI -> SYSTEM
                                           Χ
                                                 Х
                                                     DMA : SYSTEM -> SCSI
/RDSTAT = / ( /DMACYCLE * SYSSEL * /A0 * /A1 * SYSREAD ) ;
/WRCTRL = / ( /DMACYCLE * SYSSEL * /AO * /A1 * /SYSREAD ) ;
/RDDATA = / ( /DMACYCLE * SYSSEL * A0 * /A1 * SYSREAD
               + DMACYCLE * /CTLSCSI ) ;
/WRDATA = / ( /DMACYCLE * SYSSEL * A0 */A1 * /SYSREAD
               + DMACYCLE * CTLSCSI ) ;
               ID0-2 ARE THE TARGET ID CODE. THE ID REGISTER IS IMPLEMENTED
               IN THE PLUS153 BY SUPPLYING A SET TERM ( WITH DB0-2 ) AND A
               HOLD TERM ( WITH ID0-2 ).
                               * A1 * /SYSREAD
* A1 * /SYSREAD )
* A1 * /SYSREAD
         /DMACYCLE
ID0 =
                      * SYSSEL
                                                          * DB0
    + /( /DMACYCLE
                     * SYSSEL
                                                          * ID0 ;
                    * SYSSEL
                                                          * DB1
         /DMACYCLE
   + / ( /DMACYCLE * SYSSEL * A1 * /SYSREAD )
                                                         * ID1 ;
ID2 = /DMACYCLE * SYSSEL * A1 * /SYSREAD
                                                          * DB2
```

Figure 4-29. PLUS153 SCSI_DCD .BEE File

* ID2 ;

* A1 * /SYSREAD)



Signetics

Programmable Logic Design and Application Notes

Programmable Logic Devices

COMMUNICATIONS USING PLDs


PLD devices are particularly appropriate for digital communications. High speed sequencers form a natural means of handshaking and protocol checking, where PLAs and PALs can decode parallel header information. But, PLDs fill a need for digital communications—that of the emerging "standard". Once an initial specification for a communication protocol is agreed upon, the manufacturers may generate product to meet the current specification. This will probably not embody the final specification, but will closely resemble it. Unfortunately, the penalty for

having to redesign a gate array is relatively high should a communication protocol be implemented in one and require change. A PLD solution is an ideal embodiment for a product designed to implement an emerging standard because it can be changed when the "standard" changes.

This section covers several examples of data communication designs from whole protocols to simple scramblers—along with a customizable speech synthesis system using the Philips PCF8200.

The CCITT V.27 Scrambler – PLC18V8Z

The Radio Shack publication "Understanding Data Communications" contains a brief description of the CCITT V.27 recommended scrambler for use with 4800bps modems. The logic diagram for this circuit is a serial cascade of Dflip-flops with Exclusive—OR gates tapped in and out of the data stream. This class of machines implements transformations based upon Galois polynomials which are often described by linear sequential machines (i.e., D—FFs and EX—OR gates).



```
File Name: CCITT V.27 Scrambler
File Na...
Date: 10/31, 16:17:41
            10/31/1988
@DEVICE TYPE
PLC18V8Z
@DRAWING
@REVISION
@DATE
@SYMBOL
@COMPANY
@NAME
@DESCRIPTION
@PINLIST
+5V
@COMMON PRODUCT TERM "CPT LABEL = (expression)"
@I/O DIRECTION
    D7 = 1 .
@LOGIC EQUATION
    DOUT = X7*/X6*/DIN + /X7*X6*/DIN + X7*X6*DIN + /X7*/X6*DIN ;
    X1: D = DOUT;
    X2: D = X1
    X3: D = X2
 X4: D = X3
    X5: D = X4
    X6: D = X5
    X7: D = X6
                  Figure 5-2. V.27 Scrambler
```

A Novel Speech Synthesizer – PLS159A

The goal of this design was to build a small board capable of transmitting a variety of verbal messages in conjunction with the Philips PCF8200 speech synthesis part. Judicious partitioning resulted in a PLS159A acting as a controller, an HC4040 counter addressing an EPROM and an EPROM which provides binary data to the PCF8200.

The PLS159A transacts with the PCF8200 (Busy, etc.) and controls pulsing to the HC4040. Upon asserting the pushbutton, the cycle begins and proceeds to advance the HC4040 in increments 3FF (HEX) consecutive addresses. Figure 5-6 shows the system in full detail. The ultimate signal comes from the 8200, and drives an op—amp which delivers the final signal to the speaker. Various R—C combinations implement filtering and a simple pot provides the level control.

Programming the EPROM was accomplished by capturing short messages on audio tape, downloading to a Philips PCF8200 development system which analyzes and compresses the data for efficient storage. The result is an EPROM file which needs 3FF HEX addresses to store about 10sec of speech.

Figure 5-9 shows the AMAZE state equation entry file for the PLS159A which handshakes with the 8200 and 4040 parts.

```
@DEVICE TYPE
 PLS159
 GDRAWING
  .....PLD CONTROLLER FOR PCF8200 SPEECH SYNTHESIZER
 @REVISION
  .....PLS159
 @COMPANY
 ......SIGNETICS CORPORATION
 @NAME
 @DESCRIPTION
 This circuit will perform most functions required to achieve a minimum
 configuration PCF8200 speech synthesizer system.
     REV-A **Original design modified to work in existing ASP demo board. ***
      REV-B **Fixed SEE/BEE file to eliminate random quits during utterances
              1) Gray code for sequencer.
              2) Input latch added on REQ signal from PCF8200 for
                     synchronization
PER 1.5, 2.Byt.

I

-----FUNCTION------

ABEL PIN # PIN_FCT

¿_IN 1 CK
2 I

.Y 3 I I1

.D_ADRS 4 I I2

.C 5 I I3

.C 6 /B B0
6 MHZ_OUT 7 O B1


START_REQ 8 I B'
N/C 9 /B F
GND 10 OV
'C 11 /OE
12 /O
13 /O
14 /O
15 /B
6 /O
/O
/O
/O
/O
 FUNCTIONS PERFORMED:
              1. System Oscillator for sequencer controller
              2.Byte update control via EPROM to PCF8200
 "<----> <--REFERENCE-->"
 "PINLABEL PIN # PIN_FCT PIN_ID
                                                   OE CTRL"
                                                      DO
                                                     D1
                                                     D2
                                                      D3
                                                    EΑ
                                                      EA
                                                     EA
                                                     EA
                                                      EB
                                                     EB
                                                     EB
                                                      EB
             20
                         +5V
 VCC
                                      VCC
                                       Figure 5-3. PLS159A SPEECHB Pinlist
```

```
@COMMON PRODUCT TERM
@COMPLEMENT ARRAY
@I/O DIRECTION
D0 = 6 MHZ OUT;
@FLIP FLOP CONTROL
FC = 1;
@OUTPUT ENABLE
EA = 0;
EB = 0;
@REGISTER LOAD
@ASYNCHRONOUS PRESET/RESET
@FLIP FLOP MODE
@LOGIC EQUATION
" ** OSCILLATOR SECTION "
6 MHZ OUT = R C;
R_C = /(1);
"LATCH FOR SYNCHRONIZATION
OF PLD AND SPEECH CHIP
CLOCKS"
"CAPTURE OF REQ SIGNAL FROM
PCF8200"
/REQLATCH :
            K = /REQ;
               J = REQ;
 Figure 5-4. PLS159A SPEECHB
          .BEE File
```

```
@DEVICE SELECTION
SPEECHB/PLS159
"REVISION-B"
@STATE VECTORS
[SV2 , SV1 , SV0]
S0 = 000 B;
S1 = 011 B;
S2 = 101 B;
S3 = 110 B;
S4 = 100 B;
S5 = 010 B;
S6 = 111 B;
@INPUT VECTORS
@OUTPUT VECTORS
@TRANSITIONS
"Initialization at powerup"
WHILE [ SO ]
              ] THEN [ S1 ] WITH [ /RESET', WRITE', COUNT']
        TF [
WHILE [ S6 ]
        IF [ ] THEN [ S1 ] WITH [ /RESET', WRITE', COUNT']
"Wait for Start switch to be depressed"
        IF [/START REQ * /BUSY] THEN [ S2 ] WITH [/WRITE']
WHILE [ S2 ]

IF [ ] THEN [ S3 ] WITH [ WRITE' , COUNT']
WHILE [ S3 ]
        IF [ ] THEN [ S4 ] WITH [/COUNT']
WHILE [ S4 ]
        IF [REQLATCH] THEN [ S5 ] WITH [/WRITE', COUNT']
        IF [END ADRS + /BUSY] THEN [ S6 ] WITH [RESET']
WHILE [ S5 ]
        IF [/REQLATCH] THEN [ S3 ] WITH [ WRITE']
```

Figure 5-5. PLS159A SPEECHB .SEE File



CCITT Forward CRC Polynomial – PLUS405

This application illustrates the use of Signetics PLUS405 in a high speed data communication application. Typically, larger polynomial encoders permit error checking over larger data streams than smaller ones. This design implements a sixteenth order polynomial and the figures that follow show the logic equations to implement it.

```
File Name : crc gen
Date: 10/30/1987
Time: 11:10:56
LABEL
       ** FNC **PIN----- PIN **
                                    FNC ** LABEL
       ** CK ** 1-|
** I ** 2-|
                          |-28 **
|-27 **
                                    +5V **
                                           VCC
CLK
                                       ** G
N/C
       ** I
                                       ** N/C
N/C
            ** 3-|
                          1-26 **
       ** I ** 4-| P |-25 **

** I ** 5-| L |-24 **

** I ** 6-| U |-23 **
                                    I ** N/C
D
N/C
                                   I ** XI12
XI13
                                   I ** XI11
       ** I ** 7-| S |-22 **

** I ** 8-| 4 |-21 **
XT14
XI15
                    4
                          1-20 **
                                      ** XI9
       ** I ** 9-1
XT16
                                   INT ** RESET
       ** 0 ** 10-| 5 |-19 **
X016
       |-18 **
|-17 **
                                   0 ** X09
0 ** X010
X015
                                   0
      ** 0
XO14
     ** 0 ** 13-1
                           |-16 ** 0 ** XO11
XO13
                           |-15 ** 0 ** X012
      ** OV ** 14-|
GND
              Figure 5-7. PLUS405 Pinlist
```

```
File Name : crc_gen
Date: 10/30/1987
Time : 11:11:2
@DEVICE TYPE
PLUS405
@DRAWING
@REVISION
@DATE
ASYMBOT.
@COMPANY
GNAME
@DESCRIPTION
This design implements the CRC-CCITT forward polynomial with a PLUS405.
The CRC-CCITT forward polynomial is
    GF(X) = 1 + X^5 + X^{12} + X^{16}
    NOTE: Since this polynomial requires a 16-bit shift register together
    with an array of exclusive-OR's the contents of the 8 output flip-flops
    must be fed back into the array via the input pins of the PLUS405.
    Bits 1 to 8 are formed with the 8-bit internal register while the
    remaining 8-bits are made out of the 8-bit output register the outputs
    of which are externally fed back to inputs XI9 through XI16.
@INTERNAL FLIP FLOP LABELS
               X1, X2, X3, X4, X5, X6, X7, X8
@COMMON PRODUCT TERM
@COMPLEMENT ARRAY
@BURIED REGISTER CLOCK
@INIT/OE
               RO, R1, R2, R3, R4, R5, R6, R7,
    RESET =
               R8, R9, R10, R11, R12, R13, R14, R15;
                                      Figure 5-8. PLUS405 Design File
```

```
@LOGIC EQUATION
      X1 : INPUT = (D XOR XI16) * G
                  = (/D * XI16 * G) + (D * /XI16 * G); "*
  X1 : J = (D * /XI16 * G) + (/D * XI16 * G) ;
     K = /G + (D * XI16) + (/D * /XI16) ;
  X2 : J = X1
      K = /X1;
  X3 : J = X2
      K = /X2;
  X4 : J = X3
      K = /X3 ;
  X5 : J = X4
      K = /X4
  *****************
       X6 : INPUT = X5 XOR (( D XOR XI16 ) * G ) ; "
  X6 : J = (/G * X5) + (/D * X5 * XI16) + (D * X5 * XI16)
           (G * D * /X5 * /XI16) + (G * /D * /X5 * XI16) ;
      K = (/G * /X5) + (D * /X5 * XI16) + (/D * /X5 * /XI16)
          (G * D * X5 * /XI16) + (G * /D * X5 * XI16) ;
  X7 : J = X6
      K = /X6;
  X8 : J = X7
      K = /X7;
  XO9 : J = X8
      K = /X8 ;
  XO10:J = XI9
      K = /XI9;
  XO11:J = XI10 ;
     K = /XI10;
  XO12:J = XI11 ;
   K = /XI11;
 *****************
          X13 : INPUT = X12 XOR (( D XOR XI16 ) * G ) ; "
XO13 : J = (/G * XI12) + (/D * XI12 * XI16) + (D * XI12 * XI16) +
           (G * D * /XI12 * /XI16) + (G */D * /XI12 * XI16);
      K = (/G * XI12) + (D * /XI12 * XI16) + (/D * /XI12 * /XI16) +
           (G * D * XI12 * /XI16) + (G * /D * XI12 * XI16) ;
XO14 : J = XI13 ;
      K = /XI13;
XO15 : J = XI14 ;
      K = /XI14;
XO16 : J = XI15 ;
      K = /XI15;
                               Figure 5-9 PLUS405 Logic Equations
```

Signetics

Programmable Logic Design and Application Notes

Programmable Logic Devices

INSTRUMENTATION

Instrumentation typically involves the measurement and often the display of physical world parameters. Digital systems are particularly effective in this area and as usual, are largely limited only by the designer's imagination. This section describes three distinct examples of instrumentation provided from customer interaction.

The last design involves implementing the sweep circuitry for an oscilloscope. This can be extended and modified for similar designs.


Another example is a pulse width monitor which can be used in controlling power pulses, radio strength or radar/sonar timing measurements.

The first example shows several parts being used to make a plethysmographic monitor (i.e., heart rate). This has straightforward medical and health applications. The beauty of PLD solutions to these problems is simple—they are readily modifiable for adaption for another end use. The oscilloscope circuit could be altered for a laser light show. The pulse width monitor could pick up a timing pulse from

a disk and the plethysmographic system could be configured for animals rather than humans.

Heart Beat Monitor – PLS159A, PLS168A and PLS153

PLDs can be used as powerful building blocks in implementing the digital portion of a low cost portable heart beat monitor. This monitor is capable of displaying the heart beat in pulses per minute. Figure 6-1 shows the system block diagram. The digital portion is inside the dashed lines.



Operation

A transducer generates the heart beat pulses which are amplified and filtered. A level detector (one–shot) converts the amplified signals to TTL level signals. A 15 second timer is used to count the number of pulses in fifteen seconds. The number is multiplied by four to approximate the number of pulses in sixty seconds. A binary to BCD converter is used to display the result. A start switch resets the system and initiates the count.

Transducer

There are several techniques to monitor the blood flow in the peripheral system. These

techniques include optical plethysmography, ultrasonic flow measurement, piezoelectric pickup of peripheral arterial pulse, Korotkoff sounds, and recording the ECG.

Light plethysmography is used as the transducer in this design. The Tektronix light plethysmograph (Figure 6-2), operates by measuring the reflectance of skin to red light. As blood flows into the skin's capillary bed with each heart beat, the reflectance changes and this change is amplified and observed.


Amplifier/Filter


Signetics SA741 OP-amp is used as bandpass


filter with a gain of 20, and a frequency response of 1–200 Hz. Figure 6-3 shows the circuit diagram of the amplifier/filter stage.

Level Detector PLS153

The amplified signal is fed through the 'Level Detector' stage to create a square wave. A Schmitt-Trigger is used to generate the square wave. Application Note 18 in the Signetics PLD Data Manual explains the implementation of the Schmitt-Trigger in detail. A PLS153 is used to create the Schmitt Trigger. The PLS153 also holds the glue logic and other functions for the system explained further in this article (see Figure 6-4).














Figure 6-5. HTBT_153 Pinlist









Fifteen Second Timer

To create a fifteen second timer, a counter can be constructed with the PLS168A such that the number of counts is equivalent to 15 seconds. To achieve this, the 60Hz signal from the power line is passed through a transformer and a half—wave rectifier to create the clock input to the PLS168A (see Figure 6-7).

The number of counts needed to create the 15

second time interval is calculated in the following manner:


15 seconds = 15 X 60 (cycles/seconds) = 900

where '60' is the 60Hz clock input to the PLS168A.

Figure 6-8 shows the state transition diagram

for the counter. Figure 6-10 is the timing diagram to generate the number of pulses in 15 seconds.

The reset switch is used to initiate the count. This switch is debounced using the PLS153 of Figure 6-4. Figure 6-9 shows the circuit diagram of the debouncer. The design equations for the debouncer are shown as part of the design equation files of Figure 6-6.



If n = number of registers with feedback, then an n-bit counter can be created with any of Signetics sequencers using only n+1 terms.

Table 6-1 shows the implementation of the 15 second timer in the PLS168A. Input variable I0 is the input from the reset switch and '15_SEC' is the Count_End signal. At the 900th count (terms 12 & 13; HHHLLLHLL), output'0' goes to a logic low, indicating that the end of the count has been reached.

PLS168A							1		OP	TION	P/E		!	L!
E !														
R ! ! M !C!1 1		ARIABLE	! P	RESEN	T STAT	ľE	!	NI	EXT	STATE		10!	JTPUT	!
	9876			7 6 5	4 3 2	1	0!9	8 7	6 5	4 3	2 1	0!3	2 1	0 !
1!.!	,	,	- H!,		-,-	- L	H!-	-,-		-,-	- H	L!-		H!
2!.!	,	,	- H!,		-,- I	H	H!-	-,-		-,-	H L	L!-		H!
31.!	,	,	- H!,		-, L H	Н	H!-	-,-		-, H	L L	L!-	-	H!
4!.!	,													
5!.!	,	,	- H!,	L	Н,Н Н	Н	H!-	-,-	- H	L, L	L L	L!-		H!
6!.!	,	,	- H!,	- L H	Н,Н Н	H	H!-	-,-	H L	L,L	L L	L!-	-	H!
7!.!	,	,	- H!,	LHH	H,H H	Н	H!-	-,H	L L	L, L	L L	L!-		H!
8!.!	,	,	- H!- L,	н н н	Н,Н Н	H	H!-	H, L	L L	L, L	L L	L!-		H!
9!.!	,	,	- H!L H,	н н н	H,H H	H	H!H	L,L	L L	L, L	L L	L!-		H!
10!.!	,	,	- H!H H,	н н н	H,H H	H	H!L	L,L	L L	L,L	L L	L!-		H!
11!.!	,	,	- L!,		-,-	-	-!L	L, L	LL	L, L	L L	L!-		H!
12!A!			- L!H H,											
13!A!	,	,	- H!H H,											L!
14!!	,	,	! ,		,		1	,		,		!		!
15!!	,	,	1 ,		,		1	,		,		!		1
16!!	,	,	1 ,		,		1	,		,				!
17!!	,	,	! ,		,		1	,		,		!		!
18!!	,	,	! ,		,		1	,		,		!		!
19!!	,	,	! ,		,		1	,		,		1		!
20!!	,	,	! ,		,		1	,		,		!		!
******	******	*****	*****	****	*****	***	****	****	****	****	***	****	***	* *
43!A!	,	,	! ,		,		1	,		,		!		1
44!A!	,	,	! ,		,		1	,		,		!		!
45!A!	,	,	! ,		,		1	,		,		!		!
46!A!	,	,	! ,		,		!	,		,		1		!
47!A!	,	,	! ,		,		1	,		,		!		!
			R											1
			E											5
			5"											J
			E											S
			T											E
			Τ.											C

Each line (or term) in Table 6-1 is part of the state transition of the 15 second counter/timer. Term 11 is used to reset the counter when the 'RESET' switch goes low. With Don't Cares (–) in the 'Present State' column, any time reset becomes low, the counter resets to zero, regardless of the counter's current state. Terms 0–10 create the counter. The complement array is used to avoid any undefined states and also to force the counter to a known state upon power up.

To count the number of heart beats in 15 seconds, the end of count output of the 15 second timer is ANDed with the heart beat pulses. The result of this 'AND' function is the number of pulses in 15 seconds. This 'AND' function is also implemented in the PLS153 of Figure 6-4.

Pulse Counter and Multiply by Four

The resources on a single PLS159A can be used to construct the 'pulse counter' and 'multi-

ply by four' portion of the heart beat monitor. Figure 6-11 shows the block diagram of the Counter, Shift-Register, and an internal oscillator used as the clock for the shift-register.

To calculate the number of heart beats in one minute, the counter first counts the number of heart beats in 15 seconds. The counter is clocked by the 'NO_HRT_BT' signal which is the number of heart beats in 15 seconds.


When the fifteen seconds is over, the binary number stored in the counter is multiplied by four. The final value of this multiplication is the number of heart beats per minute.


The shift register multiplies the binary output of the counter by four by shifting this value twice to the left. During the 15 second period within which the counter is counting the number of heart beats, the shift register is disabled. When the 15 second period is over the counter is disabled and the shift register and the oscillator which clocks the shift register are enabled.

The shift register and the counter use the same flip-flops. When the PLS159A is in the 'counter' mode, the flip-flops are 'J-K' type. When the PLS159A is in the shift register mode, the flip-flops are switched to 'D' type.

CLOCK: The clock for the PLS159A is supplied from two sources. The number of heart beats clocks the device when the PLS159A is in the counter mode. The oscillator takes over when the device is in the shift register mode. The combinatorial outputs of the PLS159A can be used to create the oscillator. Application Note 13 (AN13) in the Signetics PLD Data Manual explains how this oscillator is implemented. Figure 6-12 shows the oscillator circuit diagram.

The oscillator output is enabled when the 15 second time period is over, so when the shift is over the outputs reflect the heart beat per minute in binary form. The maximum heart beat under extenuating circumstances can reach 300. Therefore, an 8-bit counter could measure a normal person's heart beat.






```
Binary Counter (Terms 0-7):
                              Counts the number of Heart Beat Pulses
Shift Register (Terms 8-14): Shifts the final count by 2 thus
                                multiplying the result by four.
Oscillator (Terms 16,17,D0,D1): Used to clock the PLS159 when in shift reg
                               mode
Flip Flop Control (FC):
                                Switches the flip flop mode into 'D'
                     T !
                     !A:A:A:A:A:A:A!
R!! I ! B(i) ! Q(p)
                                 ! O(n)
                                                     ! B(o) !
   !_!3_2_1_0!3_2_1 0!7 6 5 4 3 2 1 0!7 6 5 4 3 2 1 0!3 2 1 0!
 0!-!-H-H!---!--,---L!---,---0!...!
1!-!-H-H!---!---,---L!----,--0-!...!
 2!-!- H - H!- - - -!- - - -, - - L L!- - - -, - 0 - -!. . . .!
 3!-!- H - H!- - - -!- - - -, - L L L!- - - -, 0 - - -!. . . .!
  4!-!- H - H!- - - -!- - -,L L L!- - - 0,- - - -!. . . !
 5!-!- H - H!- - - -!- - L, L L L!- - 0 -, - - - -!. . . !
  6!-!- H - H!- - - -!- - L L, L L L!- 0 - -, - - - -!. . . !
  7!-!- H - H!- - - -!- L L L, L L L!O - - -, - - - -!. . . .!
 9!-!- H - L!- - - -!- - - -, - - - H!. . . . . . . A . .!. . . .
10!-!- H - L!- - - -!- - - -, - H -!. . . ., A . . .!. . .!
11!-!- H - L!- - - -!- - - -, - H - -!. . . A, . . .!. . .!
 12!-!- H - L!- - - -!- - - -, H - - -!. . А .,. . . .!. . . .!
 13!-!- H - L!- - - -!- - - H,- - - -!. A . .,. . . ! . . . !
 14!-!- H - L!- - - -!- - H -,- - - -!A . . .,. . . ! . . . !
 15!!
 16!-!- - - -!- - H -!- - - -,- - - -!- - - -,- - - -!. . . A!
 17!-!- - - -!- - - -!- - - -,- - - -!- - - -,- - - -!. . A .!
Fc!-!- - H!- - - -!- - -,- - -!
Pb!-!- L - -!- - - -!- - - - -!
Rb! !
Lb! !
Pa!-!- L - -!- - - -!-
Ra!!.
La!!
D3! 1
D2!!
D1!-!- - - -!- - - H!- - - -,- - - -!
D0!-!- - - L!- - - -!- - - -,- - - -!
                Table 6-2. Binary Counter, Shift Register, and Oscillator
```

Table 6-2 illustrates the implementation of the binary counter, shift register, and oscillator. 'l2' is the RESET signal input. 'l0' is the '15_SEC' signal input used to enable-disable the counter, shift register, and oscillator. 'B0' is the oscillator output used to clock the PLS159A when it is in the shift register mode.

Binary to BCD Converter

82S135 and 82S126 PROMs can be used to generate BCD code to drive three 7–segment displays. A look—up table is programmed in the PROMs to generate the correct BCD number. The 7–segment displays have their own decoders and display drivers. Figure 6-13 shows the overall system diagram.



The Pulse Width Monitor – PLS168

Simple in concept, this design was implemented at the fuse table level. Its elementary operation is that of a programmable timer which can detect a pulse condition exceeding a specified duration. This customer used the part in a system where the timer prevented the destruction of expensive, high—power equipment.

@DEVICE TYPE
PLS168/BCA
@DRAWING
TRANSMITTER FAULT MONITOR
@REVISION
@DATE
4/4/1988
@COMPANY
@NAME
@NAME
@DESCRIPTION

THIS DEVICE IS PROGRAMMED TO FUNCTION AS 12-BIT UP COUNTER RUNNING AT 2.5MHZ (400 NS BIT RESOLUTION / TOT. CNT OF 1.64 MS). THE COUNTER IS DYNAMICALLY CONTROLLED TO START COUNTING WHEN THE (SIGIN) INPUT IS ASSERTED HIGH.

IF THE (SIGIN) INPUT IS NOT NEGATED BY THE TIME THE COUNTER ELAPSES TO 105 US THE COUNTER ASSERTS THE ALARM OUTPUT HIGH. AT THIS POINT THE COUNTER CONTINUES TO COUNT UNTIL AN ELAPSED TIME OF 922 US + 105 US (1.027 MS).

THIS COUNT VALUE RESETS THE COUNTER BACK TO ZERO WHERE IT THEN IDLES UNTIL THE NEXT (SIGIN) INPUT REQUEST.

DURING THE 922 US CYCLE COUNT THE SEQUENCER SAMPLES THE (SIGIN INPUT) EVERY 53 US. IF THE INPUT IS ASSERTED HIGH THE SEQUENCER WILL SET THE ALARM FLAG AND TIME OUT FOR THE SPECIFIED ALARM TIME OUT CYCLE (922 US).

Figure 6-14.1 PLS168/BCA TRFDECT .BEE File (continued)

					2	1		-12 E		COUN	TER-			>		
					0 4 8	0 2 4	5 1 2	2 5 6	1 2 8	6 4	3	1 6	8	4	2	1
					Q 1 1	Q 1 0	9	Q 8	Q 7	Q 6	Q 5	Q 4	Q 3	Q 2	Q 1	Q 0
(TIME)	(DETECT E	POINTS)	(MODE) (ST)	(F1 F0	P9 P	3 P7	P6	P5 P	4 P3	P2	P1 F	0)				
		LY * /AIN			L						L	L	L	L	L	L
10 US	/(SIGIN)	* CNT = 25	TEST	P	L	L					L	- Н	Н	L	L	Н
105 US	(SIGIN)	* CNT = 256		1 P	L	L	L	L	Н	Н	Н	Н	Н	Н	Н	Н
155 US	(SIGIN)	* CNT = 388	ALARM	1 P	L	L							L	Н	L	L
208 US	(SIGIN)	* CNT = 520	ALARM		L								Н	L	L	L
261 US	(STGTN)	* CNT = 653	AT.ARM	/ P	L			L			L		Н	Н	L	Н
314 US	(SIGIN)	* CNT = 785	ALARM		L	L	Н	Н	L	L	L	_	L	L	L	Н
367 US	(SIGIN)	* CNT = 918	ALARM	1 P	L	L	Н				L	Н	L	Н	Н	L
420 US	(SIGIN)	* CNT = 10	50 ALARM	1 P	L	Н	L	L	L	L	L	Н	Н	L	Н	L
473 US	(SIGIN)	* CNT = 11	82 ALARM	1 P	L	Н	L	L				Н	Н	Н	Н	L
526 US		* CNT = 13		1 P	L			Н				L	L	L	Н	Н
579 US	(SIGIN)		48 ALARM	1 P	L			Н	Н	L	Н	L	Н	L	L	L
632 US		* CNT = 15		1 P	L	Н		L	L	L	Н	L	Н	Н	L	L
685 US	(SIGIN)	* CNT = 17	12 ALARM	1 P	L	Н		L	Н	L	Н	Н	L	L	L	L
738 US	(SIGIN)	* CNT = 18	45 ALARM		L	Н		Н	L	L	Н	H	L	Н	L	Н
791 US		* CNT = 19		1 P	L		Н	Н	Н	L	Н	Н	Н	L	Н	L
844 US	(SIGIN)		10 ALARM	1 P	Н	L	L	L	L	L	Н	Н	Н	Н	Н	L
897 US	(SIGIN)	* CNT = 22			Н	L	L	L	Н	Н	L	L	L	L	Н	L
955 US	(NORMAL)	* CNT = 2387		AL P	Н	L	L	Н	Н	L	Н	L	L	L	Н	Н
	E	ND NORMAL S	IGNAL MODE	CHECK	AND T	IME	OUT-					_				
		Ei	-14.2 PLS168	/DOA T	JEDEO.	T D.	e e	- /	41	- 41						

		BEG	IN TEST MODE	E CHECK-												
1.578 MS	JUMP	CNT = 39	45 TEST	N	Н	Н	Н	Н	L	Н	Н	L	Н	L	L	Н
1.582 MS	(SIGIN)	* CNT = 39	57 ALARM	Р	Н	Н	Н	Н	L	Н	Н	Н	L	Н	L	Н
1.588 MS	(SIGIN)	* CNT = 39	70 ALARM	Р	Н	Н	Н	Н	Н	L	L	L	L	L	Н	L
1.592 MS	(SIGIN)	* CNT = 39	82 ALARM	P	Н	Н	Н	Н	Н	L	L	L	Н	Н	Н	L
1.597 MS	(SIGIN)	* CNT = 39	94 ALARM	Р	Н	Н	Н	Н	Н	L	L	Н	Н	L	Н	L
1.602 MS	(SIGIN)	* CNT = 40	06 ALARM	Р	Н	Н	Н	Н	Н	L	Н	L	L	Н	Н	L
1.607 MS	(SIGIN)	* CNT = 40	19 ALARM	Р	Н	Н	Н	Н	Н	L	Н	Н	L	L	Н	Н
1.612 MS	(SIGIN)	* CNT = 40	32 ALARM	Р	Н	Н	Н	Н	Н	Н	L	L	L	L	L	L
1.617 MS	(SIGIN)	* CNT = 40	44 ALARM	P	Н	Н	Н	Н	Н	Н	L	L	Н	Н	L	L
1.622 MS	(SIGIN)	* CNT = 40	57 ALARM	Р	Н	Н	Н	Н	Н	Н	L	Н	Н	L	L	Н
1.627 MS	(SIGIN)	* CNT = 40	69 ALARM	P	Н	Н	Н	Н	Н	Н	Н	L	L	Н	L	Н
1.632 MS	(SIGIN)	* CNT = 40	82 ALARM	Р	Н	Н	Н	Н	Н	Н	Н	Н	L	L	Н	L
1.636 MS	(SIGIN)	* CNT = 40	90 ALARM	P	Н	Н	Н	Н	Н	Н	Н	Н	Н	L	Н	L

-----END TEST MODE CHECK-----

IF THE (SIGIN) INPUT IS NEGATED BEFORE THE ELAPSED TIME OF 105 US THE COUNTER CONTINUES TO COUNT UNTIL THE ELAPSED TIME OF 955 MS. AT THIS POINT THE COUNTER AGAIN RESETS ITSELF UNTIL THE NEXT (SIGIN) INPUT REQUEST.

DURING TEST MODE, THE SEQUENCER SAMPLES THE SIGIN PULSE AT A REPETITION RATE OF 72 US. WITH A PULSE WIDTH OF 6.5 US. THE TIME OUT FOR AN ALARM DETECT IS BASED ON SAMPLE A CHECK ONCE EVERY 5 US, AFTER THE 10 US SAMPLE FOR SIGIN NEGATION. END

Figure 6-14.3 PLS168/BCA TRFDECT .BEE File (end)

```
File Name : TRFDECT
Date: 9/14/1988
Time: 13:24:44
Cust/Project
Date
Rev/I. D.
                 - 4/4/1988
PLS168
                                                            OPTION P/E
R ! ! INPUT VARIABLE ! PRESENT STATE ! NEXT STATE !OUTPUT !
M !C!1 1 -----

      1 ! 1 0 9 8 7 6 5 4 3 2 1 0!9 8 7 6 5 4 3 2 1 0!9 8 7 6 5 4 3 2 1 0!3 2 1 0!

      0!A! - - -, - H -, L L - -! -, - - -, - - -!L L, L L L, L L L, L L L! - H - -!

      1!.! - - -, - - -, H - - -! -, - - -, - - L! -, - - -, - - H! - - -!

 2!.!- - -,- - -,H - - -!- -,- - L H!- -,- - -,- H L!- - -!
 3!.!- - - -,- - - -,H - - -!- -,- - - -,- L H H!- -,- - - -,- H L L!- - -!
 4!.!- - -,- - -,H - - -!- -,- - -,L H H H!- -,- - - -,H L L L!- - - -!
 5!.!- - - -,- - - -,H - - -!- -,- - - L,H H H H!- -,- - - H,L L L!- - - -!
 6!.!- - - -,- - - -,H - - -!- -,- - L H,H H H H!- -,- - H L,L L L!- - - -!
 7!.!- - - -,- - - -,H - - -!- -,- L H H,H H H H!- -,- H L L,L L L!- - -!
 8!.!- - - -,- - - -,H - - -!- -,L H H H,H H H H!- -,H L L L,L L L!- - - -!
 9!.!- - - -,- - - -,H - - -!- L,H H H H,H H H H!- H,L L L,L L L L!- - - -!
10!.!- - -,- - -,H - - -!L H,H H H H,H H H H!H L,L L L,L L L!- - -!
11!.!---,---,H--L!H H,H H H,H H H H!L L,L L L L,L L L L!--- H!
12!.!- - - -,- - - -,H - L H!H H,H H H H,H H H H!L L,L L L L,L L L L!- - H L!
13!.!- - - -,- - - -,H - H H!H H,H H H H,H H H H!L L,L L L,L L L,L L L!L L L!
14!.!----,----!--,----!--,----!--,----!--,----!-
               Table 6-3.1 Transmitter Fault Detector Program Table (continued)
```

```
15!A!- - - -,- - H -,H L L L!L L,H H H H,H H H H!L H,L L L,L L L L!H - L L!
16:A!- - - -,- - - -,H L H L!L H,H L L H,L L L H!L L,L L L L,L L L L!L L L L!
18!A!- - - -,- - H -,H L H L!L L,H H L L,L L H L!L H,L L L L,L L L L!H - L L!
19!A!- - - -,- - L -,H L L L!L L,L L L H,H L L H!H H,L H H L,H L L H!- - H H!
20!A!- - - -,- - H -,H L L L!L H,H L L L,L H L L!L H,L L L L,L L L L!H - L L!
21!A!- - - -, - - H -, H L L L!H L, L L L, H L L L!L H, L L L, L L L L!H - L L!
22!A!- - - -,- - H -,H L L L!H L,H L L L,H H L H!L H,L L L L,L L L L!H - L L!
23!A!- - - -,- - H -,H L L L!H H,L L L H,L L L H!L H,L L L L,L L L L!H - L L!
24!A!- - - -,- - H -,H L L L!H H,H L L H,L H H L!L H,L L L L,L L L L!H - L L!
25!A!- - - -,- - H -,H L L H!L L,L L L H,H L H L!L H,L L L L,L L L!H - L L!
26!A!- - - -,- - H -,H L L H!L L,H L L H,H H H L!L H,L L L L,L L L L!H - L L!
27!A!- - - -, - H -, H L L H!L H, L L H L, L L H H!L H, L L L L, L L L!H - L L!
28!A!- - - -,- - H -,H L L H!L H,H L H L,H L L L!L H,L L L L,L L L L!H - L L!
29!A!- - - -, - H -, H L L H!H L, L L H L, H H L L!L H, L L L, L L L!H - L L!
30!A!----,--H-,H L L H!H L,H L H H,L L L L!L H,L L L L,L L L L!H - L L!
31!A!----,--H-,H L L H!H H,L L H H,L H L H!L H,L L L L,L L L L!H - L L!
32!A!- - - -,- - H -,H L L H!H H,H L H H,H L H L!L H,L L L,L L L!H - L L!
33!A!- - - -,- - H -,H L H L!L L,L L H H,H H H L!L H,L L L L,L L L L!H - L L!
34!A!----,--H-,H L H L!L H,L H L H,L L H H!L H,L L L L,L L L L!H - L L!
35!A!- - - -, - H -, H L H L!L H, L H H H, H L L H!L H, L L L, L L L!H - L L!
36!A!----,--H-,H L H H!H H, L H H H, L H L H!L H, L L L L, L L L L!H - L L!
37!A!----,--H-,H L H H!H H,H L L L,L L H L!L H,L L L L,L L L L!H - L L!
38!A!---,--H-,H L H H!H H,H L L L,H H H L!L H,L L L L,L L L L!H - L L!
39!A!- - - -,- - H -,H L H H!H H,H L L H,H L H L!L H,L L L L,L L L L!H - L L!
40!A!- - - -,- - H -,H L H H!H H,H L H L,L H H L!L H,L L L L,L L L L!H - L L!
41!A!----,--H-,H L H H!H H,H L H H,L L H H!L H,L L L L,L L L L!H - L L!
43!A!----,--H-,H L H H!H H,H H L L,H H L L!L H,L L L L,L L L L!H - L L!
44!A!----,-- H -,H L H H!H H,H H L H,H L L H!L H,L L L L,L L L L!H - L L!
45!A!- - - -,- - H -,H L H H!H H,H H H L,L H L H!L H,L L L L,L L L L!H - L L!
46!-!- - - -,- - - -,- - - -!- -,- - - -!- -,- - - -!- -,- - - -!- - -!-
47!-!- - -,- - -,- - - -!- -,- - - -!- -,- - - -!- -,- - - -!- - -!-
    NNNNNSNSAII
                              N N N N
                                  / / / /
                                                      NNNNASFF
    /////I/IIAA
                                                      ////LIAA
    CCCCCGGGN10
                                    cccc
                                                      CCCCAG10
                                                              ML
                  Y
                                                                Y
                                                               0
                  N
              Table 6-3.2 Transmitter Fault Detector Program Table (end)
```

Scope Trace Sweep Circuit – PLS153 and PLS155

Jerry Liebler submitted this spectrum analyzer sweep circuit design.

```
@DEVICE TYPE
PLS153
@DRAWING
@REVISION
@DATE
1-27-88
@SYMBOL
@COMPANY
Tektronix Inc.
@NAME
sweep logic
@DESCRIPTION
This chip forms the sweep logic circuit for the 2710
spectrum analyzer.
@PINLIST
"<----> <--REFERENCE-->"
"PINLABEL PIN # PIN_FCT PIN_ID OE_CTRL"
        Figure 6-16. PLS153 SWP Pinlist
```

```
@COMMON PRODUCT TERM
SWPTRIG=/(EOSWP- )+/((STOUT*/STIN)+/AUTOTRIG-)+/SSDFFO+/RSFF12;
@1/O DIRECTION
DO=RSFF12;
D8=/SWPGATE*/SGDIS;
@LOGIC EQUATION
RSFF12=(EOSWP- )*/RSFF11;
RSFF11=/HOLDOFF*/RSFF12;
SWPGATE = SGDFFI*/SWPTRIG + /MANSWP- + SWPGATE*(EOSWP- )*SWPTRIG;
SWPGATE-=0;
SGDFF1= SWPTRIG+/MANSWP-+(/SWPTRIG*(EOSWP- )*SGDFF1);
HOLDOFF = 0;
STOUT=((TRIGIN*/SLOPE)+(/TRIGIN*SLOPE));
SSDFF0= SSDFF1*SSTRIG+/SINGLSWP+(EOSWP- )*/SSTRIG*SSDFF0;
SSDFF1= /SSTRIG+/SINGLSWP+(EOSWP- )*SSTRIG*SSDFF1;
```

Figure 6-17. PLS153 SWP .BEE File

```
@DEVICE TYPE
  PLS155
  @DRAWING
  @REVISION
  GDATE
  @SYMBOL
  @COMPANY
  @NAME
  @DESCRIPTION
  "<----> <--REFERENCE-->"

        NPINLABEL
        PIN #
        PIN_FCT
        PIN_ID
        OE_CT

        HCLOCK
        1
        CK
        CK
        -

        VSYNC
        2
        I
        IO
        -

        ENDVSWP
        3
        I
        II
        -

        VIDMON
        4
        I
        I2
        -

        TC-
        5
        I
        I3
        -

        VIDMON-
        6
        O
        BO
        DO

        PE-
        7
        O
        BI
        DI

        VMTST
        8
        I
        B2
        D2

        FMVID-
        9
        I
        B3
        D3

        GND
        10
        OV
        GND
        -

        N/C
        11
        /OE
        /OE
        -

        SWPGATE
        12
        B
        B4
        D4

        BLANK
        13
        O
        B5
        D5

        OBAR
        14
        /O
        F0
        EA

        ST1
        16
        /O
        F2
        EB

        TRIGGER
        17
        /O
        F3

   "PINLABEL PIN # PIN_FCT PIN_ID OE_CTRL"
                                                                                                                                         B4 D4
B5 D5
F0 EA
F1 EA
F2 FP
                                                                                                                                                                                         EB ;
                                                                                                                                                                                        D6 ;
                                                      20 +5V
  VCC
                                                                 Figure 6-18. PLS155 SWP3 Pinlist
```

August 1989 770

```
@COMMON PRODUCT TERM
@COMPLEMENT ARRAY
@I/O DIRECTION
d4=blank;
@FLIP FLOP CONTROL
@OUTPUT ENABLE
@REGISTER LOAD
@ASYNCHRONOUS PRESET/RESET
@FLIP FLOP MODE
m0=1;
@LOGIC EQUATION
blank=(/(/qbar)+hsout)*vidmon+vmtst*/fmvid-;
swpgate=0;
hsout=hsin'
vidmon-=/vidmon;
/qbar : j=vsync*vidmon;
  k=endvswp+/vidmon;
/trigger: d=/(tc-);
pe-=/(st0*/st1*vsync);
```

Figure 6-19. PLS155 SWP3 .BEE File

```
@DEVICE SELECTION
swp3/pls155
@STATE VECTORS
    [st1,st0]
   odd =00b;
stb1 =01b;
stb2 =10b;
even =11b;
@INPUT VECTORS
   [VSYNC]
           =1b;
    notvi =0b;
@OUTPUT VECTORS
@TRANSITIONS
while [odd]
if [vi] then [stb1]
if [notvi] then [odd]
while [stb1]
if [vi] then [stb2]
if [notvi] then [odd]
while [stb2]
if [vi] then [stb1]
if [notvi] then [even]
while [even]
if [vi] then [stb1]
if [notvi] then [even]
```

Figure 6-20. PLS155 SWP3 .SEE File

Signetics

Programmable Logic Design and Application Notes

Programmable Logic Devices

GENERAL APPLICATIONS

Motor Stepper Controller with the PLS155

Jim Greene designed and constructed the Stepper Motor Controller. This circuit allows control of bidirectional stepper motors for both single wave drive (only one phase on at a given time), and 2–phase drive (2 phases on at a time).

 The clock (CLK) input can be driven by a continuous pulse train for steady rate movement or a clock that ramps up and down to provide for acceleration and deceleration. (Dependent on application.)


- With the addition of control to another flip-flop, the PLS155 could provide half-step capability for finer resolution.
- The preset and reset terms on the flipflops could be used with a product term to provide an inhibit function if necessary.
- 4. The PLS155 will probably not have enough current drive for most stepper motor applications, therefore, a power buffer like the one shown (Figure 7-5) could be used. The components and values can be changed to fit your application.

Figure 7-2 shows the PLS155 pinlist, Figure 7-4 the logic diagram, Figure 7-3 corresponding design file, and Table 7-1 the final program table.


CLK			SIGNAL NAME				
	1PHASE A		1РНА				
	1PHASE B		1РНВ				
	1PHASE C		1РНС				
	1PHASE D		TPHD				
	2PHASE A		2РНА				
	2PHASE B		2РНВ				
	2PHASE C						
	2PHASE D						
Figure 7-1. Clock Phases for Stepper Control							

```
@DEVICE TYPE
PLS155
@DRAWING
@REVISION
@DATE
@SYMBOL
@COMPANY
@NAME
@DESCRIPTION
@PINLIST
"<----> <--REFERENCE-->"
                          D0 ;
                             D2 ;
                            EA ;
VCC
         20
              +5V
                       VCC
            Figure 7-2. PLS155 STEP Pinlist
```

```
@COMMON PRODUCT TERM
@COMPLEMENT ARRAY
@I/O DIRECTION
d0-1; d1=1; d2=1; d3=1; d4=1; d5=1; d6=1;
d7=1:
@FLIP FLOP CONTROL
@OUTPUT ENABLE
ea=0;
@REGISTER LOAD
 1a = 0:
@ASYNCHRONOUS PRESET/RESET
ra=/1:
@FLIP FLOP MODE
m1 = 1; m0 = 1;
@LOGIC EQUATION
1phd = 1q*2q;
1phc = 2q*/1q;
1phb = /2q*/1q;
1pha = /2q*/1q;
2phd = (1q*2q)*(2q+1q)+(/1q+/2q)*(/2q*/1q);
2phc = (2q*/1q)*(/1q+/2q)+(/2q+1q)*(1q*2q);
2phb = (/2q*1q)*(/2q+1q)+(2q+/1q)*(2q*/1q);
2pha = (/2q*/1q)*(2q+/1q)+(2q+1q)*(/2q*1q);
/2q :j = /dir*/1q+1q*dir;
    k = /dir*/1q+1q*dir;
/1q : j = 1;
     k = 1;
                  Figure 7-3. PLS155 STEP .BEE File
```



```
File Name : STEP
Date : 9/14/1988
Rev/I. D.
PLS155
                     !FF TYPE! EB EA !
                                         POLARITY
т !
                     !A:A:.:.!O :. !.
                                     !H:H:H:H:H:H:H:H:H
               B(I) ! Q(p) ! Q(n) ! P ! R !
M !C!----
                         ----!B!A!B!A!----
--! !3 2 1 0!7 6 5 4 3 2 1 0!3 2 1 0!3 2 1 0!. .!. .!7 6 5 4 3 2 1 0!
 0!A!----!----L L!O O --!...!A ..., A A ..!
 1!A!---!---L H!O O --!. . . .!. A . .,. A A .!
 5!A!----!--- L!O O O -!...!....!
 7!A!O O O O!O O O,O O O O!O O O!O O O!A A A A!A A A A,A A A A!
31!0!0 0 0 0!0 0,0 0 0 0!0 0,0 0 0 0!0 0 0 0!A A A A!A A A,A A A A!
Fc!0!0 0 0 0!0 0,0 0 0 0!0 0,0 0 0!
Lb!.!0 0 0 0!0 0,0 0 0 0!0 0,0 0 0 0!
La!.!0 0 0 0!0 0,0 0 0 0!0 0,0 0 0 0!
D7!-!- - - -!- -,- - - -!0 0,0 0 0 0!
D6!.!- - - -!- -,- - - -!- -,-
D5!-!- - - -!- -,- - - -!- -,-
D4!.!- - - -!- -,- - - -!- -,- - -!
D3!-!- - - -!- -,- - - -!- -,- - - -!
D2!-!- - - -!- -,- - - -!- -,- - -!
D1!-!- - - -!- -,- - - -!- -,- - -!
DO!.!- - - -!- -, - - - -!- -, - - -!
    N N N D 1 1 1 1 2 2 2 2 N N 2 1 N N 2 1
    /// I P P P P P P P P P / / Q Q / / Q Q
                                      PPPPPPP
    СССКИНИНИНИНСС
                                       ннннннн
          DCBADCBA
                                       DCBADCBA
               Table 7-1. STEPPER CONTROL Program Table
```



Signetics

Programmable Logic Design and Application Notes

Programmable Logic Devices

SECURITY SYSTEMS – Neil Kellet


Security systems are typified by some sensing circuit (perceiving intrusion, fire, etc.) and some basic activation circuit. Simple logic or complex sequences may be used with the sensors or the alarm generation circuits. Two of the following solutions utilize the innate capability of CMOS EPLDs to work well with RC timing circuits in generating time delays and relaxation oscillators.


A Programmable Alarm System – PLS168

This design illustrates an expansion of the design using additional PLS153 devices which were deleted in this version for brevity.

A basic alarm controller can be considered as a black box with several inputs and several outputs (Figure 8-1). Some inputs are used for detection and others for

control. Detect inputs are driven from a variety of alarm transducers such as reed switches, smoke detectors, pressure mats, etc. An ARM input switches the system into a state which allows detection of the various alarm conditions and a RE-SET input is used to reset the system after an alarm has been triggered and dealt with or on re-entering the protected area. Outputs from the system include a sounder, a beacon and status indicators.





Detect inputs can be divided into timed, untimed, fire and personal attack inputs. Timed circuits allow entry/exit delay circuits for front and rear doors, to delay operation of the alarm for approximately 16 seconds. Untimed circuits cause the alarm to operate immediately when an alarm condition occurs. These would be used to protect unusual means of entry, such as windows. Both the timed and untimed circuits should operate only if the system is armed.

The personal attack circuit is a special case untimed circuit and should operate only when the system is disarmed. The fire—detect circuit is again a special case untimed circuit and should operate regardless of whether the system is armed or not.

Outputs from the controller drive an external sounder and beacon. After 128 seconds, the sounder should turn off if the alarm has been triggered by either a timed or general untimed circuit. However, when a fire or personal attack triggers the system, the sounder should not turn off until the system is reset and the alarm condition removed.

State Machine Implementation

This design is best implemented as a state machine. The state diagram is derived from the verbal system description. Please note from

Figure 8-2 the controller can be in one of six possible states. Examine the transitions from ST_NULL as an example. If a personal attack or fire condition occurs while in this state, a transition to ST_- 1 takes place as indicated by the arrows on the diagram. Also at this time the sounder and beacon are activated, thus giving the alarm. If the fire and personal attack conditions have not occurred and the ARMSWITCH is set, then a transition to ST_- 0 takes place.

Similarly, other arrows on the state diagram represent transitions between other states when specified input conditions occur. Output parameters are shown to the right of the slash line. Where there are no output parameters specified in a transition term, this indicates that no output changes are desired during this transition. That is, an output will hold its present value until told to change.

PLD Implementation

Having defined the desired system operation it is now time to select the required device to implement the desired system function from the PLD Data Manual. In this case, the device selected is the PLS168. Figure 8-3 shows the pinning information for the alarm controller. A 10-bit counter within the controller produces the entry/exit and sounder turn-off delays since this makes more efficient use of the PLD facili-

ties than implementing the delays as part of the state machine. This counter uses seven internal registers with feedback and three without. For those registers without feedback, external wiring feeds their outputs back into the device to complete the 20-bit counter. Pins five to ten are used for this purpose. OutputT7 also forms part of the counter.

Three other registers form the state registers and are labeled SR0, SR1 and BEACON. State vectors for these registers have to be chosen with care to ensure that the beacon output is activated at the correct time. Other inputs and outputs are as already discussed. Note that the PR/OE pin is not used. This pin must be tied to ground in the final circuit.

Once the pin information has been entered, any Boolean equations desired can be defined using the Boolean equation entry (.BEE) file of AMAZE. List 1 shows the .BEE file for the alarm controller. Any internal registers used in either the Boolean equation or state equation entry file are given names in this file, in this case 1 to 16. Equations for the 10-bit counter are entered after the title line @LOGIC EQUATION, using registers t1 to t10in. Register SR0 halts and clears the counter while the controller is in certain states. This needs to be considered when defining the state vectors.


State Equation Entry


The state equation entry (.SEE) file of AMAZE uses a state-transition language, parameters of which are taken directly from the state diagram. Information is entered into this file in a free format. The only points to remember are that the square brackets should be used throughout to define the state registers and transitions, semicolons should be used to mark the end of vector definition and apostrophes should be used to indicate a registered output. State vectors can be defined in the state equation entry file as shown in List 2. State vectors are simply a means of labeling an arrangement of state registers which can be used later to define state transitions. Because we are using the BEACON output register as a state register also and SR0 is being used to halt and clear the 10—bit counter, particular care must be taken in defining the state vectors in this instance.

From the state diagram, the counter must begin counting during states ST_0 , ST_2 and ST_3 and it must be cleared during states ST_1 , ST_4 and ST_NULL . State ST_NULL represents the power—up state of the PLS168 in which all register outputs are at logic one. Thus the inactive state of the counter is defined as being when SR0 is at logic one, therefore, SR0 must be at this level during states ST_1 and ST_4 and at logic zero during other states. The alarm beacon is considered to be active by an active—low signal and must be activated during states ST_3 and ST_4 . Register SR1 must therefore be chosen to ensure mutual exclusiv-

ity between state vectors. Input and output vectors can be defined in the same manner in terms of input and output label names. In this case, however, the label names are used directly. State transitions can now be derived directly from the state diagram. This is done using a Pascal-like state transition language and can clearly be seen in Table 8-1. Note that multiple IF statements can be implemented as such or as CASE statements as shown. Entry/exit and sounder turn-off delay times are represented as a decoding of the 10-bit counter states. Thus to get the desired 16 second entry/exit delay. t7 must be decoded and to achieve the 128 second sounder turn-off delay t10in must be decoded

```
STATE MACHINE AND TIMER FOR BURGLAR ALARM
@INTERNAL SR FLIP FLOP LABELS
t6 t5 t4 t3 t2 t1
@LOGIC EQUATION
t1: s = /t1*/sr0 ;
    r = t1*/sr0
     + sr0 ;
t2 s = t1*/t2*/sr0;
   r = t1* t2*/sr0
        sr0:
t3 s = t1* t2*/t3*/sr0;
   r = t1* t2* t3*/sr0;
        sr0
t4 s = t1* t2* t3*/t4*/sr0;
         t1* t2* t3* t4*/sr0
        sr0;
        t1* t2* t3* t4*/t5*/sr0 ;
   S =
        t1* t2* t3* t4* t5*/sr0
        sr0
t6 s =
        t1* t2* t3* t4* t5*/t6*/sr0 :
        t1* t2* t3* t4* t5* t6*/sr0
        sr0;
        t1* t2* t3* t4* t5* t6*/t7*/sr0;
        t1* t2* t3* t4* t5* t6* t7*/sr0
        sr0:
         t1* t2* t3* t4* t5* t6* t7*/t8*/sr0 ;
        t1* t2* t3* t4* t5* t6* t7* t8*/sr0
        srO .
        t1* t2* t3* t4* t5* t6* t7* t8*/t9*/sr0;
        t1* t2* t3* t4* t5* t6* t7* t8* t9*/sr0
        sr0 ;
t10 s = t1* t2* t3* t4* t5* t6* t7* t8* t9*/t10*/sr0 ;
    r = t1* t2* t3* t4* t5* t6* t7* t8* t9* t10*/sr0
        sr0:
    (Can be used later to define state equations)
                 Table 8-1. Logic Equations
```





With the system fully defined, simply assemble the design information during the AMAZE assembler to produce the fuse pattern for the desired device. Should any design changes meed to be made to a device, the fuse pattern may be modified directly using the program table editor of AMAZE. However, taking this

action is not recommended since Boolean equation and state equation files are not altered correspondingly.

Functioning of the device can be verified with the AMAZE simulator, which can also be used to check A.C. timings before downloading the pattern to a device programmer, such as Stag ZL30A or Data I/O 29B, to program the device. Test vectors are produced either automatically or interactively by the simulator.

Programmability

The PLS168 device could now be used as the controller of an alarm system. As it stands, the device assumes that all the alarm inputs indicate an alarm condition when in the high state, logic one, and that the alarms are activated when the alarm outputs are active low (i.e., at logic zero).

Should an alarm input transducer be used which indicates an alarm condition as a low state, this can be catered for by altering the SEE file. For example, consider a smoke detector which outputs logic zero on detection of an alarm condition and assume that this transducer is driving the "fire" input of the device. By changing all references to 'fire' in the .SEE file to 'fire' and all instances of 'fire' to 'fire' then the activation of the alarms will occur when log-

ic zero is applied to this input and not when logic one is applied, as in the original case. Pinlist and .BEE files do not need to be altered.


Polarity of the output signals cannot be altered as easily, as the device will always power—up with the outputs at logic one. This should not prove to be a problem since the outputs simply drive output transistors and these can be used to produce the correct polarity signal for the beacon and sounder.

System Implementation

Figure 8-4 shows a typical alarm system based on this device. The system clock is produced by a relaxation oscillator built from 74HC132 Schmitt Triggers. Values of R₁ and C₁ shown result in a frequency of approximately 4Hz which will provide the desired entry/exit and

sounder turn-off delays. These delays can be modified either by changing the external oscillator circuit or by decoding a different internal counter state. For example, to increase the entry/exit delay change all references to t7 in the .SEE file to t8. Both normally-closed and normally-open loop implementations are shown. Due to the distances involved in an alarm system, the open-loop configuration may cause problems, being driven by the positive supply. to avoid this problem, input-detect polarity of the open-loop circuit can be changed by altering the .SEE file.

Status indication can be provided by connecting LEDs as in Figure 8-5. When the reset button is pressed, any LED being lit will indicate an alarm condition for that input. This will not reset the alarm system unless the arm switch is off.



```
[sr0, sr1, beacon]
st null = 111b;
st_0 = 001b;
            = 101b;
st_2 = 011b;
st_3 = 010b;
st_4 = 100b;
@TRANSITIONS
While [st_null]
                [arm* /fire * /peratak] :: [st_0]
                [peratak]
                                                                     :: [st_4
:: [st_4]
                                                                                          with [/sounder']
with [/sounder']
                [fire]
            encase
While [st 0]
                [t7 * /fire * (arm + reset)] :: [st_1]
[/arm * /reset] :: [st_null] with [sounder']
                [/arm * /reset]
                [fire]
                                                                     :: [st_4] with [/sounder']
            encase
While [st 1]
            case
              [timed1 * /fire] :: [st_2]
[timed2 * /fire] :: [st_2]
[alarm1 * /fire] :: [st_3]
[alarm3 * /fire] :: [st_3]
[/arm * /reset] :: [st_null fire]
                                                                                           with [/sounder']
                                                                     :: [st_3] with [/sounder']
:: [st_3] with [/sounder']
:: [st_null] with [sounder']
                [fire]
                                                                      :: [st_4] with [/sounder']
            encase
While [st 2]
            case

      [t7 * /fire]
      :: [st_3]
      with [/sounder']

      [alarm1 * /fire]
      :: [st_3]
      with [/sounder']

      [alarm2 * /fire]
      :: [st_3]
      with [/sounder']

      [alarm3 * /fire]
      :: [st_3]
      with [/sounder']

      [/arm * /reset]
      :: [st_null]
      with [sounder']

      [fire]
      :: [st_4]
      with [/sounder']

              [t7 * /fire]
            encase
While [st 3]
                [t10in * /fire * (arm + reset)]
                                                                                         with [sounder']
                                                                   : : [st 4]
                [[/arm * /reset]
                                                                     :: [st_null with [sounder']
:: [st 4] with [/sounder']
                [fire]
            encase
While [st 4]
            case
                        [/arm * /reset] then [st_null] with [sounder']
             i f
                                    Table 8-2. State Equations can be used to define state transitions
```



Signetics

Section 10 Package Outlines

Programmable Logic Devices

INDEX

Α	Plastic Leaded Chip Carrier	785
F	Ceramic Dual-In-Line	788
FA	Ceramic Dual-In-Line with Quartz Window	790
LA	Ceramic Leaded Chip Carrier with Quartz Window	792
N	Plastic Dual-In-Line	793

PLCC

- Package dimensions conform to JEDEC specifications for standard Plastic Leaded Chip Carrier outline (PLCC) package.
- Controlling dimensions are given in inches with dimensions in millimeters contained in parentheses.
- Dimensions and tolerancing per ANSI Y14.5M – 1982.
- "D-E" and "F-G" are reference datums on the molded body and do not include mold flash or protrusions. Mold flash or protrusions shall not exceed 0.15mm (0.006") on any side.
- Pin numbers start with pin #1 and continue counterclockwise when viewed from the top.
- Lead material: Olin 194 (Copper Alloy) or equivalent, solder dipped.
- 7. Body material: Plastic (Epoxy).
- Thermal resistance values are determined by Temperature Sensitive Parameter (TSP) method. This method uses the forward voltage drop of a calibrated diode to measure

the change in junction temperature due to a known power application. Test conditions for these values are:


Test Ambient—Still Air $\begin{tabular}{ll} Test Fixture & θ_{JA}- Glass epoxy test \\ & board (2.24" \times \\ & 2.24" \times 0.062") \\ & θ_{JC}- Water cooled heat \\ \end{tabular}$

sink


PLASTIC LEADED CHIP CARRIER (PLCC)

			TYPICAL θ_{JA}/θ_{JC} VALUES (°C/W)		
NO. OF LEADS	PACKAGE CODE	DESCRIPTION	Average θ_{JA}	Average θ_{JC}	
20	A	350mil-wide	70	30	
28	A	450mil-wide	61	26	
52	A	750mil-wide	42	14	
68	A	950mil-wide	42	14	


20-PIN PLASTIC LEADED CHIP CARRIER




28-PIN PLASTIC LEADED CHIP CARRIER



52-PIN PLASTIC LEADED CHIP CARRIER



68-PIN PLASTIC LEADED CHIP CARRIER



January 1990 787

HERMETIC CERDIP

- Package dimensions conform to JEDEC specificationS for standard Ceramic Dual Inline (CERDIP) package.
- Controlling dimensions are given in inches with dimensions in millimeters, mm, contained in parentheses.
- Dimensions and tolerancing per ANSI Y14.5M – 1982.
- Pin numbers start with pin #1 and continue counterclockwise when viewed from the top.
- These dimensions measured with the leads constrained to be perpendicular to plane T.
- 6. Lead material: ASTM alloy F-30 (Alloy 42) or equivalent tin plated or solder dipped.
- Body material: Ceramic with glass seal at leads.
- Thermal resistance values are determined by Temperature Sensitive Parameter (TSP) method. This method uses the forward voltage drop of a calibrated diode to mea-

sure the change in junction temperature due to a known power application. Test conditions for these values follow:

Test Ambient—Still Air


Test Fixture— θ_{JA} - Textool ZIF socket with 0.04" stand-

θ_{JC}– Water cooled heat sink

CERAMIC DUAL-IN-LINE PACKAGES


		* *	TYPICAL θ_{JA}/θ_{JC} VALUES (°C/W)		
NO. OF LEADS	PACKAGE CODE	DESCRIPTION	Average θ _{JA}	Average θ_{JC}	
20	F	300mil-wide	72	8	
24	F	300mil-wide	62	7	
28	F	600mil-wide	48	6	

20-PIN CERAMIC DUAL-IN-LINE




January 1990

24-PIN CERAMIC DUAL-IN-LINE



28-PIN CERAMIC DUAL-IN-LINE (600mil-wide)



HERMETIC CERDIP WITH QUARTZ WINDOW

- Package dimensions conform to JEDEC specificationS for standard Ceramic Dual Inline (CERDIP) package.
- Controlling dimensions are given in inches with dimensions in millimeters, mm, contained in parentheses.
- 3. Dimensions and tolerancing per ANSI Y14.5M 1982.
- Pin numbers start with pin #1 and continue counterclockwise when viewed from the top.
- These dimensions measured with the leads constrained to be perpendicular to plane T.
- 6. Lead material: ASTM alloy F-30 (Alloy 42) or equivalent tin plated or solder dipped.
- Body material: Ceramic with glass seal at leads.
- Thermal resistance values are determined by Temperature Sensitive Parameter (TSP) method. This method uses the forward voltage drop of a calibrated diode to mea-

sure the change in junction temperature due to a known power application. Test condition for these values follow:

Test Ambient-Still Air

 $\begin{array}{cc} \text{Test Fixture} & \theta_{\text{JA}}\text{--} \text{ Textool ZIF socket} \\ & \text{with 0.04" stand--} \end{array}$


off

 $\theta_{\text{JC}}-$ Water cooled heat sink


HERMETIC DUAL-IN-LINE PACKAGES

			TYPICAL θ _{JA} /θ _{JC} VALUES (°C/W)		
NO. OF LEADS	PACKAGE CODE	DESCRIPTION	Average θ _{JA}	Average θ_{JC}	
20	FA	300mil-wide	67	8	
24	FA	300mil-wide	52	7	
28	FA	600mil-wide	45	6	


20-PIN CERAMIC DUAL-IN-LINE WITH QUARTZ WINDOW



24-PIN CERAMIC DUAL-IN-LINE WITH QUARTZ WINDOW




28-PIN CERAMIC DUAL-IN-LINE WITH QUARTZ WINDOW



CERAMIC LEADED CHIP CARRIER WITH QUARTZ WINDOW

			TYPICAL θ _{JA} /θ _{JC} VALUES (°C/W)		
NO. OF LEADS	PACKAGE CODE	DESCRIPTION	Average θ_{JA} Average θ_{JG}		
68	LA	965mil-wide	55	25	

68-PIN CERAMIC LEADED CHIP CARRIER WITH QUARTZ WINDOW



PLASTIC DIP

- Package dimensions conform to JEDEC specification MS-001-AA for standard Plastic Dual Inline (DIP) package.
- Controlling dimensions are given in inches with dimensions in millimeters, mm, contained in parentheses.
- 3. Dimensions and tolerancing per ANSI Y14.5M 1982.
- "T", "D" and "E" are reference datums on the molded body and do not include mold flash or protrusions. Mold flash or protrusions shall not exceed 0.01 inch (0.25mm) on any side
- These dimensions measured with the leads constrained to be perpendicular to plane T.
- Pin numbers start with pin #1 and continue counterclockwise when viewed from the top.
- Lead material: Olin 194 (Copper Alloy) or equivalent, solder dipped.
- 8. Body material: Plastic (Epoxy).
- Thermal resistance values are determined by Temperature Sensitive Parameter (TSP) method. This method uses the forward

voltage drop of a calibrated diode to measure the change in junction temperature due to a known power application. Test conditions for these values are:

Test Ambient—Still Air

Test Fixture— θ_{JA} — Textool ZIF socket with 0.04" stand—


off

θ_{JC}– Water cooled heat sink


PLASTIC DUAL-IN-LINE PACKAGES

			TYPICAL θ _{JA} /θ _{JC} VALUES (°C/W)		
NO. OF LEADS	PACKAGE CODE	DESCRIPTION	Average θ _{JA}	Average θ_{JC}	
20	N	Cu. Lead Frame 300mil-wide	63	27	
24	N	Cu. Lead Frame 300mil–wide	56	26	
28	N	Cu. Lead Frame 600mil-wide	46	18	
28	N3	Cu. Lead Frame 300mil–wide	53	24	


20-PIN PLASTIC DUAL-IN-LINE (N PACKAGE)




24-PIN PLASTIC DUAL-IN-LINE (N PACKAGE)



28-PIN PLASTIC DUAL-IN-LINE (N PACKAGE)



28-PIN PLASTIC DUAL-IN-LINE (N3 PACKAGE)



Signetics

Programmable Logic Devices

Section 11
Sales Offices,
Representatives &
Distributors

Signetics

Sales Offices. Representatives & **Distributors**

Programmable Logic Devices

SIGNETICS **HEADQUARTERS**

811 East Argues Avenue P.O. Box 3409 Sunnyvale, CA 94088-3409 Phone: (408) 991-2000

ALABAMA Huntsville

Phone: (205) 830-4001

ARIZONA

Phoenix Phone: (602) 968-5777

CALIFORNIA Calabasas

Phone: (818) 880-6304

Irvine Phone: (714) 833-8980 (714) 752-2780

Los Angeles Phone: (213) 670-1101

San Diego

Phone: (619) 560-0242 Sunnyvale

Phone: (408) 991-3737 COLORADO

Phone: (303) 751-5011

GEORGIA Atlanta Phone: (404) 594-1392

ILLINOIS Phone: (312) 250-0050

INDIANA Kokomo Phone: (317) 459-5355

MASSACHUSETTS Westford Phone: (508) 692-6211

MICHIGAN Farmington Hills

Phone: (313) 553-6070 **NEW JERSEY**

Parsippany Phone: (201) 334-4405

Toms River Phone: (201) 505-1200

NEW YORK Wappingers Falls Phone: (914) 297-4074

NORTH CAROLINA Raleigh Phone: (919) 781-1900

OHIO Columbus Phone: (614) 888-7143

Dayton Phone: (513) 294-7340

Beaverton Phone: (503) 627-0110

OREGON

TEXAS

PENNSYLVANIA Plymouth Meeting Phone: (215) 825-4404

TENNESSEE

Greeneville Phone: (615) 639-0251

Austin Phone: (512) 339-9944

Phone: (713) 668-1989

Richardson Phone: (214) 644-3500

SIGNETICS CANADA, LTD. Etobicoke, Ontario Phone: (416) 626-6676

Nepean, Ontario Phone: (613) 225-5467

REPRESENTATIVES

ARIZONA Scottsdale

Thom Luke Sales, Inc. Phone: (602) 941-1901

CALIFORNIA Folsom

Webster Associates Phone: (916) 989-0843 **FLORIDA** Oviedo

Conley and Assoc., Inc. Phone: (407) 365-3283

ILLINOIS Hoffman Estates Micro-Tex. Inc. Phone: (708) 382-3001

INDIANA Indianapolis Mohrfield Marketing, Inc. Phone: (317) 546-6969

IOWA Cedar Rapids J.R. Sales Phone: (319) 393-2232

MARYLAND Columbia

Third Wave Solutions, Inc. Phone: (301) 290-5990 MINNESOTA **Eden Prairie**

High Technology Sales Phone: (612) 944-7274 **MISSOURI**

Bridgeton Centech, Inc. Phone: (314) 291-4230

Ravtown Centech, Inc. Phone: (816) 358-8100

NEW MEXICO Albuquerque F.P. Sales Phone: (505) 345-5553

NEW YORK Ithaca

Bob Dean, Inc. Phone: (607) 257-1111

Rockville Centre S-J Associates Phone: (516) 536-4242

Wappingers Falls Bob Dean, Inc. Phone: (914) 297-6406

NORTH CAROLINA Smithfield

ADI Phone: (919) 934-8136 OHIO

Centerville Bear Marketing, Inc. Phone: (513) 436-2061

Richfield Bear Marketing, Inc. Phone: (216) 659-3131

OREGON Beaverton Western Technical Sales Phone: (503) 644-8860

PENNSYLVANIA Pittsburgh Bear Marketing, Inc. Phone: (412) 531-2002

Hatboro Delta Technical Sales, Inc. Phone: (215) 975-0600

UTAH Salt Lake City Electrodyne Phone: (801) 264-8050

WASHINGTON Bellevue Western Technical Sales Phone: (206) 641-3900

Spokane Western Technical Sales

Phone: (509) 922-7600 WISCONSIN Waukesha

Micro-Tex. Inc. Phone: (414) 542-5352

CANADA Burnaby, B.C. Tech-Trek, Ltd. Phone: (604) 439-1373

Mississauga, Ontario Tech-Trek, Ltd. Phone: (416) 238-0366

Nepean, Ontario Tech-Trek, Ltd Phone: (613) 225-5161

Ville St. Laurent, Quebec Tech-Trek, Ltd. Phone: (514) 337-7540

PUERTO RICO Santurce Mectronics Sales, Inc. Phone: (809) 728-3280

Sales Offices, Representatives & Distributors

DISTRIBUTORS

Contact one of our local distributors:
Anthem Electronics
Falcon Electronics, Inc.
Gerber Electronics
Hamilton/Avnet Electronics
Marshall Industries
Schweber Electronics
Wyle/LEMG
Zentronics, Ltd.

FOR SIGNETICS PRODUCTS WORLDWIDE:

ARGENTINA
Philips Argentina S.A.
Buenos Aires
Phone: 54-1-541-4261

AUSTRALIA Philips Electronic Components & Mat'l Ltd. Artarmon, N.S.W. Phone: 61-2-439-3322

AUSTRIA
Osterrichische Philips
Wien
Phone: 43-222-60-101-820

BELGIUM S.A. MBLE Components Brussels Phone: 32-2-525-61-11

BRAZIL
Philips Do Brasil, Ltda.
Sao Paulo
Phone: 55-11-211-2600

CHILE
Philips Chilena S.A.
Santiago
Phone: 56-02-077-3816

CHINA, PEOPLES REPUBLIC OF Philips Hong Kong, Ltd. Kwai Chung, Kowloon Phone: 852-0-424-5121

COLUMBIA Iprelenso, Ltda. Bogota Phone: 57-1-2497624 DENMARK
Philips Components A/S
Copenhagen S
Phone: 45-1-54-11-33

FINLAND Oy Philips Ab Espoo Phone: 358-0-502-61

FRANCE R.T.C. Compelec Issy-les-Moulineaux Cedex Phone: 33-1-40-93-80-00

GERMANY Valvo

Hamburg Phone: 49-40-3-296-0 GREECE

Philips S.A. Hellenique Athens Phone: 30-1-4894-339

HONG KONG Philips Hong Kong, Ltd. Kwai Chung, Kowloon Phone: 852-0-424-5121

INDIA Peico Electronics & Elect. Ltd. Bombay Phone: 91-22-493-0311

INDONESIA P.T. Philips-Ralin Electronics Jakarta Selatan

Phone: 62-21-517-795
IRELAND
Philips Electrical Ltd.

Dublin Phone: 353-1-69-33-55 **SRAEL**

Rapac Electronics, Ltd. Tel Aviv Phone: 972-3-477115

Philips S.p.A.
Milano
Phone: 38-2-67-52-1

JAPAN Philips Components Japan Osaka-Shi Phone: 81-6-389-7722 Philips Components Japan Tokyo Phone: 81-3-740-5028

Philips Industries, Ltd. Seoul Phone: 82-2-794-5011

KOREA

MALAYSIA Philips Malaysia SDN Bernhad

Kuala Lumpur Phone: 60-3-734-5511

Philips Components
Guadalajara, Jal
Phone: 52-36-52-27-70

Mexico, D.F. Phone: 52-721-64-984

NETHERLANDS Philips Nederland Eindhoven Phone: 31-40-783-749

NEW ZEALAND Philips New Zealand Ltd.

Auckland Phone: 64-9-605-914

NORWAY Norsk A/S Philips Oslo

Phone: 47-2-68-02-00
PERU
Cadesa
San Isidro
Phone: 51-14-707-080

PHILIPPINES
Phillips Industrial Dev., Inc.
Makati Metro Manila
Phone: 63-2-810-01-61

PORTUGAL Philips Portuguesa SA Lisbon Phone: 351-1-68-31-21

SINGAPORE Philips Singapore Pte., Ltd. Singapore Phone: 65-350-2000 SOUTH AFRICA SA Philips (PTY), Ltd. Randburg Phone: 27-11-889-3911

SPAIN
Copresa S.A.
Barcelona
Phone: 34-3-301-63-12

SWEDEN
Philips Components A.B.
Stockholm
Phone: 46-8-782-10-00

SWITZERLAND
Philips Components A.G.
Zuerich
Phone: 41-1-488-2211

TAIWAN Philips Taiwan, Ltd. Taipei Phone: 886-2-509-7666

THAILAND
Philips Electrical Co.
of Thailand Ltd.

Bangkok Phone: 66-2-223-63309 TURKEY Turk Philips

Ticaret A.S.
Istanbul
Phone: 90-1-179-27-70

UNITED KINGDOM Philips Components London Phone: 44-1-580-6633

UNITED STATES Signetics Sunnyvale, California Phone: (408) 991-2000

URUGUAY Luzilectron S.A. Montevideo Phone: 598-91-56-41/ 42/43/44

VENEZUELA Magnetica S.A. Caracas Phone: 58-2-241-7509

11/28/89



AMAZE PLD Design Software Request

Please rush me my complimentary copy of Signetics AMAZE PLD Design Software!

I am interested in designing with the following Signetics PLDs: ☐ Programmable Logic Arrays (PLAs) ☐ Programmable Logic Sequencers (PLSs) ☐ Programmable Macro Logic Devices ☐ PAL® Compatible Devices Last Name First Name Address Company City, State & Zip Department or Division Telephone Ext. ☐ Please have a qualified Signetics engineer install the AMAZE design. ☐ Please ship the Signetics AMAZE design software directly to my office. Note: This AMAZE software request form is for new AMAZE users only and cannot be used to request updates for earlier versions of

PAL is a trademark of Monolithic Memories, Inc., a wholly-owned subsidiary of Advanced Micro Devices, Inc.

AMAZE. An update request form is included with your new AMAZE PLD software for the purpose of requesting future AMAZE



software updates.

PHILIPS

FOLD HERE



BUSINESS REPLY MAIL

First Class

Permit No. 166

Sunnyvale, California

POSTAGE WILL BE PAID BY ADDRESSEE

Signetics

a division of North American Philips Corporation

Signetics Company P.O. Box 3409 Sunnyvale, CA 94088-9950 NO POSTAGE NECESSARY IF MAILED IN THE UNITED STATES



Attn: Software Support Group, MS 25

o return mail: Please fold with business reply facing out.

Signetics Key Customer Interests PLD Data Handbook

ast name First name	Address			
ompany name	City		State	Zip
epartment or Division	Area code	Phone	number	Extension
) Consumer Products Machines () Defense 8	l Equipment () Test & Military Equipment Agency () Auto. cs System Mant on () Scier ents & Sub— () Educ ies () Othe	& Measurement (pment (/Truck/Bus (ufacturing (ntific Equipment (eational Institution () Military Facility) Sales Office	()Engineering/Design Facility ()Distribution Facility ()Manufacturing Facility ()Repair/Retrofit Facility ()Other
3. Number of employees at your location: () 1–250	() 251–500	() 501–1000	() More than 1000	
4. Number of engineers at your location:				
5. Approximate annual company revenue: () Don't Know	() Under \$50M	() \$50M to \$250M	() \$250M to \$100M	() Over \$100M
6. Would you like a sales engineer to call you? () YES	() NO			
7. Please indicate your area(s) of specific product interest by c () Digital Logic () PROM () Surface Moun () TTL/LS/S () EPROM/OTP () 10K/100K ECL () DRAM Controller () SO () FAST () FIFO () PLCC () HC/HCT/CMOS () Microprocessor () LCC () 400 Series CMOS () 68000 Family () VME Interface () ACL () 68000 Peripherals () Devices () ALS () Data Communications () MPU () Memory () CRT/Graphics () Memory () RAM/DRAM/SRAM() DSP () Data Commun () ROM	nt () Disc Con () VME/VMS () Military & Products (All As Re	troller (S Bus Controller (S Bus Controller (B Govt. B Govt	Interface/Data Convertion Small Area Networks ASIC/Semicustom Products Bipolar Std. Cell (CCL) CMOS Standard Cell (Semicustom)) Programmable Logic Devices (PLD)) PAL®) Software) Microcontroller) NMOS/CMOS Family) Bipolar Family) 80C51 Derivatives) OTP Microcontroller) 1 ² C Microcontroller
8. Your primary job responsibility/title is (check only one):			you recommend, specif hasing of electronic com ()Ye	ponents?
MANAGEMENT ENGINEERING PRO () Senior Corp () Section Leader () Mechanical () Manager () Group Leader () Materials () () Engineering () Project Engineer Specifications Manager () Design () Production () () Financial () Aerospace () Systems () Purchasing/ () Applications () Ocean/Naval ()	Electronics Buyer General Purchasing Agent Production Component Buyer Engineering Buyer	EDUCATION/ INSTRUCTION () Professor () Asst. Professor () Instructor () Industrial Instructor () Student () Research Scientist	CONSULTING ()NO	

FOLD FOR MAILING



BUSINESS REPLY
First Class Permit No. 857 MAIL

Permit No. 857

Dallas, Texas

POSTAGE WILL BE PAID BY ADDRESSEE

a division of North American Philips Corporation

Signetics Company Literature Distribution Center P.O. Box 542554 Dallas, TX 75354-9988

NO POSTAGE NECESSARY IF MAILED IN THE **UNITED STATES**



Philips Components — a worldwide Group of Companies

entina: PHILIPS ARGENTINA S.A. Div. Components, Vedia 3892, 1430 BUENOS AIRES, Tel. (01) 541-7141 to 7747.

Australia: PHILIPS COMPONENTS PTV Ltd. 11 Waltham Street ARTARMON, N.S.W. 2064, TEL. (02) 4393322

Austria: OSTERREICHISCHE PHILIPS INDUSTRIE G.m.b.H., UB Bauelemente, Triester Str. 64, 1101 WIEN. Tel. (0222) 60 101-820. Belgium: N.V. PHILIPS PROF. SYSTEMS — Components Div., 80

Rue Des Deux Gares, B-1070 BRUXELLES, Tel. (02) 5256111. Brazil: CONSTANTA-IBRAPE; (Active Devices): Av. Brigadeiro Faria Lima, 1735-SAO PAULO-SP, Tel. (011) 211-2600 CONSTANTA IBRAPE; (Passive Devices & Materials): Av. Francisco Monteiro, 702 - RIBEIRAO PIRES-SP, Tel. (011) 459-8211.

Canada: For IC Products Refer to United States

Chile: PHILIPS CHILENA S.A., Av. Santa Maria 0760, SANTIAGO, Tel. (02) 773816.

Colombia: IND. PHILIPS DE COLOMBIA S.A., c/o IPRELENSO LTD., Cra. 21, No 56-17 BOGOTA, D.E., Tel. (01) 2497624

Denmark: PHILIPS COMPONENTS A/S. Prags Boulevard 80, PB1919, DK-2300 COPENHAGEN S, Tel. 01-54113.

nd: PHILIPS COMPONENTS, Sinikaliontie 3, SF-2630 ESPOO HELSINKI 10, Tel. 358-0-50261.

France: RTC-COMPELEC, 117 Quai du President Roosevelt, 92134 ISSY-LES-MOULINEAUX Cedex. Tel. (01) 40938000.

Germany (Fed. Republic): VALVO, UB Baulemente der Philips G.m.b.H., Valvo Haus, Burchardstrasse 19, D-2 HAMBURG 1,

Greece: PHILIPS HELLENIQUE S.A., Components Division, No. 15, 25th March Street, GR 17778 TAVROS, Tel. (01) 4894339/4894911

Hong Kong: PHILIPS HONG KONG LTD., Components Div., 15/F Philips Ind. Bldg., 24-28 Kung Yip St., KWAI CHUNG, Tel. (0)-245121.

India: PEICO ELECTRONICS & ELECTRICALS LTD., Components Dept., Band Box Building, 254-D Dr. Annie Besant Rd., BOMBAY - 400025, Tel. (022) 4920211/4930590.

Indonesia: P.T. PHILIPS-RALIN ELECTRONICS, Components Div., Setiabudi II Building, 6th Fl., Jalan H.R. Rasuna Said (P.O. Box 223/KBY) Kuningan, JAKARTA 12910, Tel. (021) 517995.

Ireland: PHILIPS ELECTRONICS (IRELAND) LTD., Components Division, Newstead, Clongskeagh, DUBLIN 14, Tel. (01) 693355. Italy: PHILIPS S.p.A., Philips Components, Piazza IV Novembre 3, I-20124 MILANO, Tel. (02) 67521.

Japan: NIHON PHILIPS CORP., Shuwa Sinagawa Bldg., 26-33 Takanawa 3-chome, Minato-ku, TOKYO (108), Tel. (03) 448-5611. (IC Products) SIGNETICS JAPAN LTD., 8-7 Sanbancho Chivoda-ku, TOKYO 102, Tel. (03) 230-1521.

Korea (Republic of): PHILIPS ELECTRONICS (KOREA) LTD., Elcoma Div., Philips House, 260-199 Itaewon-dong, Yongsan-ku, SEOUL, Tel. (02) 794-5011.

Malaysia: PHLIPS MALAYSIA SDN BHD, Components Div. 3 Jalan SS15/2A SUBANG, 47500 PETALING JAYA, Tel. (02) 7345511. Mexico: ELECTRONICA, S.A. de C.V., Carr. Mexico-Toluca km. 62.5, TOLUCA, Edo. de Mexico 50140,

Tel. Toluca 91 (721) 613-00. Netherlands: PHILIPS NEDERLAND, Marktgroep Philips

Components, Postbus 90050, 5600 PB EINDHOVEN. Tel. (040) 783749. New Zealand: PHILIPS NEW ZEALAND LTD., Componer

Division, 110 Mt. Eden Road, C.P.O. Box 1041, AUCKLAND, Tel. (09) 605-914 Norway: NORSK A/S PHILIPS, Philips Components, Box 1,

Manglerud 0612, OSLO, Tel. (02) 680200. Pakistan: PHILIPS ELECTRICAL CO. OF PAKISTAN LTD>, Philips

Markaz, M.A. Jinnah Rd., KARACHI-3, Tel. (021) 725772. Peru: CADESA, Av. Pardo y Aliaga No. 695, 6th Floor, San Isidro, LIMA 27, Tel. (014) 707080.

Philippines: PHILIPS INDUSTRIAL DEV. INC., 2246 Pasong Tamo, P.O. Box 911, Makati Comm. Centre, MAKATI-RIZAL 3116, Tel. (02) 868951 to 59.

98-7001-230

Portugal: PHILIPS PORTUGESA S.A.R.L., Av. Eng. Duarte Pacheco 6, 1009 LISBOA Codex, Tel. (019) 683121

Singapore: PHILIPS PROJECT DEV. (Singapore) PTE LTD. Components Div., Lorong 1, Toa Payoh, SINGAPORE 1231.

Spain: PHILIPS Components, Balmes 22, 08007 BARCELONA Tel. (03) 3016312.

Sweden: PHILIPS Components, A.B., Tegeluddsvagen 1, S-11584 STOCKHOLM, Tel. (0)8-7821000.

Switzerland: PHILIPS A.G., Components Dept., Allmendstrasse 140-142, CH-8027 ZURICH, Tel. (01) 4882211.

Taiwan: PHILIPS TAIWAN LTD., 150 Tun Hua North Road, P.O. Box 22918, TAIPEL Taiwan, Tel. (02) 7120500. Thailand: PHILIPS ELECTRICAL CO. OF THAILAND LTD., 283

Silom Road, P.O. Box 961, BANGKOK, Tel. (02) 233-6330-9. Turkey: TURK PHILIPS TICARET A.S., Philips Components, Talatpasa Cad, No. 5, 80640 LEVENT/ISTANBUL

United Kingdom: PHILIPS COMPONENTS LTD., Mullard House, Torrington Place, LONDON WC1e 7HD, Tel. (01) 5806633.

United States: IC Products:

Tel (01) 1792770

PHILIPS COMPONENTS-SIGNETICS 811 East Arques Avenue Sunnyvale, CA 94088-3409

Tel. (408) 991-2000

Discrete Semiconductors, Passive Components, Materials, and Professional Components:

PHILIPS COMPONENTS-DISCRETE PRODUCTS DIVISION

2001 West Blue Heron Boulevard Riviera Beach, FL. 33404 Tel. (305) 881-3200

Color Picture Tubes - Monochrome and Color Display Tubes PHILIPS DISPLAY COMPONENTS

P.O. Box 963 Ann Arbor, MI 48106 Tel. (313) 996-9400

Uruguay: LUZILECTRON S.A., Avda Uruguay 1287, P.O. Box 907, MONTEVIDEO Tel (02) 985395

Venezuela: IND. VENEZOLANAS PHILIPS S.A., c/o MAGNETICA S.A., Calle 6, Ed Las Tres Jotas, App. Post. 78117, CARACAS, Tel. (02) 2393931.

For all other countries apply to: Philips Components Division, International Business Relations, P.O. Box 218, 5600 MD EINDHOVEN, The Netherlands, Telex 35000 phtcnl

AS67

©Philips Export B.V. 1989

All Rights are reserved. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner.

The information presented in this document does not form part of any quotation or contract, is believed to be accurate and reliable and may be changed without notice. No liability will be accepted by the publisher for any consequence of its use. Publication thereof does not convey nor imply any license under patent industrial or intellectual property rights.

© Copyright 1989 NAPC Printed in U.S.A. 9280A/80M/CR3/1289

Philips Components



PHILIPS